



HAL
open science

Robust fractional order differentiators using generalized modulating functions method

Da-Yan Liu, Taous-Meriem Laleg-Kirati

► **To cite this version:**

Da-Yan Liu, Taous-Meriem Laleg-Kirati. Robust fractional order differentiators using generalized modulating functions method. 2014. hal-00923748v1

HAL Id: hal-00923748

<https://inria.hal.science/hal-00923748v1>

Preprint submitted on 4 Jan 2014 (v1), last revised 5 May 2014 (v3)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Robust fractional order differentiators using generalized modulating functions method

Da-Yan Liu^a, Taous-Meriem Laleg-Kirati^b

^a*INSA Centre Val de Loire, 88 Boulevard Lahitolle, 18000 Bourges, France*

^b*CEMSE Division, King Abdullah University of Science and Technology (KAUST), 23955-6900 Thuwal, KSA*

Abstract

This paper addresses the design in the time domain of fractional order differentiators for a class of signals satisfying a linear differential equation with unknown parameters. We first estimate the unknown parameters using modulating function method. Then, by applying generalized modulating function method and fractional integration by parts formula the left-sided Riemann-Liouville fractional derivative with an arbitrary order of a considered signal is given by two different integral formulae respectively. Thus, we take these integral formulae as proposed fractional order differentiators which do not contain any sources of errors in continuous noise free case. Unlike the improper integral in the definition of the left-sided Riemann-Liouville fractional derivative, the integrals in the proposed formulae can be proper and be considered as a low-pass filter by choosing appropriate modulating functions. Hence, digital fractional order differentiators applicable for on-line applications are deduced using a numerical integration method in discrete noisy case. Moreover, some error analysis are given for noise error contributions due to a class of stochastic processes. Finally, numerical examples are given to show the accuracy and robustness of the proposed fractional order differentiators.

Keywords: Fractional order differentiator, Riemann-Liouville derivative, Generalized modulating functions method, Noise

1. Introduction

Fractional calculus were introduced in many fields of science and engineering long time ago. It was first developed by mathematicians in the middle of the ninetieth century [1]. During the past decades, fractional calculus has gained great interest in several applications [2, 3, 4]. For instance, fractional derivatives can improve the performances and robustness properties in control design (see, e.g., [5, 6, 7, 8]) and in signal processing applications (see, e.g., [9, 10, 11, 12]). The fractional order numerical differentiation is concerned with the estimation of the fractional order derivatives of an unknown signal from its discrete noisy observed data. As in the integer order case, this problem is an ill-posed problem in the sense that a small noise can lead to a large error in approximated derivatives. In order to overcome this problem, various robust fractional order differentiators have been proposed in the frequency domain (see, e.g., [13, 14]) and in the time domain, such as digital fractional order Savitzky-Golay differentiator [15], fractional order Jacobi differentiator [16, 17], and B-Spline functions-based fractional order differentiator [18]. The main idea of the latter fractional

Email addresses: dayan.liu@ensi-bourges.fr (Da-Yan Liu), taousmeriem.laleg@kaust.edu.sa (Taous-Meriem Laleg-Kirati)

order differentiators designed in the time domain is to use a polynomial to approximate the unknown signal whose fractional order derivatives are estimated by differentiating the polynomial. If we consider the used polynomial as the truncated Taylor series expansion of the unknown signal, then these fractional order differentiators contain an estimation error due to the truncated term in the Taylor series expansion (see [17] for some error analysis). When estimating the fractional order derivatives of an unknown signal, even in the noise free case, this kind of truncation errors can produce large errors near the boundaries of the interval where the fractional order derivatives are estimated [16, 18, 17].

The mentioned fractional order differentiators are extensions of their corresponding integer order differentiators [19, 20, 21]. When estimating the derivatives of an unknown signal, these differentiators do not depend on any model which gives the unknown signal. Hence, we call them model-free differentiators. In order to avoid truncation errors, integer order model-based differentiators have been proposed using a recent algebraic parametric method to estimate the state variables of an input-output linear system [22, 23, 24]. The successive integer order derivatives of output were accurately estimated from its noisy observation without any truncation error. The idea of this algebraic parametric method is to apply the Laplace transform to the linear differential equation which defines the studied linear system. By applying some algebraic operations (such as differentiations and multiplications) in the Laplace operational domain, undesired terms in the obtained equation can be eliminated. When returning into the time domain, the integer order derivatives of output can be exactly given by integral formulae involving the output and a combination of the weight functions of Jacobi orthogonal polynomials. Then, integer order differentiators are deduced by taking the noisy observation of output in the obtained integral formulae. It has been shown in [25, 26] that thanks to the integral formulae these differentiators exhibit good robustness properties with respect to corrupting noises even the statistical properties of the noises are unknown. Recall that the algebraic parametric method was introduced by Fliess and Sira-Ramírez for linear identification [27], and has been extended to many applications in noisy environment, such as design of integer order model-free differentiators (see, e.g., [28, 29, 30, 31]) and parameter estimation (see, e.g., [32, 33, 34, 35, 36, 37]). Very recently, it has been applied for fractional order model-free differentiators [38] and for fractional order systems identification [39]. However, it seems difficult to apply the algebraic parametric method to obtain fractional order model-based differentiators. On the one hand, the integer order model-based differentiator obtained in [22] is an anti-causal estimator using a sliding window. This is not suitable for the fractional derivative which is an hereditary operator and needs a total memory of past states [3]. On the other hand, the ones obtained in [23, 24] need to apply the Leibniz rule which gives infinity terms in fractional case (see [3] p. 96).

Modulating functions method introduced by Shinbrot [40] is very similar to the algebraic parametric method. This method has been widely used for linear and non-linear identification of continuous-time systems (see, e.g., [41, 42, 43]), and parameter estimation of noisy sinusoidal signals (see, e.g., [44, 36]). The idea of this method is to multiply a class of modulating functions to a linear differential equation of the analyzed signal. Then, an integration over a finite interval is taken to the obtained equation. Application of integration par parts allows to remove the derivative operations from the analyzed signal to the multiplied modulating functions, and the undesired boundary values are eliminated by the properties of modulating functions. Finally, estimators are obtained by solving a linear system of algebraic equations and given by integral formulae involving the noisy observation of the analyzed signal. Since the weight functions of Jacobi orthogonal polynomials obtained by the algebraic parametric method in integral formulae are also a class of modulating functions, the modulating functions method can be considered as a generalization of the algebraic parametric method in

some cases (see, e.g., [36]). It has similar advantages to the algebraic parametric method, especially the robustness properties with respect to corrupting noises. Moreover, inspired by the algebraic parametric method, the modulating functions method can be generalized for more applications. In [45], a fractional integration by parts formula has been obtained by working in the operational domain, then the modulating functions method has been generalized to fractional order systems identification problem. Inspired by [22, 23, 24], generalized modulating functions have been given, whose existence can be guaranteed by the algebraic parametric method. Then, the modulating functions method has been generalized to design an integer order model-based differentiator [46], where the proposed differentiator does not contain any truncation error. Unlike the differentiators proposed in [22, 23, 24], this differentiator is a causal estimator and does not need to apply the Leibniz rule. Having these ideas in mind, the aim of this paper is to generalize the modulating functions method to design a robust fractional order model-based differentiator without any truncation error. For this purpose, we will focus on a specific class of signals satisfying a linear differential equation with unknown parameters.

This paper is organized as follows. Section 2 begins with some basic definition of fractional order derivatives. Then, a recent fractional integration by parts formula is recalled. In Section 3, we first generalize classical modulating functions' definition. Then, the unknown parameters of the linear differential equation are given using the modulating functions method. Inspired by this method, we apply the generalized modulating functions and the fractional integration by parts formula to obtain fractional order differentiators in continuous noise free case, which provide exact integral expressions for fractional order derivatives. Then, digital fractional order differentiators are deduced using the obtained integral expressions in discrete noisy case. Moreover, some error analysis for noise error contribution are given. Numerical results are given in Section 4 to show the accuracy and robustness of the proposed fractional order differentiators. Finally, we give some conclusions and perspectives in Section 5. In Appendix, we give some classes of generalized modulating functions.

2. Preliminary

2.1. Riemann-Liouville and Caputo fractional derivatives

Let $l \in \mathbb{N}$, $\alpha \in \mathbb{R} \setminus \mathbb{N}$ with $l - 1 < \alpha < l$, and $f \in \mathcal{C}^l(\mathbb{R})$ where $\mathcal{C}^l(\mathbb{R})$ refers to the set of functions being l -times continuously differentiable on \mathbb{R} . Then, we recall the following definitions.

Definition 1 ([3] p. 62) *The left-sided Riemann-Liouville fractional derivative of f is defined as follows: $\forall t \in [a, +\infty[$,*

$${}_R D_{a,t}^\alpha f(\cdot) := \frac{1}{\Gamma(l-\alpha)} \frac{d^l}{dt^l} \int_a^t (t-\tau)^{l-\alpha-1} f(\tau) d\tau, \quad (1)$$

where $\Gamma(\cdot)$ is the Gamma function (see [47] p. 255).

Definition 2 ([3] p. 79) *The left-sided Caputo fractional derivative of f is defined as follows: $\forall t \in [a, +\infty[$,*

$${}_C D_{a,t}^\alpha f(\cdot) := \frac{1}{\Gamma(l-\alpha)} \int_a^t (t-\tau)^{l-\alpha-1} f^{(l)}(\tau) d\tau. \quad (2)$$

Definition 3 ([4] p. 92) *The right-sided Caputo fractional derivative of f is defined as follows: $\forall t \in]-\infty, b]$,*

$${}_C D_{t,b}^\alpha f(\cdot) := \frac{(-1)^l}{\Gamma(l-\alpha)} \int_t^b (\tau-t)^{l-\alpha-1} f^{(l)}(\tau) d\tau. \quad (3)$$

Consequently, if $-1 < \alpha < l = 0$, then we have ${}_R D_{a,t}^\alpha f(\cdot) \equiv {}_C D_{a,t}^\alpha f(\cdot)$. If $l \in \mathbb{N}^*$ ($\alpha \in \mathbb{R}_+ \setminus \mathbb{N}$), by applying integration by parts to (1), we get (see [3] pp. 75-76): $\forall t \in [a, +\infty[$,

$${}_R D_{a,t}^\alpha f(\cdot) = \sum_{i=0}^{l-1} \frac{(t-a)^{i-\alpha}}{\Gamma(i+1-\alpha)} f^{(i)}(a) + {}_C D_{a,t}^\alpha f(\cdot). \quad (4)$$

In the following lemma, we give the right-sided Caputo fractional derivative of a polynomial.

Lemma 1 *Let $f(\cdot) = (\cdot)^{n+l}$ with $l, n \in \mathbb{N}$, then the right-sided Caputo fractional derivative of f is given by: $\forall t \in]-\infty, b]$,*

$${}_C D_{t,b}^\alpha f(\cdot) = \frac{(-1)^l (n+l)!}{\Gamma(l-\alpha) n!} \sum_{i=0}^n \binom{n}{i} \frac{t^{n-i} (b-t)^{i+l-\alpha}}{i+l-\alpha}, \quad (5)$$

where $\alpha \in \mathbb{R} \setminus \mathbb{N}$ with $l-1 < \alpha < l$.

Proof. By using (3), we get:

$${}_C D_{t,b}^\alpha f(\cdot) = \frac{(-1)^l (n+l)!}{\Gamma(l-\alpha) n!} \int_t^b (\tau-t)^{l-\alpha-1} \tau^n d\tau. \quad (6)$$

Then, by taking the following change of variables $\tau \rightarrow \tau + t$, we obtain:

$${}_C D_{t,b}^\alpha f(\cdot) = \frac{(-1)^l (n+l)!}{\Gamma(l-\alpha) n!} \int_0^{b-t} \tau^{l-\alpha-1} (\tau+t)^n d\tau. \quad (7)$$

Finally, this proof can be completed by applying the binomial theorem and calculating the integral in (7). ■

2.2. Fractional integration by parts

The integration by parts is a crucial tool for the use of modulating functions method which we are going to apply in this paper. For this reason, we recall the generalized integration by parts in the following lemma which can be obtained by recursively applying the classical integration by parts.

Lemma 2 *Let $y, g \in \mathcal{C}^l(\mathbb{R})$ with $l \in \mathbb{N}^*$. Then, for any interval $[a, b] \subset \mathbb{R}$, we have:*

$$\int_a^b g(t) y^{(l)}(t) dt = \sum_{k=0}^{l-1} (-1)^k [g^{(k)}(t) y^{(l-1-k)}(t)]_{t=a}^{t=b} + (-1)^l \int_a^b g^{(l)}(t) y(t) dt. \quad (8)$$

The previous formula has been extended to the fractional order case in [48]. Hence, fractional integration by parts formulae can be given in the following lemma.

Lemma 3 [48] *Let $y, g \in \mathcal{C}^l(\mathbb{R})$ with $l \in \mathbb{N}$. Then, for any interval $[a, b] \subset \mathbb{R}$, we have:*

$$\int_a^b g(t) {}_R D_{a,t}^\alpha y(\cdot) dt = \int_a^b {}_C D_{t,b}^\alpha g(\cdot) y(t) dt, \quad (9)$$

where $-1 < \alpha < l = 0$. Moreover, we have:

$$\int_a^b g(t) {}_R D_{a,t}^\alpha y(\cdot) dt = \sum_{k=0}^{l-1} (-1)^k [g^{(k)}(t) {}_R D_{a,t}^{\alpha-1-k} y(\cdot)]_{t=a}^{t=b} + \int_a^b {}_C D_{t,b}^\alpha g(\cdot) y(t) dt, \quad (10)$$

where $l \in \mathbb{N}^*$ and $l-1 < \alpha < l$.

3. Main result

In this paper, we consider a class of signals satisfying the following differential equation:

$$\forall t \in I, \sum_{i=0}^N a_i y^{(i)}(t) = u(t), \quad (11)$$

where $y \in \mathcal{C}^N(I)$ with $N \in \mathbb{N}^*$ and $I = [a, b] \subset \mathbb{R}$. Moreover, u is assumed to be known, and $a_N \in \mathbb{R}^*$, $a_i \in \mathbb{R}$, for $i = 0, \dots, N-1$, are unknown. In the case where $u \equiv 0$, we assume $a_N = 1$. In the case where $u \neq 0$, we can consider u as an input of a linear system defined by (11), and y is the corresponding output.

In this section, we will propose fractional order differentiators for the left-sided Riemann-Liouville fractional derivatives of y both in continuous noise free case and in discrete noisy case. For this purpose, we begin with a generalization of classical modulating functions in the following subsection.

3.1. Generalized modulating functions

Definition 4 Let $[a, b] \subset \mathbb{R}$, $l, n \in \mathbb{N}$ with $n \leq l$, and g be a function satisfying the following properties:

$$(P_1) : g \in \mathcal{C}^{l+1}([a, b]);$$

$$(P_2) : g^{(i)}(a) = 0, \text{ for } i = 0, 1, \dots, l;$$

$$(P_3) : g^{(i)}(b) = 0, \text{ for } i = 0, 1, \dots, n, \text{ and } g^{(n+1)}(b) \neq 0, \text{ if } n < l.$$

Then, g is called $(l, n)^{th}$ order modulating function on $[a, b]$ (see, [45]). If g satisfies only the properties (P_1) and (P_2) for any $n \in \mathbb{N}$, i.e. $g(b) \neq 0$, then g is called $(l, -1)^{th}$ order modulating function on $[a, b]$. If $l = n$, then g is the classical l^{th} order modulating function on $[a, b]$ (see, [41]). If g satisfies the properties (P_1) , (P_2) and the following property:

$$(P_4) : g^{(i)}(b) = 0, \text{ for } i = 0, 1, \dots, l, \text{ except } i = n.$$

Then, g is called strict $(l, n-1)^{th}$ order modulating function on $[a, b]$.

Consequently, if g is a $(l-1)^{th}$ order modulating function on $[a, b]$, then the boundaries values in (8) and (10) can be canceled. If g is a strict $(l-1, n-1)^{th}$ order modulating function on $[a, b]$, then it remains only the boundary value $g^{(n)}(b)y^{(l-1-n)}(b)$ (resp. $g^{(n)}(b)_R D_{a,b}^{\alpha-1-n}y(\cdot)$) in (8) (resp. (10)).

3.2. Unknown parameter identification in continuous noise free case

Before giving fractional order differentiators, we first calculate the unknown coefficients in (11). Modulating functions method is a classical identification method for continuous-time systems (see, e.g. [40, 41, 42, 43]). The use of modulating functions allows to transform a differential equation of the analyzed signal into a sequence of algebraic integral equations. Then, parameters can be estimated by solving a linear system. In the following proposition, we apply this method to give integral formulae for the unknown coefficients.

Proposition 1 [41] *If $u \neq 0$ in (11), then let g_n , for $n = 0, \dots, L$, be a sequence of $(N - 1)^{th}$ order modulating functions on $[t - T, t]$ with $N \leq L$, $a + T \leq t \leq b$ and $0 < T \leq b - a$. The unknown coefficients can be given by solving the following linear system:*

$$Y_{t,T} \begin{pmatrix} a_0 \\ \vdots \\ a_N \end{pmatrix} = U_{t,T}, \quad (12)$$

where $Y_{t,T}(n+1, i+1) = (-1)^i \int_{t-T}^t g_n^{(i)}(\tau) y(\tau) d\tau$ and $U_{t,T}(n+1) = \int_{t-T}^t g_n(\tau) u(\tau) d\tau$, for $n = 0, \dots, L$ and $i = 0, \dots, N$.

Proof. Step 1. Multiplication and integration: By multiplying both sides of (11) by g_n and integrating from $t - T$ to t , we obtain: for $n = 0, \dots, L$,

$$\sum_{i=0}^N a_i \int_{t-T}^t g_n(\tau) y^{(i)}(\tau) d\tau = \int_{t-T}^t g_n(\tau) u(\tau) d\tau. \quad (13)$$

Step 2. Integration by parts: By applying the generalized integration by parts given in Lemma 2, we get: for $n = 0, \dots, L$,

$$\sum_{i=0}^N (-1)^i a_i \int_{t-T}^t g_n^{(i)}(\tau) y(\tau) d\tau = \int_{t-T}^t g_n(\tau) u(\tau) d\tau, \quad (14)$$

where the boundaries values are eliminated thanks to the properties of g_n . Consequently, this proof can be completed by solving the linear system given in (12). \blacksquare

We can see in Proposition 1 that by using the modulating functions method the unknown coefficients can be obtained using a sliding integration window of finite length. Moreover, we do not need to calculate the derivatives of y . Similar result can be also given using the algebraic parametric method (see, e.g. [33]). By using a similar way, we can obtain the following corollary.

Corollary 1 *If $u \equiv 0$ and $a_N = 1$ in (11), then let g_n , for $n = 0, \dots, L - 1$, be a sequence of $(N - 1)^{th}$ order modulating functions on $[t - T, t]$ with $N \leq L$, $a + T \leq t \leq b$ and $0 < T \leq b - a$. The unknown coefficients can be given by solving the following linear system:*

$$\hat{Y}_{t,T} \begin{pmatrix} a_0 \\ \vdots \\ a_{N-1} \end{pmatrix} = \begin{pmatrix} (-1)^{N+1} \int_{t-T}^t g_0^{(N)}(\tau) y(\tau) d\tau \\ \vdots \\ (-1)^{N+1} \int_{t-T}^t g_{L-1}^{(N)}(\tau) y(\tau) d\tau \end{pmatrix}, \quad (15)$$

where $\hat{Y}_{t,T}(n + 1, i + 1) = (-1)^i \int_{t-T}^t g_n^{(i)}(\tau) y(\tau) d\tau$, for $n = 0, \dots, L - 1$ and $i = 0, \dots, N - 1$.

Remark that if we apply generalized modulating functions in the proof of Proposition 1, then the boundary values at $\tau = t$ are not canceled. Thus, the integer order derivatives of y can be given. This is the idea of the generalized modulating functions for integer order numerical differentiation problem [45]. Bearing this idea in mind, we will give the fractional order derivatives of y using generalized modulating functions in the next subsection.

3.3. Exact fractional order differentiators in continuous noise free case

In this subsection, we give fractional order differentiators in continuous noise-free case. For this purpose, we first need to transfer the differential equation (11) into a fractional order differential equation.

Lemma 4 *Let $y \in \mathcal{C}^N(I)$ with $N \in \mathbb{N}^*$ satisfy the differential equation given in (11), then we have:*

$$\forall t \in I, \sum_{i=0}^N a_i {}_R D_{a,t}^{i-\beta} y(\cdot) = {}_R D_{a,t}^{-\beta} u(\cdot) + \sum_{i=1}^N a_i \sum_{j=0}^{i-1} \frac{(t-a)^{j-i+\beta}}{\Gamma(j+1-i+\beta)} y^{(j)}(a), \quad (16)$$

where $0 < \beta < 1$.

Proof. By using (1) with $l = 0$ and $\beta = -\alpha$, we can take the $-\beta^{th}$ order left-sided Riemann-Liouville fractional derivative to (11). Thus, we obtain:

$$\forall t \in I, \sum_{i=0}^N a_i \frac{1}{\Gamma(\beta)} \int_a^t (t-\tau)^{\beta-1} y^{(i)}(\tau) d\tau = \frac{1}{\Gamma(\beta)} \int_a^t (t-\tau)^{\beta-1} u(t) d\tau. \quad (17)$$

Then, according to (2), (17) becomes:

$$\forall t \in I, \sum_{i=0}^N a_i {}_C D_{a,t}^{i-\beta} y(\cdot) = {}_R D_{a,t}^{-\beta} u(\cdot). \quad (18)$$

Finally, this proof can be completed using (4). ■

Now, by using generalized modulating functions and the fractional integration by parts, we can give the following theorem.

Theorem 1 *Let h_n , for $n = 0, \dots, N-1$, be a sequence of strict $(N-1, n-1)^{th}$ order modulating functions on $[a, t]$ with $t \in I$. If h_n also satisfies the following property:*

$$(P_5) : \int_a^t (\tau-a)^{\beta-i} h_n(\tau) d\tau = 0, \text{ for } i = 1, 2, \dots, N, \text{ with } 0 < \beta < 1.$$

Then, the left-sided Riemann-Liouville fractional derivatives of y is given by: $\forall t \in I$,

$${}_R D_{a,t}^{-\beta} y(\cdot) = \frac{(-1)^{N-1}}{h_{N-1}^{(N-1)}(t) a_N} \left(\int_a^t {}_C D_{\tau,t}^{-\beta} h_{N-1}(\cdot) u(\tau) d\tau - \sum_{i=0}^N a_i \int_a^t {}_C D_{\tau,t}^{i-\beta} h_{N-1}(\cdot) y(\tau) d\tau \right), \quad (19)$$

and for $n = N-2, N-3, \dots, 0$,

$$\begin{aligned} {}_R D_{a,t}^{N-n-1-\beta} y(\cdot) &= \frac{(-1)^n}{h_n^{(n)}(t) a_N} \int_a^t {}_C D_{\tau,t}^{-\beta} h_n(\cdot) u(\tau) d\tau - \sum_{i=n+1}^{N-1} \frac{a_i}{a_N} {}_R D_{a,t}^{i-n-1-\beta} y(\cdot) \\ &\quad + \frac{1}{h_n^{(n)}(t) a_N} \sum_{i=0}^N (-1)^{n+1} a_i \int_a^t {}_C D_{\tau,t}^{i-\beta} h_n(\cdot) y(\tau) d\tau, \end{aligned} \quad (20)$$

where a_i , for $i = 0, \dots, N$, is given by Proposition 1 or Corollary 1.

Remark 1 If the order α of the derivative which we want to estimate is larger than N , then in order to apply Theorem 1 we need to differentiate Equation (11) ($[\alpha] - N$) times, where $[\alpha]$ denotes the smallest integer greater than α .

Proof of Theorem 1. Step 1. Multiplication and integration: By multiplying both sides of (16) by h_n and integrating from a to t , we obtain: for $n = 0, \dots, N-1, \forall t \in I$,

$$\sum_{i=0}^N a_i \int_a^t h_n(\tau) {}_R D_{a,\tau}^{i-\beta} y(\cdot) d\tau = \int_a^t h_n(\tau) {}_R D_{a,\tau}^{-\beta} u(\cdot) d\tau + \sum_{i=1}^N a_i \sum_{j=0}^{i-1} y^{(j)}(a) \int_a^t \frac{h_n(\tau) (\tau - a)^{j-i+\beta}}{\Gamma(j+1-i+\beta)} d\tau. \quad (21)$$

Step 2. Elimination of all the initial conditions: Since h_n satisfies the property (P_5) , all the unknown initial conditions $y^{(j)}(a)$ can be eliminated in (21). Thus, we get: $\forall t \in I$,

$$\sum_{i=0}^N a_i \int_a^t h_n(\tau) {}_R D_{a,\tau}^{i-\beta} y(\cdot) d\tau = \int_a^t h_n(\tau) {}_R D_{a,\tau}^{-\beta} u(\cdot) d\tau. \quad (22)$$

Step 3. Fractional integration by parts: By applying the fractional integration by parts given in Lemma 3, we get: $\forall t \in I$,

$$\begin{aligned} \int_a^t {}_C D_{\tau,t}^{-\beta} h_n(\cdot) u(\tau) d\tau &= \sum_{i=0}^N a_i \int_a^t {}_C D_{\tau,t}^{i-\beta} h_n(\cdot) y(\tau) d\tau \\ &+ \sum_{i=1}^N a_i \sum_{k=0}^{i-1} (-1)^k [h_n^{(k)}(\tau) {}_R D_{a,\tau}^{i-\beta-1-k} y(\cdot)]_{\tau=a}^{\tau=t}. \end{aligned} \quad (23)$$

Step 4. Elimination of all the boundaries values at $\tau = a$: Since h_n satisfies the property (P_2) with $l = N-1$, we have $h_n^{(i)}(a) = 0$, for $i = 0, \dots, N-1$. Hence, (23) becomes: $\forall t \in I$,

$$\begin{aligned} \int_a^t {}_C D_{\tau,t}^{-\beta} h_n(\cdot) u(\tau) d\tau &= \sum_{i=0}^N a_i \int_a^t {}_C D_{\tau,t}^{i-\beta} h_n(\cdot) y(\tau) d\tau \\ &+ \sum_{i=1}^N a_i \sum_{k=0}^{i-1} (-1)^k h_n^{(k)}(t) {}_R D_{a,t}^{i-\beta-1-k} y(\cdot). \end{aligned} \quad (24)$$

Then, all the boundaries values at $\tau = t$ in (24) can be given in the following matrix:

$$\begin{pmatrix} a_1 h_n^{(0)}(t) {}_R D_{a,t}^{-\beta} y(\cdot) & a_2 h_n^{(0)}(t) {}_R D_{a,t}^{1-\beta} y(\cdot) & \cdots & a_N h_n^{(0)}(t) {}_R D_{a,t}^{N-1-\beta} y(\cdot) \\ 0 & -a_2 h_n^{(1)}(t) {}_R D_{a,t}^{-\beta} y(\cdot) & \cdots & -a_N h_n^{(1)}(t) {}_R D_{a,t}^{N-2-\beta} y(\cdot) \\ 0 & 0 & \cdots & (-1)^2 a_N h_n^{(2)}(t) {}_R D_{a,t}^{N-3-\beta} y(\cdot) \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & \cdots & (-1)^{N-1} a_N h_n^{(N-1)}(t) {}_R D_{a,t}^{-\beta} y(\cdot) \end{pmatrix}. \quad (25)$$

Step 5. Calculation of the boundary values at $\tau = t$: Since h_n satisfies the property (P_4) with $l = N-1$, we have $h_n^{(i)}(t) = 0$, for $i = 0, \dots, N-1$, except $i = n$. Hence, all the rows in (25) are equal to 0, except the $(n+1)^{th}$ row. Thus, (24) becomes: for $n = 0, \dots, N-1, \forall t \in I$,

$$\int_a^t {}_C D_{\tau,t}^{-\beta} h_n(\cdot) u(\tau) d\tau = \sum_{i=0}^N a_i \int_a^t {}_C D_{\tau,t}^{i-\beta} h_n(\cdot) y(\tau) d\tau + (-1)^n h_n^{(n)}(t) \sum_{i=n+1}^N a_i {}_R D_{a,t}^{i-n-1-\beta} y(\cdot). \quad (26)$$

Consequently, this proof can be completed using (26). ■

We can see in Theorem 1 that the fractional order derivatives of y are simultaneous given in a recursive way. Inspired by Theorem 1, we can obtain the following corollary, where the fractional order derivatives of y are independently given.

Corollary 2 *Let f_n , for $n = 0, \dots, N - 1$, be a sequence of functions satisfying the properties (P_1) , (P_2) and (P_5) on $[a, t]$ with $l = N - 1$ and $t \in I$. If f_n also satisfies the following property:*

$$(P_6) : F_i(t) := \sum_{j=0}^{N-1-i} (-1)^j a_{i+1+j} f_i^{(j)}(t) = 0, \text{ for } i = 0, 1, \dots, N - 1, \text{ except } i = n.$$

Then, the left-sided Riemann-Liouville fractional derivatives of y can be given by: for $n = 0, 1, \dots, N - 1$, $\forall t \in I$,

$${}_R D_{a,t}^{n-\beta} y(\cdot) = \frac{1}{F_n(t)} \left(\int_a^t {}_C D_{\tau,t}^{-\beta} f_n(\cdot) u(\tau) d\tau - \sum_{i=0}^N a_i \int_a^t {}_C D_{\tau,t}^{i-\beta} f_n(\cdot) y(\tau) d\tau \right), \quad (27)$$

where $0 < \beta < 1$, a_i , for $i = 0, \dots, N$, is given by Proposition 1 or Corollary 1.

The proof of Corollary 2 is similar to the one of Theorem 1, except Step 5. The property (P_6) allows us to eliminate all the undesired boundary values at $\tau = t$ in the diagonals of (25). In Appendix, we will give two classes of generalized modulating functions satisfying respectively the properties required in Theorem 1 and Corollary 2.

According to Theorem 1 and Corollary 2, the left-sided Riemann-Liouville fractional derivatives of y are exactly given by integral formulae. Unlike the improper integral in the definition of the left-sided Riemann-Liouville fractional given in (1), the proposed integral formulae can be proper by choosing appropriate modulating functions. Consequently, the proposed fractional order differentiators do not contain any source of errors in continuous noise free case. Moreover, they can be used for on-line applications.

Similarly, if we apply $\{f_n(a + t - \cdot)\}$ as generalized modulating functions on $[a, t]$ in the proof of Theorem 1, where $\{f_n(\cdot)\}$ are given in Corollary 2, then the initial conditions at $\tau = a$ can be given by integral formulae. Then, by using Corollary 2 and Equation (4), the left-sided Caputo fractional derivatives of y can be also given. This is out of the scope of this paper.

3.4. Digital fractional order differentiators in noisy case

From now on, let y^ϖ be a discrete noisy observation of y on $I = [a, b]$:

$$y^\varpi(t_i) = y(t_i) + \varpi(t_i), \quad (28)$$

where $t_i = a + iT_s$, for $i = 0, 1, \dots, M$, with an equidistant sampling period $T_s = \frac{b-a}{M}$. Moreover, the noise $\{\varpi(t), t \in I\}$ is assumed to be a continuous stochastic process satisfying the following conditions:

(C_1) : for any $s, t \in I$, $s \neq t$, $\varpi(s)$ and $\varpi(t)$ are independent;

(C_2) : the mean value function of $\{\varpi(t), t \in I\}$ denoted by $\mathbb{E}[\cdot]$ is equal to zero;

(C_3) : the variance function of $\{\varpi(t), t \in I\}$ denoted by $\text{Var}[\cdot]$ is bounded on I , i.e. $\exists \delta \in \mathbb{R}_+, \forall t \in I, \text{Var}[\varpi(t)] \leq \delta$.

Note that a zero-mean white Gaussian noise satisfies these conditions.

In order to estimate the left-sided fractional derivatives of y using its discrete noisy observation y^ϖ , we apply the integral formulae given in Theorem 1 or Corollary 2. Since y^ϖ is a discrete measurement and the integrals in the formulae can be proper, we apply a numerical integration method to approximate the integrals so as to obtain digital fractional order differentiators. Let us denote the integrals involving y in Equations (19), (20) and (27) as follows:

$$I_q^y(t) := \int_a^t q(\tau) y(\tau) d\tau, \quad (29)$$

where q denotes the right-sided Caputo fractional derivatives of the used modulating functions. Hence, I_q^y can be approximated in the discrete case by:

$$I_q^{y,i} := T_s \sum_{j=0}^i w_j q(t_j) y(t_j), \quad (30)$$

where $w_i \in \mathbb{R}_+$ is the weights for a given numerical integration method. By using the discrete noisy observation y^ϖ , we get:

$$I_q^{y^\varpi,i} = I_q^{y,i} + e_q^{\varpi,i}, \quad (31)$$

where $e_q^{\varpi,i} := T_s \sum_{j=0}^i w_j q(t_j) \varpi(t_j)$. Thus, the integral $I_q^y(t)$ is subject to two sources of errors:

- the numerical error which comes from the numerical integration method;
- the noise error contributions $e_q^{\varpi,i}$.

Similarly, we can deduce that the integral formulae given in Proposition 1 and Corollary 1 for the unknown coefficients contain also these two sources of errors. Consequently, the proposed digital fractional order differentiators contain the numerical error and the noise error contributions in the noisy case. It is well known that the numerical error converges to zero when $T_s \rightarrow 0$. In the following proposition, we show the convergence of the noise error contributions when $T_s \rightarrow 0$.

Proposition 2 *Let $\{\varpi(t_i)\}$ be a sequence of $\{\varpi(t), t \in I\}$ with an equidistant sampling period T_s , where $\{\varpi(t), t \in I\}$ is a continuous stochastic process satisfying conditions $(C_1) - (C_3)$. Assume that $q \in \mathcal{L}^2([a, t])$, then we have:*

$$e_q^{\varpi,i} \xrightarrow[T_s \rightarrow 0]{\mathcal{L}^2([a,t])} 0, \quad (32)$$

where $e_q^{\varpi,i}$ is given by (31).

The proof of the previous proposition can be obtained using a similar way to Theorem 1 in [36]. In fact, using (C_1) , (C_2) and (C_3) we obtain: $\mathbb{E}[e_q^{\varpi,i}] = 0$ and

$$\mathbb{E} \left[(e_q^{\varpi,i})^2 \right] = \text{Var} \left[e_q^{\varpi,i} \right] \leq T_s \delta \left(T_s \sum_{j=0}^i w_j^2 q^2(t_j) \right). \quad (33)$$

Hence, if $q \in \mathcal{L}^2([a, t])$ then the convergence in Equation (32) can be obtained. A similar result has been shown using non-standard analysis in [25, 26]. Consequently, we can reduce both the numerical

error and the noise error contributions in our digital fractional order differentiators by decreasing the sampling period T_s .

When the sampling period is set, on the one hand the numerical error can be bounded by the well-known error bounds for numerical integration methods [49], on the other hand the noise error contribution $e_q^{\varpi,i}$ can be bounded using the Bienaymé-Chebyshev inequality:

$$\forall \gamma \in \mathbb{R}_+^*, \Pr \left(|e_q^{\varpi,i}| < \gamma (\text{Var}[e_q^{\varpi,i}])^{\frac{1}{2}} \right) > 1 - \frac{1}{\gamma^2}, \quad (34)$$

i.e. the probability for $|e_q^{\varpi,i}|$ to be smaller than $\gamma (\text{Var}[e_q^{\varpi,i}])^{\frac{1}{2}}$ is larger than $1 - \frac{1}{\gamma^2}$. Thus, we deduce from (33) and (34) the following error bound:

$$|e_q^{\varpi,i}| \stackrel{p_\gamma}{<} \gamma T_s \left(\delta \sum_{j=0}^i w_j^2 q^2(t_j) \right)^{\frac{1}{2}}, \quad (35)$$

where $a \stackrel{p_\gamma}{<} b$ means that the probability for a real number b to be larger than an other real number a is equal to p_γ with $p_\gamma > 1 - \frac{1}{\gamma^2}$. In particular, if ϖ is a white Gaussian noise, then according to the three-sigma rule, we have:

$$|e_q^{\varpi,i}| \stackrel{p_\gamma}{\leq} \gamma T_s \left(\delta \sum_{j=0}^i w_j^2 q^2(t_j) \right)^{\frac{1}{2}}, \quad (36)$$

where $p_1 = 68.26\%$, $p_2 = 95.44\%$ and $p_3 = 99.73\%$, for $\gamma = 1, 2, 3$, respectively.

4. Simulation results

In this section, we give some numerical results to show the accuracy and robustness of the proposed digital fractional order differentiators. We assume that $y^\varpi(t_i) = y(t_i) + \varpi(t_i)$ is a discrete noisy observation defined in (28) with $I = [0, 10]$ and $T_s = 10^{-3}$, where the noise $\{\varpi(t_i)\}$ is simulated from a zero-mean white Gaussian *iid* sequence, and the variance is adjusted such that the signal-to-noise ratio $\text{SNR} = 10 \log_{10} \left(\frac{\sum |y^\varpi(t_i)|^2}{\sum |\varpi(t_i)|_2^2} \right)$ is equal to $\text{SNR} = \rho$ dB with $\rho \in \mathbb{R}_+^*$. In the following subsections, we assume y is a polynomial signal and a sinusoidal signal respectively.

4.1. Polynomial signal

In this subsection, we consider a second order polynomial given by:

$$\forall t \in I, y(t) = p_2 t^2 + p_1 t + p_0, \quad (37)$$

where $p_2, p_1, p_0 \in \mathbb{R}_+^*$. Hence, y satisfies the following third order differential equation:

$$\forall t \in I, y^{(3)}(t) = 0. \quad (38)$$

Moreover, the left-side Riemann-Liouville fractional derivative of y can be given using the following formula ([3], p. 72):

$$\forall t \in I, {}_R D_{0,t}^\alpha (\cdot)^n = \frac{\Gamma(n+1)}{\Gamma(n+1-\alpha)} t^{n-\alpha}, \quad \alpha \in \mathbb{R}_+ \setminus \mathbb{N}. \quad (39)$$

Since there is no unknown parameter in (38), we can directly apply Theorem 1. Then, we obtain:
 $\forall t \in I$,

$${}_R D_{0,t}^{1-\beta} y(\cdot) = \frac{1}{h_1^{(1)}(t)} \int_0^t {}_C D_{\tau,t}^{3-\beta} h_1(\cdot) y(\tau) d\tau, \quad (40)$$

$${}_R D_{a,t}^{2-\beta} y(\cdot) = -\frac{1}{h_0(t)} \int_0^t {}_C D_{\tau,t}^{3-\beta} h_0(\cdot) y(\tau) d\tau, \quad (41)$$

where $0 < \beta < 1$, h_0 and h_1 are given by Proposition 3 with $N = 3$. Consequently, we can estimate ${}_R D_{0,t}^\alpha y(\cdot)$ for any $\alpha \in]0, 1[\cup]1, 2[$.

Example 1. In this example, we take $p_2 = p_0 = 1$, $p_1 = -10$ and $\rho = 30$ (SNR = 30 dB). The corresponding y and y^ϖ are shown in Fig. 1.

We are going to estimate ${}_R D_{0,t_i}^{0.5} y(\cdot)$ and ${}_R D_{0,t_i}^{1.5} y(\cdot)$ for $t_i \in [0.5, 10]$. For this purpose, we apply the trapezoidal numerical integration method to approximate the integrals in (40) and (41) with the noisy observation y^ϖ . The obtained estimations and the corresponding absolute estimation errors are given in Fig. 2 and Fig. 3. We give in Fig. 4 the absolute estimation errors obtained in the noise-free case, which correspond to the numerical errors. Consequently, we can see that the noise error is relatively large in the beginning, when t is larger than 4, we have good results both in the noisy case and in the noise free case. Moreover, we can observe that the numerical errors are much smaller than the noise error contributions.

4.2. Sinusoidal signal

In this subsection, we consider a sinusoidal signal with the following form:

$$\forall t \in I, y(t) = A \sin(\omega t + \phi), \quad (42)$$

where the parameters $A \in \mathbb{R}_+^*$, $\omega \in \mathbb{R}_+^*$ and $-\frac{1}{2}\pi < \phi < \frac{1}{2}\pi$ are unknown. Hence, y satisfies the following harmonic oscillator equation:

$$\forall t \in I, \ddot{y}(t) + \omega^2 y(t) = 0. \quad (43)$$

Moreover, the left-side Riemann-Liouville fractional derivative of y can be given using the expansion of y and the linearity of the Riemann-Liouville fractional derivative ([3], p. 91):

$$\forall t \in I, {}_R D_{0,t}^\alpha y(\cdot) = A \cos \phi {}_R D_{0,t}^\alpha \sin(\omega \cdot) + A \sin \phi {}_R D_{0,t}^\alpha \cos(\omega \cdot) \quad (44)$$

with

$${}_R D_{0,t}^\alpha \sin(\omega \cdot) = \frac{\omega t^{1-\alpha}}{\Gamma(2-\alpha)} {}_1F_2 \left(1; \frac{1}{2}(2-\alpha), \frac{1}{2}(3-\alpha); -\frac{1}{4}\omega^2 t^2 \right), \quad (45)$$

$${}_R D_{0,t}^\alpha \cos(\omega \cdot) = \frac{t^{-\alpha}}{\Gamma(1-\alpha)} {}_1F_2 \left(1; \frac{1}{2}(1-\alpha), \frac{1}{2}(2-\alpha); -\frac{1}{4}\omega^2 t^2 \right), \quad (46)$$

where ${}_1F_2$ is the generalized hypergeometric function (see [50] p. 83, p. 303 and pp. 317-318).

Step 1. Estimation of the unknown parameter: According to Corollary 1, the unknown frequency ω^2 can be given using a sliding integration window as follows:

$$\forall t \in [T, b], \omega^2 = -\frac{\int_{t-T}^t \ddot{g}_{t,T}(\tau) y(\tau) d\tau}{\int_{t-T}^t g_{t,T}(\tau) y(\tau) d\tau}, \quad (47)$$

where $g_{t,T}$ is a first order modulating functions on $[t-T, t]$ with $0 < T \leq b$. Then, it can be estimated in the discrete noisy case by: for $i = m, \dots, M$,

$$\tilde{\omega}^2(t_i) := -\frac{I_{\dot{g}_{t_i,T}}^{y^\varpi}}{I_{g_{t_i,T}}^{y^\varpi}}, \quad (48)$$

where $T = mT_s$ with $1 \leq m \leq M$, $I_{\dot{g}_{t_i,T}}^{y^\varpi}$ and $I_{g_{t_i,T}}^{y^\varpi}$ are respectively the approximations of the integrals obtained in (47) by applying the trapezoidal numerical integration method with the noisy observation y^ϖ . Similar estimators have been also obtained using the algebraic parametric method in [32, 37].

Remark that if $I_{g_{t_i,T}}^{y^\varpi} = 0$, then there is a singular value in (48). In order to solve this problem, we use the following weighted least square criterion as done in [44]: for $i = m, \dots, M$,

$$\min_{\theta_i \in \mathbb{R}} J(\theta_i) = \frac{1}{2} \sum_{j=m}^i \nu^{i+1-j} \left(I_{\dot{g}_{t_j,T}}^{y^\varpi} + I_{g_{t_j,T}}^{y^\varpi} \theta_i \right)^2, \quad (49)$$

where $\theta_i := \tilde{\omega}^2(t_i)$, and $\nu \in]0, 1]$ which represents a forgetting factor to exponentially discard the “old” data in the recursive schema. By solving $\frac{dJ(\theta_i)}{d\theta_i} = 0$, we can find the value of θ_i which minimizes the criterion (49): for $i = m, \dots, M$,

$$\theta_i = -\frac{\sum_{j=m}^i \nu^{i+1-j} I_{\dot{g}_{t_j,T}}^{y^\varpi} I_{g_{t_j,T}}^{y^\varpi}}{\sum_{j=m}^i \nu^{i+1-j} \left(I_{g_{t_j,T}}^{y^\varpi} \right)^2}. \quad (50)$$

Moreover, by using a similar way as done in [44], we obtain the following recursive algorithm:

$$\theta_{i+1} = \frac{\nu}{\mu_{i+1}} \left(\mu_i \theta_i - I_{\dot{g}_{t_{i+1},T}}^{y^\varpi} I_{g_{t_{i+1},T}}^{y^\varpi} \right), \quad i = m, \dots, M, \quad (51)$$

where $\mu_i = \sum_{j=m}^i \nu^{i+1-j} \left(I_{g_{t_j,T}}^{y^\varpi} \right)^2$ which can be recursively calculated by $\mu_{i+1} = \nu \left(\mu_i + \left(I_{g_{t_{i+1},T}}^{y^\varpi} \right)^2 \right)$.

Step 2. Estimation of the fractional order derivatives: We want to estimate ${}_R D_{0,t}^\alpha y(\cdot)$ for any $\alpha \in]0, 1[\cup]1, 2[$. According to Remark 1, we need to take once differentiation to (43). Hence, we get:

$$\forall t \in I, \quad y^{(3)}(t) + \omega^2 y^{(1)}(t) = 0. \quad (52)$$

Then, by applying Corollary 2, we obtain:

$${}_R D_{0,t}^{1-\beta} y(\cdot) = \frac{1}{f_1^{(1)}(t)} \left(\int_0^t {}_C D_{\tau,t}^{3-\beta} f_1(\cdot) y(\tau) d\tau + \omega^2 \int_0^t {}_C D_{\tau,t}^{1-\beta} f_1(\cdot) y(\tau) d\tau \right), \quad (53)$$

$${}_R D_{0,t}^{2-\beta} y(\cdot) = -\frac{1}{f_2(t)} \left(\int_0^t {}_C D_{\tau,t}^{3-\beta} f_2(\cdot) y(\tau) d\tau + \omega^2 \int_0^t {}_C D_{\tau,t}^{1-\beta} f_2(\cdot) y(\tau) d\tau \right), \quad (54)$$

where $0 < \beta < 1$, f_1 and f_2 are given by Corollary 3 with $N = 3$, $a_3 = 1$, $a_1 = \omega^2$ and $a_2 = a_0 = 0$. Consequently, we can estimate ${}_R D_{0,t}^\alpha y(\cdot)$ for any $\alpha \in]0, 1[\cup]1, 2[$.

Example 2. In this example, we take $A = 3$, $\omega = 5$, $\phi = 0.5$ and $\rho = 15$ (SNR = 15 dB). The corresponding y and y^ϖ are shown in Fig. 5(a). The trapezoidal numerical integration method is also applied to approximate the integrals with the noisy observation y^ϖ . We first estimate the unknown frequency using (51) with $T = 0.5$ and $\nu = 1$. The obtained relative error is given in Fig. 5(b). Then, we estimate ${}_R D_{0,t_i}^{0.5} y(\cdot)$ and ${}_R D_{0,t_i}^{1.5} y(\cdot)$ for $t_i \in [0.5, 10]$. The obtained estimations and the corresponding absolute estimation errors are given in Fig. 6 and Fig. 7. We give in Fig. 8 the absolute estimation errors obtained in the noise-free case, which correspond to the numerical errors. Consequently, we can see that the noise error is relatively large in the beginning, when t become larger, we have good results both in the noisy case and in the noise free case. Moreover, as shown in the previous example, the numerical errors are much smaller than the noise error contributions. However, since the used modulating functions are polynomials, the noise error can increase with respective to t . In order to solve this problem, the *Short-Memory Principle* can be applied (see [3], p. 203). Otherwise, we can consider other types of modulating functions. This is out of the scope of this paper.

5. Conclusions

In this paper, robust fractional order differentiators have been proposed in the time domain for a class of signals satisfying a linear differential equation with unknown parameters. We have first generalized the classical modulating function method which has been used to estimate the unknown parameters. Then, by applying two different classes of generalized modulating functions and the fractional integration by parts formula, the left-sided Riemann-Liouville fractional derivative of the considered signal have been given by integral formulae by two different ways respectively. These formulae have been considered as proposed fractional order differentiators which do not contain any sources of errors in continuous noise free case. Digital fractional order differentiators have been deduced using a numerical integration method in discrete noisy case. They can be used for on-line applications to estimate the left-sided Riemann-Liouville fractional derivative with an arbitrary order. There are two sources of errors for these digital fractional order differentiators: the numerical error and the noise error contribution. On the one hand, since the integrals in the proposed fractional order differentiators can be proper by choosing appropriate modulating functions, the numerical error can be much smaller than the noise error contribution. On the other hand, since the integrals can be considered as a low-pass filter, it has been shown that the noise error contributions due to a class of stochastic processes can be reduced when the sampling period decreases. Moreover, some error bounds have been given for the noise error contributions. Finally, two numerical examples have been given to show the accuracy and robustness of the proposed fractional order differentiators. In these examples, we have only considered polynomials as generalized modulating functions which have been constructed in Appendix. The other types of generalized modulating functions and their influences to the noise error contribution will be studied in a future work.

6. Appendix

There exists several kinds of modulating functions in the literatures (see, e.g. [41]). Unlike classical integer order derivatives, the fractional order derivatives of the existing modulating functions usually cannot be formally calculated. For this reason, we consider polynomials whose fractional order derivatives are easy to calculate. Moreover, inspired by the algebraic parametric method it is easy to find polynomials satisfying the properties of generalized modulating functions.

Proposition 3 Let $[a, t] \subset \mathbb{R}$, $n \in \mathbb{N}$, $N \in \mathbb{N}^*$ with $n \leq N - 1$, and h_n be a polynomial with the following form:

$$h_n(\tau) = \sum_{i=0}^{2N-1} c_i t^{2N-1-i} (\tau - a)^{N+i}, \quad (55)$$

where the coefficient vector $(c_0, \dots, c_{2N-1})^T$ is the solution of the following system:

$$A_n \begin{pmatrix} c_0 \\ \vdots \\ c_{2N-1} \end{pmatrix} = I_n, \quad (56)$$

where for $j = 0, \dots, 2N - 1$, $I_n(n) = 1$, $I_n(j) = 0$ with $j \neq n$, and for $i = 0, \dots, 2N - 1$,

$$A_n(j, i) = \begin{cases} \frac{(N+i)!}{(N+i-j)!} t^{2N-1-i} (t-a)^{N+i-j}, & \text{for } j = 0, \dots, N-1, \\ \frac{1}{2N+i+\beta-j} t^{2N-1-i} (t-a)^{2N+i+\beta-j}, & \text{for } j = N, \dots, 2N-1. \end{cases} \quad (57)$$

Then, h_n is a strict $(N-1, n-1)^{th}$ order modulating function satisfying the property (P_5) on $[a, t]$.

Proof. By calculating the j^{th} order derivative of h_n , for $j = 0, \dots, N-1$, we obtain:

$$h_n^{(j)}(\tau) = \sum_{i=0}^{2N-1} c_i \frac{(N+i)!}{(N+i-j)!} t^{2N-1-i} (\tau - a)^{N+i-j}. \quad (58)$$

Hence, g_n satisfies the properties (P_1) and (P_2) on $[a, t]$ with $l = N - 1$. Then, we calculate the following integral: for $j = 1, \dots, N$,

$$\int_a^t (\tau - a)^{\beta-j} g_n(\tau) d\tau = \sum_{i=0}^{2N-1} c_i \frac{t^{2N-1-i} (t-a)^{N+i+\beta-j+1}}{N+i+\beta-j+1}. \quad (59)$$

Consequently, if $(c_0, \dots, c_{2N-1})^T$ is the solution of the system (56), then g_n satisfies also the properties (P_4) and (P_5) on $[a, t]$. ■

Let us remark that if $a = 0$ in Proposition 3, then the power of t in each row of A_n is equal. Hence, A_n can be simplified by the following form:

$$\hat{A}_n(j, i) = \begin{cases} \frac{(N+i)!}{(N+i-j)!}, & \text{for } j = 0, \dots, N-1, \\ \frac{1}{2N+i+\beta-j}, & \text{for } j = N, \dots, 2N-1. \end{cases} \quad (60)$$

Consequently, the coefficient vector $(c_0, \dots, c_{2N-1})^T$ dose not depend on t such that we need only to solve the linear system (56) once for every t .

In a similar way, we can give the generalized modulating functions satisfying the properties (P_1) , (P_2) , (P_5) and (P_6) required in Corollary 2.

Corollary 3 Let $[a, t] \subset \mathbb{R}$, $n \in \mathbb{N}$, $N \in \mathbb{N}^*$ with $n \leq N - 1$, and f_n be a polynomial with the following form:

$$f_n(\tau) = \sum_{i=0}^{2N-1} d_i (\tau - a)^{N+i}, \quad (61)$$

where the coefficient vector $(d_0, \dots, d_{2N-1})^T$ is the solution of the following system:

$$B_n \begin{pmatrix} d_0 \\ \vdots \\ d_{2N-1} \end{pmatrix} = I_n, \quad (62)$$

where for $j = 0, \dots, 2N - 1$, $I_n(n) = 1$, $I_n(j) = 0$ with $j \neq n$, and for $i = 0, \dots, 2N - 1$,

$$B_n(j, i) = \begin{cases} \sum_{k=0}^{N-1-j} (-1)^k a_{j+1+k} \frac{(N+i)!}{(N+i-k)!} (t-a)^{N+i-k}, & \text{for } j = 0, \dots, N-1, \\ \frac{1}{2N+i+\beta-j} (t-a)^{2N+i+\beta-j}, & \text{for } j = N, \dots, 2N-1. \end{cases} \quad (63)$$

Then, f_n is a generalized modulating function satisfying the properties (P_1) , (P_2) , (P_5) and (P_6) on $[a, t]$.

References

- [1] B. Ross, The development of fractional calculus 1695-1900, *Hist. Math.*, 4, 1, pp. 75-89, 1977.
- [2] K.B. Oldham and J. Spanier, *The Fractional Calculus*, Academic Press, New York 1974.
- [3] I. Podlubny, *Fractional Differential Equations*, Academic Press, New York, NY, USA, 1999.
- [4] A.A. Kilbas, H.M. Srivastava and J.J. Trujillo, *Theory and Applications of Fractional Differential Equations*, vol. 204 of North-Holland Mathematics Studies, Elsevier, Amsterdam, The Netherlands, 2006.
- [5] A. Oustaloup, B. Mathieu and P. Lanusse, The CRONE control of resonant plants: application to a flexible transmission, *European Journal of Control*, vol. 1, no. 2, pp. 113-121, 1995.
- [6] A. Oustaloup, J. Sabatier and X. Moreau, From fractal robustness to the CRONE approach, in *Proc. ESAIM: Proceedings*, pp. 177-192, Dec. 1998.
- [7] A. Oustaloup, J. Sabatier and P. Lanusse, From fractal robustness to the CRONE control, *FCAA*, vol. 1, no. 2, pp. 1-30, Jan. 1999.
- [8] V. Pommier, J. Sabatier, P. Lanusse and A. Oustaloup, CRONE control of a nonlinear hydraulic actuator, *Control Engineering Practice*, vol. 10, pp. 391-402, Jan. 2002.
- [9] B. Mathieu, P. Melchior, A. Oustaloup, and Ch. Ceyral, Fractional differentiation for edge detection, *Signal Processing*, vol. 83, pp. 2421-2432, 2003.
- [10] B. Guo, J. Li, and H. Zmuda, A new FDTD formulation for wave propagation in biological media with colecole model, *IEEE Microwave and Wireless Components Letters*, vol. 16, no. 12, pp. 633-635, 2006.
- [11] M. Benmalek, and A. Charef, Digital fractional order operators for R-wave detection in electrocardiogram signal, *IET Signal Processing*, vol. 3, no. 5, pp. 381-391, 2009.

- [12] R. Magin, M.D. Ortigueira, I. Podlubny and J. Trujillo, On the fractional signals and systems, *Signal Processing*, vol. 91, pp. 350-371, 2011.
- [13] J.A.T. Machado, Calculation of fractional derivatives of noisy data with genetic algorithms, *Nonlinear Dynamics*, vol. 57, pp. 253-260, 2009.
- [14] J.A.T. Machado, Exploiting sensor redundancy for the calculation of fractional derivatives in the presence of noise, *Signal Processing*, vol. 92, pp. 204-209, 2012.
- [15] D.L. Chen, Y.Q. Chen and D.Y. Xue, Digital Fractional Order Savitzky-Golay Differentiator, *IEEE Transactions on Circuits and Systems II: Express Briefs*, vol. 58, no. 11, pp. 758-762, 2011.
- [16] D.Y. Liu, O. GIBARU, W. Perruquetti and T.M. Laleg-Kirati, Fractional order differentiation by integration with Jacobi polynomials, in *Proc. 51st IEEE Conference on Decision and Control*, Hawaii, USA, 2012.
- [17] D.Y. Liu, O. GIBARU, W. Perruquetti and T.M. Laleg-Kirati, Fractional order differentiation by integration and error analysis in noisy environment, submitted to *IEEE Transactions on Automatic Control*.
- [18] D.Y. Liu, T.M. Laleg-Kirati, O. GIBARU and W. Perruquetti, Fractional Order Numerical Differentiation with B-Spline Functions, *The International Conference on Fractional Signals and Systems*, Gent, Belgium, 2013.
- [19] A. Savitzky and M.J.E. Golay, Smoothing and differentiation of data by simplified least squares procedures, *Anal. Chem.*, vol. 36, no. 8, pp. 1627-1639, 1964.
- [20] D.Y. Liu, O. GIBARU and W. Perruquetti, Differentiation by integration with Jacobi polynomials, *J. Comput. Appl. Math.*, vol. 235, no. 9, pp. 3015-3032, 2011.
- [21] S. Ibrir and S. Diop, A numerical procedure for filtering and efficient high-order signal differentiation, *Internat. J. Appl. Math. Comput. Sci.*, vol. 14, pp. 201-208, 2004.
- [22] M. Fliess and H. Sira-Ramírez, Reconstructeurs d'états, *C.R. Acad. Sci. Paris, Ser. I*, vol. 338, pp. 91-96, 2004.
- [23] Y. Tian, T. Floquet and W. Perruquetti, Fast state estimation in linear time-varying systems: an algebraic approach, in *Proc. 47th IEEE Conference on Decision and Control*, Cancun Mexique, 2008.
- [24] Y. Tian, T. Floquet and W. Perruquetti, Fast state estimation in linear time-invariant systems: an algebraic approach, in *16th Mediterranean Conference on Control and Automation (MED'08)*, Ajaccio, Corsica, France, 2008.
- [25] M. Fliess, Analyse non standard du bruit, *C.R. Acad. Sci. Paris, Ser. I*, vol. 342, pp. 797-802, 2006.
- [26] M. Fliess, Critique du rapport signal à bruit en communications numériques – Questioning the signal to noise ratio in digital communications, *International Conference in Honor of Claude Lobry, Revue africaine d'informatique et de Mathématiques appliquées*, vol. 9, pp. 419-429, 2008.

- [27] M. Fliess and H. Sira-Ramírez, An algebraic framework for linear identification, *ESAIM Control Optim. Calc. Variat.*, vol. 9, pp. 151-168, 2003.
- [28] M. Mboup, C. Join and M. Fliess, Numerical differentiation with annihilators in noisy environment, *Numerical Algorithms*, vol. 50, no. 4, pp. 439-467, 2009.
- [29] M. Mboup, C. Join and M. Fliess, A revised look at numerical differentiation with an application to nonlinear feedback control, in *Proc. 15th Mediterranean conference on Control and automation (MED'07)*, Athenes, Greece, 2007.
- [30] D.Y. Liu, O. Gibaru and W. Perruquetti, Error analysis of Jacobi derivative estimators for noisy signals, *Numerical Algorithms*, vol. 58, no. 1, pp. 53-83, 2011.
- [31] D.Y. Liu, O. Gibaru and W. Perruquetti, Convergence Rate of the Causal Jacobi Derivative Estimator, *Curves and Surfaces 2011, LNCS 6920 proceedings*, pp. 45-55, 2011.
- [32] J.R. Trapero, H. Sira-Ramírez and V.F. Battle, An algebraic frequency estimator for a biased and noisy sinusoidal signal, *Signal Processing*, vol. 87, pp. 1188-1201, 2007.
- [33] M. Mboup, Parameter estimation for signals described by differential equations, *Applicable Analysis*, vol. 88, pp. 29-52, 2009.
- [34] R. Ushirobira, W. Perruquetti, M. Mboup and M. Fliess, Algebraic parameter estimation of a multi-sinusoidal waveform signal from noisy data, in *Proc. 2013 European Control Conference*, Zurich, Switzerland, 2013.
- [35] W. Perruquetti, P. Fraise, M. Mboup and R. Ushirobira, An algebraic approach for Humane posture estimation in the sagittal plane using accelerometer noisy signal, in *Proc. 51st IEEE Conference on Decision and Control*, Hawaii, USA, 2012.
- [36] D.Y. Liu, O. Gibaru and W. Perruquetti, Parameters estimation of a noisy sinusoidal signal with time-varying amplitude, in *Proc. 19th Mediterranean conference on Control and automation (MED'11)*, Corfu, Greece, 2011.
- [37] D.Y. Liu, O. Gibaru, W. Perruquetti, M. Fliess and M. Mboup, An error analysis in the algebraic estimation of a noisy sinusoidal signal, in *Proc. 16th Mediterranean conference on Control and automation (MED'08)*, Ajaccio, France, 2008.
- [38] D.Y. Liu, O. Gibaru and W. Perruquetti, Non-asymptotic fractional order differentiators via an algebraic parametric method, 1st International Conference on Systems and Computer Science, Villeneuve d'ascq, France, 2012.
- [39] N. Gehring and J. Rudolph, An Algebraic Approach for Identification of Linear Systems with Fractional Derivatives, arXiv:1302.4071, 2013.
- [40] M. Shinbrot, On the analysis of linear and nonlinear dynamic systems from transient-response data, National Advisory Committee for Aeronautics NACA, Technical Note 3288, Washington, 1954.
- [41] H.A. Preising and D.W.T. Rippin, Theory and application of the modulating function method. I: Review and theory of the method and theory of the splinetype modulating functions, *Computers and Chemical Engineering*, vol. 17, pp. 1-16, 1993.

- [42] T.B. Co and S. Ungarala, Batch scheme recursive parameter estimation of continuous-time system using the modulating functions method, *Automatica*, vol. 33, no. 6, pp. 1185-1191, 1997.
- [43] H. Unbehauen and G.P. Rao, A review of identification in continuous-time systems, *Annual Reviews in Control*, vol. 222, pp. 145-171, 1998.
- [44] G. Fedele and L. Coluccio, A recursive scheme for frequency estimation using the modulating functions method, *Appl. Math. Comput.*, vol. 216, pp. 1393-1400, 2010.
- [45] D.Y. Liu, T.M. Laleg-Kirati, O. Gibaru and W. Perruquetti, Identification of fractional order systems using modulating functions method, in *Proc. 2013 American Control Conference*, Washington, DC, USA, 2013.
- [46] D.Y. Liu, T.M. Laleg-Kirati, Y. Tian, W. Perruquetti and O. Gibaru, Non-asymptotic state estimation for a class of linear time-varying systems with unknown inputs, submitted to *The 19th World Congress of the International Federation of Automatic Control*, Cape Town, South Africa, 2014.
- [47] M. Abramowitz and I.A. Stegun, editors, *Handbook of mathematical functions*, GPO, 1965.
- [48] I. Podlubny and Y.Q. Chen, Adjoint fractional differential expressions and operators, in *Proc. the ASME 2007 International Design Engineering Technical Conferences & Computers and Information in Engineering Conference IDETC/CIE 2007*, Las Vegas, NV, September 4-7, 2007.
- [49] A. Ralston, A first course in numerical analysis, McGraw-Hill, New York, 1965.
- [50] K.S. Miller and B. Ross, *An Introduction to the Fractional Calculus and Fractional Differential Equations*, Wiley, New York, 1993.






Figure 1: Discrete polynomial signal and noisy discrete polynomial in Example 1.




(a) $\alpha = 0.5$.




(b) $\alpha = 1.5$.

Figure 2: Estimations in noisy case.




(a) $\alpha = 0.5$.




(b) $\alpha = 1.5$.

Figure 3: Absolute estimation errors in noisy case.




(a) $\alpha = 0.5$.




(b) $\alpha = 1.5$.

Figure 4: Absolute estimation errors in noise free case (numerical errors).




(a) Discrete sinusoidal signals.




(b) Relative estimation error of ω^2 in noisy case.

Figure 5: Example 2.




(a) $\alpha = 0.5$.




(b) $\alpha = 1.5$.

Figure 6: Estimations in noisy case.




(a) $\alpha = 0.5$.




(b) $\alpha = 1.5$.

Figure 7: Absolute estimation errors in noisy case.



(a) $\alpha = 0.5$.



(b) $\alpha = 1.5$.

Figure 8: Absolute estimation errors in noise free case (numerical errors).