



HAL
open science

Unit Sliding Mode Control: Revised

Andrey Polyakov

► **To cite this version:**

| Andrey Polyakov. Unit Sliding Mode Control: Revised. 2022. hal-03868972v1

HAL Id: hal-03868972

<https://inria.hal.science/hal-03868972v1>

Preprint submitted on 24 Nov 2022 (v1), last revised 17 May 2023 (v2)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Unit Sliding Mode Control: Revised

Andrey Polyakov

Abstract—The methodology of the unit sliding mode control design (known since 1970s) for linear systems is revised based on the concept of the generalized homogeneity. The restriction about a consistency of the number of control inputs with the dimension of the sliding surface is eliminated. A simple procedure of control parameters tuning based on a known maximal magnitude of matched perturbations is developed. To deal with perturbations of unknown magnitude, a sliding mode control with integral action is designed using the obtained unit control. The theoretical results are supported by numerical simulations.

I. INTRODUCTION

The sliding mode control (SMC) seems to be the first robust control design methodology known since 1960s (see [37] and references therein). The unit control proposed by [12] is one of famous SMC algorithms supported with a very simple rule of control parameters tuning (see [38], [6], [36]). In the SISO (Single Input Single Output) case, the unit control simply coincides with the conventional relay SMC. The difference can be discovered for linear MIMO (Multiply Inputs Multiply Outputs) systems. Indeed, in this case the unit control has discontinuities only on a set being an intersection of several $(n - 1)$ -dimensional linear surfaces, while the relay SMC is discontinuous on each such hyperplane. Therefore, the discontinuity set of the unit control has a smaller dimension than the discontinuity set of the conventional relay SMC. The latter may simplify a practical implementation and a chattering attenuation of SMC system (see e.g., [34]). The main well-known restriction of the conventional SMC design for linear MIMO systems is a consistency of dimensions of the sliding surface and the control input. Namely, to implement the unit control for the linear MIMO system, the sliding surface $Cx = 0$ must be of the dimension $n - p$ with $1 \leq p \leq m$ (i.e., $C \in \mathbb{R}^{p \times n}$), where n is a dimension of the state vector $x \in \mathbb{R}^n$ and m is the number of control inputs. The first aim of this paper is eliminate this restriction and to develop a unit control design methodology ensuring sliding mode on a linear surface of any dimension less than n . For SISO case, this problem is treated by the so-called high order sliding mode (HOSM) algorithms (see [18], [34]). Design procedures for HOSM controllers are rather complicated and have to be supported with a non-trivial stability analysis (see, e.g. [4] and references therein). An extension of the HOSM control methodology to MIMO systems requires even more cumbersome constructions (see e.g., [28], [27], [10]).

The homogeneity is a dilation symmetry, which is well-known in mathematics due to the papers of [43], [9], [16], [8]. A Lie symmetry in general and the dilation symmetry in particular is a feature of many physical process (see, e.g.

[24]). A lot of PDE models of mathematical physics are homogeneous in a generalized sense. Such systems have the so-called self-similar solutions known since 1940s (see, e.g., [35] for more details). The standard (or Euler) homogeneity is a symmetry of a mathematical object (a function, a set, a differential equation, etc) with respect to the standard dilation $x \mapsto e^s x$ being simply a multiplication of a vector x by a positive scalar e^s , where $s \in \mathbb{R}$. The generalized dilation (see [43], [16]) is defined as $x \mapsto \mathbf{d}(s)x$, where $\mathbf{d}(s)$ is a family of operators (parameterized by $s \in \mathbb{R}$) having a topological characterization typical for a dilation (see [15]). The generalized homogeneity is widely utilized in control and systems theory for control design ([3], [19], [25], [1], [42]), state estimation ([26], [5], [20]) and stability/controllability/robustness analysis ([13], [33], [11], [14]). In fact, the conventional unit control is a standard homogeneous control algorithm (as explained in Section IV). This paper shows that using the generalized homogeneity, the methodology of the unit control can be adapted to sliding surfaces $Cx = 0$ which may have any dimension less than n , but all other advantages of the unit control known before are preserved.

In the case of linear PI (Proportional-Integral) control, the integral action allows to compensate an matched constant perturbation of unknown magnitude (and unknown bound). The super-twisting algorithm [17] is the most famous sliding mode control with an integral action, which have more advanced (with respect to linear PI control) property. Namely, it may reject perturbations of unknown magnitude, which are (sufficiently) slowly varying Lipschitz continuous functions of time ([22]). Based on results of [21], [40], a modification of the homogeneous unit control with an integral action having the property mentioned above is proposed.

The paper is organized as follows. First, a problem statement, basic assumptions and the classical scheme of unit control design are presented. In Section 3, some notions of homogeneity theory are briefly recalled. Homogeneous unit control is designed in Section 4 for system with a known magnitude of perturbations. The sliding mode control for systems with unknown magnitude of perturbations is designed in Section 5. Finally, Section 6 presents some conclusions.

Notation. \mathbb{R} is the field of reals; $\|\cdot\|$ denotes the weighted Euclidean norm \mathbb{R}^n : $\|x\| = \sqrt{x^\top P x}$ with $x \in \mathbb{R}^n$ and $P = P^\top \in \mathbb{R}^{n \times n} : P \succ 0$, where the inequality $P \succ 0$ means that the matrix P is positive definite; $|\cdot|$ denotes the Euclidean norm in \mathbb{R}^n , i.e., $|x| = \sqrt{x^\top x}$; $I_n \in \mathbb{R}^{n \times n}$ is the identity matrix; $\text{rank } M$ denotes the rank of a matrix M ; $\mathbf{0}$ is a zero element of a vector space. $L^\infty(\mathbb{R}^p)$ is a set of measurable essentially uniformly bounded functions $\mathbb{R} \mapsto \mathbb{R}^p$.

II. PROBLEM STATEMENT

Let us consider the linear MIMO system

$$\dot{x} = Ax + B(u + \gamma(t, x)), \quad t > 0, \quad x(0) = x_0, \quad (1)$$

where $x(t) \in \mathbb{R}^n$ is the system state, $u(t) \in \mathbb{R}^m$ is the control input, the matrices $A \in \mathbb{R}^{n \times n}$ and $B \in \mathbb{R}^{n \times m}$ are known and $\gamma : \mathbb{R} \times \mathbb{R}^n \mapsto \mathbb{R}^m$ is an unknown measurable locally bounded function, which models the matched system uncertainties and disturbances. The system (1) has Filippov solutions for any locally bounded locally measurable feedback law $u = u(t, x)$ (see [7]).

Assumption 1: There exists a known constant $\bar{\gamma} \geq 0$:

$$|\gamma(t, x)| \leq \bar{\gamma}, \quad \forall t \geq 0, \quad \forall x \in \mathbb{R}^n. \quad (2)$$

For the system (1) we consider the problem of the sliding mode control design (see [38], [6]). Namely, the **control aim** is to synthesize a feedback control law such that any trajectory of the closed-loop reaches a desired linear surface

$$Cx = \mathbf{0}, \quad C \in \mathbb{R}^{p \times n}, \quad \text{rank } C = p, \quad (3)$$

in a finite time and slides on it after then. The so-called unit control (see [12], [38], [6])

$$\tilde{u} = \hat{K}x + K \frac{Cx}{|Cx|}, \quad (4)$$

solves this problem provided that a) $p = m$, b) the matrix CB is invertible and c) the matrices $\hat{K} \in \mathbb{R}^{m \times n}$ and $K \in \mathbb{R}^{m \times p}$ are properly selected: $\hat{K} = -(CB)^{-1}CA$ and $K = -(\delta + |CB|\bar{\gamma})(CB)^{-1}$ with $\delta > 0$. This paper relaxes the restriction $p = m$, $\det(CB) \neq 0$ by the following mild assumption.

Assumption 2: There exists $\tilde{K} \in \mathbb{R}^{m \times n}$ such that

$$C(A + B\tilde{K})(I_n - C^\top(CC^\top)^{-1}C) = \mathbf{0} \quad (5)$$

and the pair $\{A_\sigma, B_\sigma\}$ is controllable, where

$$A_\sigma = C(A + B\tilde{K})C^\top(CC^\top)^{-1}, \quad B_\sigma = CB. \quad (6)$$

If CB is invertible then the latter assumption is always fulfilled for $\tilde{K} = -(CB)^{-1}CA$. However, this assumption is fulfilled in many other cases, for example, if $C = I_n$ and the pair $\{A, B\}$ is controllable. Assumption 2 simply means that the dynamics of the sliding variable $\sigma = Cx$ is completely controllable. Indeed, below we show that, under Assumption 2, we have $\dot{\sigma} = A_\sigma\sigma + B_\sigma(u - \tilde{K}x + \gamma)$, so an influence of any other (possibly uncontrollable) component of the system state may be rejected by a control. Notice that the controllability of the pair $\{A_\sigma, B_\sigma\}$ is necessary for a finite-time reaching of the sliding surface $Cx = 0$ for all initial states $x_0 \in \mathbb{R}^n$, so further relaxation of Assumption 2 seems impossible.

Assumption 2 can be easily checked by solving the linear algebraic equation (5) with respect to the variable \tilde{K} . The absence of solution would simply mean that the selected sliding surface is not appropriate for the unit SMC design. The sliding surface $Cx = 0$ is usually designed such that the closed-loop system is, at least, exponentially stable. Any method of a stable sliding surface design (see, e.g., [38], [6], [34]) can be utilized taking into account Assumption 2.

The sliding mode control is known to be robust with respect to bounded matched disturbances. The Assumption 1

is conventional for the SMC theory (see, e.g., [38], [6], [34]). Therefore, the *first aim* is to design a unit sliding mode control under the classical Assumption 1 and the relaxed Assumption 2. To solve the problem, the term $\frac{Cx}{|Cx|}$ in (4) is going to be modified using the concept of a generalized homogeneity.

The SMC design under Assumption 1 uses a knowledge of a maximal magnitude of perturbations. If the magnitude is unknown then some information about a structure of the perturbation γ is required to design a robust control.

Assumption 3: There exists a known constant $\bar{\gamma} \geq 0$ such that the unknown function γ admits the representation:

$$\gamma(t, x) = \gamma_0 + \tilde{\gamma}(t, x), \quad \forall t \geq 0, \forall x \in \mathbb{R}^n, \quad (7)$$

$$|\tilde{\gamma}(t, x)| \leq \bar{\gamma} \max\{|Cx|, 1\}, \quad \forall t \geq 0, \forall x \in \mathbb{R}^n, \quad (8)$$

where $\gamma_0 \in \mathbb{R}^m$ is an unknown vector.

In this case, we assume that the uncertain function γ converges to an unknown constant γ_0 as $|Cx| \rightarrow 0$. Below we show that the latter assumption can be relaxed allowing the constant γ_0 to be a Lipschitz continuous function of time. In the latter case, the Assumption 3 becomes similar to the case of the super-twisting SMC design (see e.g., [17], [22]). The *second aim* is to design SMC under Assumptions 2 and 3.

III. PRELIMINARIES: LINEAR HOMOGENEITY

The linear dilation in \mathbb{R}^n is given by (see [29])

$$\mathbf{d}(s) = e^{sG_d} = \sum_{i=0}^{\infty} \frac{(sG_d)^i}{i!}, \quad s \in \mathbb{R}, \quad (9)$$

where $G_d \in \mathbb{R}^{n \times n}$ is an anti-Hurwitz matrix¹ being a *generator of linear dilation*. The latter implies that \mathbf{d} satisfies the limit property, $\|\mathbf{d}(s)x\| \rightarrow 0$ as $s \rightarrow -\infty$ and $\|\mathbf{d}(s)x\| \rightarrow +\infty$ as $s \rightarrow +\infty$, required for a group \mathbf{d} to be a dilation in \mathbb{R}^n (see, e.g., [16]). The linear dilation introduces an alternative norm topology in \mathbb{R}^n by means of the canonical homogeneous norm.

Definition 1: ((29)) The function $\|\cdot\|_d : \mathbb{R}^n \mapsto \mathbb{R}_+$ given by $\|x\|_d = 0$ for $x = \mathbf{0}$ and

$$\|x\|_d = e^{s_x}, \quad \text{where } s_x \in \mathbb{R} : \|\mathbf{d}(-s_x)x\| = 1, \quad x \neq \mathbf{0} \quad (10)$$

is called the *canonical homogeneous norm* in \mathbb{R}^n , where \mathbf{d} is a linear monotone dilation².

Notice that $\|x\| = 1$ is equivalent to $\|x\|_d = 1$. Moreover, $\|\mathbf{d}(-\ln \|x\|_d)x\| = 1$, so the operator $\mathbf{d}(-\ln \|x\|_d)x$ is the so-called *\mathbf{d} -homogeneous projector of x on the unit sphere* [30, page 159]. For the standard dilation $\mathbf{d}(s) = e^s I_n$, $s \in \mathbb{R}$ we have $\|\cdot\| = \|\cdot\|_d$ and $\mathbf{d}(-\ln \|x\|_d)x = \frac{x}{\|x\|}$ is a the standard homogeneous projector of x on the unit sphere.

Theorem 1 ([29]): If $\|x\| = \sqrt{x^\top P x}$ with a symmetric matrix $P \in \mathbb{R}^{n \times n}$ satisfying $PG_d + G_d^\top P \succ 0$, $P \succ 0$ then \mathbf{d} is monotone and the canonical homogeneous norm $\|\cdot\|_d$ is continuous on \mathbb{R}^n , smooth on $\mathbb{R}^n \setminus \{\mathbf{0}\}$,

$$\frac{\partial \|x\|_d}{\partial x} = \frac{\|x\|_d x^\top \mathbf{d}^\top(-\ln \|x\|_d) P \mathbf{d}(-\ln \|x\|_d)}{x^\top \mathbf{d}^\top(-\ln \|x\|_d) P G_d \mathbf{d}(-\ln \|x\|_d) x}, \quad \forall x \neq \mathbf{0}. \quad (11)$$

¹A matrix $G_d \in \mathbb{R}^{n \times n}$ is anti-Hurwitz if $-G_d$ is Hurwitz.

²A dilation in \mathbb{R}^n is monotone if for any $x \in \mathbb{R}^n \setminus \{\mathbf{0}\}$ the function $s \mapsto \|\mathbf{d}(s)x\|$, $s \in \mathbb{R}$ is strictly increasing.

Moreover, $\underline{\sigma}(\|x\|) \leq \|x\|_{\mathbf{d}} \leq \bar{\sigma}(\|x\|), \forall x \in \mathbb{R}^n$, with

$$\underline{\sigma}(r) = \begin{cases} r^{1/\alpha} & \text{if } r \geq 1, \\ r^{1/\beta} & \text{if } r < 1, \end{cases} \quad \bar{\sigma}(r) = \begin{cases} r^{1/\beta} & \text{if } r \geq 1, \\ r^{1/\alpha} & \text{if } r < 1, \end{cases}$$

where $\alpha = 0.5\lambda_{\max}(P^{1/2}G_{\mathbf{d}}P^{-1/2} + P^{-1/2}G_{\mathbf{d}}^{\top}P^{1/2}) > 0$ and $\beta = 0.5\lambda_{\min}(P^{1/2}G_{\mathbf{d}}P^{-1/2} + P^{-1/2}G_{\mathbf{d}}^{\top}P^{1/2}) > 0$.

Below the canonical homogeneous norm is utilized as a Lyapunov function for a homogeneous unit control design.

Definition 2 ([16], [3]): A vector field $f : \mathbb{R}^n \mapsto \mathbb{R}^n$ (resp. a function $h : \mathbb{R}^n \mapsto \mathbb{R}$) is said to be \mathbf{d} -homogeneous of degree $\mu \in \mathbb{R}$ if $f(\mathbf{d}(s)x) = e^{\mu s}\mathbf{d}(s)f(x)$ (resp. $h(\mathbf{d}(s)x) = e^{\mu s}h(x)$), for all $x \in \mathbb{R}^n, s \in \mathbb{R}$.

If f is \mathbf{d} -homogeneous of degree μ then solutions of $\dot{x} = f(x)$ are symmetric ([16], [3]): $x(e^{-\mu s}t, \mathbf{d}(s)x_0) = \mathbf{d}(s)x(t, x_0)$, where $x(t, z)$ denotes a solution with $x(0) = z$.

By definition, the system $\dot{x} = f(x)$ is \mathbf{d} -homogeneous if the vector field is \mathbf{d} -homogeneous.

The homogeneity degree specifies the convergence rate of a stable homogeneous system.

Theorem 2: ([3]) Let the vector field $f : \mathbb{R}^n \mapsto \mathbb{R}^n$ be \mathbf{d} -homogeneous of degree $\mu \in \mathbb{R}$. If the system $\dot{x} = f(x)$ is locally asymptotically stable then it is globally uniformly finite-time stable for $\mu < 0$.

Any homogeneous sliding mode control implicitly uses this result for ensuring a finite-time reaching of a sliding surface.

The homogeneous control systems are robust (ISS) with respect to a rather large class of perturbations ([14], [1]).

IV. HOMOGENEOUS UNIT CONTROL

The conventional unit control (4) has two components. The meaning of each component can be explained in the context of the homogeneity theory: the linear component is aimed at a homogenization of the unperturbed dynamics of the sliding variable $\sigma = Cx$, $C \in \mathbb{R}^{p \times n}$, while the second (stabilizing) component is discontinuous and homogeneous negative degree to guarantee finite-time stability of the sliding variable. Indeed, for (1), (4) we have

$$\dot{\sigma} = (CA + CB\hat{K})x + CBK \frac{\sigma}{|\sigma|} + CB\gamma.$$

Since, in the conventional case, $p = m$ and $\det(CB) \neq 0$ then in order to eliminate the linear term in the above equation, the matrix \hat{K} is traditionally selected as $\hat{K} = -(CB)^{-1}CA$. In the latter case, the unperturbed system $\dot{\sigma} = CBK \frac{\sigma}{|\sigma|}$ is obviously standard homogeneous of negative degree ($\mu = -1$). Moreover, the perturbed system ($\gamma \neq 0$) is globally uniformly finite-time stable under proper selection of control parameters (e.g., $K = -(\delta + |CB|\bar{\gamma})(CB)^{-1}$, $\delta > 0$). We follow this homogeneity-based interpretation in order to design a similar two component feedback law for the case $p \neq m$. Namely, the linear component should homogenize (in a generalized sense) the dynamics of the sliding variable, while the discontinuous one should be uniformly bounded and generalized homogeneous of degree $\mu = -1$. Moreover, the dynamics of the sliding variable has to be globally uniformly finite-time stable even in the perturbed case.

Notice that the linear vector field $\sigma \mapsto A_{\sigma}\sigma$ may be standard homogeneous of non-zero degree if and only if $A_{\sigma} = \mathbf{0}$. This

explains the structure of the matrix $\hat{K} = -(CB)^{-1}CA$ in the classical unit control (4). To relax this condition, we use the generalized homogeneity. Indeed, according to [30, Lemma 7.5] and [42, Lemma 1]), a linear vector field $\sigma \mapsto A_{\sigma}\sigma$ is \mathbf{d} -homogeneous of non-zero degree if and only if the matrix A_{σ} is nilpotent. On the other hand, the operator $\frac{\sigma}{|\sigma|}$ is the standard homogeneous projector on the unit sphere (*that is why the feedback law (4) is called the unit control*). Such a projector for a dilation \mathbf{d} is defined as $\mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}})\sigma$, where $\|\cdot\|_{\mathbf{d}}$ is a homogeneous norm.

Following the above explanations we define the control law:

$$u = \hat{K}x + K\mathbf{d}(-\ln \|Cx\|_{\mathbf{d}})Cx, \quad \hat{K} = \tilde{K} + K_0C, \quad (12)$$

where $\sigma = Cx$ is the sliding variable, the matrix $\tilde{K} \in \mathbb{R}^{m \times n}$ is defined in Assumption 2, the matrix $K_0 \in \mathbb{R}^{m \times p}$ is required for \mathbf{d} -homogenization of a linear component of the dynamics of σ , the matrix $K \in \mathbb{R}^{m \times p}$ has to be properly designed for the finite-time stabilization of the dynamics of the sliding variable, \mathbf{d} is a linear dilation in \mathbb{R}^p and $\|\cdot\|_{\mathbf{d}}$ is a canonical homogeneous norm to be defined. Since, by definition, $\|\mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}})\sigma\| = 1$ then (12) is a unit control as well. However, its design is based on the concept of a generalized (non-standard) homogeneity, so, in order distinguish the conventional and suggested algorithms, we call the feedback law (12) by *the homogeneous unit control*.

If \tilde{K} satisfies Assumption 2 then using the identity

$$C(I_n - C^{\top}(CC^{\top})^{-1}C) = \mathbf{0}$$

we derive

$$CA + CB\tilde{K} = C(A + B\tilde{K})(I_n - C^{\top}(CC^{\top})^{-1}C) + C(A + B\tilde{K})C^{\top}(CC^{\top})^{-1}C = A_{\sigma}C$$

where $A_{\sigma} = C(A + B\tilde{K})C^{\top}(CC^{\top})^{-1}$. Therefore, the sliding variable $\sigma = Cx$ of the closed-loop system (1), (12) satisfies the equation

$$\dot{\sigma} = (A_{\sigma} + B_{\sigma}K_0)\sigma + B_{\sigma}K\mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}})\sigma + B_{\sigma}\gamma, \quad (13)$$

where $B_{\sigma} = CB$. Since the pair $\{A_{\sigma}, B_{\sigma}\}$ is assumed to be controllable then the matrix $A_0 = A_{\sigma} + B_{\sigma}K_0$ can be designed nilpotent by means of a proper selection of K_0 and the system (13) can be homogeneously stabilized to zero in a finite time by a proper selection of the gain K .

Theorem 3: If Assumptions 1 and 2 are fulfilled for $\bar{\gamma} \geq 0$ and $C \in \mathbb{R}^{p \times m}$ then

1) the linear algebraic equation

$$A_{\sigma}G_0 - G_0A_{\sigma} + B_{\sigma}Y_0 = A, \quad G_0B_{\sigma} = \mathbf{0} \quad (14)$$

always has a solution $Y_0 \in \mathbb{R}^{m \times p}$, $G_0 \in \mathbb{R}^{p \times p}$; moreover, for any solution of (14), the matrix

$$G_{\mathbf{d}} = I_n - G_0 \quad (15)$$

is anti-Hurwitz, the matrix

$$A_0 = A_{\sigma} - B_{\sigma}Y_0G_{\mathbf{d}}^{-1} \quad (16)$$

is nilpotent and satisfies the identity

$$A_0G_{\mathbf{d}} = (G_{\mathbf{d}} - I_n)A_0, \quad G_{\mathbf{d}}B_{\sigma} = B_{\sigma}; \quad (17)$$

2) the linear algebraic system

$$(A_0 + \rho G_d)X + X(A_0 + \rho G_d)^\top + B_\sigma Y + Y^\top B_\sigma^\top + \bar{\gamma}X = -\bar{\gamma}B_\sigma B_\sigma^\top, \\ G_d X + X G_d^\top > 0, \quad X = X^\top > 0 \quad (18)$$

has a solution $X \in \mathbb{R}^{n \times n}$, $Y \in \mathbb{R}^{m \times n}$ for any $\rho > 0$;

3) the system (13) with the control (12) is globally uniformly finite-time stable and

$$\sigma(t) = \mathbf{0}, \quad \forall t \geq \frac{\|\sigma(0)\|_d}{\rho},$$

provided that $\mathbf{d}(s) = e^{sG_d}$ with $s \in \mathbb{R}$,

$$K_0 = -Y_0 G_d^{-1}, \quad K = YX^{-1}, \quad (19)$$

and $\|\cdot\|_d$ is the canonical homogeneous norm induced by the weighted Euclidean norm $\|\sigma\| = \sqrt{\sigma^\top X^{-1} \sigma}$.

Proof. The feasibility of (14) (as well as property of G_0) is studied in ([23]), but the feasibility of (18) is proven in [32] and refined in [42]. Let us prove the finite-time stability of (13). Using (11), (12) we derive

$$\frac{d\|\sigma(t)\|_d}{dt} = \|\sigma\|_d \frac{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} \mathbf{d}(-\ln \|\sigma\|_d) \dot{\sigma}}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} G_d \mathbf{d}(-\ln \|\sigma\|_d) \sigma}.$$

The identity (17) means that [30, Lemma 7.5]

$$A_0 \mathbf{d}(s) = e^{-s} \mathbf{d}(s) A_0, \quad \mathbf{d}(s) B = e^s B, \quad \forall s \in \mathbb{R}.$$

Hence, we conclude

$$\frac{d\|\sigma(t)\|_d}{dt} = \frac{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} (A_0 + B_\sigma K) \mathbf{d}(-\ln \|\sigma\|_d) \sigma}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} G_d \mathbf{d}(-\ln \|\sigma\|_d) \sigma} \\ + \frac{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} B_\sigma \gamma}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} G_d \mathbf{d}(-\ln \|\sigma\|_d) \sigma}.$$

Since $X^{-1}(A_0 + B_\sigma K) = X^{-1}(A_0 X + B_\sigma Y) X^{-1}$ then using the identity (18) we derive

$$\frac{d\|\sigma(t)\|_d}{dt} = -\rho \frac{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) (X^{-1} G_d + G_d^\top X^{-1}) \mathbf{d}(-\ln \|\sigma\|_d) \sigma}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) (X^{-1} G_d + G_d^\top X^{-1}) \mathbf{d}(-\ln \|\sigma\|_d) \sigma} \\ - \frac{\bar{\gamma} \sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} \mathbf{d}(-\ln \|\sigma\|_d) \sigma}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) (X^{-1} G_d + G_d^\top X^{-1}) \mathbf{d}(-\ln \|\sigma\|_d) \sigma} \\ - \frac{\bar{\gamma} \sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} B_\sigma B_\sigma^\top X^{-1} \mathbf{d}(-\ln \|\sigma\|_d) \sigma}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) (X^{-1} G_d + G_d^\top X^{-1}) \mathbf{d}(-\ln \|\sigma\|_d) \sigma} \\ + \frac{2\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} B_\sigma \gamma}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) (X^{-1} G_d + G_d^\top X^{-1}) \mathbf{d}(-\ln \|\sigma\|_d) \sigma}.$$

For $\bar{\gamma} > 0$ and $\xi = \left(\frac{\bar{\gamma}}{\sqrt{\bar{\gamma} B_\sigma^\top X^{-1} \mathbf{d}(-\ln \|\sigma\|_d) \sigma}} \right)$ we have

$$0 \leq \xi^\top \begin{pmatrix} I_m & -I_m \\ -I_m & I_m \end{pmatrix} \xi = \frac{|\gamma|^2}{\bar{\gamma}} - 2\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} B_\sigma \gamma \\ + \bar{\gamma} \sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} B_\sigma B_\sigma^\top X^{-1} \mathbf{d}(-\ln \|\sigma\|_d) \sigma.$$

Therefore, using the identity

$$\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) X^{-1} \mathbf{d}(-\ln \|\sigma\|_d) \sigma = 1$$

(see the definition of $\|\cdot\|_d$) we derive

$$\frac{d\|\sigma(t)\|_d}{dt} = -\rho - \frac{\bar{\gamma} - \frac{|\gamma|^2}{\bar{\gamma}}}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) (X^{-1} G_d + G_d^\top X^{-1}) \mathbf{d}(-\ln \|\sigma\|_d) \sigma} \\ - \frac{\xi^\top \begin{pmatrix} I_m & -I_m \\ -I_m & I_m \end{pmatrix} \xi}{\sigma^\top \mathbf{d}^\top(-\ln \|\sigma\|_d) (X^{-1} G_d + G_d^\top X^{-1}) \mathbf{d}(-\ln \|\sigma\|_d) \sigma} \\ \leq -\rho.$$

and $\sigma(t) = 0$ for $t \geq \|\sigma(0)\|_d / \rho$. The proof is complete.

The homogeneous unit control (12) is discontinuous only on the sliding surface $Cx = 0$ and rejects bounded matched

perturbations $|\gamma(t, x)| \leq \bar{\gamma}$. The following simple *algorithm* of its design can be proposed.

- *Step 1:* given $C \in \mathbb{R}^{p \times m}$ solve the linear algebraic equation (5) with respect to the variable $\tilde{K} \in \mathbb{R}^{m \times n}$.
- *Step 2:* check the controllability of the pair $\{A_\sigma, B_\sigma\}$, where $A_\sigma \in \mathbb{R}^{p \times p}$ and $B_\sigma \in \mathbb{R}^{p \times n}$ are given by (6).
- *Step 3:* solve the linear algebraic equation (14) with respect to $Y_0 \in \mathbb{R}^{m \times p}$ and $G_0 \in \mathbb{R}^{p \times p}$.
- *Step 4:* solve the linear matrix inequality (18) with respect to $Y \in \mathbb{R}^{m \times p}$ and $X \in \mathbb{R}^{p \times p}$.
- *Step 5:* compute the parameters $K_0 \in \mathbb{R}^{m \times p}$ and $K \in \mathbb{R}^{m \times p}$ of the homogeneous unit control (12) by the formulas (19), (15).

Remark 1 (On sliding motion equation): Using the equivalent control method (see [38]) for $t \geq \|Cx(0)\|_d$ we derive the sliding motion equation in the form:

$$\dot{x}(t) = (A + B\tilde{K})x(t), \quad Cx(t) = \mathbf{0}, \quad (20)$$

where $\tilde{K} \in \mathbb{R}^{m \times n}$ is defined in Assumption 2. If the control aim is to stabilize the system (1) then the sliding surface $Cx = 0$ has been selected such that the system (20) is globally asymptotically stable. The simplest condition to C in this case is given by the following matrix inequality

$$P(A + B\tilde{K}) + (A + B\tilde{K})^\top P - \beta C^\top C < 0, \quad P > 0, \quad \beta > 0. \quad (21)$$

Indeed, considering the Lyapunov function candidate $V = x^\top P x$ we derive

$$\dot{V} = 2x^\top P(A + B\tilde{K})x \\ = x^\top (P(A + B\tilde{K}) + (A + B\tilde{K})^\top P - \beta C^\top C)x < 0,$$

where the identity $Cx = 0$ and the inequality (21) are utilized on the last step. Therefore, to design a stabilizing homogeneous unit control (12) for the system (1) it is sufficient to find a matrix C satisfying Assumption 2 and the matrix inequality (21).

Remark 2 (On chattering attenuation): Following the conventional approach to the chattering reduction (see, e.g., [38]), the discontinuous term in (12) can be "smoothed" using the saturation function:

$$u_\alpha = \hat{K}x + K \mathbf{d}(-\ln \max\{\alpha, \|Cx\|_d\}) Cx. \quad \alpha \geq 0 \quad (22)$$

coincides with (12) for $\alpha = 0$. On the one hand, the parameter $\alpha > 0$ simply defines an attractive set of the sliding variable σ . Indeed, in the view of Theorem 3 for the closed-loop system (1), (22) we have

$$\frac{d\|\sigma(t)\|_d}{dt} \leq -\rho \quad \text{if} \quad \|\sigma(t)\|_d \geq \alpha.$$

The latter means that the sliding variable σ converges to the homogeneous ball $\|\sigma\|_d \leq \alpha$ in a finite time. On the other hand, the nonlinear term in (22) becomes linear $K \mathbf{d}(-\ln \alpha) Cx$ for $\|x\|_d \leq \alpha$, so the feedback law u_α is continuous on \mathbb{R}^n if $\alpha > 0$. Therefore, in practice the parameter α can be utilized for an attenuation of the chattering caused by discontinuity of SMC.

Remark 3 (On computation of $\|\cdot\|_d$): Since the canonical homogeneous norm is defined implicitly by the formula (10),

a computational algorithm is required for practical implementation of the homogeneous unit control given by (12). In [29], [30, Chapter 8], [41] a scheme for an approximation of $\|\cdot\|_{\mathbf{d}}$ by an explicit homogeneous function is presented. Issues of numerical on-line computation of $\|\cdot\|_{\mathbf{d}}$ are studied in [31], [32] based on a bisection method. This numerical method is shown to be very efficient in practice (see e.g., [39]).

Remark 4 (On exactness of the reaching time estimate): If $\bar{\gamma} = 0$ and $\rho = 1$ then $T(x_0) = \|Cx_0\|_{\mathbf{d}}$ is the *exact* reaching time of the sliding surface $Cx = 0$ by a trajectory of the closed loop system (1), (12). Indeed, repeating the proof of Theorem 3 we derive

$$\frac{d\|\sigma(t)\|_{\mathbf{d}}}{dt} = -1, \quad t > 0,$$

i.e., $\sigma(t) \neq \mathbf{0}$ for all $t \in [0, \|\sigma(0)\|_{\mathbf{d}})$ and $\sigma(t) = \mathbf{0}$ for all $t \geq \|\sigma(0)\|_{\mathbf{d}}$. The reaching time can be tuned by the parameter $\rho > 0$. The larger ρ , faster the reaching of the sliding surface (see the estimate of the reaching time in Theorem 3). Theoretically, the reaching time may be adjusted arbitrary small. However, a selection of a too large ρ may lead to a large feedback gains and a large chattering in practice. Therefore, in practice, ρ could be one more tuning parameter for the chattering attenuation.

V. HOMOGENEOUS SMC WITH INTEGRAL ACTION

Inspired by [21], [40], let us consider the control law with integral action

$$\begin{aligned} u(x) &= \hat{K}x + \sqrt{\|\sigma\|_{\mathbf{d}}} \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma + \int_0^t u_i d\tau, \\ u_i &= \frac{K_i \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma}{q(\sigma)}, \quad \sigma = Cx. \quad K_i \in \mathbb{R}^{m \times p}, \end{aligned} \quad (23)$$

where $\hat{K} = \tilde{K} + K_0 C$, $\mathbf{d}(s) = e^{sG_{\mathbf{d}}}$, $G_{\mathbf{d}} = I_n - 0.5G_0$, $K = YX^{-1}$, $P = X^{-1}$, K_0 and G_0 are defined in Theorem 3, but $Q = Q^{\top} \in \mathbb{R}^{m \times p}$ is a positive definite matrix $Q \succ 0$,

$$q(\sigma) = \sigma^{\top} \mathbf{d}^{\top}(-\ln \|\sigma\|_{\mathbf{d}}) (PG_{\mathbf{d}} + G_{\mathbf{d}}^{\top} P) \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma$$

In this case, under Assumption 2 and 3 the dynamics of the sliding variable admits the representation

$$\begin{aligned} \dot{\sigma} &= A_0 \sigma + B_{\sigma} \left(\|\sigma\|_{\mathbf{d}}^{\frac{1}{2}} \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma + \eta + \tilde{\gamma}(t, x) \right), \\ \dot{\eta} &= u_i(\sigma) \end{aligned} \quad (24)$$

where $\eta = \gamma_0 + \int_0^t u_i d\tau$. Since $\|\mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma\| = 1$ then $0 < \beta \leq q(\sigma) \leq \alpha$, where the constants α, β are defined in Theorem 1. The latter means that a kind of the unit control is utilized to define the integral action u_i . Notice that for $p = 1$ we have $A_{\sigma}, B_{\sigma} \in \mathbb{R}$, $\tilde{K} = \hat{K} - A_{\sigma} C / B_{\sigma} \in \mathbb{R}$, $K = -\rho / B_{\sigma}$, $\rho > 0$, $P = G_{\mathbf{d}} = 1$, $\mathbf{d}(s) = e^s$, $\sigma = x$, $\|\sigma\|_{\mathbf{d}} = |\sigma|$ and $\mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma = \text{sign}(\sigma)$, so the control (23) becomes

$$u = -\hat{K}x - B_{\sigma}^{-1} \left(\rho \sqrt{|\sigma|} \text{sign}(\sigma) + Q \int_0^t \text{sign}(\sigma(\tau)) d\tau \right).$$

Therefore, in the single-input case the control law (23) is the super-twisting algorithm.

Theorem 4: Let Assumptions 2 and 3 be fulfilled for $C \in \mathbb{R}^{p \times n}$ and $\bar{\gamma} > 0$.

- 1) If the parameters K_0, G_0 are defined as in Theorem 3 and $G_{\mathbf{d}} = I_n - 0.5G_0$ then the system of linear matrix inequalities is

$$\begin{aligned} (A_0 + \rho G_{\mathbf{d}})X + X(A_0 + \rho G_{\mathbf{d}})^{\top} + B_{\sigma}Y + Y^{\top}B_{\sigma}^{\top} + \bar{\gamma}X &= -\bar{\gamma}B_{\sigma}B_{\sigma}^{\top}, \\ G_{\mathbf{d}}X + XG_{\mathbf{d}}^{\top} \succ X, \quad I_n \succeq X \succ 0 \end{aligned} \quad (25)$$

feasible for any $\bar{\gamma} \geq 0$.

- 2) For $K = YX^{-1}$, $K_i = -QB_{\sigma}^{\top}P$ and any $Q \succ 0$
 - a) the unperturbed system (24) is $\tilde{\mathbf{d}}$ -homogeneous of degree $-1/2$ with respect to the dilation in \mathbb{R}^{p+m} defined as follows

$$\tilde{\mathbf{d}}(s) = \begin{pmatrix} \mathbf{d}(s) & \mathbf{0} \\ \mathbf{0} & e^{\frac{1}{2}s} \end{pmatrix}, \quad s \in \mathbb{R};$$

- b) the perturbed system (24) is globally uniformly finite-time stable.

Proof: 1) Denoting $\tilde{G}_{\mathbf{d}} = I_n - G_0$ and $Y = Y_1 + 0.5\rho B_{\sigma}^{\top}$ and the system (25) without $X \succeq I_n$ can be rewritten as

$$\begin{aligned} (A_0 + \frac{1}{2}\rho\tilde{G}_{\mathbf{d}})X + X(A_0 + \frac{1}{2}\rho\tilde{G}_{\mathbf{d}})^{\top} + B_{\sigma}Y_1 + Y_1^{\top}B_{\sigma}^{\top} + (\rho + \bar{\gamma})X &= \\ -(\rho + \bar{\gamma})B_{\sigma}B_{\sigma}^{\top}, \\ 0.5(\tilde{G}_{\mathbf{d}}X + X\tilde{G}_{\mathbf{d}}^{\top}) \succ 0, \quad X \succ 0 \end{aligned}$$

The above system of LMIs is feasible (see Theorem 3) for any $\bar{\gamma} \geq 0$ and any $\rho > 0$. Making the change of variable $Y_1 = \tilde{Y} - 0.5(\bar{\gamma} + \rho)B_{\sigma}^{\top}$ we derive the equivalent feasible system of LMIs:

$$\begin{aligned} (A_0 + \frac{1}{2}\rho\tilde{G}_{\mathbf{d}})X + X(A_0 + \frac{1}{2}\rho\tilde{G}_{\mathbf{d}})^{\top} + B_{\sigma}\tilde{Y} + \tilde{Y}^{\top}B_{\sigma}^{\top} + (\rho + \bar{\gamma})X &= 0, \\ \tilde{G}_{\mathbf{d}}X + X\tilde{G}_{\mathbf{d}}^{\top} \succ 0, \quad X \succ 0 \end{aligned}$$

If the pair X and \tilde{Y} is a solution of the above LMI then for any $\lambda > 0$ the pair λX and $\lambda \tilde{Y}$ is also a solution of the latter system of LMIs as well. Hence, for a sufficiently small $\lambda > 0$ we derive $I_n \succeq \lambda X$. Therefore, the system (25) is feasible.

2) For the selected matrix $G_{\mathbf{d}}$ we have $A_0 G_{\mathbf{d}} = (-0.5I_n + G_{\mathbf{d}})A_0$, $G_{\mathbf{d}}B = B$. Hence, for

$$f(\zeta) = \begin{pmatrix} A_0 \sigma + B_{\sigma} \|\sigma\|_{\mathbf{d}}^{\frac{1}{2}} \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma + B_{\sigma} \eta \\ u_i(\sigma) \end{pmatrix}, \quad \zeta = \begin{pmatrix} \sigma \\ \eta \end{pmatrix}$$

we have

$$\begin{aligned} f(\tilde{\mathbf{d}}(s)\zeta) &= \begin{pmatrix} A_0 \mathbf{d}(s) \sigma + B_{\sigma} \|\mathbf{d}(s) \sigma\|_{\mathbf{d}}^{\frac{1}{2}} \mathbf{d}(-\ln \|\mathbf{d}(s) \sigma\|_{\mathbf{d}}) \mathbf{d}(s) \sigma + B_{\sigma} e^{\frac{1}{2}s} \eta \\ u_i(\mathbf{d}(s) \sigma) \end{pmatrix} \\ &= \begin{pmatrix} e^{-\frac{1}{2}s} \mathbf{d}(s) \left(A_0 \sigma + B_{\sigma} \|\sigma\|_{\mathbf{d}}^{\frac{1}{2}} \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma + B_{\sigma} \eta \right) \\ u_i(\sigma) \end{pmatrix} \\ &= e^{-\frac{1}{2}s} \mathbf{d}(s) f(\zeta) \end{aligned}$$

Let us consider the Lyapunov function candidate

$$V = \|\sigma\|_{\mathbf{d}} + \eta^{\top} Q^{-1} \eta.$$

Using \mathbf{d} -homogeneity we derive

$$\begin{aligned} \dot{V} &= \|\sigma\|_{\mathbf{d}} \frac{\sigma^{\top} \mathbf{d}^{\top}(-\ln \|\sigma\|_{\mathbf{d}}) X^{-1} \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \dot{\sigma}}{\sigma^{\top} \mathbf{d}^{\top}(-\ln \|\sigma\|_{\mathbf{d}}) X^{-1} G_{\mathbf{d}} \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma} + 2\eta^{\top} Q^{-1} \dot{\eta} \\ &= \sqrt{\|\sigma\|_{\mathbf{d}}} \frac{\sigma^{\top} \mathbf{d}^{\top}(-\ln \|\sigma\|_{\mathbf{d}}) X^{-1} (A_0 + B_{\sigma} K) \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}}) \sigma}{0.5q(\sigma)} \\ &\quad + \frac{\sigma^{\top} \mathbf{d}^{\top}(-\ln \|\sigma\|_{\mathbf{d}}) X^{-1} B_{\sigma} (\tilde{\gamma} + \eta)}{0.5q(\sigma)} + 2\eta^{\top} Q^{-1} \dot{\eta} \\ &= -\rho \|\sigma\|_{\mathbf{d}}^{\frac{1}{2}} + \frac{2\pi^{\top} P B_{\sigma} \frac{\tilde{\gamma}}{\sqrt{\|\sigma\|_{\mathbf{d}}}} - \bar{\gamma} - \bar{\gamma}^{\top} X^{-1} B_{\sigma} B_{\sigma}^{\top} X^{-1} \pi}{q(\sigma)}, \end{aligned}$$

where $\pi = \mathbf{d}(-\ln \|\sigma\|_{\mathbf{d}})\sigma$ is a homogeneous projection of σ on the unit sphere $\|\sigma\| = 1$.

If $|\tilde{\gamma}| \leq \bar{\gamma}\sqrt{\|\sigma\|_{\mathbf{d}}}$ then repeating the proof of Theorem 3 we derive

$$\dot{V} \leq -\rho\|\sigma\|_{\mathbf{d}}^{0.5}.$$

Hence, we conclude that the set $\{V(x) = 1\}$ is a strictly positively invariant set of the system (24). In the case of homogeneous system, the latter guarantees global asymptotic stability of the system (see, [3]), but the negative homogeneity degree implies the finite-time stability.

To complete the proof we just need to show that $\min\{|\sigma|^2, 1\} \leq \|\sigma\|_{\mathbf{d}}$. Indeed, if $|\sigma| \geq 1$ then we need to show that $\|\sigma\|_{\mathbf{d}} \geq 1$ or equivalently

$$\sigma^{\top} X^{-1} \sigma \geq 1.$$

The latter inequality holds since $\sigma^{\top} \sigma$ is assumed to be greater than 1 but $X^{-1} \succeq I_n$ due to $I_n \succeq X$ (see LMI (25)). In the case $|\sigma| \leq 1$ we need to prove that $|\sigma|^2 \leq \|\sigma\|_{\mathbf{d}}$. Since $X^{-1} \succeq I_n$ then $|\sigma| \leq \|\sigma\|$. In this case, for the function $\underline{\sigma}$ defined in Theorem 1 we have

$$\underline{\sigma}(|\sigma|) \leq \underline{\sigma}(\|\sigma\|) \leq \|\sigma\|_{\mathbf{d}}.$$

The inequality $G_{\mathbf{d}}X + XG_{\mathbf{d}}^{\top} \succ X$ (see (25)) guarantees that $\beta \geq 0.5$, where the parameter β defines the function $\underline{\sigma}$ (see Theorem 1). So, for $|\sigma| \leq 1$ we have

$$|\sigma|^2 \leq |\sigma|^{1/\beta} \leq \|\sigma\|_{\mathbf{d}}.$$

The proof is complete. \blacksquare

According the proven theorem the homogeneous control (23) with integral action forces a sliding mode in the system (1) on the surface $Cx = 0$ in a finite time provided that the uncertain function γ satisfies Assumption 3. The known parameter $\bar{\gamma}$ is utilized for the tuning of the controller.

Corollary 1: If an unknown vector γ_0 in Assumption 3 is replaced with a Lipschitz continuous function of time $\gamma_0 : \mathbb{R} \mapsto \mathbb{R}^m$, i.e.,

$$\exists \bar{\gamma}_0 > 0 \quad : \quad |\dot{\gamma}_0(t)| \leq \bar{\gamma}_0 \quad \text{almost everywhere} \quad (26)$$

then Theorem 4 remains valid provided that the Lipschitz constant $\bar{\gamma}_0$ is sufficiently small.

Proof: For $\dot{\gamma}_0 = 0$ Theorem 4 guarantees global uniform asymptotic stability of the system $\dot{\zeta} = f(\zeta)$, where f and ζ are defined in the proof of Theorem 4. Then by Zubov-Rosier theorem ([43], [33], [2]) there exists a \mathbf{d} -homogeneous Lyapunov function $V \in C(\mathbb{R}^n) \cap C^{\infty}(\mathbb{R}^n \setminus \{\mathbf{0}\})$ of degree 1 and a constant $c_0 > 0$:

$$\dot{V} = \frac{\partial V}{\partial \zeta} f(\zeta) \leq -c_0, \quad \forall \zeta \neq \mathbf{0},$$

If $\dot{\gamma}_0 \neq \mathbf{0}$ for the same Lyapunov function we have

$$\dot{V} = \frac{\partial V}{\partial \zeta} (f(\zeta) + \begin{pmatrix} \mathbf{0} \\ \dot{\gamma}_0 \end{pmatrix}) \leq -c_0 + \bar{\gamma}_0 \left| \frac{\partial V}{\partial \zeta} \right|.$$

Since V is a \mathbf{d} -homogeneous function of degree 1 then $\left| \frac{\partial V}{\partial \zeta} \right|$ is a \mathbf{d} homogeneous function of degree 0. Taking into account $V \in C^{\infty}(\mathbb{R}^n \setminus \{\mathbf{0}\})$ we conclude that $\left| \frac{\partial V}{\partial \zeta} \right|$ is bounded on the unit sphere and on \mathbb{R}^n (due to the zero homogeneity degree).

Therefore, the system (24) remains finite-time stable provided that $\bar{\gamma}_0$ is sufficiently small. \blacksquare

The proven corollary relaxes Assumption 3 and shows that the homogeneous sliding mode control with integral action can also reject (sufficiently) slowly-varying matched perturbations of an unknown magnitude. This repeats the property of the super-twisting algorithm.

VI. NUMERICAL EXAMPLE

Let us consider the system with

$$A = \begin{pmatrix} 0 & 1 & 0 & 0 \\ -1 & 0 & 0 & 0 \\ 0 & 0 & 1 & -1 \\ 1 & 0 & 2 & 1 \\ 0 & 1 & -1 & 3 \end{pmatrix}, B = \begin{pmatrix} 0 & 0 \\ 0 & 0 \\ 0 & 0 \\ 1 & 0 \\ 0 & 1 \end{pmatrix}, C = \begin{pmatrix} 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 1 \end{pmatrix}.$$

The pair $\{A, B\}$ is not controllable, so the first two components of the state vector cannot be affected by the control. However, the selected matrix C means that the sliding mode needs to be enforced in the last three components of the state vector simultaneously. Since the dimensions of C and B are not consistent then we cannot use the conventional scheme of the unit control design. Let us design the homogeneous unit control according to Theorem 3.

The equation (5) has the unique solution

$$\tilde{K} = \begin{pmatrix} 0 & -1 & 0 & 0 & 0 \\ -1 & 0 & 0 & 0 & 0 \end{pmatrix}.$$

In this case, we derive

$$A_{\sigma} = \begin{pmatrix} 1 & -1 & 1 \\ 0 & 2 & 1 \\ 1 & -1 & 3 \end{pmatrix}, \quad B_{\sigma} = \begin{pmatrix} 0 & 0 \\ 1 & 0 \\ 0 & 1 \end{pmatrix}.$$

The pair $\{A_{\sigma}, B_{\sigma}\}$ is controllable, so Assumption 2 is fulfilled. A solution of (14) is given by

$$G_0 = \begin{pmatrix} -1 & 0 & 0 \\ -0.5 & 0 & 0 \\ 0.5 & 0 & 0 \end{pmatrix}, \quad Y_0 = \begin{pmatrix} -0.5 & -2.5 & -0.5 \\ -1.5 & 1.5 & -3.5 \end{pmatrix}$$

so the generator of the dilation \mathbf{d} is defined as

$$G_{\mathbf{d}} = \begin{pmatrix} 2 & 0 & 0 \\ 0.5 & 1 & 0 \\ -0.5 & 0 & 1 \end{pmatrix}, K_0 = \begin{pmatrix} 0 & 0 & 0.5000 & -2.5000 & -0.5000 \\ 0 & 0 & -1.5000 & 1.5000 & -3.5000 \end{pmatrix}.$$

A. Homogeneous unit control

First, let us consider the disturbance-free case $\gamma \equiv \mathbf{0}$. Solving the linear system (18) for $\bar{\gamma} = 0$ and $\rho = 1$ we derive

$$K = \begin{pmatrix} 4.75 & -2 & 1 \\ -4.75 & 1 & -2 \end{pmatrix}, \quad P = \begin{pmatrix} 4.6 & -1.2 & 1.2 \\ -1.2 & 0.5538 & -0.2462 \\ 1.2 & -0.2462 & 0.5538 \end{pmatrix}.$$

The numerical simulation of the closed-loop system (1), (12) with $x_0 = (1, 0, 2, 0, 1)^{\top}$ was done in MATLAB using the explicit Euler method with the constant step $h = 0.001$. The simulation results for the disturbance-free case ($\gamma \equiv \mathbf{0}$) are depicted on Fig. 1.

In the disturbance-free case, the canonical homogeneous norm defines the reaching time. Indeed, according to Remark 4 the reaching time of the trajectory of the closed loop system is $\|Cx_0\|_{\mathbf{d}} \approx 2.8860$. The numerical simulations confirms this (up to the computation precision).

The homogeneous unit control design in the perturbed case uses Assumption 1 to define the maximum magnitude of the matched perturbations. Solving the linear system (18) for $\bar{\gamma} = 0.5$ we derive the control parameters

$$K = \begin{pmatrix} 5.8379 & -2.5103 & 1.1938 \\ -5.8379 & 1.1938 & -2.5103 \end{pmatrix}, P = \begin{pmatrix} 5.3112 & -1.3265 & 1.3265 \\ -1.3265 & 0.5413 & -0.2751 \\ 1.3265 & -0.2751 & 0.5413 \end{pmatrix}.$$




Fig. 1. The system with homogeneous unit control (disturbance-free case)




Fig. 2. The system with homogeneous unit control (perturbed case)

According to Theorem 3 the homogeneous unit control rejects bounded matched disturbances γ of the magnitude $\bar{\gamma} = 0.5$. The numerical simulations for the system with the matched disturbances modeled by $\gamma(t) = 0.5(\sin(10t), \cos(10t))^T$ are presented on Fig. 2.

Finally, to demonstrate the efficiency of the chattering attenuation scheme suggested in Remark 2, we present numerical simulations for the homogeneous unit control with the saturated canonical homogeneous norm (see the formula (22)). The simulation results for the system with matched perturbations and the saturation parameter $\alpha = 0.002$ are depicted in Fig. 3.

B. Homogeneous SMC with integral action

Selection of the parameters of the homogeneous SMC control with integral action is inspired by Theorem 4:

$$K = \begin{pmatrix} 4.4043 & -2.2933 & 0.9462 \\ -4.4043 & 0.9462 & -2.2933 \end{pmatrix}, K_1 = \begin{pmatrix} 1.3174 & -0.6732 & 0.2849 \\ -1.3174 & 0.2849 & -0.6732 \end{pmatrix}$$

with $\bar{\gamma} = 0.5$. The simulation for homogeneous SMC with integral action with $\gamma_0 = 1$ and $\tilde{\gamma} = |x_2|0.5(\sin(10t), \cos(10t))^T$ are depicted on Fig. 4. In contrast to the homogeneous unit control, the homogeneous SMC with integral action does not have a large (visible) chattering even without use of any chattering attenuation technique. This repeats the observation for the super-twisting controller in the single input case [17], [22].

VII. CONCLUSIONS

A methodology of a unit (sliding mode) control design has been revised. It is shown that a linear sliding surface $Cx = 0$ can be selected independently of the number of control inputs provided that the dynamics of the sliding variable $\sigma = Cx$ is controllable. The design is essentially based on the so-called homogeneous norm, which defines the homogeneous projector on the unit sphere. The mentioned homogeneous projector forms the discontinuous component of the unit control (in




Fig. 3. The system with homogeneous unit control with chattering attenuation




Fig. 4. The system with homogeneous SMC with integral action

both classical and revised cases), while the linear (continuous) component of the unit control is utilized (as usual) for a homogenization of the dynamics of the sliding variable. A possible extension of the super-twisting algorithm to the multi-input case is proposed as well. The simplicity of the control design and parameters tuning is demonstrated on example.

VIII. DEDICATION

This paper is dedicated to the memory of Prof. Vadim Utkin who passed away recently and who inspired me with the presented revision of the unit sliding mode control method.

REFERENCES

- [1] V. Andrieu, L. Praly, and A. Astolfi. Homogeneous Approximation, Recursive Observer Design, and Output Feedback. *SIAM Journal of Control and Optimization*, 47(4):1814–1850, 2008.
- [2] E. Bernuau, D. Efimov, W. Perruquetti, and A. Polyakov. On homogeneity and its application in sliding mode control. *Journal of The Franklin Institute*, 351(4):1866–1901, 2014.
- [3] S. P. Bhat and D. S. Bernstein. Geometric homogeneity with applications to finite-time stability. *Mathematics of Control, Signals and Systems*, 17:101–127, 2005.
- [4] E. Cruz-Zavala and J. A. Moreno. Homogeneous high order sliding mode design: A Lyapunov approach. *Automatica*, 80(6):232–238, 2017.
- [5] E. Cruz-Zavala, J.A. Moreno, and L.M. Fridman. Uniform robust exact differentiator. *IEEE Transactions on Automatic Control*, 56(11):2727–2733, 2011.
- [6] C. Edwards and S. Spurgeon. *Sliding Mode Control: Theory and Applications*. Taylor and Francis, 1998.
- [7] A. F. Filippov. *Differential Equations with Discontinuous Right-hand Sides*. Kluwer Academic Publishers, 1988.
- [8] V. Fischer and M. Ruzhansky. *Quantization on Nilpotent Lie Groups*. Springer, 2016.
- [9] G. Folland. Subelliptic estimates and function spaces on nilpotent Lie groups. *Arkiv for Matematik*, 13(1-2):161–207, 1975.
- [10] J. F. García-Mathey and J. A. Moreno. Mimo super-twisting controller: A new design. In *The 16th Workshop on Variable Structure Systems*, 2022.
- [11] L. Grüne. Homogeneous state feedback stabilization of homogeneous systems. *SIAM Journal of Control and Optimization*, 38(4):1288–1308, 2000.
- [12] S. Gutman and G. Leitmann. Stabilizing feedback control for dynamical systems with bounded uncertainties. In *IEEE Conference on Decision and Control*, pages 94–99, 1976.

- [13] H. Hermes. Nilpotent approximations of control systems and distributions. *SIAM Journal of Control and Optimization*, 24(4):731, 1986.
- [14] Y. Hong. H_∞ control, stabilization, and input-output stability of nonlinear systems with homogeneous properties. *Automatica*, 37(7):819–829, 2001.
- [15] L.S. Husch. Topological Characterization of The Dilation and The Translation in Frechet Spaces. *Mathematical Annals*, 190:1–5, 1970.
- [16] M. Kawski. Families of dilations and asymptotic stability. *Analysis of Controlled Dynamical Systems*, pages 285–294, 1991.
- [17] A. Levant. Sliding order and sliding accuracy in sliding mode control. *International Journal of Control*, 58(6):1247–1263, 1993.
- [18] A. Levant. Higher-order sliding modes, differentiation and output-feedback control. *International Journal of Control*, 76(9-10):924–941, 2003.
- [19] A. Levant. Homogeneity approach to high-order sliding mode design. *Automatica*, 41(5):823–830, 2005.
- [20] F. Lopez-Ramirez, A. Polyakov, D. Efimov, and W. Perruquetti. Finite-time and fixed-time observer design: Implicit Lyapunov function approach. *Automatica*, 87(1):52–60, 2018.
- [21] A. Mercado-Urbe, J. A. Moreno, A. Polyakov, and D. Efimov. Multiple-input multiple-output homogeneous integral control design using the implicit lyapunov function approach. *International Journal of Robust and Nonlinear Control*, 2021.
- [22] J. Moreno and M. Osorio. Strict Lyapunov functions for the super-twisting algorithm. *IEEE Transactions on Automatic Control*, 57:1035–1040, 2012.
- [23] A. Nekhoroshikh, D. Efimov, A. Polyakov, W. Perruquetti, and I. Furtat. Finite-time stabilization under state constraints. In *Conference on Decision and Control*, 2021.
- [24] E. Noether. Invariante variationsprobleme,. *Kgl. Ges. d. Wiss. Nachrichten, Math.-phys. Klasse (In German)*, pages 235–257, 1918.
- [25] Y. Orlov. Finite time stability and robust control synthesis of uncertain switched systems. *SIAM Journal of Control and Optimization*, 43(4):1253–1271, 2005.
- [26] W. Perruquetti, T. Floquet, and E. Moulay. Finite-time observers: application to secure communication. *IEEE Transactions on Automatic Control*, 53(1):356–360, 2008.
- [27] A. Pisano. On the multi-input second-order sliding-mode control of nonlinear uncertain systems. *International Journal of Robust and Nonlinear Control*, 22(15):1765–1778, 2012.
- [28] F. Plestan, A. Glumineau, and S. Laghrouche. A new algorithm for high order sliding mode control. *International Journal of Robust and Nonlinear Control*, 18:441–453, 2008.
- [29] A. Polyakov. Sliding mode control design using canonical homogeneous norm. *International Journal of Robust and Nonlinear Control*, 29(3):682–701, 2019.
- [30] A. Polyakov. *Generalized Homogeneity in Systems and Control*. Springer, 2020.
- [31] A. Polyakov, D. Efimov, and W. Perruquetti. Finite-time and fixed-time stabilization: Implicit Lyapunov function approach. *Automatica*, 51(1):332–340, 2015.
- [32] A. Polyakov, D. Efimov, and W. Perruquetti. Robust stabilization of MIMO systems in finite/fixed time. *International Journal of Robust and Nonlinear Control*, 26(1):69–90, 2016.
- [33] L. Rosier. Homogeneous Lyapunov function for homogeneous continuous vector field. *Systems & Control Letters*, 19:467–473, 1992.
- [34] Y. Shtessel, C. Edwards, L. Fridman, and A. Levant. *Sliding Mode Control and Observation*. Birkhauser, 2014.
- [35] K.P. Stanyukovich. *Unsteady motion of continuous media*. Oxford: Pergamon Press, 1960.
- [36] V. Utkin, A. Poznyak, Y. Orlov, and A. Polyakov. *Road Map for Sliding Mode Control Design*. Springer, 2020.
- [37] V. I. Utkin. Variable structure systems with sliding modes. *IEEE Transaction on Automatic Control*, AC-22:212–222, 1977.
- [38] V. I. Utkin. *Sliding Modes in Control Optimization*. Springer-Verlag, Berlin, 1992.
- [39] S. Wang, A. Polyakov, and G. Zheng. Generalized homogenization of linear controllers: Theory and experiment. *International Journal of Robust and Nonlinear Control*, 31(9):3455–3479, 2021.
- [40] Y. Zhou, A. Polyakov, and G. Zheng. On strict homogeneous lyapunov function for generalized homogeneous pi controller. In *IEEE Conference on Decision and Control*, 2021.
- [41] K. Zimenko, A. Polyakov, D. Efimov, and W. Perruquetti. On simple scheme of finite/fixed-time control design. *International Journal of Control*, 93(6):1353–1361, 2020.
- [42] K. Zimenko, A. Polyakov, D. Efimov, and W. Perruquetti. Robust feedback stabilization of linear mimo systems using generalized homogenization. *IEEE Transactions on Automatic Control*, 2020.
- [43] V.I. Zubov. On systems of ordinary differential equations with generalized homogeneous right-hand sides. *Izvestia vuzov. Mathematica (in Russian)*, 1:80–88, 1958.