HAL
open science

Optimal Control of an Ensemble of Bloch Equations with Applications in MRI

Jérémy Rouot, Bernard Bonnard, Alain Jacquemard

To cite this version:

Jérémy Rouot, Bernard Bonnard, Alain Jacquemard. Optimal Control of an Ensemble of Bloch Equations with Applications in MRI. 55th IEEE Conference on Decision and Control, Dec 2016, Las Vegas, United States. hal-02483336

HAL Id: hal-02483336

https://inria.hal.science/hal-02483336v1

Submitted on 18 Feb 2020

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Optimal Control of an Ensemble of Bloch Equations with Applications in MRI.

55th IEEE Conference on Decision and Control

Bernard Bonnard, Alain Jacquemard and Jérémy Rouot

- Ensemble of spin particles: mathematical model in Nuclear Magnetic Resonance
- (Multi)Saturation problem, constrast problem
  $\Longrightarrow$ Optimal control problem (Mayer formalism)
- Geometric optimal control: Pontryagin Maximum Principle, second order optimality conditions
- Numerical methods: Direct methods (Bocop software), Indirect methods (Hampath Software), Global methods based on SOS-moment approach (Globtipoly)

Bloch equations M_i: magnetization vector of the spin particle $i \in \{1 \dots N\}$.

$$\dot{M}_i(t) = \kappa M_i(t) \times B(t) + R(M_i)$$

- dissipative term:

$$R(M_i) = (\, M_{x_i}/T_2^i, M_{y_i}/T_2^i, (M_{z_i} - M_0^i)/T_1^i \,)$$

. M_0^i: equilibrium magnetizarion.

. T_1^i, T_2^i: relaxation parameters, chemical signature of the species.



- $B(t) = B_0 + B_1(t)$,

. B_0: **strong static field.**

. $B_1 = (B_x, B_y, 0)$: **control RF-field**.

$$u = -\kappa B_y, \qquad v = -\kappa B_x, \qquad u^2 + v^2 \leq m$$

Rotating frame

$$M_i(t) = S(t)\, q_i(t), \quad q_i = (x_i, y_i, z_i), \quad S(t) = \exp(\omega t \Omega_z),\ \Omega_z = \begin{pmatrix} 0 & -1 & 0 \\ 1 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix}$$

$$u_2 = u\cos(\omega t) - v\sin(\omega t),\ u_1 = u\sin(\omega t) + v\cos(\omega t)$$

$$\frac{\mathrm{d}}{\mathrm{d}t}\begin{pmatrix} x_i \\ y_i \\ z_i \end{pmatrix} = \begin{pmatrix} -1/T_2^i & -\Delta\omega_i & u_2 \\ \Delta\omega_i & -1/T_2^i & -u_1 \\ -u_2 & u_1 & -1/T_1^i \end{pmatrix}\begin{pmatrix} x_i \\ y_i \\ z_i \end{pmatrix} + \begin{pmatrix} 0 \\ 0 \\ M_0^i/T_1^i \end{pmatrix}$$

with $\Delta\omega_i$ the resonance offset.

Affine control system

$$\dot{q} = F_0(q) + u_1 F_1(q) + u_2 F_2(q), \quad q = (q_1, \ldots, q_N)$$

- **saturation problem** for N spins: $\min t_f$, $q_i(0) = (0, 0, M_0^i)$, $q_i(t_f) = O$, $i = 1, \ldots N$.
- **contrast problem** for 2 spins: $\min -|q_2(t_f)|^2$, $q_i(0) = (0, 0, M_0^i)$, $i = 1, 2$, $q_1(t_f) = O$.

$\Longrightarrow$ Mayer problem

- system with k controls, state $q \in \mathbf{R}^n$

$$\dot{q} = F_0(q) + \sum_{i=1}^{m} u_i F_i(q), \quad u \in U \subset \mathbf{R}^m, \quad q(0) = q_0$$

- final boundary condition: $g(q(t_f)) = 0$
- cost to minimize: $\min_{u \in \mathscr{U}} c(q(t_f))$, $\mathscr{U}$ = admissible controls.

Necessary conditions: (q^*, u^*) optimal $\Longrightarrow \exists\ p^* \in \mathbf{R}^n$

$$\dot{q}^* = \frac{\partial H}{\partial p}(q^*, p^*, u^*), \quad \dot{p}^* = -\frac{\partial H}{\partial q}(q^*, p^*, u^*), \quad H(q, p, u) = \langle p, F_0(q) + \sum_{i=1}^{m} u_i F_i(q) \rangle.$$

maximization condition:

$$H(q^*, p^*, u^*) = \max_{u \in U} H(q^*, p^*, u) = constant.$$

transversality condition:

$$p^*(t_f) = p_0 \frac{\partial c}{\partial q}(q^*(t_f)) + \sum_{i=1}^{l} \sigma_i \frac{\partial g_i}{\partial q}(q^*(t_f)), \quad \boldsymbol{p_0} \leq \mathbf{0}, \quad \sigma = (\sigma_1, \ldots, \sigma_l) \in \mathbf{R}^l.$$

Definition 1. *Extremal: solution* (q, p, u) *of the Hamiltonian system of the PMP.*

Define the input state mapping for (T, q_0) fixed:

$$E_{T,q_0} : u \in \mathscr{U} \mapsto q(T, q_0, u)$$

Definition 2. u *is singular on* $[0, T]$ *if the Fréchet derivative of* E *is not of full rank when evaluated at* u *and the corresponding trajectory* $q(., q_0, u)$ *is called singular on* $[0, T]$.

Symmetry of revolution along z axis: reduction to the case: $u_2 = 0$, $u_1 = u$, $M_0 = 1$, $\tau = mt$.
$\Gamma = 1/mT_2$, $\gamma = 1/mT_1$ with $2\Gamma > \gamma \to$ Bloch ball $= \{q, |q| \leq 1\}$ invariant.

$$\dot{q} = F(q) + uG(q), \quad q = (y,z), \quad |u| \leq 1$$

Definition 3. • *Regular extremal (bang):* $u = \mathit{sign}\, H_G, \quad H_G = \langle p, G(q) \rangle$,

• *Singular extremal:* $H_G(q,p) = 0$...

Computations of singular extremals

$$\begin{aligned} &H_G(q,p) = 0 \Longrightarrow \{H_G, H_F\}(q,p) = 0, \\ &\Longrightarrow \{\{H_G, H_F\}, H_F\}(q,p) + u_s \{\{H_G, H_F\}, H_G\}(q,p) = 0, \end{aligned}$$

$\Longrightarrow u_s(\boldsymbol{q}, \boldsymbol{p})$ is defined for $(q,p) \in \Sigma_2 : H_G = \{H_G, H_F\} = 0 \setminus \{\{H_G, H_F\}, H_G\} = 0$.

Singular arcs are contained in the set $\{q, \det(G(q), [F,G](q)) = 0\}$ with an expresion of $u_s(\boldsymbol{q})$.

Time minimal synthesis for 1 spin (Bonnard et al.) 2012



Solutions for the saturation problem



Time minimal solution (left) compared with inversion sequence (right).
(left): $\tau_f = T_{\min}$, ($T_{\min}$ known) $\rightarrow \delta_+ \, \delta_s^h \, \delta_+ \, \delta_s^v$
(right): Time minimal solutions: Bang-Singular: $\delta_+ \, \delta_s^v$

$N = 2$ spins, $(q_1, (\Gamma_1, \gamma_1))$, $(q_2, (\Gamma_2, \gamma_2))$.
Optimal control problem: $|u| \leq 1$.

- $q(t_f) = (0,0)$, $q = (q_1, q_2)$,
- Mayer cost: $c(q(t_f))$,
- Dynamic: $\dot{q}_i = F_0^i(q_i) + u_1 F_1^i(q_i) + u_2 F_2^i(q_i), \quad i = 1,2$ where

$$F_0^i = -\Gamma_i x_i \partial_{x_i} - \Gamma_i y_i \partial_{y_i} + \gamma_i (1 - z_i) \partial_{z_i},$$
$$F_1^i = -z_i \partial_{y_i} + y_i \partial_{z_i}, \quad F_2^i = z_i \partial_{x_i} - x_i \partial_{z_i}.$$

Maximization condition of the PMP. if $w = (q,p) \notin \Sigma = \{w, H_1 = H_2 = 0\}$:

$$u_j = H_j / \sqrt{H_1^2 + H_2^2}, \quad H_j = \langle p, F_j \rangle, \ j = 1,2$$

Singular extremals: u singular $\Longrightarrow (q,p,u)$ is an extremal satisfying

$$\dot{q} = \frac{\partial H}{\partial p}, \quad \dot{p} = -\frac{\partial H}{\partial q}, \quad \frac{\partial H}{\partial u} = 0 \ \text{ where } \ H = H_0 + u_1 H_1 + u_2 H_2.$$

Stratification of the surface $\Sigma = \{w = (q,p), H_1 = H_2 = 0\}$.

$$\Sigma = \Sigma_1 \cup \Sigma_2 \cup \Sigma_3$$

- If $\boldsymbol{w = (q,p) \in \Sigma_1 = \Sigma \setminus \{H_1, H_2\} = 0}$, singular control:

$$u_s(w) = \frac{(\{H_2, H_0\}(w), \{H_0, H_1\}(w))}{\{H_1, H_2\}(w)}$$

  ... but it's not an admissible control $|u_s^1| > 1$.

- Goh condition: $\{H_1, H_2\} = 0$.
  If $w \in \Sigma \cap \{H_1, H_2\} = 0$, then

$$\{H_0, H_1\} = \{H_2, H_0\} = 0$$

  We get 3 relations that we differentiate w.r.t. the time and the singular control u_s satisfies

$$A(w) + u_s B(w) = 0$$

  u_s is defined provided $\boldsymbol{w \in \Sigma_2 : H_1 = H_2 = \{H_1, H_2\} = 0 \setminus \det B = 0}$.

With

$$A = \begin{pmatrix} \{\{H_0, H_1\}, H_0\} \\ \{\{H_0, H_2\}, H_0\} \end{pmatrix}, \quad B = \begin{pmatrix} \{\{H_0, H_1\}, H_1\} & \{\{H_0, H_1\}, H_2\} \\ \{\{H_0, H_2\}, H_1\} & \{\{H_0, H_2\}, H_2\} \end{pmatrix}$$

Remark 4. *It is possible to write u_s function of q only.*

$$\boldsymbol{\Sigma_3 : H_1 = H_2 = \{H_1, H_2\} = \{H_0, H_1\} = \{H_0, H_2\} = \det(B) = 0}$$

We can find singular extremals in Σ_3.

- $y_2 x_1 - x_2 y_1$ divides $\det B$,
- $x_1 = x_2 = 0$ is invariant by the singular flow imposing $u_2 = 0$ $\Longrightarrow \det B = 0$ is forced to be invariant,
- $\{H_1, H_2\}(w) = (p_{y_1} x_1 - p_{x_1} y_1) + (p_{y_2} x_2 - p_{x_2} y_2)$ is first integral (symmetry of revolution).

Proposition 5. *The singular extremals of the single-input case with $u_2 = 0$ are extremals of the bi-input case with the additional condition: $x_1 = p_{x_1} = x_2 = p_{x_2} = 0$.*

It amounts to study the single input system

$$\dot{q} = F_0(q) + u F_1(q), \quad q = (y, z)$$

with singular control

$$u_s(w) = -\frac{\{\{H_0, H_1\}, H_0\}(w)}{\{\{H_0, H_1\}, H_1\}(w)}$$

Application: multisaturation of the same species with B_1-inhomogeneity

$q = (q_1, q_2)$, same relaxations parameters (Γ, γ) for q_1 and q_2.

pixels with different B_1



$$
\begin{array}{ll}
\min & t_f \\
\text{s.t.} & \dot{q}_1 = F_0(q_1) + u F_1(q_1), \\
& \dot{q}_2 = F_0(q_2) + u\,\boldsymbol{(1-\varepsilon)}\,F_1(q_2), \\
& q_1(t_f) = q_2(t_f) = 0, \\
& q(0) = ((0,1),(0,1)).
\end{array}
$$

Additionnal constraint: $H = 0$ (t_f free).
Singular control in $H_0 = H_1 = \{H_1, H_0\} = \det B = 0$:

$$u_s(q) = -\frac{D'(q)}{D(q)}$$

$D = \det(F_0, F_1, [F_1, F_0], [[F_1, F_0], F_1])$, $D' = \det(F_0, F_1, [F_1, F_0], [[F_1, F_0], F_0])$.
$\Longrightarrow$ analysis of the flow of $F_0 - D'/D\,F_1$ i.e. of

$$X(q) = D(q)\,F_0(q) - D'(q)\,F_1(q)$$

Computations of the equilibirum points of X. Non trivial algebraic problem (Gröbner basis).

Theorem 6. *For $\varepsilon \neq 1$, the equilibirum points of X are all contained in $\{D(q) = 0\} \cap \{D'(q) = 0\}$.*

Proposition 7. *$\{D = 0\} \cap \{D' = 0\}$ is an algebraic variety of dimension 2 whose components are located in the hyperplane $z_1 = z_2$ and in the hypersurface $(\varepsilon - 1) z_1 y_2 + z_2 y_1 = 0$.*

Algebraic analysis of these components $\Longrightarrow$ computations of equilibirum points.

Further analysis: behaviours of the solutions of X near these equilibrium points using linearized methods.