



Averaging techniques in the time minimal orbital transfer using low propulsion

Jérémie Rouot, Bernard Bonnard, Jean-Baptiste Caillau, Jean-Baptiste Pomet

► To cite this version:

Jérémie Rouot, Bernard Bonnard, Jean-Baptiste Caillau, Jean-Baptiste Pomet. Averaging techniques in the time minimal orbital transfer using low propulsion. Nonlinear Control and Geometry, Aug 2015, Bedlewo, Poland. hal-02483388

HAL Id: hal-02483388

<https://inria.hal.science/hal-02483388>

Submitted on 18 Feb 2020

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Averaging techniques in the time minimal orbital transfer using low propulsion

Jérémie Rouot

NONLINEAR CONTROL AND GEOMETRY
Będlewo, Poland, 24-28 August 2015

jeremy.rouot@inria.fr



Joint work with B. Bonnard, J.B. Caillau and J.B. Pomet.

Some historical points about optimal control and orbital transfer with low thrust

- ≈ 1970 , electro-ionic propulsion where the thrust is very low (spiral transfer).
Missions: Artemis-ESA (2001, GST), Smart-1-ESA (2006, GST to lunar orbit), BepiColombo-ESA (2016, Mercury).
- Epenoy-Geffroy (1997) use averaging techniques coupled with the Pontryagin Maximum Principle for low thrust transfer.
- Bonnard-Caillau (2007) computed explicitly the averaged Hamiltonian in the case of the energy cost.
It defines a Riemannian metric which allows to compute extremal curves for coplanar transfers.


Time minimal orbital transfer problem

$q \in \mathbb{R}^3$: position vector of the satellite,

$$\ddot{q} + \nabla V(q) = 0, \quad V(q) = -\frac{1}{|q|}.$$

Elliptic orbits: restriction to $\mathcal{E} = \{(q, \dot{q}) \mid q \times \dot{q} \neq 0 \text{ and } \frac{1}{2}|\dot{q}|^2 - V(q) < 0\}$.

Kepler's orbital elements



$(a, e, i, \omega, \Omega)$: shape and orientation of the ellipse,

θ : angle locating the satellite on its orbit.

The uncontrolled motion can be described by $(I, \varphi = F(I, \theta))$

$$\begin{aligned}\dot{I} &= 0 \\ \dot{\varphi} &= \nu(I).\end{aligned}$$

$0 < \varepsilon \ll 1$, $(I(t), \varphi(t)) \in \mathbb{R}^5 \times S^1$: state variables of the satellite, $u(t) \in \mathbb{R}^3$, $F_i(I, \varphi, \varepsilon), G_i(I, \varphi, \varepsilon)$ $i = 1..3$ are **2π -periodic** vector fields with respect to φ .

Time minimal orbital transfer problem


$$\min_{|u| \leq 1} t_f(u)$$

subject to $\dot{I} = \varepsilon F_0(I, \varphi, \varepsilon) + \varepsilon \sum_{i=1}^3 u_i F_i(I, \varphi, \varepsilon)$, $\dot{\varphi} = \nu(I) + \varepsilon \sum_{i=1}^3 u_i G_i(I, \varphi, \varepsilon)$

$$I(0) = I_0, \quad I(t_f(u)) = I_f.$$

The vector field F_0 takes into account conservative perturbations such as

- lunar and solar attraction,
- J_2 -effect.



Averaging principle for dynamical system

Let $f(X, \psi, \varepsilon), g(X, \psi, \varepsilon)$ be two smooth **2π -periodic** vector fields with respect to $\psi \in S^1$.

Perturbed system

$$\begin{aligned}\dot{X} &= \varepsilon f(X, \psi, \varepsilon) \\ \dot{\psi} &= \nu(X) + \varepsilon g(X, \psi, \varepsilon).\end{aligned}$$

Averaged system

$$\begin{aligned}\dot{Y} &= \varepsilon F(Y) \\ \text{where } F(Y) &= \frac{1}{2\pi} \int_0^{2\pi} f(Y, \psi, \varepsilon = 0) d\psi.\end{aligned}$$

Theorem 1. Assume $|\nu(X)| > R > 0$ and let $\tau > 0$ fixed.

If

- $(X_\varepsilon(.), \psi_\varepsilon(.))_\varepsilon$ is a family of solutions of the **perturbed system** on $[0, \frac{\tau}{\varepsilon}]$,
- $X_\varepsilon(0) \xrightarrow[\varepsilon \rightarrow 0]{} X_0^0$.

Then $t \rightarrow X_\varepsilon(\varepsilon t)$ uniformly converges on $[0, \tau]$ to $t \rightarrow \bar{Y}(t)$ such that

- $\bar{Y}(.)$ is a solution of the **averaged system**,
- $\bar{Y}(0) = X_0^0$.

Non averaged system

Applying the PMP, a minimizing trajectory is projection of an extremal $(I(.), \varphi(.), p_I(.), p_\varphi(.))$ solution of the Hamiltonian system defined by

$$H(I, \varphi, p_I, p_\varphi, \varepsilon) = p_\varphi \nu(I) + \varepsilon K(I, \varphi, p_I, p_\varphi, \varepsilon),$$

$$K := \sqrt{\sum_{i=1}^m H_i^2}, \quad H_i(I, \varphi, p_I, p_\varphi, \varepsilon) = p_I F_i(I, \varphi, \varepsilon) + p_\varphi G_i(I, \varphi, \varepsilon), \quad i=0, \dots, m.$$

The extremal system is

$$\begin{aligned} \dot{I} &= \varepsilon \frac{\partial K}{\partial p_I}, & \dot{p}_I &= -p_\varphi \nu' - \varepsilon \frac{\partial K}{\partial I} \\ \dot{\varphi} &= \nu + \varepsilon \frac{\partial K}{\partial p_\varphi}, & \dot{p}_\varphi &= -\varepsilon \frac{\partial K}{\partial \varphi}. \end{aligned} \tag{*}$$

The adjoint vector p_I might be not a slow variable ($\dot{p}_I = O(\varepsilon)$?).

Normalization of the non averaged system

We decide to normalize on the energy level $H(I, \varphi, p_I, p_\varphi, \varepsilon) = \varepsilon$, then one can reduce our system by setting $p_\varphi = \varepsilon \frac{K-1}{\nu}$, and locally we can write

$$p_\varphi = -\varepsilon h(I, \varphi, p_I, \varepsilon).$$

This yields to have p_I as a **slow variable**, so is I .

→ The system can be averaged classically with respect to φ .

Boundary conditions and transversality conditions

$$I(0) = I_0, \quad p_\varphi(0) = 0, \quad I(t_f(\varepsilon)) = I_f, \quad p_\varphi(t_f(\varepsilon)) = 0, \quad H = \varepsilon.$$

Remark. Parameterizing by φ , the non averaged extremal system (*) is hamiltonian

$$\frac{dI}{d\varphi} = \varepsilon \frac{\partial h}{\partial p_I}, \quad \frac{dp_I}{d\varphi} = -\varepsilon \frac{\partial h}{\partial I}. \quad (\text{non averaged})$$

Averaged of the orbital transfer problem

The averaged dynamic is defined by

$$\begin{aligned}\bar{h}(I, p_I) &:= \frac{1}{2\pi} \int_0^{2\pi} h(I, \varphi, p_I, \varepsilon = 0) d\varphi \\ &= \frac{1}{2\pi} \int_0^{2\pi} \frac{K-1}{\nu}(I, \varphi, p_I, p_\varphi = 0, \varepsilon = 0) d\varphi.\end{aligned}$$

Parameterizing by $s := \varepsilon(\varphi - \varphi_0)$ leads to the **averaged boundary value problem**

$$\begin{aligned}\frac{dI}{ds} &= \frac{\partial \bar{h}}{\partial p_I}, & \frac{dp_I}{ds} &= -\frac{\partial \bar{h}}{\partial I}, & & (averaged) \\ I(0) &= I_0, & I(s_f) &= I_f, & \bar{h} &= 0.\end{aligned}$$

This system defines a distance on the set of elliptic Keplerian orbits

$$d(I_0, I_f) = s_f.$$

Singularity

The Hamiltonian H is non smooth on the set

$$\mathcal{S}_\varepsilon = \{(I, \varphi, p_I, p_\varphi) | H(I, \varphi, p_I, p_\varphi) - \varepsilon = 0 \text{ and } H_i(I, \varphi, p_I, p_\varphi, \varepsilon) = 0, i = 1, 2, 3\}.$$

$$\text{codim}(\mathcal{S}_\varepsilon) = 3 \text{ in } \{(I, \varphi, p_I, p_\varphi) | H(I, \varphi, p_I, p_\varphi) - \varepsilon = 0\}.$$

We define

$$\mathcal{S}_0 = \{(I, \varphi, p_I, p_\varphi) | p_\varphi = 0 \text{ and } H_i(I, \varphi, p_I, p_\varphi = 0, \varepsilon = 0) = 0, i = 1, 2, 3\}.$$

Then, the averaged Hamiltonian is non smooth on

$$\overline{\mathcal{S}} = \{(I, p_I) | \exists \varphi, (I, \varphi, p_I, 0) \in \mathcal{S}_0\}$$

which is of **codimension 2**.

Convergence theorem

Let V an open subset of the lifted Keplerian elliptic orbits set such that $\overline{\mathcal{S}} \cap V = \emptyset$.

Theorem 2. If


- $(I^\varepsilon(.), \varphi^\varepsilon(.), p_{I^\varepsilon}(.), p_\varphi^\varepsilon(.))_\varepsilon$ is a family of extremals defined on $[0, t_f(\varepsilon)]$ of the non averaged boundary value problem,
- $\forall t \in [0, t_f(\varepsilon)], (I^\varepsilon(t), p_{I^\varepsilon}(t)) \in K \subset V$, K compact, so that, for ε small enough $(I^\varepsilon(t), \varphi^\varepsilon(t), p_{I^\varepsilon}(t), p_\varphi^\varepsilon(t)) \notin \mathcal{S}_\varepsilon$.

Then $t \rightarrow (I^\varepsilon(\varepsilon t), p_{I^\varepsilon}(\varepsilon t))$ converges uniformly to $t \rightarrow (\bar{I}(t), \bar{p}_I(t))$ on $[0, \bar{t}_f]$ which is an extremal of the averaged boundary values problem with conditions

$$\bar{I}(0) = I_0, \quad \bar{I}(\bar{t}_f) = I_f.$$


Dowód. Using the uniform convergence on $[0, T]$ of the previous averaging theorem and the equicontinuity of the family $(I^\varepsilon(.))_\varepsilon$, the uniform convergence and the boundary conditions are satisfied. □

States : $I(t) = (P, e_x, e_y, h_x, h_y)(t)$ et $\varphi(t) = l(t)$




*Minimizing trajectories - Thrust 3N, $\varepsilon \approx 2e-2$
black: non averaged, red: averaged.*

States : $I(t) = (P, e_x, e_y, h_x, h_y)(t)$ et $\varphi(t) = l(t)$




*Minimizing trajectories - Thrust 0.5N, $\varepsilon \approx 4e-3$
black: non averaged, red: averaged.*

Adjoints $p_I(t) = (p_P, p_{e_x}, p_{e_y}, p_{h_x}, p_{h_y})(t)$ et $p_\varphi(t) = p_l(t)$




*Minimizing trajectories - Thrust 3N, $\varepsilon \approx 2e-2$
 black: non averaged, red: averaged.*

Adjoints $p_I(t) = (p_P, p_{e_x}, p_{e_y}, p_{h_x}, p_{h_y})(t)$ et $p_\varphi(t) = p_l(t)$




Minimizing trajectories - Thrust 0.5N, $\varepsilon \approx 4e-3$
black: non averaged, red: averaged.

Cartesian coordinates




Thrust 3N - some orbits of the averaged trajectories are represented in red.

Cartesian coordinates



Thrust 0.5N - some orbits of the averaged trajectories are represented in red.



Relative error between $t_{f_{optimal}}$ (non averaged optimal time) et $t_{f_{moy}}$ (estimated from normalized optimal angle s_f of the averaged system).

References

- [1] Bombrun, Alex; Pomet, Jean-Baptiste. *The averaged control system of fast-oscillating control systems.* SIAM J. Control Optim. 51 (2013), no. 3, 2280–2305.
- [2] Thèses et habilitations / Ph.D Theses and Habilitation Theses Sophie Geffroy. *Généralisation des techniques de moyennation en contrôle optimal - Application aux problèmes de transfert et rendez-vous orbitaux à poussée faible.* Thèse de doctorat, Institut National Polytechnique de Toulouse, octobre 1997.
- [3] Bonnard, Bernard; Caillau, Jean-Baptiste. *Riemannian metric of the averaged energy minimization problem in orbital transfer with low thrust.* Ann. Inst. H. Poincaré Anal. Non Linéaire 24 (2007), no. 3, 395–411.