

Asymptotic models for Hamilton-Jacobi-Bellman equations

Antonio Siconolfi

▶ To cite this version:

Antonio Siconolfi. Asymptotic models for Hamilton-Jacobi-Bellman equations. NETCO 2014 - New Trends in Optimal Control, Jun 2014, Tours, France. hal-01024609

HAL Id: hal-01024609 https://inria.hal.science/hal-01024609

Submitted on 16 Jul 2014

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Asymptotic models for Hamilton–Jacobi–Bellman equations

A. Siconolfi

Università di Roma La Sapienza

partially in collaboration with Nguyen Thuong

Tours, June 2014

We deal with a singularly perturbed optimal control problem with a slow variable, and a fast one depending on a parameter ε devoted to become infinitesimal.

We deal with a singularly perturbed optimal control problem with a slow variable, and a fast one depending on a parameter ε devoted to become infinitesimal.

We study the asymptotics, as ε goes to 0, of the corresponding value functions following a PDE approach proposed in this context by Alvarez–Bardi.

We deal with a singularly perturbed optimal control problem with a slow variable, and a fast one depending on a parameter ε devoted to become infinitesimal.

We study the asymptotics, as ε goes to 0, of the corresponding value functions following a PDE approach proposed in this context by Alvarez–Bardi.

It is in turn, inspired by tools developed in the framework of homogenization of Hamilton–Jacobi equations, Lions–Papanicolau–Varadhan and Evans, and requires periodicity in the fast variable.

We deal with a singularly perturbed optimal control problem with a slow variable, and a fast one depending on a parameter ε devoted to become infinitesimal.

We study the asymptotics, as ε goes to 0, of the corresponding value functions following a PDE approach proposed in this context by Alvarez–Bardi.

It is in turn, inspired by tools developed in the framework of homogenization of Hamilton–Jacobi equations, Lions–Papanicolau–Varadhan and Evans, and requires periodicity in the fast variable.

However Arstein–Gaitsgory (2000) have studied a similar model with other techniques where periodicity is in a sense replaced by coercivity conditions.

We deal with a singularly perturbed optimal control problem with a slow variable, and a fast one depending on a parameter ε devoted to become infinitesimal.

We study the asymptotics, as ε goes to 0, of the corresponding value functions following a PDE approach proposed in this context by Alvarez–Bardi.

It is in turn, inspired by tools developed in the framework of homogenization of Hamilton–Jacobi equations, Lions–Papanicolau–Varadhan and Evans, and requires periodicity in the fast variable.

However Arstein–Gaitsgory (2000) have studied a similar model with other techniques where periodicity is in a sense replaced by coercivity conditions.

Our aim is to recover their results adapting Alvarez–Bardi techniques to the nonperiodic case.

The controlled dynamics with a slow and a fast variable is given by

The controlled dynamics with a slow and a fast variable is given by

$$\begin{cases} \dot{x} = f(x, y, \alpha) \\ \varepsilon \dot{y} = g(x, y, \alpha) \end{cases}$$
 (CD_{\varepsilon})

The controlled dynamics with a slow and a fast variable is given by

$$\begin{cases} \dot{x} = f(x, y, \alpha) \\ \varepsilon \dot{y} = g(x, y, \alpha) \end{cases}$$
 (CD_{\varepsilon})

where

• both the state variables x and y lies in \mathbb{R}^N

The controlled dynamics with a slow and a fast variable is given by

$$\begin{cases} \dot{x} = f(x, y, \alpha) \\ \varepsilon \dot{y} = g(x, y, \alpha) \end{cases}$$
 (CD_{\varepsilon})

where

- both the state variables x and y lies in \mathbb{R}^N
- \circ α is measurable bounded control taking values in a compact subset A of \mathbb{R}^M

The controlled dynamics with a slow and a fast variable is given by

$$\begin{cases} \dot{x} = f(x, y, \alpha) \\ \varepsilon \dot{y} = g(x, y, \alpha) \end{cases}$$
 (CD_{\varepsilon})

where

- o both the state variables x and y lies in \mathbb{R}^N
- α is measurable bounded control taking values in a compact subset A of \mathbb{R}^M
- $f,g:\mathbb{R}^N\times\mathbb{R}^N\times A$ satisfy the usual conditions in order to have, for any initial datum (x_0,y_0) and control α unique solution $(x(t;x_0,y_0,\alpha),y(t;x_0,y_0,\alpha))$ to $(\mathsf{CD}_\varepsilon)$

The controlled dynamics with a slow and a fast variable is given by

$$\begin{cases} \dot{x} = f(x, y, \alpha) \\ \varepsilon \dot{y} = g(x, y, \alpha) \end{cases}$$
 (CD_{\varepsilon})

where

- both the state variables x and y lies in \mathbb{R}^N
- α is measurable bounded control taking values in a compact subset A of \mathbb{R}^M
- $f,g:\mathbb{R}^N\times\mathbb{R}^N\times A$ satisfy the usual conditions in order to have, for any initial datum (x_0,y_0) and control α unique solution $(x(t;x_0,y_0,\alpha),y(t;x_0,y_0,\alpha))$ to $(\mathsf{CD}_\varepsilon)$
- f and g are bounded.



• an uniformly continuous running cost $\ell : \mathbb{R}^N \times \mathbb{R}^N \times A \to \mathbb{R}$.

- o an uniformly continuous running cost $\ell : \mathbb{R}^N \times \mathbb{R}^N \times A \to \mathbb{R}$.
- a bounded continuous terminal cost that we assume for simplicity solely depending on the slow variable, $u_0(x)$, $u_0: \mathbb{R}^N \to \mathbb{R}$

- o an uniformly continuous running cost $\ell : \mathbb{R}^N \times \mathbb{R}^N \times A \to \mathbb{R}$.
- a bounded continuous terminal cost that we assume for simplicity solely depending on the slow variable, $u_0(x)$, $u_0: \mathbb{R}^N \to \mathbb{R}$

and the related optimal control problem

$$\min_{\alpha} \int_{0}^{t} \ell(x(s), y(s), \alpha(s)) ds + u_{0}(x(t))$$
 (Min_{\varepsilon})

with

- o an uniformly continuous running cost $\ell: \mathbb{R}^N \times \mathbb{R}^N \times A \to \mathbb{R}$.
- a bounded continuous terminal cost that we assume for simplicity solely depending on the slow variable, $u_0(x)$, $u_0: \mathbb{R}^N \to \mathbb{R}$

and the related optimal control problem


$$\min_{\alpha} \int_{0}^{\tau} \ell(x(s), y(s), \alpha(s)) ds + u_{0}(x(t))$$
 (Min_{\varepsilon})

with

$$x(\cdot) = x(\cdot, x_0, y_0, \alpha)$$

 $y(\cdot) = y(\cdot, x_0, y_0, \alpha)$

solutions to (CD_{ε}) with initial data (x_0, y_0) .



Aim

We deal with the related singular perturbation problem, namely with the asymptotics as $\varepsilon \to 0$. Our specific aim is to

Aim

We deal with the related singular perturbation problem, namely with the asymptotics as $\varepsilon \to 0$. Our specific aim is to

• study the convergence of the value functions of (Min_{ε}) to the value function of the limit problem.

Aim

We deal with the related singular perturbation problem, namely with the asymptotics as $\varepsilon \to 0$. Our specific aim is to

study the convergence of the value functions of (Min_{ε}) to the value function of the limit problem.

The form of the limit problem is well understood thanks to a series of papers of Arstein and Gaitsgory (1998–2005) where they adapt, to describe it, the Krylov–Bogolyubov theory of invariant measures for flows.

We fix the slow variable x_0 , a control α , and consider the trajectory $y(\cdot)$ solution to

$$\dot{y}=g(x_0,y,\alpha)$$

with some initial datum y_0

We fix the slow variable x_0 , a control α , and consider the trajectory $y(\cdot)$ solution to

$$\dot{y} = g(x_0, y, \alpha)$$

with some initial datum y₀

We define a probability measure on $\mathbb{R}^N \times A$ via

$$\frac{1}{t}\int_0^t \mathbb{I}_E(y(s), \alpha(s)) ds$$

where E is any Borel subset of $\mathbb{R}^N \times A$ and \mathbb{I}_E the corresponding indicator function.

We fix the slow variable x_0 , a control α , and consider the trajectory $y(\cdot)$ solution to

$$\dot{y} = g(x_0, y, \alpha)$$

with some initial datum y_0

We define a probability measure on $\mathbb{R}^N \times A$ via

$$\frac{1}{t}\int_0^t \mathbb{I}_E(y(s), \alpha(s)) ds$$

where E is any Borel subset of $\mathbb{R}^N \times A$ and \mathbb{I}_E the corresponding indicator function.

The controls of the limit system (depending on the state) are given by the closure $M(x_0)$ wit respect to the weak convergence of the previous measures.

These are called limit occupational or holonomic measures.

The limit dynamics is given by

The limit dynamics is given by

$$\dot{x} = f(x, \mu)$$
 $\mu \in M(x)$

with

$$f(x,\mu) = \int f(x,y,a) \, d\mu(y,a)$$

The limit dynamics is given by

$$\dot{x} = f(x, \mu)$$
 $\mu \in M(x)$

with

$$f(x,\mu) = \int f(x,y,a) \, d\mu(y,a)$$

and the limit cost by

$$\ell(x,\mu) = \int \ell(x,y,a) \, d\mu(y,a)$$

We write the Hamiltonian

$$H(x, y, p, q) = \max_{a \in A} \{-p \cdot f(x, y, a) - q \cdot g(x, y, a) - \ell(x, y, a)\}$$

We write the Hamiltonian

$$H(x, y, p, q) = \max_{a \in A} \{-p \cdot f(x, y, a) - q \cdot g(x, y, a) - \ell(x, y, a)\}$$

and the limit Hamiltonian

$$\overline{H}(x,p) = \max_{\mu \in M(x)} \{-p \cdot f(x,\mu) - -\ell(x,\mu)\}$$

We write the Hamiltonian

$$H(x, y, p, q) = \max_{a \in A} \{-p \cdot f(x, y, a) - q \cdot g(x, y, a) - \ell(x, y, a)\}$$

and the limit Hamiltonian

$$\overline{H}(x,p) = \max_{\mu \in M(x)} \{ -p \cdot f(x,\mu) - -\ell(x,\mu) \}$$

we write the family of Hamilton-Jacobi-Bellman equations

$$\begin{cases} v_t^{\varepsilon} + H\left(x, y, D_x v^{\varepsilon}, \frac{D_y v^{\varepsilon}}{\varepsilon}\right) &= 0\\ v^{\varepsilon}(x, y, 0) &= u_0(x) \end{cases}$$
(Hj_{\varepsilon})

We write the Hamiltonian

$$H(x, y, p, q) = \max_{a \in A} \{-p \cdot f(x, y, a) - q \cdot g(x, y, a) - \ell(x, y, a)\}$$


and the limit Hamiltonian

$$\overline{H}(x,p) = \max_{\mu \in M(x)} \{ -p \cdot f(x,\mu) - -\ell(x,\mu) \}$$

we write the family of Hamilton-Jacobi-Bellman equations

$$\begin{cases} v_t^{\varepsilon} + H\left(x, y, D_x v^{\varepsilon}, \frac{D_y v^{\varepsilon}}{\varepsilon}\right) &= 0\\ v^{\varepsilon}(x, y, 0) &= u_0(x) \end{cases}$$
(Hj_{\varepsilon})

Under our assumptions on ℓ , u_0 , the value functions v^{ε} of (Min_{ε}) uniquely solve (Hj_{ε}) .



We write the limit equation

$$\begin{cases} v_t + \overline{H}(x, Dv) &= 0 \\ v(x, 0) &= u_0(x) \end{cases}$$
 (Hj)

We write the limit equation

$$\begin{cases} v_t + \overline{H}(x, Dv) &= 0 \\ v(x, 0) &= u_0(x) \end{cases}$$
 (\overline{Hj})

We aim at studying the asymptotic behavior v^{ε} in relation to the limit problem (\overline{Hj}) .

periodicity of dynamics and cost in the fast variable

periodicity of dynamics and cost in the fast variable

plus a controllability condition:

Given x_0 , any pair y_1 , y_2 of values the fast variable can be linked (up to a vector of \mathbb{Z}^N) by a trajectory of a fast dynamics, with x_0 fixed, in a time $t \leq T(x_0)$.

periodicity of dynamics and cost in the fast variable

plus a controllability condition:

Given x_0 , any pair y_1 , y_2 of values the fast variable can be linked (up to a vector of \mathbb{Z}^N) by a trajectory of a fast dynamics, with x_0 fixed, in a time $t \leq T(x_0)$.

Theorem

If the system satisfies the periodicity and controllability conditions, and, in addition, the limit equation satisfies a comparison principle, then the value functions $v^{\varepsilon}(x,y,t)$ locally uniformly converge to the value function v(x,t) of the limit problem (\overline{Hj}) .

periodicity of dynamics and cost in the fast variable

plus a controllability condition:

Given x_0 , any pair y_1 , y_2 of values the fast variable can be linked (up to a vector of \mathbb{Z}^N) by a trajectory of a fast dynamics, with x_0 fixed, in a time $t \leq T(x_0)$.

Theorem

If the system satisfies the periodicity and controllability conditions, and, in addition, the limit equation satisfies a comparison principle, then the value functions $v^{\varepsilon}(x,y,t)$ locally uniformly converge to the value function v(x,t) of the limit problem (\overline{Hj}) .

If the comparison principle does not hold for the limit equation then a weaker convergence result is obtained through semilimits. The theorem is based on the analysis of the family of the so-called cell problems, which are stationary Hamilton-Jacobi-Bellman equations in the fast variable.

The theorem is based on the analysis of the family of the so-called cell problems, which are stationary Hamilton-Jacobi-Bellman equations in the fast variable.

For any fixed (x_0, p_0) , they are given by

The theorem is based on the analysis of the family of the so–called cell problems, which are stationary Hamilton–Jacobi–Bellman equations in the fast variable.

For any fixed (x_0, p_0) , they are given by

$$H(x_0, y, p_0, Du) = c$$
 $c \in \mathbb{R}$ $(Cell(x_0, p_0)_c)$

The theorem is based on the analysis of the family of the so–called cell problems, which are stationary Hamilton–Jacobi–Bellman equations in the fast variable.

For any fixed (x_0, p_0) , they are given by

$$H(x_0, y, p_0, Du) = c$$
 $c \in \mathbb{R}$ $(Cell(x_0, p_0)_c)$

This methodology is inspired by periodic homogenization techniques for Hamilton–Jacobi equations.

The theorem is based on the analysis of the family of the so-called cell problems, which are stationary Hamilton–Jacobi–Bellman equations in the fast variable.

For any fixed (x_0, p_0) , they are given by

$$H(x_0, y, p_0, Du) = c$$
 $c \in \mathbb{R}$ $(Cell(x_0, p_0)_c)$

This methodology is inspired by periodic homogenization techniques for Hamilton–Jacobi equations.

Lions–Papanicolau–Varadhan (1987)

The theorem is based on the analysis of the family of the so–called cell problems, which are stationary Hamilton–Jacobi–Bellman equations in the fast variable.

For any fixed (x_0, p_0) , they are given by

$$H(x_0, y, p_0, Du) = c$$
 $c \in \mathbb{R}$ $(Cell(x_0, p_0)_c)$

This methodology is inspired by periodic homogenization techniques for Hamilton–Jacobi equations.

- Lions–Papanicolau–Varadhan (1987)
- Evans (1990) perturbed test function method.

The theorem is based on the analysis of the family of the so–called cell problems, which are stationary Hamilton–Jacobi–Bellman equations in the fast variable.

For any fixed (x_0, p_0) , they are given by

$$H(x_0, y, p_0, Du) = c$$
 $c \in \mathbb{R}$ $(Cell(x_0, p_0)_c)$

This methodology is inspired by periodic homogenization techniques for Hamilton–Jacobi equations.

- Lions–Papanicolau–Varadhan (1987)
- Evans (1990) perturbed test function method.

The controllability condition can be viewed as a weak form of coercivity, which is needed for homogenization. There are examples of periodic noncoercive Hamiltonians for which homogenization does not take place.

The crucial fact linking cell problems and asymptotic analysis is the following ergodicity property: The crucial fact linking cell problems and asymptotic analysis is the following ergodicity property:

Proposition

Under periodicity and controllability assumptions, there is, for any (x_0, p_0) , an unique value $c_0 = c_0(x_0, p_0)$ such that the corresponding cell equation $(\text{Cell}(x_0, p_0)_c)$, with $c = c_0$, admits an usc periodic subsolution and a lsc periodic supersolution problem. In this case

$$c_0(x_0,p_0)=\overline{H}(x_0,p_0)$$

The crucial fact linking cell problems and asymptotic analysis is the following ergodicity property:

Proposition

Under periodicity and controllability assumptions, there is, for any (x_0, p_0) , an unique value $c_0 = c_0(x_0, p_0)$ such that the corresponding cell equation (Cell $(x_0, p_0)_c$), with $c = c_0$, admits an usc periodic subsolution and a lsc periodic supersolution problem. In this case

$$c_0(x_0, p_0) = \overline{H}(x_0, p_0)$$

Periodic sub/super solutions of the cell problem play the role of correctors allowing to adapt Evans perturbed test function method to this setting.

• $\lim_{|y|\to +\infty} \min_{a\in A} \ell(x_0,y,a) = +\infty$, for any fixed x_0 .

• $\lim_{|y|\to+\infty} \min_{a\in A} \ell(x_0,y,a) = +\infty$, for any fixed x_0 .

We also assume a local version of controllability

Given x_0 , the previous controllability condition holds in any compact subset, say K of the fast variable and the time to link two points of K, say y_1 and y_2 , depends on x_0 and K.

• $\lim_{|y|\to+\infty} \min_{a\in A} \ell(x_0,y,a) = +\infty$, for any fixed x_0 .

We also assume a local version of controllability

Given x_0 , the previous controllability condition holds in any compact subset, say K of the fast variable and the time to link two points of K, say y_1 and y_2 , depends on x_0 and K.

We obtain the following result:

Theorem

If the system satisfies the coercivity and local controllability conditions, and, in addition, the limit equation satisfies a comparison principle, then we get the same assertion of Alvarez–Bardi Theorem.

Natural questions are:

Is there an alternative property of sub/supersolutions of the cell problems which should be required in order to select one and only one $c = c(x_0, p_0)$ in the cell problem family ?

Natural questions are:

- Is there an alternative property of sub/supersolutions of the cell problems which should be required in order to select one and only one $c = c(x_0, p_0)$ in the cell problem family ?
- If yes, the identity $c(x_0, p_0) = \overline{H}(x_0, p_0)$ is still valid ?

Natural questions are:

- Is there an alternative property of sub/supersolutions of the cell problems which should be required in order to select one and only one $c = c(x_0, p_0)$ in the cell problem family ?
- If yes, the identity $c(x_0, p_0) = \overline{H}(x_0, p_0)$ is still valid ?
- If yes, are the sub/supersolution so selected suitable for adapted perturbed test function method?

The answer to the first question is given by the following ergodicity result:

The answer to the first question is given by the following ergodicity result:

Proposition


Under coercivity and local controllability assumptions, there is, for any (x_0, p_0) , an unique value $c_0 = c_0(x_0, p_0)$ such that the corresponding cell equation $(\text{Cell}(x_0, p_0)_c)$, with $c = c_0$, admits an usc locally bounded coercive subsolution and a lsc locally bounded coercive supersolution problem.

The answer to the first question is given by the following ergodicity result:

Proposition

Under coercivity and local controllability assumptions, there is, for any (x_0, p_0) , an unique value $c_0 = c_0(x_0, p_0)$ such that the corresponding cell equation $(\text{Cell}(x_0, p_0)_c)$, with $c = c_0$, admits an usc locally bounded coercive subsolution and a lsc locally bounded coercive supersolution problem.

Answer to the other questions are positive, and this is actually the way of proving our convergence theorem.



Approximate, in the local uniform convergence, the Hamiltonian $(y,p) \mapsto H(x_0,y,p_0,p)$ by a sequence of coercive Hamiltonians $H_k(y,p)$, decreasing in k

- Approximate, in the local uniform convergence, the Hamiltonian $(y,p) \mapsto H(x_0,y,p_0,p)$ by a sequence of coercive Hamiltonians $H_k(y,p)$, decreasing in k
- Define $c_0^k = \min\{c \mid H_k = c \text{ admits subsolutions in } \mathbb{R}^N\}$

- Approximate, in the local uniform convergence, the Hamiltonian $(y,p) \mapsto H(x_0,y,p_0,p)$ by a sequence of coercive Hamiltonians $H_k(y,p)$, decreasing in k
- Define $c_0^k = \min\{c \mid H_k = c \text{ admits subsolutions in } \mathbb{R}^N\}$
- Exploit coercivity condition to prove that there is a corresponding nonempty Aubry sets A_k

- Approximate, in the local uniform convergence, the Hamiltonian $(y,p) \mapsto H(x_0,y,p_0,p)$ by a sequence of coercive Hamiltonians $H_k(y,p)$, decreasing in k
- Define $c_0^k = \min\{c \mid H_k = c \text{ admits subsolutions in } \mathbb{R}^N\}$
- Exploit coercivity condition to prove that there is a corresponding nonempty Aubry sets A_k
- Use representation formulas for solutions to $H_k = c_0^k$ via Aubry set to show that c_0^k is the unique value for which there are coercive solutions

- Approximate, in the local uniform convergence, the Hamiltonian $(y, p) \mapsto H(x_0, y, p_0, p)$ by a sequence of coercive Hamiltonians $H_k(y, p)$, decreasing in k
- Define $c_0^k = \min\{c \mid H_k = c \text{ admits subsolutions in } \mathbb{R}^N\}$
- Exploit coercivity condition to prove that there is a corresponding nonempty Aubry sets A_k
- Use representation formulas for solutions to $H_k = c_0^k$ via Aubry set to show that c_0^k is the unique value for which there are coercive solutions
- Exploit local controllability to show that there is a sequence of locally equibounded coercive solutions u_k to $H_k = c_0^k$

- Approximate, in the local uniform convergence, the Hamiltonian $(y,p) \mapsto H(x_0,y,p_0,p)$ by a sequence of coercive Hamiltonians $H_k(y,p)$, decreasing in k
- Define $c_0^k = \min\{c \mid H_k = c \text{ admits subsolutions in } \mathbb{R}^N\}$
- Exploit coercivity condition to prove that there is a corresponding nonempty Aubry sets A_k
- Use representation formulas for solutions to $H_k = c_0^k$ via Aubry set to show that c_0^k is the unique value for which there are coercive solutions
- Exploit local controllability to show that there is a sequence of locally equibounded coercive solutions u_k to $H_k = c_0^k$
- pass to the semilimits, as $k \to +\infty$ to get sub/supersolution to

$$H(x_0, y, p_0, Du) = c_0(x_0, p_0) =: \lim_k c_k$$

with the desired properties.