

LIMIT SOLUTIONS (on estensions of input-output for unbounded controls)

Franco Rampazzo, Maria Soledad Aronna

▶ To cite this version:

Franco Rampazzo, Maria Soledad Aronna. LIMIT SOLUTIONS (on estensions of input-output for unbounded controls). NETCO 2014 - New Trends in Optimal Control, Jun 2014, Tours, France. hal-01024721

HAL Id: hal-01024721 https://inria.hal.science/hal-01024721

Submitted on 18 Jul2014

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

LIMIT SOLUTIONS (on estensions of input-output for unbounded controls)

FRANCO RAMPAZZO, University of Padova, PADOVA, ITALY joint work with MARIA S. ARONNA (IMPA)

> NETCO CONFERENCE New trends in Optimal Control JUNE 23-27, 2014 TOURS, FRANCE





2 "LIMIT" SOLUTIONS

- Existing notions of solutions
- Proposed definition of Limit Solution



"LIMIT" SOLUTIONS

- Existing notions of solutions
- Proposed definition of Limit Solution

・ 同 ト ・ ヨ ト ・ ヨ ト

(A) Find a NOTION OF SOLUTION x for

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \qquad t \in [a, b]$$

such that:

э

(4回) (1回) (1回)

(A) Find a NOTION OF SOLUTION x for

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \qquad t \in [a, b]$$

such that:

i) x is \mathcal{L}^1 and is defined for \mathcal{L}^1 inputs u

▲ 문 ▶ . ▲ 문 ▶

(A) Find a NOTION OF SOLUTION x for

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \qquad t \in [a, b]$$

such that:

i) x is \mathcal{L}^1 and is defined for \mathcal{L}^1 inputs u Here \mathcal{L}^1 denotes the set of integrable maps defined everywhere

(A) Find a NOTION OF SOLUTION x for

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \qquad t \in [a, b]$$

such that:

i) x is \mathcal{L}^1 and is defined for \mathcal{L}^1 inputs u

Here \mathcal{L}^1 denotes the set of integrable maps *defined everywhere*

ii) x subsumes former concepts of solution.

(A) Find a NOTION OF SOLUTION x for

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \qquad t \in [a, b]$$

such that:

- i) x is L¹ and is defined for L¹ inputs u
 Here L¹ denotes the set of integrable maps defined everywhere
- ii) x subsumes former concepts of solution.We shall call this solution

LIMIT SOLUTION

(A) Find a NOTION OF SOLUTION x for

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \qquad t \in [a, b]$$

such that:

- i) x is \mathcal{L}^1 and is defined for \mathcal{L}^1 inputs u Here \mathcal{L}^1 denotes the set of integrable maps defined everywhere
- ii) x subsumes former concepts of solution.We shall call this solution

LIMIT SOLUTION

(B) Minimum problems with end-point constraints $x(b) \in S$ as **PROPER EXTENSIONS** of regular problems $(u \in AC)$? (Aronna's talk)

APPLICATIONS of impulsive systems:

• Spiking models of synaptic behaviour

APPLICATIONS of impulsive systems:

- Spiking models of synaptic behaviour
- Mechanical systems using some coordinates as controls

APPLICATIONS of impulsive systems:

- Spiking models of synaptic behaviour
- Mechanical systems using some coordinates as controls
- In general, coupled fast-slow dynamics

Underlying thought:

We can accept a notion of discontinuous (=*impulsive*) trajectory only if

it is, in some sense to be made precise, the limit of faster and faster trajectories

Outline

HEURISTICS

2 "LIMIT" SOLUTIONS

- Existing notions of solutions
- Proposed definition of Limit Solution

▶ ∢ ⊒ ▶

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

э.

▲□ → ▲圖 → ▲ 画 → ▲ 画 → →

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

$$\dot{x} = \dot{u}$$

• For this eqution one would like to have

$$x(t) = u(t) + x(0) \qquad \forall t \in [0, T]$$

$$(1)$$

as a solution, which is obviously true as soon as $x, u \in AC$ (i.e. absolutely continuous).

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

$$\dot{x} = \dot{u}$$

• For this eqution one would like to have

$$x(t) = u(t) + x(0) \qquad \forall t \in [0, T] \tag{1}$$

as a solution, which is obviously true as soon as $x, u \in AC$ (i.e. absolutely continuous).

• Another idea could be a distributional approach: BUT

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

$$\dot{x} = \dot{u}$$

• For this eqution one would like to have

$$x(t) = u(t) + x(0) \qquad \forall t \in [0, T] \tag{1}$$

as a solution, which is obviously true as soon as $x, u \in AC$ (i.e. absolutely continuous).

- Another idea could be a distributional approach: BUT
 - 1) does not give pointwise information
 - 2) it is "wrong" in the general nonlinear case.

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

$$\dot{x} = \dot{u}$$

• For this eqution one would like to have

$$x(t) = u(t) + x(0) \qquad \forall t \in [0, T] \tag{1}$$

as a solution, which is obviously true as soon as $x, u \in AC$ (i.e. absolutely continuous).

- Another idea could be a distributional approach: BUT
 - 1) does not give pointwise information
 - 2) it is "wrong" in the general nonlinear case.
- Can we take (1) as a definition for $u, x \in \mathcal{L}^1$?

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

э

< 日 > < 同 > < 三 > < 三 >

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

There are at least TWO cases for which a "good" notion of solution already does exist:

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

There are at least TWO cases for which a "good" notion of solution already does exist: • the commutative case

$$[g_{\alpha},g_{\beta}]=0$$

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}$$

There are at least TWO cases for which a "good" notion of solution already does exist: • the commutative case

$$[g_{\alpha},g_{\beta}]=0$$

• the non commutative case

$$[g_{\alpha},g_{\beta}] \neq 0$$

with the controls $u(\cdot)$ having bounded variation,

$$\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u)\dot{u}_{\alpha}$$

The commutative case

æ

・ロト ・四ト ・ヨト ・ヨト

$$\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha}$$

The commutative case =the "trivial" case:

・ロト ・聞 と ・ ヨ と ・ ヨ と …

$$= f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha}$$

ż

The commutative case = the "trivial" case:

Due to [g_α, g_β] = 0, by multiple flow-box theorem there exists a (global) coordinates' change

$$(x, u) \rightarrow (\xi, z) = (\xi(x, u), u)$$

such that the system becomes *trivial*:

- 4 同 6 4 日 6 4 日 6

$$\dot{\mathbf{x}} = f(\mathbf{x}, \mathbf{u}, \mathbf{v}) + \sum g_{\alpha}(\mathbf{x}, \mathbf{u}) \dot{\mathbf{u}}_{\alpha}$$

The commutative case = the "trivial" case:

Due to [g_α, g_β] = 0, by multiple flow-box theorem there exists a (global) coordinates' change

$$(x, u) \rightarrow (\xi, z) = (\xi(x, u), u)$$

such that the system becomes *trivial*:

$$\dot{\xi} = F(t, \xi, z, v)$$

 $\dot{z} = \dot{u}$

$$\dot{\mathbf{x}} = f(\mathbf{x}, \mathbf{u}, \mathbf{v}) + \sum g_{\alpha}(\mathbf{x}, \mathbf{u}) \dot{\mathbf{u}}_{\alpha}$$

The commutative case =the "trivial" case:

Due to [g_α, g_β] = 0, by multiple flow-box theorem there exists a (global) coordinates' change

$$(x, u) \rightarrow (\xi, z) = (\xi(x, u), u)$$

such that the system becomes *trivial*:

$$\dot{\xi} = F(t, \xi, z, v)$$

 $\dot{z} = \dot{u}$

Set z(t) := u(t) and define the solution x(·) by using the inverse change of coordinates:

$$x(t) = x\Big(\xi(t), z(t)\Big)$$

$$\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha}$$

The commutative case = the "trivial" case:

Due to [g_α, g_β] = 0, by multiple flow-box theorem there exists a (global) coordinates' change

$$(x, u) \rightarrow (\xi, z) = (\xi(x, u), u)$$

such that the system becomes trivial:

$$\dot{\xi} = F(t, \xi, z, v)$$

 $\dot{z} = \dot{u}$

Set z(t) := u(t) and define the solution x(·) by using the inverse change of coordinates:

$$x(t) = x\Big(\xi(t), z(t)\Big)$$

Notice: One has continuity of $u \to x$ with respect to L^1 topologies on both u and x.

$$\dot{\mathbf{x}} = f(\mathbf{x}, \mathbf{u}, \mathbf{v}) + \sum g_{\alpha}(\mathbf{x}, \mathbf{u}) \dot{\mathbf{u}}_{\alpha}$$

The commutative case =the "trivial" case:

Due to [g_α, g_β] = 0, by multiple flow-box theorem there exists a (global) coordinates' change

$$(x, u) \rightarrow (\xi, z) = (\xi(x, u), u)$$

such that the system becomes *trivial*:

$$\dot{\xi} = F(t, \xi, z, v)$$

 $\dot{z} = \dot{u}$

Set z(t) := u(t) and define the solution x(·) by using the inverse change of coordinates:

$$x(t) = x\Big(\xi(t), z(t)\Big)$$

Notice: One has continuity of $u \to x$ with respect to L^1 topologies on both u and x. Actually, stronger continuity properties are verified

References include

A. Bressan and F. Rampazzo. Impulsive control systems with commutative vector fields. J. Optim. Theory Appl., 71, p.67-83, (1991).

A.V. Sarychev. Nonlinear systems with impulsive and generalized function controls,vol. 9 of Progr. Systems Control Theory, p. 244-257, (1991).

$$\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha},$$

The noncommutative case

э

イロン イロン イヨン イヨン

 $\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha},$

The noncommutative case =non "trivializable":

・ロン ・四 と ・ ヨ と ・ ヨ と ・

$$\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha},$$

The noncommutative case =non "trivializable":

For regular (=absolutely continuous) controls u, one can reparameterize time t(s) = φ₀(s) and set φ(s) := u ο φ₀ = u(t(s)):

$$egin{aligned} t'(s) &= arphi_0'(s) \ y'(s) &= f(arphi_0, y, arphi, v \circ arphi_0) arphi_0'(s) + \sum_{lpha = 1}^m g_lpha(y, u) arphi_lpha'(s) \end{aligned}$$

・ロト ・得ト ・ヨト ・ヨト

$$\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha},$$

The noncommutative case = non "trivializable":

For regular (=absolutely continuous) controls u, one can reparameterize time t(s) = φ₀(s) and set φ(s) := u ο φ₀ = u(t(s)):

$$egin{aligned} t'(s) &= arphi_0'(s) \ y'(s) &= f(arphi_0, y, arphi, v \circ arphi_0) arphi_0'(s) + \sum_{lpha = 1}^m g_lpha(y, u) arphi_lpha'(s) \end{aligned}$$

for BV(=bounded variation) controls u, let (φ₀, φ) be a graph completions of u.
 Namely:

$$\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha},$$

The noncommutative case = non "trivializable":

For regular (=absolutely continuous) controls u, one can reparameterize time t(s) = φ₀(s) and set φ(s) := u ο φ₀ = u(t(s)):

$$egin{aligned} t'(s) &= arphi_0'(s) \ y'(s) &= f(arphi_0, y, arphi, v \circ arphi_0) arphi_0'(s) + \sum_{lpha = 1}^m g_lpha(y, u) arphi_lpha'(s) \end{aligned}$$

for BV(=bounded variation) controls u, let (φ₀, φ) be a graph completions of u.
 Namely: one bridges the jumps of u and parameterize them on s-subintervals where time t(s)(= φ₀(s)) is constant.

$$egin{aligned} t'(s) &= arphi_0'(s) \ y'(s) &= f(arphi_0, y, arphi, v \circ arphi_0) arphi_0'(s) + \sum_{lpha = 1}^m g_lpha(y, u) arphi_lpha'(s) \end{aligned}$$

$$t \to x(t) := y \circ \varphi_0^{-1}(t)$$

is called the **graph-completion solution** corresponding to the graph completion (φ_0, φ) of u. It is set-valued on a countable subset of [a, b].

$$egin{aligned} t'(s) &= arphi_0'(s) \ y'(s) &= f(arphi_0, y, arphi, v \circ arphi_0) arphi_0'(s) + \sum_{lpha = 1}^m g_lpha(y, u) arphi_lpha'(s) \end{aligned}$$

$$t \to x(t) := y \circ \varphi_0^{-1}(t)$$

is called the **graph-completion solution** corresponding to the graph completion (φ_0, φ) of u. It is set-valued on a countable subset of [a, b].

single-valued version:

・ 同 ト ・ ヨ ト ・ ヨ ト

$$egin{aligned} t'(s) &= arphi_0'(s) \ y'(s) &= f(arphi_0, y, arphi, v \circ arphi_0) arphi_0'(s) + \sum_{lpha = 1}^m g_lpha(y, u) arphi_lpha'(s) \end{aligned}$$

$$t \to x(t) := y \circ \varphi_0^{-1}(t)$$

is called the **graph-completion solution** corresponding to the graph completion (φ_0, φ) of u. It is set-valued on a countable subset of [a, b].


single-valued version: If $\sigma : [0, T] \rightarrow [0, 1]$ is a Clock, i.e. $\sigma(t) \in (\varphi_0, \varphi)^{\leftarrow}(t, u(t))$, we say that

$$t \to x := y \circ \sigma(t)$$

is a single-valued graph-completion solution.

$$t'(s) = \varphi'_0(s)$$


$$y'(s) = f(\varphi_0, y, \varphi, v \circ \varphi_0)\varphi'_0(s) + \sum_{\alpha=1}^m g_\alpha(y, u)\varphi'_\alpha(s)$$



・ロト ・回ト ・モト ・モト

$$t'(s) = \varphi'_0(s)$$


$$y'(s) = f(\varphi_0, y, \varphi, v \circ \varphi_0)\varphi'_0(s) + \sum_{\alpha=1}^m g_\alpha(y, u)\varphi'_\alpha(s)$$



<ロ> <同> <同> < 同> < 同>

$$t'(s) = \varphi'_0(s)$$


$$y'(s) = f(\varphi_0, y, \varphi, v \circ \varphi_0)\varphi'_0(s) + \sum_{\alpha=1}^m g_\alpha(y, u)\varphi'_\alpha(s)$$



・ロト ・ 日 ・ ・ ヨ ・ ・ ヨ ・

$$t'(s) = \varphi'_0(s)$$


$$y'(s) = f(\varphi_0, y, \varphi, v \circ \varphi_0)\varphi'_0(s) + \sum_{\alpha=1}^m g_\alpha(y, u)\varphi'_\alpha(s)$$



・ロト ・聞ト ・ヨト ・ヨト

$$t'(s) = \varphi'_0(s)$$


$$y'(s) = f(\varphi_0, y, \varphi, v \circ \varphi_0)\varphi'_0(s) + \sum_{\alpha=1}^m g_\alpha(y, u)\varphi'_\alpha(s)$$



・ロト ・回ト ・モト ・モト

$$t'(s) = \varphi'_0(s)$$

$$y'(s) = f(\varphi_0, y, \varphi, v \circ \varphi_0)\varphi'_0(s) + \sum_{\alpha=1}^m g_\alpha(y, u)\varphi'_\alpha(s)$$



・ロト ・回ト ・モト ・モト

An incomplete list of authors who have investigated this subject:

Bressan Bressan- Rampazzo Bressan-Mazzola Briani-7idani Pereira-Vinte Miller Motta-Rampazzo Camilli-Falcone Motta-Sartori Silva-Vinter. Zabic-Wolenski

∃ ► < ∃ ►

M.S. Aronna and F. Rampazzo. \mathcal{L}^1 limit solutions for control systems. (accepted for publ. on JDE)

M.S. Aronna and F. Rampazzo. \mathcal{L}^1 limit solutions for control systems. (accepted for publ. on JDE) **Some requirements should be met**:

M.S. Aronna and F. Rampazzo. \mathcal{L}^1 limit solutions for control systems. (accepted for publ. on JDE)

Some requirements should be met:

• consistency with the Carathéodory notion of solution for $u \in AC$;

M.S. Aronna and F. Rampazzo. \mathcal{L}^1 limit solutions for control systems. (accepted for publ. on JDE)

Some requirements should be met:

- consistency with the Carathéodory notion of solution for $u \in AC$;
- x single-valued at each t;

M.S. Aronna and F. Rampazzo. \mathcal{L}^1 limit solutions for control systems. (accepted for publ. on JDE)

Some requirements should be met:

- consistency with the Carathéodory notion of solution for $u \in AC$;
- x single-valued at each t;
- existence of an output

M.S. Aronna and F. Rampazzo. \mathcal{L}^1 limit solutions for control systems. (accepted for publ. on JDE)

Some requirements should be met:

- consistency with the Carathéodory notion of solution for $u \in AC$;
- x single-valued at each t;
- existence of an output (and possibly uniqueness) results

M.S. Aronna and F. Rampazzo. \mathcal{L}^1 limit solutions for control systems. (accepted for publ. on JDE)

Some requirements should be met:

- consistency with the Carathéodory notion of solution for $u \in AC$;
- x single-valued at each t;
- existence of an output (and possibly *uniqueness*) results
- former definitions of solution for impulsive systems should be subsumed by this extended notion

直 と く ヨ と く ヨ と

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$$

FRANCO RAMPAZZO, University of Padova, LIMIT SOLUTIONS (on estensions of input

< ロ > < 同 > < 回 > < 回 >

$$\dot{x} = f(x, u, v) + \sum_{lpha=1}^{m} g_{lpha}(x, u) \dot{u}_{lpha}, \quad x(a) = ar{x}$$

 $u \in \mathcal{L}^1([a, b]; U), \text{ (and } v \in L^1)$

$$\dot{x}=f(x,u,v)+\sum_{lpha=1}^m g_lpha(x,u)\dot{u}_lpha,\quad x(a)=ar{x}$$

 $u\in \mathcal{L}^1([a,b];U), \hspace{0.2cm} (ext{and} \hspace{0.2cm} v\in L^1)$

Definition

A map x : [a, b] → Rⁿ is a LIMIT SOLUTION if, for every τ ∈ [a, b], there exists a sequence of absolutely continuous controls (u^τ_k) such that
 |(x^τ_k, u^τ_k)(τ) - (x, u)(τ)| + ||(x^τ_k, u^τ_k) - (x, u)||₁ → 0,

$$\dot{x} = f(x, u, v) + \sum_{lpha=1}^{m} g_{lpha}(x, u) \dot{u}_{lpha}, \quad x(a) = ar{x}$$

 $u\in \mathcal{L}^1([a,b];U), \hspace{0.2cm} (ext{and} \hspace{0.2cm} v\in L^1)$

Definition

- A map $x : [a, b] \to \mathcal{R}^n$ is a LIMIT SOLUTION if, for every $\tau \in [a, b]$, there exists a sequence of absolutely continuous controls (u_k^{τ}) such that $|(x_k^{\tau}, u_k^{\tau})(\tau) (x, u)(\tau)| + ||(x_k^{\tau}, u_k^{\tau}) (x, u)||_1 \to 0$,
- SIMPLE LIMIT SOLUTION: if (u^τ_k) can be chosen independently of τ, i.e. (u^τ_k) = (u_k).

$$\dot{x} = f(x, u, v) + \sum_{lpha=1}^{m} g_{lpha}(x, u) \dot{u}_{lpha}, \quad x(a) = ar{x}$$

 $u\in \mathcal{L}^1([a,b];U), \hspace{0.2cm} (ext{and} \hspace{0.2cm} v\in L^1)$

Definition

- A map $x : [a, b] \to \mathcal{R}^n$ is a LIMIT SOLUTION if, for every $\tau \in [a, b]$, there exists a sequence of absolutely continuous controls (u_k^{τ}) such that $|(x_k^{\tau}, u_k^{\tau})(\tau) (x, u)(\tau)| + ||(x_k^{\tau}, u_k^{\tau}) (x, u)||_1 \to 0$,
- SIMPLE LIMIT SOLUTION: if (u^τ_k) can be chosen independently of τ, i.e. (u^τ_k) = (u_k).
- BV-SIMPLE LIMIT SOLUTION if the approximating inputs *u*_k have **equibounded variation**.

 $(x_k^{\tau}$ is the Carathéodory solution corresponding to $(u_k^{\tau}, y))$

э

< 日 > < 同 > < 三 > < 三 >

Theorem 1.

• Existence and uniqueness For every control $u \in \mathcal{L}^1$ (and every $v \in L^1$) there exists a unique limit solution of $\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$

Theorem 1.

- Existence and uniqueness For every control $u \in \mathcal{L}^1$ (and every $v \in L^1$) there exists a unique limit solution of $\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$
- Continuous dependence: for every $au \in [a, b]$ one has

$$|x_1(\tau) - x_2(\tau)| + ||x_1 - x_2||_1 \le M \Big[|\bar{x}_1 - \bar{x}_2| + |u_1(a) - u_2(a)| + |u_1(t) - u_2(t)| + ||u_1 - u_2||_1 \Big].$$

Theorem 1.

- Existence and uniqueness For every control $u \in \mathcal{L}^1$ (and every $v \in L^1$) there exists a unique limit solution of $\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$
- Continuous dependence: for every $au \in [a, b]$ one has

$$|x_1(\tau) - x_2(\tau)| + ||x_1 - x_2||_1 \le M \Big[|ar{x}_1 - ar{x}_2| + |u_1(a) - u_2(a)| + |u_1(t) - u_2(t)| + ||u_1 - u_2||_1 \Big].$$

moreover: one has continuous dependence w.r. to the standard control $v(\cdot)$ in L^1 norm

- 4 同 6 4 日 6 4 日 6 - 日

э

< 日 > < 同 > < 三 > < 三 >

Proposition 2. The *limit solution coincides* with the solution previously given via change of coordinates.

Proposition 2. The *limit solution coincides* with the solution previously given via change of coordinates.

Remarks:

(1) Proposition 2 was proved in Bressan-Rampazzo(1991) when f independent of v.

Proposition 2. The *limit solution coincides* with the solution previously given via change of coordinates.

Remarks:

(1) Proposition 2 was proved in Bressan-Rampazzo(1991) when f independent of v.

(2) Proposition 2 gives an idea for the general definition of solution

- 4 同 6 4 日 6 4 日 6

Example

$$\dot{x} = xv + x\dot{u}, \quad x(0) = \bar{x},$$

on the interval [0,1], with $v(t) := \chi_{[0,1/2[}$ Consider the \mathcal{L}^1 control

$$u(t) := \left\{ egin{array}{ll} (-1)^{k+1}, & ext{for } t \in [1-rac{1}{k}, 1-rac{1}{k+1}[, \ k \in \mathcal{N}, \ 0, & ext{for } t=1. \end{array}
ight.$$

The *limit* solution x is given by

$$x(t) := \begin{cases} \bar{x}e^t, & \text{for } t \in [0, \frac{1}{2}[, \\ \bar{x}e^{1/2}e^{-2}, & \text{for } t \in \bigcup_{k=1}^{\infty}[1 - \frac{1}{2k}, 1 - \frac{1}{2k+1}[, \\ \bar{x}e^{1/2}, & \text{for } t \in \bigcup_{k=1}^{\infty}[1 - \frac{1}{2k+1}, 1 - \frac{1}{2k+2}[, \\ \bar{x}e^{-1/2}, & \text{for } t = 1. \end{cases}$$

Example

$$\dot{x} = xv + x\dot{u}, \quad x(0) = \bar{x},$$

on the interval [0,1], with $v(t) := \chi_{[0,1/2[}$ Consider the \mathcal{L}^1 control

$$u(t) := \left\{ egin{array}{ll} (-1)^{k+1}, & ext{for } t \in [1-rac{1}{k}, 1-rac{1}{k+1}[, \ k \in \mathcal{N}, \ 0, & ext{for } t=1. \end{array}
ight.$$

The *limit solution x* is given by

$$x(t) := \begin{cases} \bar{x}e^t, & \text{for } t \in [0, \frac{1}{2}[, \\ \bar{x}e^{1/2}e^{-2}, & \text{for } t \in \bigcup_{k=1}^{\infty}[1 - \frac{1}{2k}, 1 - \frac{1}{2k+1}[, \\ \bar{x}e^{1/2}, & \text{for } t \in \bigcup_{k=1}^{\infty}[1 - \frac{1}{2k+1}, 1 - \frac{1}{2k+2}[, \\ \bar{x}e^{-1/2}, & \text{for } t = 1. \end{cases}$$

Notice that both u and x have infinitely many discontinuities, unbounded variation, and are defined everywhere.

Proposed definition of Limit Solution

THE GENERIC, NON COMMUTATIVE, CASE $\dot{x} = f(x, u, v) + \sum_{\alpha} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$ $\alpha = 1$

THE GENERIC, NON COMMUTATIVE, CASE $\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$

 $u \in \mathcal{L}^1([a, b]; U), \text{ (and } v \in L^1).$

 $u \in \mathcal{L}^1([a, b]; U), \text{ (and } v \in L^1).$

• Existence of *limit solutions*?

 $u \in \mathcal{L}^1([a, b]; U), \text{ (and } v \in L^1).$

- Existence of *limit solutions*?
- Existence of simple limit solutions, possibly BV?

 $u \in \mathcal{L}^1([a, b]; U), \text{ (and } v \in L^1).$

- Existence of *limit solutions*?
- Existence of simple limit solutions, possibly BV?
- Uniqueness?

 $u \in \mathcal{L}^1([a, b]; U), \text{ (and } v \in L^1).$

- Existence of *limit solutions*?
- Existence of simple limit solutions, possibly BV?
- Uniqueness?

 $\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$

3

< ロ > < 同 > < 回 > < 回 > < □ > <

$$\dot{x} = f(x, u, v) + \sum g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$$

Let us focus on BV-simple limit solutions (for $u \in BV$). Do they have something to to with graph-completion solutions?

$$\dot{x} = f(x, u, v) + \sum g_{lpha}(x, u) \dot{u}_{lpha}, \quad x(a) = ar{x}$$

Let us focus on BV-simple limit solutions (for $u \in BV$). Do they have something to to with graph-completion solutions?

Theorem

$$f(x, u, v) + \sum g_{\alpha}(x, u)\dot{u}_{\alpha}, \quad x(a) = \bar{x}$$

Let us focus on BV-simple limit solutions (for $u \in BV$). Do they have something to to with graph-completion solutions?

Theorem

 $\dot{x} =$

 \boldsymbol{x} a single-valued graph completion solution

x is a BV-simple limit solution.

Main ingredients of the proof:

Main ingredients of the proof:

• (more or less known): *pointwise* density for increasing maps plus reparameterizations;

Main ingredients of the proof:

• (more or less known): *pointwise* density for increasing maps plus reparameterizations;

Main ingredients of the proof:

- (more or less known): *pointwise* density for increasing maps plus reparameterizations;
- (new) : compactness, by Helly's and Ascoli-Arzelà's theorem, plus ad hoc approximation tecqniques.

Observe preliminarly that the question is not obvious even for the trivial equation

$$\dot{x} = \dot{u}$$
 $x(a) = 0$

Indeed:

Observe preliminarly that the question is not obvious even for the trivial equation

$$\dot{x} = \dot{u}$$
 $x(a) = 0$

Indeed:

claiming (as we do) that $x(t) \equiv u(t)$, $t \in [a, b]$, would mean that the BV map $u : [a, b] \to \mathbb{R}^m$ can be approximated pointwise by a sequence of absolutely continuous maps u_n with $Var(u_n) \leq L$.

(4月) (日) (日) 日

Observe preliminarly that the question is not obvious even for the trivial equation

$$\dot{x} = \dot{u}$$
 $x(a) = 0$

Indeed:

claiming (as we do) that $x(t) \equiv u(t)$, $t \in [a, b]$, would mean that the BV map $u : [a, b] \to \mathbb{R}^m$ can be approximated pointwise by a sequence of absolutely continuous maps u_n with $Var(u_n) \leq L$. (This is not straightforward: consider e.g. a BV map with a dense set of discontinuities)

(ロ・・「聞・・」 目・ 「日・」 日

EXISTENCE of BV-SIMPLE LIMIT SOLUTIONS for

 $\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$

Theorem

Let U have the Whitney property. For any control pair

$$(u, v) \in \mathsf{BV}([\mathbf{a}, \mathbf{b}]; \mathbf{U}) \times L^1([\mathbf{a}, \mathbf{b}]; V)$$

there exists a **BV-simple limit solution**.

Theorem

Let U have the Whitney property. For any control pair

$$(u, v) \in \mathsf{BV}([\mathbf{a}, \mathbf{b}]; \mathbf{U}) \times L^1([\mathbf{a}, \mathbf{b}]; V)$$

there exists a **BV-simple limit solution**.

(An arc-wise connected set *U* has the Whitney property if $d(x, y) \le M|x - y|$, where *d* is the geodesic distance.)

Theorem

Let U have the Whitney property. For any control pair

$$(u, v) \in \mathsf{BV}([\mathbf{a}, \mathbf{b}]; \mathbf{U}) \times L^1([\mathbf{a}, \mathbf{b}]; V)$$

there exists a **BV-simple limit solution**.

(An arc-wise connected set *U* has the Whitney property if $d(x, y) \le M|x - y|$, where *d* is the geodesic distance.)

Let $u \in AC$.

- 4 同 ト 4 ヨ ト 4 ヨ ト

Let $u \in AC$. Clearly **the Carathéodory solution** x_C of

$$\dot{x} = f(x, u, v) + \sum_{lpha=1}^{m} g_{lpha}(x, u) \dot{u}_{lpha}, \quad x(a) = ar{x}$$

is a (BV-uniform) limit solution.

Let $u \in AC$. Clearly **the Carathéodory solution** x_C of

$$\dot{x} = f(x, u, v) + \sum_{lpha=1}^{m} g_{lpha}(x, u) \dot{u}_{lpha}, \quad x(a) = ar{x}$$

is a (BV-uniform) limit solution.

Question:

伺 ト イヨト イヨト

Let $u \in AC$. Clearly **the Carathéodory solution** x_C of

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$$

is a (BV-uniform) limit solution.

Question:

Is $x_{\mathcal{C}}$ the ONLY limit solution?

Let $u \in AC$. Clearly **the Carathéodory solution** x_C of

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$$

is a (BV-uniform) limit solution.

Question:

Is $x_{\mathcal{C}}$ the ONLY limit solution? NO.

Let $u \in AC$. Clearly **the Carathéodory solution** x_C of

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}$$

is a (BV-uniform) limit solution.

Question:

Is x_C the ONLY limit solution? NO. For instance

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

 $g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad ext{so} \ [g_1, g_2] = (0, 0, -2).$

э

< ロ > < 同 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < 回 > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ > < □ >

$$\begin{split} \dot{x} &= g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.\\ g_1(x) &:= (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2). \end{split}$$
Of course the Carathéodory solution corresponding to $u \equiv (0, 0)$ is
$$x_{\mathcal{C}}(t) \equiv (0, 0, 0)$$

< 日 > < 同 > < 三 > < 三 >

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

 $g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).$

Of course the Carathéodory solution corresponding to $u \equiv (0,0)$ is

$$x_{\mathcal{C}}(t) \equiv (0,0,0)$$

On the other hand, the input $u_k(t) := (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt)$

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

 $g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).$

Of course the Carathéodory solution corresponding to $u \equiv (0,0)$ is

$$x_{\mathcal{C}}(t) \equiv (0,0,0)$$

On the other hand, the input $u_k(t) := (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt)$ generates the trajectory $x_k(t) = (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt, -t + k^{-1} \sin kt)^t.$

- ▲□ ▶ ▲□ ▶ ▲□ ▶ ● ● ●

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

 $g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).$

Of course the Carathéodory solution corresponding to $u \equiv (0,0)$ is

$$x_{\mathcal{C}}(t) \equiv (0,0,0)$$

On the other hand, the input $u_k(t) := (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt)$ generates the trajectory $x_k(t) = (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt, -t + k^{-1} \sin kt)^t.$ Since $u_k(t) \rightarrow (0,0), \quad x_k(t) \rightarrow (0,0,-t)^t$, uniformly, the map $\hat{x}(t) := (0,0,-t)^t$

is a (simple) limit solution.

・ロ ・ ・ ヨ ・ ・ ヨ ・ ・ ・ 日 ・ う へ つ ・

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

 $g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).$

Of course the Carathéodory solution corresponding to $u \equiv (0,0)$ is

$$x_{\mathcal{C}}(t) \equiv (0,0,0)$$

On the other hand, the input $u_k(t) := (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt)$ generates the trajectory $x_k(t) = (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt, -t + k^{-1} \sin kt)^t.$ Since $u_k(t) \rightarrow (0,0), \quad x_k(t) \rightarrow (0,0,-t)^t$, uniformly, the map $\hat{x}(t) := (0,0,-t)^t$

is a (simple) limit solution. In particular $\hat{x} \neq x_{\mathcal{C}}$

・ロ ・ ・ ヨ ・ ・ ヨ ・ ・ ・ 日 ・ う へ つ ・

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

 $g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).$

Of course the Carathéodory solution corresponding to $u \equiv (0,0)$ is

$$x_{\mathcal{C}}(t) \equiv (0,0,0)$$

On the other hand, the input $u_k(t) := (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt)$ generates the trajectory $x_k(t) = (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt, -t + k^{-1} \sin kt)^t$. Since $u_k(t) \rightarrow (0,0)$, $x_k(t) \rightarrow (0,0,-t)^t$, uniformly, the map $\hat{x}(t) := (0,0,-t)^t$

is a (simple) limit solution. In particular $\hat{x} \neq x_{\mathcal{C}}$ Notice that $Var(u_k) \rightarrow +\infty$

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

 $g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).$

Of course the Carathéodory solution corresponding to $u \equiv (0,0)$ is

$$x_{\mathcal{C}}(t) \equiv (0,0,0)$$

On the other hand, the input $u_k(t) := (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt)$ generates the trajectory $x_k(t) = (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt, -t + k^{-1} \sin kt)^t$. Since $u_k(t) \rightarrow (0,0)$, $x_k(t) \rightarrow (0,0,-t)^t$, uniformly, the map $\hat{x}(t) := (0,0,-t)^t$

is a (simple) limit solution. In particular $\hat{x} \neq x_{\mathcal{C}}$ Notice that $Var(u_k) \rightarrow +\infty$ BUT...

 $u \in AC$

- 4 同 ト 4 ヨ ト 4 ヨ ト

 $u \in AC$ **THEOREM.**

Let $\hat{x} \in AC$ be a BV-uniform limit solution of

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}.$$

Then $\hat{x} = x_{\mathcal{C}}$

イロト イポト イヨト イヨト

CONSISTENCY with Carathéodory solutions x_C

 $u \in AC$ **THEOREM**.

Let $\hat{x} \in AC$ be a BV-uniform limit solution of

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}.$$

Then $\hat{x} = x_{\mathcal{C}}$

Remark : By the previous example, the fact that \hat{x} is a smooth simple limit solution does not imply that x is a Carathéodory solution.

CONSISTENCY with Carathéodory solutions x_C

 $u \in AC$ **THEOREM**.

Let $\hat{x} \in AC$ be a BV-uniform limit solution of

$$\dot{x} = f(x, u, v) + \sum_{\alpha=1}^{m} g_{\alpha}(x, u) \dot{u}_{\alpha}, \quad x(a) = \bar{x}.$$

Then $\hat{x} = x_{\mathcal{C}}$

Remark : By the previous example, the fact that \hat{x} is a smooth simple limit solution does not imply that x is a Carathéodory solution.

э

<ロ> <同> <同> < 同> < 同>

• Proper extension for minimum problems (next talk by Aronna)

∃ ► < ∃ ►</p>

- Proper extension for minimum problems (next talk by Aronna)
- Classify other classes of solutions with unbounded variation.

- Proper extension for minimum problems (next talk by Aronna)
- Classify other classes of solutions with unbounded variation.
- Necessary conditions for minimum problems, Hamilton-Jacobi

- Proper extension for minimum problems (next talk by Aronna)
- Classify other classes of solutions with unbounded variation.
- Necessary conditions for minimum problems, Hamilton-Jacobi
- Compactness, existence of minima

Many thanks for your patience

・ロト ・同ト ・ヨト ・ヨト

æ

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

 $g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).$

æ

・ロト ・四ト ・ヨト ・ヨト

$$\begin{split} \dot{x} &= g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.\\ g_1(x) &:= (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).\\ \end{split}$$
Carathéodory solution corresponding to $u \equiv (0, 0)$ is : $x_{\mathcal{C}}(t) \equiv (0, 0, 0)$

э

(日) (同) (三) (三)

$$\begin{split} \dot{x} &= g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.\\ g_1(x) &:= (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).\\ \\ \text{Carathéodory solution corresponding to } u &\equiv (0, 0) \text{ is } : x_{\mathcal{C}}(t) \equiv (0, 0, 0)\\ u_k(t) &:= (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt) \end{split}$$

æ

イロン イロン イヨン イヨン

$$\dot{x} = g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.$$

$$g_1(x) := (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).$$
Carathéodory solution corresponding to $u \equiv (0, 0)$ is : $x_c(t) \equiv (0, 0, 0)$

$$u_k(t) := (k^{-1/2}\cos kt - 1, k^{-1/2}\sin kt) \text{ generates the trajectory}$$

$$x_k(t) = (k^{-1/2}\cos kt - 1, k^{-1/2}\sin kt, -t + k^{-1}\sin kt)^t.$$

$$x_k(t)to\hat{x}(t) := (0, 0, -t)^t$$
so \hat{x} is a (simple) limit solution

a (simple) mini solution.

æ

・ロン ・雪 と ・ ヨ と ・

$$\begin{split} \dot{x} &= g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.\\ g_1(x) &:= (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so} \ [g_1, g_2] = (0, 0, -2).\\ \end{split}$$
Carathéodory solution corresponding to $u \equiv (0, 0)$ is : $x_{\mathcal{C}}(t) \equiv (0, 0, 0)$
 $u_k(t) := (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt)$ generates the trajectory
 $x_k(t) = (k^{-1/2} \cos kt - 1, k^{-1/2} \sin kt, -t + k^{-1} \sin kt)^t.$
 $x_k(t) to\hat{x}(t) := (0, 0, -t)^t$

so \hat{x} is a (simple) limit solution. In particular $\hat{x} \neq x_{\mathcal{C}}$

э

・ロト ・聞 ト ・ ヨト ・ ヨト …

$$\begin{split} \dot{x} &= g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.\\ g_1(x) &:= (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).\\ \text{Carathéodory solution corresponding to } u &\equiv (0, 0) \text{ is } : x_{\mathcal{C}}(t) \equiv (0, 0, 0)\\ u_k(t) &:= (k^{-1/2}\cos kt - 1, k^{-1/2}\sin kt) \text{ generates the trajectory}\\ x_k(t) &= (k^{-1/2}\cos kt - 1, k^{-1/2}\sin kt, -t + k^{-1}\sin kt)^t. \end{split}$$

 $x_k(t)to\hat{x}(t) := (0, 0, -t)^t$

so \hat{x} is a (simple) limit solution. In particular $\hat{x} \neq x_{\mathcal{C}}$ Notice that $Var(u_k) \doteq \int_0^1 |\dot{u}_k| dt \to +\infty$

3

・ロト ・回ト ・ヨト ・ヨト

$$\begin{split} \dot{x} &= g_1(x)\dot{u}_1 + g_2(x)\dot{u}_2, \quad x(0) = 0.\\ g_1(x) &:= (1, 0, x_2), \quad g_2(x) := (0, 1, -x_1), \quad \text{so } [g_1, g_2] = (0, 0, -2).\\ \text{Carathéodory solution corresponding to } u &\equiv (0, 0) \text{ is } : x_{\mathcal{C}}(t) \equiv (0, 0, 0)\\ u_k(t) &:= (k^{-1/2}\cos kt - 1, k^{-1/2}\sin kt) \text{ generates the trajectory}\\ x_k(t) &= (k^{-1/2}\cos kt - 1, k^{-1/2}\sin kt, -t + k^{-1}\sin kt)^t. \end{split}$$

 $x_k(t)to\hat{x}(t) := (0, 0, -t)^t$

so \hat{x} is a (simple) limit solution. In particular $\hat{x} \neq x_{\mathcal{C}}$

Notice that $Var(u_k) \doteq \int_0^1 |\dot{u}_k| dt \to +\infty$ **BUT...** the *iterated integral*

$$\int_0^1 |\dot{u}_k^2 u_k^1 - \dot{u}_k^1 u_k^2| dt$$

IS BOUNDED as *k* goes to ∞ .

▲日 ▶ ▲冊 ▶ ▲ 田 ▶ ▲ 田 ▶ ● ● ● ● ●