

On the time discretization of stochastic optimal control problems: the dynamic programming approach

Joseph Frédéric Bonnans, Justina Gianatti, Francisco J Silva

▶ To cite this version:

Joseph Frédéric Bonnans, Justina Gianatti, Francisco J Silva. On the time discretization of stochastic optimal control problems: the dynamic programming approach. 2017. hal-01474285v1

HAL Id: hal-01474285 https://inria.hal.science/hal-01474285v1

Preprint submitted on 22 Feb 2017 (v1), last revised 7 Mar 2018 (v2)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

ON THE TIME DISCRETIZATION OF STOCHASTIC OPTIMAL CONTROL PROBLEMS: THE DYNAMIC PROGRAMMING APPROACH

J. FRÉDÉRIC BONNANS, JUSTINA GIANATTI, AND FRANCISCO J. SILVA

ABSTRACT. In this work we consider the time discretization of stochastic optimal control problems. Under general assumptions on the data, we prove the convergence of the value functions associated with the discrete time problems to the value function of the original problem. Moreover, we prove that any sequence of optimal solutions of discrete problems is minimizing for the continuous one. As a consequence of the Dynamic Programming Principle for the discrete problems, the minimizing sequence can be taken in discrete time feedback form.

1. INTRODUCTION

Stochastic optimal control problems in continuous time have been extensively studied during the last decades. This important area of research has a wide range of applications, such as in economy, mathematical finance and engineering. Usually, there are two approaches to deal with these problems. The first one is related to the Bellman's Dynamic Programming Principle (DPP), which allows to characterize the value function as the unique viscosity solution of the associated Hamilton-Jacobi-Bellman (HJB) equation [19, 20, 21]. The second one is the variational approach, which deals with extensions of the Pontryagin maximum principle [24] to the stochastic framework. For a detailed account of the theory and historical remarks we refer the reader to the classical monographs [28], [17] and [12].

Almost independently, another active field of research in the last decades has been the optimal control of discrete time processes and general state space. In that framework, controls at time k (also called policies) are probability measures on the actions space, which depend on the history of states at time k and the chosen actions up to time k - 1. Given a control, an action is chosen according to the probability measure associated with this control and this fixes the transition probability function between the states at time k and k + 1. The literature on this subject is too extensive and we refer the reader to the classical monographs [9, 3, 13, 25, 29], and the references therein, for a comprehensive presentation and historical remarks. Generally speaking, the assumptions in this theory are rather general and a common theme is the investigation of existence of optimal (or ε -optimal) Markov policies, i.e. the chosen control at time k depends only on the value of the state at time k.

In this work, we consider a continuous time stochastic optimal control problem with deterministic coefficients and a finite horizon T > 0. Given a grid with diameter, h > 0, we study its natural time discretization. While we consider only uniform grids, our analysis is easily extended for general time grids. The state equation is discretized with the classical stochastic explicit Euler scheme. Since at the continuous level we consider the *strong* formulation for the state equation (see [28, Chapter 2, Section 4.1]), i.e. the control acts pathwise on the state on a fixed probability space, it is natural to consider at the discrete level a similar formulation. In this case, the controls are assumed to be adapted to the filtration generated by the increments of the Brownian motion on the time grid. In this sense and similarly to the continuous time case (see [28, Chapter 2, Section 4.1]) our formulation is more specific than the one described in the

Date: February 22, 2017.

²⁰¹⁰ Mathematics Subject Classification. Primary: 93E20, 49L20; Secondary: 90C15, 93C55.

Key words and phrases. Stochastic Control, Discrete Time Systems, Dynamic Programming Principle, Value Function, Feedback Control.

The first and second author thank the Laboratoire de Finance des Marchés de l'Energie for its support. The first and third authors thank the support from project iCODE : *"Large-scale systems and Smart grids: distributed decision making"* and from the Gaspar Monge Program for Optimization and Operation Research (PGMO). The second author was also supported by Centro Internacional Franco Argentino de Ciencias de la Información y de Sistemas (CIFASIS).

previous paragraph, which is more related to the *weak* formulation of the continuous problem (see [28, Chapter 2, Section 4.2]).

The study of the discrete time case arises from different objectives. For instance, it can be used to prove the existence of optimal controls for the continuous time problem, as the limit of optimal discrete time policies (see e.g. [7] and [18]). Another application is to derive the DPP for the continuous time problem as a consequence of this property in the discrete time case (see e.g. [17] and [23]). We point out that in [17, 15] and [23], given a discrete time control the associated state solves the continuous time stochastic differential equation and so the state is not discrete in time. Finally, discrete time problems appear naturally as the first step in obtaining a numerical approximation of the continuous time problem, the second step being the discretization of the state space (see e.g. [18]) or the resolution by Monte Carlo methods.

The simplicity of our pathwise formulation and the regularity of the coefficients defining the continuous problems, which, as we will see, yields the continuity of the optimal cost as a function of the initial state, allow us to simplify the proof of the DPP for the discrete time problem by arguing as in [5]. Thus, we do not have to deal with delicate measurability issues as in [3]. Although we consider controls adapted to the filtrations generated by the increments of the Brownian motion, a consequence of the DPP is the existence of discrete time optimal feedback (or Markov) controls. This important property in the discrete time case is in contrast with the analogous property in the continuous time case, where the existence of an optimal feedback control can be assured only in exceptional cases (see [28, Chapter 5, Section 6] and Remark 4.9). In some sense, this is similar to the existence issues for continuous time Stochastic Differential Equations (SDEs), where the Euler scheme is always well-posed even when the continuous time SDEs does not admit explicit solutions.

We study several properties of the discrete time value functions V^h , which are analogous to their continuous time counterparts, such as Lipschitz continuity and semiconcavity with respect to the state variable on bounded sets. When extended by linear interpolation to the entire interval [0, T], we prove that V^h is Hölder continuous in time, on bounded sets of the space variable. Using an approximation result by Krylov (see [17, Lemma 6, Section 3.2, p.143]), we also prove with a direct approach the local uniform convergence of V^h to V, the value function of the continuous time problem. Since we work under quite general assumptions, this convergence result is more general than those already proved in [7], where under stronger assumptions weak convergence to a feedback control of the continuous time problems is shown, and [12, Chapter 9]. Probably, the convergence of the value functions can also be proved by using analytical methods based on viscosity solution theory (see e.g. [2] and [12, Chapter 9]), however, our direct approach allows us to prove the important fact that optimal (or ε -optimal) discrete time controls form a minimizing sequence for the continuous time problem. In particular, there always exists a minimizing sequence of discrete time optimal feedback controls. In addition, under some convexity (strong convexity) assumptions, we obtain the weak (strong) convergence of the discrete time optimal controls to a solution of the original problem. In this general framework, we have not established error estimates for the discrete value functions. We refer the reader to [15] and [16] where, under additional assumptions, the author tackles this problem.

The paper is organized as follows. In Section 2 we state the continuous time and discrete time problems and our main assumptions. Section 3 is devoted to some technical and fundamental estimates relating the continuous time and discrete time states associated with piecewise constant controls. In Section 4 we prove the DPP for the discrete time problem and show the existence of feedback optimal controls. The continuity of the discrete value function plays an important role here and simplifies its proof. Next, in Section 5 we prove several regularity properties of V^h , which are analogous to those of V. Finally, in Section 6 we prove in Theorem 6.2 the local uniform convergence of V^h to V and that the sequence of discrete time optimal controls is a minimizing sequence of the continuous problem. Under some convexity assumptions, the convergence of this sequence to an optimal control of the continuous problem is also shown.

2. Preliminaries

We begin by defining the problems we are interested in.

2.1. Continuous time problem. Let $(\Omega, \mathcal{F}, \mathbb{F}, \mathbb{P})$ be a filtered probability space on which an *m*dimensional standard Brownian motion $W(\cdot)$ is defined. We suppose that $\mathbb{F} = \{\mathcal{F}_t\}_{t \in [0,T]}$ (T > 0)is the natural filtration, augmented by all the P-null sets in \mathcal{F} , associated with $W(\cdot)$ and we recall that \mathbb{F} is right-continuous. Let us consider the following controlled Stochastic Differential Equation (SDE):

(1)
$$\begin{cases} dy(t) &= f(t, y(t), u(t))dt + \sigma(t, y(t), u(t))dW(t) \quad t \in]0, T[, \\ y(0) &= x \in \mathbb{R}^n, \end{cases}$$

where $f: [0,T] \times \mathbb{R}^n \times \mathbb{R}^r \to \mathbb{R}^n$ and $\sigma: [0,T] \times \mathbb{R}^n \times \mathbb{R}^r \to \mathbb{R}^{n \times m}$ are given maps. In the notation above $y \in \mathbb{R}^n$ denotes the state function and $u \in \mathbb{R}^r$ the control. We define the cost functional

(2)
$$J(u) = \mathbb{E}\left\{\int_0^T \ell(t, y(t), u(t)) \mathrm{d}t + g(y(T))\right\},$$

where $\ell: [0,T] \times \mathbb{R}^n \times \mathbb{R}^r \to \mathbb{R}$ and $g: \mathbb{R}^n \to \mathbb{R}$ are given maps. A precise definition of the control space and assumptions over the data will be provided in the next sections.

Let U_{ad} be a non-empty closed subset of \mathbb{R}^r and

(3)
$$\mathcal{U}_{ad} := \left\{ u \in (\mathbb{H}^2)^r; \ u(t,\omega) \in U_{ad}, \text{ for almost all (a.a.) } (t,\omega) \in (0,T) \times \Omega \right\},$$
where

where

$$\mathbb{H}^2 := \left\{ v \in L^2([0,T] \times \Omega); \text{ the process } (t,\omega) \in [0,T] \times \Omega \mapsto v(t,\omega) \text{ is } \mathbb{F}\text{-adapted} \right\}$$

The control problem that we consider is

(P)
$$\operatorname{Min} J(u)$$
 subject to $u \in \mathcal{U}_{ad}$.

2.2. Discrete time problem. Let us introduce a discrete time approximation of (P). Given $N \in \mathbb{N}$ define h := T/N. Let us set $t_k = kh$ $(k = 0, \dots, N)$ and consider the sequence of independent and identically distributed (i.i.d.) *m*-valued random vectors, defined as $\Delta W_{i+1} =$ $W(t_{j+1}) - W(t_j)$, for j = 0, ..., N - 1 and $\Delta W_0 = 0$ a.s. Then, $\mathbb{E}(\Delta W_k) = 0$ and $\mathbb{E}(\Delta W_k^i \Delta W_k^j) = 0$ $h\delta_{ij}$ (where $\delta_{ij} = 1$ if i = j and $\delta_{ij} = 0$ otherwise). Consider the discrete time filtration $(\mathcal{F}_k)_{k=0}^N$ defined as $\mathcal{F}_0 = \{\emptyset, \Omega\}$ and $\mathcal{F}_k = \sigma(\Delta W_{k'}; 0 \le k' \le k)$. For simplicity, we note $\mathbb{E}_k(\cdot) := \mathbb{E}(\cdot | \mathcal{F}_k)$. Let us set $L^2_{\mathcal{F}_k} := L^2(\Omega, \mathcal{F}_k, \mathbb{P})$ and let us define $\mathcal{U}^h := \Pi^{N-1}_{k=0} L^2_{\mathcal{F}_k}$, which we endow with the norm $\|u\|^2_{\mathcal{U}^h} := h \sum_{k=0}^{N-1} \mathbb{E}|u_k|^2$.

We consider the following discretization of the state equation, given by an explicit Euler scheme:

(4)
$$\begin{cases} y_k = y_{k-1} + hf(t_{k-1}, y_{k-1}, u_{k-1}) + \sigma(t_{k-1}, y_{k-1}, u_{k-1})\Delta W_k, & k = 1, ..., N \\ y_0 = x \in \mathbb{R}^n. \end{cases}$$

The discrete cost $J^h : \mathcal{U}^h \to \mathbb{R}$ is defined as

(5)
$$J^{h}(u) := \mathbb{E}\left[h\sum_{k=0}^{N-1}\ell(t_{k}, y_{k}, u_{k}) + g(y_{N})\right],$$

where $y = (y_0, \ldots, y_N)$ is the solution of (4). Finally, we consider the admissible set of controls as

(6)
$$\mathcal{U}_{ad}^h := \{ u \in \mathcal{U}^h; \ u_k \in U_{ad} \quad \mathbb{P} \text{ - almost surely (a.s.)}, \ \forall \ k = 0, \dots, N-1 \}.$$

Then, the discrete time control problem that we will consider is

$$(P^h) \qquad \qquad \text{Min } J^h(u) \text{ subject to } u \in \mathcal{U}^h_{ad}.$$

2.3. Assumptions. We present the hypothesis that we consider in this paper.

(H1) Assumptions on the dynamics:

- (a) The maps $\varphi = f, \sigma$ are $\mathcal{B}([0,T] \times \mathbb{R}^n \times \mathbb{R}^r)$ measurable.
- (b) For almost all $t \in [0,T]$ the map $(y,u) \mapsto \varphi(t,y,u)$ is C^1 and there exists a constant L > 0 such that for almost all $t \in [0, T]$ and for all $y \in \mathbb{R}^n$ and $u \in U_{ad}$ we have

(7)
$$\begin{cases} |\varphi(t, y, u)| \le L [|y| + |u| + 1], \\ |\varphi_y(t, y, u)| + |\varphi_u(t, y, u)| \le L, \end{cases}$$

where
$$\varphi_y(t, y, u) := D_y \varphi(t, y, u)$$
 and $\varphi_u(t, y, u) := D_u \varphi(t, y, u)$

(c) There exists an increasing modulus of continuity $\overline{\omega} : [0, +\infty[\rightarrow [0, +\infty[$ such that for $\varphi = f, \sigma$, and for all $y \in \mathbb{R}^n$, $u \in U_{ad}$, $s, t \in [0, T]$ we have

(8)
$$|\varphi(s, y, u) - \varphi(t, y, u)| \le \overline{\omega}(|s - t|).$$

(H2) Assumptions on the cost:

- (a) The maps ℓ and g are respectively $\mathcal{B}([0,T] \times \mathbb{R}^n \times \mathbb{R}^r)$ and $\mathcal{B}(\mathbb{R}^n)$ measurable.
- (b) For almost all $t \in [0, T]$ the map $(y, u) \mapsto \ell(t, y, u)$ is C^1 , and there exists L > 0 such that for all $y \in \mathbb{R}^n$ and $u \in U_{ad}$,

(9)
$$\begin{cases} |\ell(t, y, u)| \le L [|y| + |u| + 1]^2, \\ |\ell_y(t, y, u)| + |\ell_u(t, y, u)| \le L [|y| + |u| + 1] \end{cases}$$

where $\ell_y(t, y, u) := D_y \ell(t, y, u)$ and $\ell_u(t, y, u) := D_u \ell(t, y, u)$.

(c) The map $y \mapsto g(y)$ is C^1 and there exists L > 0 such that for all $y \in \mathbb{R}^n$,

(10)
$$\begin{cases} |g(y)| \le L [|y|+1]^2, \\ |\nabla g(y)| \le L [|y|+1]. \end{cases}$$

3. Estimates on the states of the discrete and continuous formulations

In this section, we study some estimates for the difference between the discrete and continuous time states associated with the same discrete time control, which is extended as a piecewise constant control at each interval $[t_k, t_{k+1}]$.

We start by proving an estimate of the norm of the state in terms of the control and the initial condition. For a fixed h, let $u^h = (u_k)_{k=0}^{N-1} \in \mathcal{U}_{ad}^h$ be a given discrete control and define the associated discrete state $y^h = (y_k)_{k=0}^N$ as the solution of (4).

Lemma 3.1. Assume that (H1) holds. Then, there exists C > 0, such that

(11)
$$\mathbb{E}\left[\max_{k=0,\dots,N}|y_k|^2\right] \le C\left[|x|^2 + \|u^h\|_{\mathcal{U}^h}^2 + 1\right].$$

Proof. For all k = 1, ..., N we have

(12)
$$y_k = x + h \sum_{j=0}^{k-1} f(t_j, y_j, u_j) + \sum_{j=0}^{k-1} \sigma(t_j, y_j, u_j) \Delta W_{j+1}.$$

Then, by **(H1)**-(b) there exists $C_0 > 0$ such that,

(13)
$$|y_k|^2 \leq 3 \left[|x|^2 + Nh^2 \sum_{j=0}^{k-1} |f(t_j, y_j, u_j)|^2 + (\sum_{j=0}^{k-1} \sigma(t_j, y_j, u_j) \Delta W_{j+1})^2 \right] \\ \leq C_0 \left[|x|^2 + h \sum_{j=0}^{k-1} [|y_j|^2 + |u_j|^2 + 1] + (\sum_{j=0}^{k-1} \sigma(t_j, y_j, u_j) \Delta W_{j+1})^2 \right].$$

By the Doob's maximal inequality (see [14, Chapter 2, Theorem 6.10]), the Itô isometry, and by **(H1)**-(b) there exist $C_1 > 0$ and $C_2 > 0$ such that

$$\mathbb{E}\left[\max_{0\leq i\leq k}|y_{i}|^{2}\right] \leq C_{0}\left[|x|^{2}+h\sum_{j=0}^{k-1}\left[\mathbb{E}\left[\max_{0\leq i\leq j}|y_{i}|^{2}\right]+\mathbb{E}\left[|u_{j}|^{2}\right]+1\right]\right.$$

$$\left.+C_{1}\mathbb{E}\left[h\sum_{j=0}^{k-1}|\sigma(t_{j},y_{j},u_{j})|^{2}\right]\right]$$

$$\leq C_{2}\left[|x|^{2}+h\sum_{j=0}^{k-1}\left[\mathbb{E}\left[\max_{0\leq i\leq j}|y_{i}|^{2}\right]+\mathbb{E}\left[|u_{j}|^{2}\right]+1\right]\right].$$

The results follows by the discrete Grönwall's lemma [8].

Let $u_c^h \in \mathbb{H}^2_{\mathbb{F}}$ be defined as $u_c^h(t) := u_k$ for all $t \in [t_k, t_{k+1})$ and y be the associated continuous state, i.e. the unique solution of

(15)
$$\begin{cases} dy(t) = f(t, y(t), u_c^h(t))dt + \sigma(t, y(t), u_c^h(t))dW(t), & t \in]0, T[, \\ y(0) = x. \end{cases}$$

Now we are going to analyse the relationship between y and y^h . Note that $\|u_c^h\|_{\mathbb{H}^2_{\mathbb{H}}} = \|u^h\|_{\mathcal{U}^h}$.

Lemma 3.2. Assume that (H1) holds true. Then, there exists C > 0 such that

(16)
$$\max_{k=0,\dots,N} \mathbb{E} |y(t_k) - y_k|^2 \le Ch \left[|x|^2 + ||u^h||_{\mathcal{U}^h}^2 + 1 \right] + C\overline{\omega}^2(h),$$

for all k = 0, ..., N.

Proof. For all k = 0, ..., N - 1 we define $\Delta y_k := y(t_k) - y_k$,

(17) $\Delta f_k(t) := f(t, y(t), u_k) - f(t_k, y_k, u_k), \text{ and } \Delta \sigma_k(t) := \sigma(t, y(t), u_k) - \sigma(t_k, y_k, u_k).$ We have,

(18)
$$\Delta y_{k+1} = \Delta y_k + \int_{t_k}^{t_{k+1}} \Delta f_k(t) \mathrm{d}t + \int_{t_k}^{t_{k+1}} \Delta \sigma_k(t) \mathrm{d}W(t).$$

Therefore, by the Cauchy-Schwarz inequality and the Itô isometry, we obtain

(19)

$$\mathbb{E}\left[|\Delta y_{k+1}|^{2}\right] \leq \mathbb{E}\left[|\Delta y_{k}|^{2}\right] + \mathbb{E}\left[|\int_{t_{k}}^{t_{k+1}}\Delta f_{k}(t)dt|^{2}\right] + \mathbb{E}\left[|\int_{t_{k}}^{t_{k+1}}\Delta\sigma_{k}(t)dW(t)|^{2}\right] + 2\left(\mathbb{E}[|\Delta y_{k}|^{2}]\right)^{\frac{1}{2}} \left(\mathbb{E}[|\int_{t_{k}}^{t_{k+1}}\Delta f_{k}(t)dt|^{2}]\right)^{\frac{1}{2}} + 2\left(\mathbb{E}[|\int_{t_{k}}^{t_{k+1}}\Delta f_{k}(t)dt|^{2}]\right)^{\frac{1}{2}} \left(\mathbb{E}[|\int_{t_{k}}^{t_{k+1}}\Delta\sigma_{k}(t)dW(t)|^{2}]\right)^{\frac{1}{2}}.$$

Applying the Young's inequality in the last two terms, we have

(20)
$$\mathbb{E}\left[\left|\Delta y_{k+1}\right|^{2}\right] \leq [1+h]\mathbb{E}\left[\left|\Delta y_{k}\right|^{2}\right] + [1+\frac{2}{h}]\mathbb{E}\left[\left|\int_{t_{k}}^{t_{k+1}}\Delta f_{k}(t)dt\right|^{2}\right] + [1+h]\mathbb{E}\left[\left|\int_{t_{k}}^{t_{k+1}}\Delta \sigma_{k}(t)dW(t)\right|^{2}\right].$$

Now, we study all the square terms in the r.h.s. of (20) separately. By the Cauchy-Schwarz inequality and (H1), we obtain

$$\mathbb{E}\left[\left|\int_{t_{k}}^{t_{k+1}} \Delta f_{k}(t) dt\right|^{2}\right] \leq h\mathbb{E}\left[\int_{t_{k}}^{t_{k+1}} |\Delta f_{k}(t)|^{2} dt\right] \\
\leq 2h\mathbb{E}\int_{t_{k}}^{t_{k+1}} |f(t, y(t), u_{k}) - f(t, y_{k}, u_{k})|^{2} dt \\
+2h\mathbb{E}\int_{t_{k}}^{t_{k+1}} |f(t, y_{k}, u_{k}) - f(t_{k}, y_{k}, u_{k})|^{2} dt \\
\leq 2h\left[\int_{t_{k}}^{t_{k+1}} L^{2}\mathbb{E}|y(t) - y_{k}|^{2} dt + \int_{t_{k}}^{t_{k+1}} \overline{\omega}^{2}(|t - t_{k}|) dt\right] \\
\leq 2hL^{2}\int_{t_{k}}^{t_{k+1}} \mathbb{E}|y(t) - y_{k}|^{2} dt + 2h^{2}\overline{\omega}^{2}(h).$$

In order to estimate the last term in (21), note that for all $t_k \leq t < t_{k+1}$ we have,

(22)
$$y(t) - y_k = \Delta y_k + \int_{t_k}^t f(t, y(t), u(t)) ds + \int_{t_k}^t \sigma(t, y(t), u(t)) dW(s).$$

Then, by (H1), the Cauchy-Schwarz inequality and the Itô isometry, we deduce that there exists $C_0 > 0$ such that for all $t_k \le t < t_{k+1}$,

(23)

$$\mathbb{E}\left[|y(t) - y_k|^2\right] \leq C_0 \mathbb{E}\left[|\Delta y_k|^2\right] + C_0 h \mathbb{E}\left[\int_{t_k}^{t_{k+1}} L^2[|y(t)|^2 + |u_k|^2 + 1]dt\right] \\
+ C_0 \mathbb{E}\left[\int_{t_k}^{t_{k+1}} L^2[|y(t)|^2 + |u_k|^2 + 1]dt\right] \\
\leq C_0 \mathbb{E}\left[|\Delta y_k|^2\right] + C_0 h\left[|x|^2 + ||u^h||_{\mathcal{U}^h}^2 + \mathbb{E}|u_k|^2 + 1\right],$$

where the last inequality follows from [22, Proposition 2.1]. So, by (21) and (23), there exist positive constants C_1 and C_2 such that, (24)

$$\mathbb{E}\left[\left|\int_{t_{k}}^{t_{k+1}} \Delta f_{k}(t) \mathrm{d}t\right|^{2}\right] \leq C_{1}h^{2}\mathbb{E}\left[|\Delta y_{k}|^{2}\right] + C_{2}h^{3}\left[|x|^{2} + \|u^{h}\|_{\mathcal{U}^{h}}^{2} + \mathbb{E}|u_{k}|^{2} + 1\right] + 2h^{2}\overline{\omega}^{2}(h).$$

By the Itô isometry and (23) we have, (25)

$$\mathbb{E}\left[\int_{t_k}^{t_{k+1}} \Delta \sigma_k(t) \mathrm{d}W(t)\right]^2 = \mathbb{E}\int_{t_k}^{t_{k+1}} |\Delta \sigma_k(t)|^2 \mathrm{d}t$$

$$\leq 2\mathbb{E}\int_{t_k}^{t_{k+1}} L^2 |y(t) - y_k|^2 + \overline{\omega}^2 (|t - t_k|) \mathrm{d}t$$

$$\leq C_3 h \mathbb{E}\left[|\Delta y_k|^2\right] + C_4 h^2 \left[|x|^2 + ||u^h||_{\mathcal{U}^h}^2 + \mathbb{E}|u_k|^2 + 1\right] + 2h\overline{\omega}^2(h),$$

for suitable positive constants C_3 and C_4 .

Combining (20), (24) and (25) we conclude that there exist $C_5 > 0$, $C_6 > 0$ and $C_7 > 0$ such that

(26)
$$\mathbb{E}\left[\left|\Delta y_{k+1}\right|^{2}\right] \leq [1+C_{5}h]\mathbb{E}\left[\left|\Delta y_{k}\right|^{2}\right] + C_{6}h^{2}\left[\left|x\right|^{2} + \left\|u^{h}\right\|_{\mathcal{U}^{h}}^{2} + \mathbb{E}|u_{k}|^{2} + 1\right] + C_{7}h\overline{\omega}^{2}(h).$$

Therefore, we deduce that (27)

for a suitable constant C > 0.

Corollary 3.3. Assume that **(H1)** holds and that at least one of the following assumptions holds true: (a) for all $(y, u) \in \mathbb{R}^n \times \mathbb{R}^r$ and almost all $t \in [0, T]$ we have $\sigma_u(t, y, u) \equiv 0$; (b) the set U_{ad} is compact. Then, there exists C > 0 such that for all k = 0, ..., N - 1,

(28)
$$\mathbb{E}\left[\sup_{t_k \le t < t_{k+1}} |y(t) - y_k|^2\right] \le Ch\left[|x|^2 + ||u||_{\mathcal{U}^h}^2 + 1\right] + C\overline{\omega}^2(h).$$

Proof. For all $t_k \leq t < t_{k+1}$, we have

(29)
$$y(t) - y_k = [y(t_k) - y_k] + \int_{t_k}^t f(s, y(s), u_k) ds + \int_{t_k}^t \sigma(s, y(s), u_k) dW(s).$$

Then, by the Doob's maximal inequality and the Itô isometry, there exists K > 0 such that

(30)
$$\mathbb{E}\left[\sup_{t_k \le t < t_{k+1}} |y(t) - y_k|^2\right] \le 2\mathbb{E}\left[|y(t_k) - y_k|^2\right] + 4h\mathbb{E}\left[\int_{t_k}^{t_{k+1}} |f(s, y(s), u_k)|^2 ds\right] + 4K\mathbb{E}\left[\int_{t_k}^{t_{k+1}} |\sigma(s, y(s), u_k)|^2 ds\right].$$

By (H1) and [22, Proposition 2.1], there exists $C_0 > 0$ such that

(31)
$$\mathbb{E}\int_{t_k}^{t_{k+1}} |f(s, y(s), u_k)|^2 \, \mathrm{d}s \le C_0 \left[h \left[|x|^2 + \|u^h\|_{\mathcal{U}^h}^2 + 1 \right] + \|u^h\|_{\mathcal{U}^h}^2 + h \right].$$

If (a) holds, there exists $C_1 > 0$ such that

(32)
$$\mathbb{E}\int_{t_k}^{t_{k+1}} |\sigma(s, y(s), u_k)|^2 \,\mathrm{d}s \le C_1 h\left[[|x|^2 + ||u^h||_{\mathcal{U}^h}^2 + 1] + 1 \right],$$

then, by the previous lemma we have

(33)
$$\mathbb{E}\left[\sup_{t_k \le t < t_{k+1}} |y(t) - y_k|^2\right] \le Ch\left[|x|^2 + ||u||_{\mathcal{U}^h}^2 + 1\right] + C\overline{\omega}^2(h),$$

for a suitable C > 0. On the other hand, if (b) holds, for some $M_U > 0$ we have $|u| \le M_U$ for all $u \in U_{ad}$. Then there exists $C_2 > 0$ such that,

(34)
$$\mathbb{E}\int_{t_k}^{t_{k+1}} |\sigma(s, y(s), u_k)|^2 \,\mathrm{d}s \le C_2 h\left[[\|x\|^2 + \|u^h\|_{\mathcal{U}^h}^2 + 1] + M_U^2 + 1 \right].$$

Thus, by the previous lemma we obtain the existence of C > 0 such that

(35)
$$\mathbb{E}\left[\sup_{t_k \le t < t_{k+1}} |y(t) - y_k|^2\right] \le Ch\left[|x|^2 + ||u||_{\mathcal{U}^h}^2 + 1\right] + C\overline{\omega}^2(h).$$

4. DISCRETE TIME DYNAMIC PROGRAMMING PRINCIPLE

Our goal in this section is to prove the DPP for problem (P^h) parameterized by the initial discrete time and initial state. Besides its own importance, the DPP implies the existence of discrete time optimal feedback controls, and it is also useful to prove the convergence of the discrete value functions to the continuous one, as we will see in Section 6.

Throughout this section we consider h = T/N fixed and assume that U_{ad} is compact. Since problem (P^h) will be parametrized by the initial time and initial state, we need to deal with new filtrations and space of admissible controls. For each k = 0, ..., N consider the filtrations,

(36)
$$\mathcal{F}_k^k = \{\emptyset, \Omega\}$$
 and $\mathcal{F}_j^k = \sigma(\Delta W_{k'}; k+1 \le k' \le j)$ for all $j \in \{k+1, ..., N\}$.

For $k = 0, \ldots, N - 1$, we consider the *admissible control* sets

(37)
$$\mathcal{U}_k^h := \{ u = (u_k, ..., u_{N-1}) \in \prod_{j=k}^{N-1} L^2_{\mathcal{F}_j^k} : u_j(\omega) \in U_{ad} \quad \mathbb{P} - \text{a.s.}, \ j = k, ..., N-1 \}.$$

Given $u \in \mathcal{U}_k^h$, $x \in \mathbb{R}^n$ and $k = 0, \ldots, N-1$, we recursively define the state $y_j^{k,x,u}$, $j = k, \ldots, N$, associated with u, x and k as

(38)
$$\begin{cases} y_{j+1}^{k,x,u} = y_j^{k,x,u} + hf(t_j, y_j^{k,x,u}, u_j) + \sigma(t_j, y_j^{k,x,u}, u_j) \Delta W_{j+1}, & j = k, \dots, N-1, \\ y_k^{k,x,u} = x. \end{cases}$$

Note that $y_j^{k,x,u} \in L^2_{\mathcal{F}_j^k}$, for all $j = k, \ldots, N$. It is easy to see that all the estimates presented in the previous section remain true if we consider the state starting at time t_k .

Finally, we associate to each $u \in \mathcal{U}_k^h$ the cost function,

(39)
$$J_k^h(x,u) := \mathbb{E}\left[h\sum_{j=k}^{N-1} \ell(t_j, y_j^{k,x,u}, u_j) + g(y_N^{k,x,u})\right]$$

The value function is defined over \mathbb{R}^n as

(40)
$$V^N(x) := g(x), \text{ and } V^k(x) := \inf_{u \in \mathcal{U}_k^h} J_k^h(x, u) \text{ for } k = 0, \dots, N-1.$$

Our aim is to prove the following DPP for V^k

(41)
$$V^{k}(x) = \inf_{u \in U_{ad}} \left\{ h\ell(t_{k}, x, u) + \mathbb{E}\left[V^{k+1}(x + hf(t_{k}, x, u) + \sigma(t_{k}, x, u)\Delta W_{k+1}) \right] \right\},$$
for all $k = 0, ..., N - 1.$

4.1. **Preliminary estimates.** In order to prove the DPP, we need some preliminary results about the state and the cost.

Lemma 4.1. Let **(H1)** holds. Then, for every $p \ge 2$, there exists $C_p > 0$, such that for all $x, y \in \mathbb{R}^n$, k = 0, ..., N - 1 and $u \in \mathcal{U}_k^h$, we have

(42)
$$\mathbb{E}\left[\max_{j=k,\dots,N}\left|y_{j}^{k,x,u}-y_{j}^{k,y,u}\right|^{p}\right] \leq C_{p}|x-y|^{p}.$$

Proof. By notational convenience, we omit the indexes k and u in the states. Denoting $\Delta y_j = y_j^x - y_j^y$, and $\Delta \varphi_j = \varphi(t_j, y_j^x, u_j) - \varphi(t_j, y_j^y, u_j)$ for $\varphi = f, \sigma$, we obtain for $i = k, \ldots N - 1$,

(43)
$$\Delta y_{i+1} = x - y + \sum_{j=k}^{i} h \Delta f_j + \sum_{j=k}^{i} \Delta \sigma_j \Delta W_{j+1}$$

We have,

(44)
$$|\Delta y_{i+1}|^{p} \leq 3^{p-1} \left[|x-y|^{p} + \left| \sum_{j=k}^{i} h \Delta f_{j} \right|^{p} + \left| \sum_{j=k}^{i} \Delta \sigma_{j} \Delta W_{j+1} \right|^{p} \right].$$

By (H1) we get

(45)
$$\left|\sum_{j=k}^{i} h\Delta f_{j}\right|^{p} \leq N^{p-1}h^{p}\sum_{j=k}^{i} |\Delta f_{j}|^{p} \leq T^{p-1}hL^{p}\sum_{j=k}^{i} |\Delta y_{j}|^{p}.$$

Now, by (H1) and the Burkholder-Davis-Gundy inequality [6], there exists K_p such that

(46)

$$\mathbb{E}\left(\max_{k\leq m\leq i}|\sum_{j=k}^{m}\Delta\sigma_{j}\Delta W_{j+1}|^{p}\right) \leq K_{p}\mathbb{E}\left(\left[h\sum_{j=k}^{i}|\Delta\sigma_{j}|^{2}\right]^{\frac{p}{2}}\right) \\
\leq K_{p}N^{\frac{p}{2}-1}h^{\frac{p}{2}}\sum_{j=k}^{i}\mathbb{E}(|\Delta\sigma_{j}|^{p}) \\
\leq K_{p}T^{\frac{p}{2}-1}hL^{p}\sum_{j=k}^{i}\mathbb{E}(|\Delta y_{j}|^{p}).$$

Combining (44), (45) and (46), there exists c_p such that

(47)
$$\mathbb{E}\left(\max_{k\leq m\leq i+1}|\Delta y_m|^p\right)\leq c_p|x-y|^p+c_ph\sum_{j=k}^i\mathbb{E}\left(\max_{k\leq m\leq j}|\Delta y_m|^p\right).$$

The conclusion follows from the discrete Grönwall's lemma [8].

Now we prove that the discrete value function is Lipschitz continuous w.r.t. the state variable, on bounded sets.

Lemma 4.2. Assume that **(H1)** and **(H2)** hold. Then, there exists a constant C > 0 (independent of h), such that for all $x, y \in \mathbb{R}^n$, and for all $u \in \mathcal{U}_k^h$, we have

(48)
$$\left| J_k^h(x,u) - J_k^h(y,u) \right| \le C \left[|x| + |y| + 1 \right] |x - y|, \quad \forall \ k = 0, \dots, N - 1.$$

As a consequence,

(49)
$$\left| V^{k}(x) - V^{k}(y) \right| \leq C \left[|x| + |y| + 1 \right] |x - y| \quad \forall \ k = 0, \dots, N.$$

Proof. Using the same notation of the above lemma, we have for fixed k and $u \in \mathcal{U}_k^h$

(50)
$$|J_k^h(x,u) - J_k^h(y,u)| \le \mathbb{E}\left[h\sum_{j=k}^{N-1} |\ell(t_j, y_j^x, u_j) - \ell(t_j, y_j^y, u_j)| + |g(y_N^x) - g(y_N^y)|\right].$$

By (H2) we have for all $k \leq j \leq N - 1$, (51)

$$\begin{split} \mathbb{E}\left[|\ell(t_j, y_j^x, u_j) - \ell(t_j, y_j^y, u_j)|\right] &\leq \mathbb{E}\left[\int_0^1 |\ell_y(t_j, y_j^x + s(y_j^y - y_j^x), u_j)(y_j^y - y_j^x)| \mathrm{d}s\right] \\ &\leq \mathbb{E}\left[\int_0^1 [L(1 + |y_j^x| + s|y_j^y - y_j^x| + |u_j|)|y_j^y - y_j^x|] \mathrm{d}s\right] \\ &\leq L\mathbb{E}\left[|y_j^y - y_j^x| + |y_j^x||y_j^y - y_j^x| + |y_j^y - y_j^x|^2 + |u_j||y_j^y - y_j^x|\right]. \end{split}$$

Since the set U_{ad} is compact, it is bounded by a positive constant M_U , and so by the Cauchy-Schwarz inequality, Lemma 3.1 and Lemma 4.1 there exists $C_0 > 0$ such that

(52)
$$\mathbb{E}\left[|y_{j}^{y} - y_{j}^{x}|\right] \leq \left(\mathbb{E}[|y_{j}^{y} - y_{j}^{x}|^{2}]\right)^{\frac{1}{2}} \leq C_{0}|x - y| \\
\mathbb{E}\left[|y_{j}^{x}||y_{j}^{y} - y_{j}^{x}|\right] \leq \left(\mathbb{E}[|y_{j}^{x}|^{2}]\right)^{\frac{1}{2}} \left(\mathbb{E}[|y_{j}^{y} - y_{j}^{x}|^{2}]\right)^{\frac{1}{2}} \leq C_{0}\left[|x|^{2} + TM_{U}^{2} + 1|\right]^{\frac{1}{2}}|x - y| \\
\mathbb{E}\left[|u_{j}||y_{j}^{y} - y_{j}^{x}|\right] \leq \left(\mathbb{E}[|u_{j}|^{2}]\right)^{\frac{1}{2}} \left(\mathbb{E}[|y_{j}^{y} - y_{j}^{x}|^{2}]\right)^{\frac{1}{2}} \leq C_{0}M_{U}|x - y| \\
\mathbb{E}\left[|y_{j}^{y} - y_{j}^{x}|^{2}\right] \leq C_{0}|x - y|^{2} \leq C_{0}\left[|x| + |y|\right]|x - y|.$$

We conclude that there exists $C_1 > 0$ such that,

(53)
$$\mathbb{E}\left[\left|\ell(t_j, y_j^x, u_j) - \ell(t_j, y_j^y, u_j)\right|\right] \le C_1 \left[|x| + |y| + 1\right] |x - y|.$$

Analogously we can deduce that

(54)
$$\mathbb{E}\left[|g(y_N^x) - g(y_N^y)|\right] \le C_1 \left[|x| + |y| + 1\right] |x - y|.$$

Since C_1 in (53) does not depend on j, we conclude that

(55)
$$|J_k^h(x,u) - J_k^h(y,u)| \leq (T+1)C_1[|x| + |y| + 1]|x - y|,$$

and (48) follows.

Since the set \mathcal{U}_k^h is bounded, and the constant C_1 obtained is independent of $u \in \mathcal{U}_k^h$, relation (49) easily follows from, the inequality

(56)
$$|V^{k}(x) - V^{k}(y)| \leq \sup_{u \in \mathcal{U}_{k}^{h}} |J_{k}^{h}(x, u) - J_{k}^{h}(y, u)|.$$

4.2. Dynamic Programming Principle. In order to prove the DPP, for all $x \in \mathbb{R}^n$ we define

(57)
$$S^{k}(x) := \inf_{u \in U_{ad}} \left\{ h\ell(t_{k}, x, u) + \mathbb{E}\left[V^{k+1}(y_{k+1}^{k, x, u}) \right] \right\}, \quad \forall \ k = 0, \dots, N-1$$
$$S^{N}(x) := g(x),$$

where,

(58)
$$y_{k+1}^{k,x,u} = x + hf(t_k, x, u) + \sigma(t_k, x, u)\Delta W_{k+1}.$$

Lemma 4.3. Under assumptions (H1) and (H2), there exists C > 0 (independent of h), such that for all $x, y \in \mathbb{R}^n$, and k = 0, ..., N - 1,

(59)
$$\left| S^{k}(x) - S^{k}(y) \right| \leq C \left[|x| + |y| + 1 \right] |x - y|.$$

Proof. By the definition of S^k and the previous lemma, there exists $C_0 > 0$ such that (60)

$$\begin{aligned} |S^{k}(x) - S^{k}(y)| &\leq \sup_{u \in U_{ad}} \left\{ h|\ell(t_{k}, x, u) - \ell(t_{k}, y, u)| + \mathbb{E}\left[|V^{k+1}(y_{k+1}^{k, x, u}) - V^{k+1}(y_{k+1}^{k, y, u})|\right] \right\} \\ &\leq hC_{0}\left[|x| + |y| + 1 \right] |x - y| + \mathbb{E}\left[C_{0}[|y_{k+1}^{k, x, u}| + |y_{k+1}^{k, y, u}| + 1]|y_{k+1}^{k, x, u} - y_{k+1}^{k, y, u}| \right]. \end{aligned}$$

By the Cauchy-Schwarz inequality, we obtain (61)

$$\mathbb{E}\left[[|y_{k+1}^{k,x,u}| + |y_{k+1}^{k,y,u}| + 1]|y_{k+1}^{k,x,u} - y_{k+1}^{k,y,u}|\right] \le \left(\mathbb{E}[[|y_{k+1}^{k,x,u}| + |y_{k+1}^{k,y,u}| + 1]^2]\right)^{\frac{1}{2}} \left(\mathbb{E}[|y_{k+1}^{k,x,u} - y_{k+1}^{k,y,u}|^2]\right)^{\frac{1}{2}}.$$

By Lemma 3.1 and Lemma 4.1 we conclude that there exists $C_1 > 0$, independent of u because U_{ad} is bounded, such that

(62)
$$\left(\mathbb{E}[[|y_{k+1}^{k,x,u}| + |y_{k+1}^{k,y,u}| + 1]^2] \right)^{\frac{1}{2}} \left(\mathbb{E}[|y_{k+1}^{k,x,u} - y_{k+1}^{k,y,u}|^2] \right)^{\frac{1}{2}} \le C_1 \left[|x| + |y| + 1 \right] |x - y|.$$

Combining (60) and (62), we deduce that (59) holds true.

Lemma 4.4. For all $x \in \mathbb{R}^n$, and for all k = 0, ..., N, the map $u \in \mathbb{R}^m \mapsto \mathbb{E}[V^{k+1}(y_{k+1}^{k,x,u})]$ is Lipschitz continuous. As a consequence, $S^k(x) \in \mathbb{R}$, for all $x \in \mathbb{R}^n$.

Proof. Let $u, v \in \mathbb{R}^r$, then by **(H1)** and the Itô isometry, (63)

$$\begin{split} \mathbb{E}\left[|y_{k+1}^{k,x,u} - y_{k+1}^{k,x,v}|^2\right] &\leq \mathbb{E}\left[|h(f(t_k,x,u) - f(t_k,x,v)) + (\sigma(t_k,x,u) - \sigma(t_k,x,v))\Delta W_{k+1}|^2\right] \\ &\leq 2h^2 \mathbb{E}\left[|f(t_k,x,u) - f(t_k,x,v)|^2\right] + 2h \mathbb{E}\left[|\sigma(t_k,x,u) - \sigma(t_k,x,v)|^2\right] \\ &\leq 2h^2 L^2 |u-v|^2 + 2h L^2 |u-v|^2. \end{split}$$

Thus, arguing as in proof of the previous lemma, by Lemma 3.1, Lemma 4.2 and the Cauchy-Schwarz inequality, there exist $C_0 > 0$ and C > 0 such that, (64)

$$\begin{split} \left| \mathbb{E}[V^{k+1}(y_{k+1}^{k,x,u}) - V^{k+1}(y_{k+1}^{k,x,v})] \right| &\leq \mathbb{E}\left[|C_0[|y_{k+1}^{k,x,u})| + |y_{k+1}^{k,x,v})| + 1] |y_{k+1}^{k,x,u} - y_{k+1}^{k,x,v}| \right] \\ &\leq \left(\mathbb{E}[|C_0[|y_{k+1}^{k,x,u})| + |y_{k+1}^{k,x,v})| + 1] |^2] \right)^{\frac{1}{2}} \left(\mathbb{E}[|y_{k+1}^{k,x,u} - y_{k+1}^{k,x,v}|^2] \right)^{\frac{1}{2}} \\ &\leq C\left[|x| + 1 \right] |u - v|. \end{split}$$

By (64) and **(H2)**, we conclude that the map $u \mapsto \mathbb{E}[V^{k+1}(y_{k+1}^{k,x,u})]$ is Lipschitz continuous, and so $S^k(x)$ is finite.

Now we prove the DPP. Since V^k is continuous, we can directly prove the result following the arguments in [5] without needing to embed our problem in the general framework of [3].

Theorem 4.5 (DPP). Under assumptions **(H1)** and **(H2)**, for all $x \in \mathbb{R}^n$ we have (65) $V^k(x) = S^k(x) \quad \forall \ k = 0, ..., N.$

Proof. We start by proving that $V^k(x) \geq S^k(x)$. Let $u = (u_k, ..., u_{N-1})$ be any element of \mathcal{U}_k^h . By the definition of the set \mathcal{U}_k^h , we can write u_j for $j \in \{k + 1, ..., N - 1\}$, as a measurable function of the increments of the Brownian motion, i.e. $u_j(\Delta W_{k+1}, ..., \Delta W_j)$. For fixed $\Delta \omega_{k+1} \in \mathbb{R}^m$ and j = k + 1, ..., N - 1, we define the maps

(66)
$$\hat{u}_j(\Delta\omega_{k+1}): \omega \in \Omega \mapsto u_j(\Delta\omega_{k+1}, \Delta W_{k+2}(\omega), ..., \Delta W_j(\omega)).$$

Setting $\hat{u}(\Delta \omega_{k+1}) = (\hat{u}_{k+1}(\Delta \omega_{k+1}), \dots, \hat{u}_{N-1}(\Delta \omega_{k+1}))$, we obtain $\hat{u}(\Delta \omega_{k+1}) \in \mathcal{U}_{k+1}^h$. Then, we can also define,

(67)
$$\hat{y}_{k+1}(\Delta\omega_{k+1}) := x + hf(t_k, x, u_k) + \sigma(t_k, x, u_k)\Delta\omega_{k+1}$$

which is deterministic, and for j = k + 2, ..., N,

(68)
$$\hat{y}_j(\Delta\omega_{k+1}): \omega \in \Omega \mapsto y_j^{k+1,\hat{y}_{k+1}(\Delta\omega_{k+1}),\hat{u}(\Delta\omega_{k+1})(\omega)}(\omega).$$

Then, by the independence of the increments of a Brownian motion, we have (69)

$$\mathbb{E}\left[h\sum_{j=k+1}^{N-1}\ell(t_j, y_j^{k,x,u}, u_j) + g(y_N^{k,x,u})\right] = \int_{\mathbb{R}^m} \mathbb{E}\left[h\sum_{j=k+1}^{N-1}\ell(t_j, \hat{y}_j(\Delta\omega_{k+1}), \hat{u}_j(\Delta\omega_{k+1})) + g(\hat{y}_N(\Delta\omega_{k+1}))\right] d\mathbb{P}_{\Delta W_{k+1}}(\Delta\omega_{k+1}),$$

where $\mathbb{P}_{\Delta W_{k+1}}$ is the measure induced from \mathbb{P} by ΔW_{k+1} on \mathbb{R}^m (see [1, Section 4.13]). So, we obtain, (70)

$$\begin{split} \mathbb{E} \left[h \sum_{j=k+1}^{N-1} \ell(t_j, y_j^{k,x,u}, u_j) + g(y_N^{k,x,u}) \right] \\ &= \int_{\mathbb{R}^m} \left(h \ell(t_{k+1}, \hat{y}_{k+1}(\Delta \omega_{k+1}), \hat{u}_{k+1}(\Delta \omega_{k+1})) \right. \\ &+ \mathbb{E} \left[h \sum_{j=k+2}^{N-1} \ell(t_j, \hat{y}_j(\Delta \omega_{k+1}), \hat{u}_j(\Delta \omega_{k+1})) + g(\hat{y}_N(\Delta \omega_{k+1})) \right] \right] d\mathbb{P}_{\Delta W_{k+1}}(\Delta \omega_{k+1}) \\ &\geq \int_{\mathbb{R}^m} V^{k+1}(\hat{y}_{k+1}(\Delta \omega_{k+1})) d\mathbb{P}_{\Delta W_{k+1}}(\Delta \omega_{k+1}) \\ &= \mathbb{E} \left[V^{k+1}(x + hf(t_k, x, u_k) + \sigma(t_k, x, u_k) \Delta W_{k+1}) \right]. \end{split}$$

Then for all $u = (u_k, ..., u_{N-1}) \in \mathcal{U}_k^h$, since $u_k \in L^2_{\mathcal{F}_k^k}$ and $\mathcal{F}_k^k = \{\emptyset, \Omega\}$, we obtain

(71)

$$\ell(t_k, x, u_k) + \mathbb{E} \left[h \sum_{j=k+1}^{N-1} \ell(t_j, y_j^{k, x, u}, u_j) + g(y_N^{k, x, u}) \right]$$

$$\geq \ell(t_k, x, u_k) + \mathbb{E} \left[V^{k+1}(x + hf(t_k, x, u_k) + \sigma(t_k, x, u_k) \Delta W_{k+1}) \right]$$

$$\geq S^k(x).$$

Minimizing w.r.t $u \in \mathcal{U}_k^h$ in the l.h.s. we deduce

(72)
$$V^k(x) \ge S^k(x).$$

We next prove the converse inequality by an induction argument. It is clear by the definitions that

(73)
$$V^N(x) = S^N(x) \text{ and } V^{N-1}(x) = S^{N-1}(x) \quad \forall x \in \mathbb{R}^n.$$

Now, let ε be a positive number, for each $x \in \mathbb{R}^n$ let $\delta_x > 0$ be such that $C[|x| + |y| + 1]|x - y| < \frac{\varepsilon}{3}$ for all $y : |x - y| < \delta_x$, where C is the maximum of the constants given in Lemma 4.2 and Lemma 4.3. Then, for all k = 0, ..., N and $u \in \mathcal{U}_k^h$,

(74)
$$\max\left\{|J_k^h(x,u) - J_k^h(y,u)|, |V^k(x) - V^k(y)|, |S^k(x) - S^k(y)|\right\} < \frac{\varepsilon}{3}, \quad \forall \ y : |x - y| < \delta_x.$$

Since \mathbb{R}^n is a Lindelöf space, i.e. every open cover has a countable subcover, there exists a sequence $(\xi_i)_{i\in\mathbb{N}}\subset\mathbb{R}^n$ such that $\mathbb{R}^n=\bigcup_{i=1}^{\infty}B(\xi_i,\delta_{\xi_i})$. In order to obtain a disjoint union, we can define

(75)
$$\hat{B}_1 := B(\xi_1, \delta_{\xi_1}), \text{ and } \hat{B}_k := B(\xi_k, \delta_{\xi_k}) \setminus (\bigcup_{j=1}^{k-1} \hat{B}_j), \forall k > 1.$$

Let k < N-1, and assume that $V^n \equiv S^n$, for all n = k+1, ..., N. Let $u_j^i \in U_{ad}$ be an $\frac{\varepsilon}{3}$ -optimal solution of $S^j(\xi_i)$, for j = k, ..., N-1, i.e.

(76)
$$h\ell(t_j,\xi_i,u_j^i) + \mathbb{E}\left[V^{j+1}(\xi_i + hf(t_j,\xi_i,u_j^i) + \sigma(t_j,\xi_i,u_j^i)\Delta W_{j+1})\right] \le S^j(\xi_i) + \frac{\varepsilon}{3}$$

We define the measurable function $u_j(x) = \sum_{i=1}^{\infty} u_j^i \chi_{\hat{B}_i}(x)$. Let $x \in \mathbb{R}^n$ and i such that $x \in \hat{B}_i$ (see (75)). Then,

(77)

$$h\ell(t_j, x, u_j(x)) + \mathbb{E}\left[V^{j+1}(x + hf(t_j, x, u_j(x)) + \sigma(t_j, x, u_j(x))\Delta W_{j+1})\right]$$

$$= h\ell(t_j, x, u_j^i) + \mathbb{E}\left[V^{j+1}(x + hf(t_j, x, u_j^i) + \sigma(t_j, x, u_j^i)\Delta W_{j+1})\right]$$

$$\leq \frac{\varepsilon}{3} + h\ell(t_j, \xi_i, u_j^i) + \mathbb{E}\left[V^{j+1}(\xi_i + hf(t_j, \xi_i, u_j^i) + \sigma(t_j, \xi_i, u_j^i)\Delta W_{j+1})\right]$$

$$\leq \frac{\varepsilon}{3} + S^j(\xi_i) + \frac{\varepsilon}{3}$$

$$\leq S^j(x) + \varepsilon.$$

Now, we fix $x \in \mathbb{R}^n$ and take $\bar{u}_k = u_k(x) \in U_{ad}$. We define inductively $u_j : \Omega \to \mathbb{R}^r$, for all $k < j \le N - 1$, as

(78)
$$\bar{u}_{j+1}(\omega) := u_{j+1} \left(y_{j+1}^{k,x,(\bar{u}_k,\dots,\bar{u}_j)}(\omega) \right),$$

where $\left(y_r^{k,x,(\bar{u}_k,...,\bar{u}_j)}\right)_{r=k}^{j+1}$ satisfies the first equation in (4) for $\bar{u}_k,...,\bar{u}_j$, and $y_k^{k,x,(\bar{u}_k,...,\bar{u}_j)} = x$. Since the function u_{j+1} is measurable and bounded, and $y_{j+1}^{k,x,(\bar{u}_k,...,\bar{u}_j)}$ is measurable with respect to \mathcal{F}_{j+1}^k , we obtain that $\bar{u} = (\bar{u}_k,...,\bar{u}_{N-1}) \in \mathcal{U}_k^h$. Using the same ideas as in (69)-(70), and the assumption $V^j \equiv S^j$, for all $k < j \le N-1$, we get that

$$\begin{aligned} J_{k}^{h}(x,\bar{u}) &= h\ell(t_{k},x,\bar{u}_{k}) + \mathbb{E}\left[h\sum_{j=k+1}^{N-1}\ell(t_{j},y_{j}^{k,x,\bar{u}},u_{j}(y_{j}^{k,x,\bar{u}})) + g(y_{N}^{k,x,\bar{u}})\right] \\ &= h\ell(t_{k},x,\bar{u}_{k}) + \mathbb{E}\left[h\sum_{j=k+1}^{N-1}\ell(t_{j},y_{j}^{k,x,\bar{u}},u_{j}(y_{j}^{k,x,\bar{u}})) + V^{N}(y_{N}^{k,x,\bar{u}})\right] \\ &\leq h\ell(t_{k},x,\bar{u}_{k}) + \mathbb{E}\left[h\sum_{j=k+1}^{N-2}\ell(t_{j},y_{j}^{k,x,\bar{u}},u_{j}(y_{j}^{k,x,\bar{u}})) + S^{N-1}(y_{N-1}^{k,x,\bar{u}}) + \varepsilon\right] \\ &= h\ell(t_{k},x,\bar{u}_{k}) + \mathbb{E}\left[h\sum_{j=k+1}^{N-2}\ell(t_{j},y_{j}^{k,x,\bar{u}},u_{j}(y_{j}^{k,x,\bar{u}})) + V^{N-1}(y_{N-1}^{k,x,\bar{u}}) + \varepsilon\right] \\ &\leq h\ell(t_{k},x,\bar{u}_{k}) + \mathbb{E}\left[V^{k+1}(y_{k+1}^{k,x,\bar{u}})\right] + (N-1)\varepsilon \\ &\leq S^{k}(x) + N\varepsilon. \end{aligned}$$

Where the inequality in the third line above is obtained by using (77). We conclude that,

(80)
$$V^k(x) \le J^h_k(x,\bar{u}) \le S^k(x) + N\varepsilon.$$

Since $\varepsilon > 0$ is arbitrary, we obtain

(81)
$$V^k(x) \le S^k(x)$$

Remark 4.6. If in the definition (40) of V^k , instead of minimizing over the set \mathcal{U}_k^h , we minimize over $\overline{\mathcal{U}}_k^h := \{u \in \prod_{j=k}^{N-1} L^2_{\mathcal{F}_j} : u_j \in U_{ad} \text{ a.e. } \forall j = k, \ldots, N-1\}$, we obtain the same function. Indeed, define

(82)
$$\bar{V}^k(x) := \inf_{u \in \bar{\mathcal{U}}_k^h} \mathbb{E}\left[h\sum_{j=k}^{N-1} \ell(t_k, y_j^{k, x, u}, u_j) + g(y_N^{k, x, u})\right].$$

Clearly we have $\bar{V}^k(x) \leq V^k(x)$, for all x and k. In order to prove the converse inequality, let $u = (u_k, ..., u_{N-1})$ be any control in $\bar{\mathcal{U}}_k^h$, then each u_j can be written as measurable function of $(\Delta W_r)_{r=0}^j$. Thus, for fixed $(\Delta \omega_r)_{r=0}^k \in \mathbb{R}^{m \times (k+1)}$, we can define the functions

(83)
$$\hat{u}_j((\Delta\omega_r)_{r=0}^k) : \omega \in \Omega \mapsto u_j((\Delta\omega_r)_{r=0}^k, (\Delta W_r(\omega))_{r=k+1}^j),$$

obtaining $\hat{u}((\Delta\omega_r)_{r=0}^k) := (\hat{u}_k((\Delta\omega_r)_{r=0}^k), \dots, \hat{u}_{N-1}((\Delta\omega_r)_{r=0}^k)) \in \mathcal{U}_k^h$. By the definition of $y_j^{k,x,u}$ it is clear that for fixed $(\Delta\omega_r)_{r=0}^k$ we have that $y_j^{k,x,\hat{u}((\Delta\omega_r)_{r=0}^k)}$ is \mathcal{F}_j^k -measurable, and so (84)

$$\mathbb{E}\left[h\sum_{j=k}^{N-1}\ell(t_{k}, y_{j}^{k,x,u}, u_{j}) + g(y_{N}^{k,x,u})\right] = \int_{\mathbb{R}^{m\times(k+1)}} \mathbb{E}\left[\sum_{j=k}^{N-1}\ell(t_{k}, y_{j}^{k,x,\hat{u}((\Delta\omega_{r})_{r=0}^{k})}, \hat{u}_{j}((\Delta\omega_{r})_{r=0}^{k})) + g(y_{N}^{k,x,\hat{u}((\Delta\omega_{r})_{r=0}^{k})}(\omega))\right] d\mathbb{P}_{(\Delta W_{r})_{r=0}^{k}}((\Delta\omega_{r})_{r=0}^{k}) \\ \geq \int_{\mathbb{R}^{m\times(k+1)}} V^{k}(x) d\mathbb{P}_{(\Delta W_{r})_{r=0}^{k}}((\Delta\omega_{r})_{r=0}^{k}) = V^{k}(x).$$

Now, minimizing in the l.h.s we obtain $\overline{V}^k(x) \ge V^k(x)$.

Remark 4.7. Now we analyse the cases where instead of dealing with \mathcal{F}_j and \mathcal{F}_j^k , for j = k, ..., N, we consider \mathcal{F}_{t_j} or $\mathcal{F}_{t_j}^{t_k}$, which are the completion of $\sigma(W(t) : 0 \le t \le t_j)$ and $\sigma(W(t) - W(t_k) : t_k \le t \le t_j)$, respectively. Arguing as in the previous remark, setting

(85)
$$\begin{cases} \bar{\mathcal{U}}_{k}^{1} := \{ u \in \Pi_{j=k}^{N-1} L_{\mathcal{F}_{t_{j}}}^{2} : u_{j} \in U_{ad}, \mathbb{P}-a.s. \ \forall j=k,\dots,N-1 \}, \\ \bar{\mathcal{U}}_{k}^{2} := \{ u \in \Pi_{j=k}^{N-1} L_{\mathcal{F}_{t_{j}}}^{2} : u_{j} \in U_{ad}, \mathbb{P}-a.s. \ \forall j=k,\dots,N-1 \}, \end{cases}$$

we get that

(86)
$$\inf_{u \in \bar{\mathcal{U}}_k^1} J_k^h(x, u) = \inf_{u \in \bar{\mathcal{U}}_k^2} J_k^h(x, u)$$

Also, all the results of the current section including the DDP, remain true if we deal with $\overline{\mathcal{U}}_k^2$ instead of \mathcal{U}_k^h . Indeed, the proofs are based in the fact that the processes are adapted to the given filtration and the increments of Brownian motions are independent. Let us denote,

(87)
$$\tilde{V}^k(x) = \inf_{u \in \bar{\mathcal{U}}^2_k} J^h_k(x, u).$$

Since $\tilde{V}^N(x) = V^N(x) = g(x)$, and (\tilde{V}^k) and (V^k) satisfy (65), we can conclude that

(88)
$$\tilde{V}^k(x) = V^k(x), \quad \forall k = 0, ..., N.$$

4.3. Feedback optimal control. The aim of this section is to prove that there exists a feedback optimal control for (P^h) . For notational convenience we define for all $0 \le k \le N-1$, the function $F^k : \mathbb{R}^n \times U_{ad} \to \mathbb{R}$ as

(89)
$$F^{k}(x,u) := h\ell(t_{k},x,u) + \mathbb{E}\left[V^{k+1}(x+hf(t_{k},x,u)+\sigma(t_{k},x,u)\Delta W_{k+1})\right].$$

Then, by the DPP, for all $x \in \mathbb{R}^n$ and $k = 0, \dots, N - 1$, we have,

(90)
$$V^k(x) = \inf_{u \in U_{ad}} F^k(x, u) \quad \text{and} \quad V^N(x) = g(x).$$

Based on a measurable selection theorem due to Schäl [26, Theorem 5.3.1], we can prove the following result.

Proposition 4.8. Under the above assumptions, for all k = 0, ..., N-1 there exists a measurable function $\bar{u}^k : \mathbb{R}^n \to U_{ad}$ such that

(91)
$$F^k(x, \bar{u}^k(x)) = V^k(x),$$

for all $x \in \mathbb{R}^n$.

Proof. Arguing as in the proof of Lemma 4.3, it is easy to check that $(x, u) \mapsto F^k(x, u)$ is continuous. Since U_{ad} is compact we can apply [26, Theorem 5.3.1]. The result follows.

Remark 4.9. As a corollary of the previous results and the DPP, in this discrete framework, we always have a discrete time feedback (also called Markov) optimal control. Indeed, the sequence of measurable functions $\bar{u}_0, \ldots, \bar{u}_{N-1}$ given by the previous proposition, defines the optimal control $\bar{u} = (\bar{u}^0(y_0), \bar{u}^1(y_1), \ldots, \bar{u}^{N-1}(y_{N-1}))$, where (y_0, \ldots, y_N) is defined recursively as

(92)
$$\begin{cases} y_{k+1} = y_k + hf(t_k, y_k, \bar{u}^k(y_k)) + \sigma(t_k, y_k, \bar{u}^k(y_k)) \Delta W_{k+1} & \forall k = 0, \dots, N-1, \\ y_0 = x. \end{cases}$$

Let us point out an interesting phenomenon, not underlined enough in the literature, which shows the power of the DPP. In the continuous time case it is well known (see e.g. [10, Chapter VI] and [11, Chapters 3 and 4]) that if the Hamilton-Jacobi-Bellman equation associated with the stochastic control problem, which is a consequence of the DPP in continuous time, admits a solution v which is regular enough, then we can construct a feedback optimal control. This is known as a verification result and, under standard assumptions, usually holds when σ does not depend on u and, setting $a = \sigma \sigma^{\top}$, we have that

$$\sum_{1 \le i, j \le n} a_{i,j}(x,t) \xi_i \xi_j \ge c |\xi|^2 \quad \forall \ \xi \in \mathbb{R}^d,$$

for some c > 0. In particular, if we fix $(t, x) \in [0, T[\times \mathbb{R}^n, we get the existence of an optimal feedback policy for the problem associated with <math>V(t, x)$ (defined in (93) below). The main feature of this analysis is that existence of an optimum is obtained without some usual convexity assumptions required in the strong formulation (see e.g. [28, Chapter 2, Section 5.2]). On the other hand, as we have just seen, for the problem obtained by discretizing the time variable we always have the existence of a feedback control without any extra assumption. This is still an infinite dimensional problem for which existence does not follow by standard methods, but it is a consequence of the DPP.

5. Other regularity properties of the value function

In this section we analyse some properties of the value function of the continuous and the discrete problems. The value function of the continuous problem $V : [0, T] \times \mathbb{R}^n \to \mathbb{R}$ is defined as

(93)
$$V(s,x) := \inf_{u \in \mathcal{U}_{ad}^s} J^{s,x}(u) := \mathbb{E}\left[\int_s^T \ell(t, y_u^{s,x}(t), u(t)) dt + g(y_u^{s,x}(T))\right],$$

where $y_u^{s,x}$ is the solution of

(94)
$$\begin{cases} dy_u^{s,x}(t) &= f(t, y_u^{s,x}(t), u(t))dt + \sigma(t, y_u^{s,x}(t), u(t))dW(t), \quad t \in]s, T[x] \\ y_u^{s,x}(s) &= x, \end{cases}$$

and the control set is defined as (95)

 $\mathcal{U}_{ad}^{s} := \left\{ u \in L^{2}([s,T] \times \Omega) : u(t) \text{ is } \mathbb{F}^{s} \text{-adapted and } u(t,\omega) \in U_{ad}, \text{for a.a. } (t,\omega) \in [s,T] \times \Omega \right\},$ where $\mathbb{F}^{s} = \{\mathcal{F}_{t}^{s}\}_{t \in [s,T]}$ and \mathcal{F}_{t}^{s} is the completion of $\sigma(W(r) - W(s) : s \leq r \leq t)$ for $t \in [s,T]$.

In the following result we show the local (in space) Hölder continuity in time for V as well as an analogous result for its discrete version $\{V^k ; k = 0, ..., N\}$ defined in (40). The former result is classical, see e.g. [27, Section 3.4] and [28, Chapter 4, Proposition 3.1]). However, for the sake of completeness, we prove here a version adapted to our assumptions.

In the statement of the following result we use the r.h.s. of (40) (respectively (93)) to extend $J_k^h(x, \cdot)$ (respectively $J^{s,x}(\cdot)$) to \mathcal{U}_{ad}^h (respectively \mathcal{U}_{ad}).

Theorem 5.1. Under assumptions (H1) and (H2), there exists C > 0 (independent of h), such that for all $x \in \mathbb{R}^n$, $u \in \mathcal{U}_{ad}$ and $s, t \in [0, T]$,

(96)
$$|J^{s,x}(u) - J^{t,x}(u)| \le C[1+|x|^2]|s-t|^{\frac{1}{2}}$$

and for all $u \in \mathcal{U}_{ad}^h$ and $r, k = 0, \ldots, N$,

(97)
$$|J_r^h(x,u) - J_k^h(x,u)| \le C[1+|x|^2]|k-r|^{\frac{1}{2}}h^{\frac{1}{2}}.$$

As a consequence,

(98)
$$|V(s,x) - V(t,x)| \le C[1+|x|^2]|s-t|^{\frac{1}{2}} \quad \forall x \in \mathbb{R}^n, \ s,t \in [0,T],$$

and

(99)
$$|V^{r}(x) - V^{k}(x)| \le C[1 + |x|^{2}]|k - r|^{\frac{1}{2}}h^{\frac{1}{2}} \quad \forall x \in \mathbb{R}^{n}, \ r, k = 0, \dots, N.$$

Proof. First of all note that for all $s \in [0, T]$ and $x \in \mathbb{R}^n$, we have

(100)
$$V(s,x) = \inf_{u \in \mathcal{U}_{ad}} J^{s,x}(u).$$

Indeed, it is clear that $V(s, x) \geq \inf_{u \in \mathcal{U}_{ad}} J^{s,x}(u)$. On the other hand, if $u \in \mathcal{U}_{ad}$, then for all $s \leq t \leq T$ the function u(t) is \mathcal{F}_t -measurable, and so there exists measurable map $u_t((\omega_r)_{0 \leq r \leq s}, (\omega_r - \omega_s)_{s \leq r \leq t})$ such that $u(t, \omega) = u_t((W_r(\omega))_{0 \leq r \leq s}, (W_r(\omega) - W_s(\omega))_{s \leq r \leq t})$, \mathbb{P} -a.s. ([1]). Then if we fix $(\omega_r)_{0 \leq r \leq s}$ we can define the function

(101)
$$\hat{u}_t((\omega_r)_{0 \le r \le s}) : \omega \in \Omega \mapsto u_t((\omega_r)_{0 \le r \le s}, (W_r(\omega) - W_s(\omega))_{s \le r \le t}),$$

which belongs to \mathcal{F}_t^s . Again, by the independence of the increments of Brownian motions, and using the same ideas that in Remarks 4.6 and 4.7 we obtain the other inequality [5, Remark 5.2].

Without loss of generality, assume that $0 \le s \le t \le T$. We consider a fixed initial state x and a control $u \in \mathcal{U}_{ad}$. For simplicity we denote $y^s := y_u^{s,x}, y^t := y_u^{t,x}$ and for $t \le r \le T$, and $\varphi = f, \sigma$,

(102)
$$\Delta y(r) := y^s(r) - y^t(r) \text{ and } \Delta \varphi(r) = \varphi(r, y^s(r), u(r)) - \varphi(r, y^t(r), u(r)).$$

Then, we obtain for $t \leq r \leq T$

(103)
$$\Delta y(r) = \int_{s}^{t} f(\tau, y^{s}(\tau), u(\tau)) d\tau + \int_{s}^{t} \sigma(\tau, y^{s}(\tau), u(\tau)) dW(\tau) + \int_{t}^{r} \Delta f(\tau) d\tau + \int_{t}^{r} \Delta \sigma(\tau) dW(\tau).$$

By assumption (H1), the Cauchy-Schwarz inequality and the Itô isometry we have

(104)
$$\mathbb{E}\left[|\Delta y(r)|^2\right] \leq 4[|s-t|+1] \int_s^t 3L^2(1+\mathbb{E}[|y^s(\tau)|^2] + \mathbb{E}[|u(\tau)|^2]) d\tau +4[|s-t|+1] \int_t^r L^2 \mathbb{E}[|\Delta y(\tau)|^2] d\tau.$$

Since the set U_{ad} is compact, by the Grönwall lemma [8] and [22, Proposition 2.1] there exists $C_0 > 0$ such that

(105)
$$\sup_{t \le r \le T} \mathbb{E}\left[|\Delta y(r)|^2\right] \le C_0 \left[1 + |x|^2\right] |s - t|$$

Now we compare $J^{s,x}(u)$ and $J^{t,x}(u)$, we denote $\Delta \ell(r) := \ell(r, y^s(r), u(r)) - \ell(r, y^t(r), u(r))$ and $\Delta g = g(y^s(T)) - g(y^t(T))$. We have

(106)
$$|J^{s,x}(u) - J^{t,x}(u)| \leq \mathbb{E} \int_s^t |\ell(r, y^s(r), u(r))| \mathrm{d}r + \mathbb{E} \int_t^T |\Delta \ell(r)| \mathrm{d}r + \mathbb{E} |\Delta g|.$$

By assumption (H2) we obtain,

(107)
$$\mathbb{E}\int_{s}^{t} |\ell(r, y^{s}(r), u(r))| \mathrm{d}r \leq 3L \int_{s}^{t} \left[\mathbb{E}[|y^{s}(r)|^{2}] + \mathbb{E}[|u(r)|^{2}] + 1\right] \mathrm{d}r,$$

and since U_{ad} is bounded, again by [22, Proposition 2.1] there exists $C_1 > 0$ such that

(108)
$$\mathbb{E}\int_{s}^{t} |\ell(r, y^{s}(r), u(r))| \mathrm{d}r \leq C_{1}[1 + |x|^{2}]|s - t|.$$

On the other hand, for the last two terms we obtain,

(109)

$$\mathbb{E}\left[|\Delta \ell(r)|\right] \leq \mathbb{E}\left[\int_{0}^{1}|\ell_{y}(r, y^{t}(r) + \xi \Delta y(r), u(r))\Delta y(r)|d\xi\right] \\
\leq \mathbb{E}\left[\int_{0}^{1}[L(1 + |y^{t}(r)| + \xi |\Delta y(r)| + |u(r)|)|\Delta y(r)|]d\xi\right] \\
\leq L\mathbb{E}\left[[1 + |y^{s}(r)| + |\Delta y(r)| + |u(r)|]|\Delta y(r)|\right].$$

By the Cauchy-Schwarz, [22, Proposition 2.1], the compactness of U_{ad} and (105), we deduce that there exists $C_2 > 0$ such that

(110)
$$\mathbb{E}\left[|\Delta \ell(r)|\right] \le C_2 \left[1 + |x|^2\right] |s - t|^{\frac{1}{2}}$$

An analogous estimate holds for Δg and so the result follows.

Now for the discrete value function by Remark 4.6 we have that for all $x \in \mathbb{R}^n$ and $k \in \{0, \ldots, N\}$,

(111)
$$V^{k}(x) = \inf_{u \in \mathcal{U}_{ad}^{h}} \mathbb{E} \left[h \sum_{j=k}^{N-1} \ell(t_{j}, y_{j}^{k, x, u}, u_{j}) + g(y_{N}^{k, x, u}) \right].$$

Let $u = (u_j) \in \mathcal{U}_{ad}^h$ be a given control and $r, k \in \{0, \dots, N-1\}$ such that r < k. Let us set (112) $\Delta y_j = y_j^{r,x,u} - y_j^{k,x,u}, \ \Delta \varphi_j = \varphi(t_j, y_j^{r,x,u}, u_j) - \varphi(t_j, y_j^{k,x,u}, u_j)$ and $\Delta g = g(y_N^{r,x,u}) - g(y_N^{k,x,u}),$ for $\varphi = f, \sigma, \ell$ and $j = k, \dots, N-1$. Then (113) $\Delta u_{ij} = \Delta u_{ij} + b \Delta f_i + \Delta \sigma \Delta W_{ij}$

(113)
$$\Delta y_{j+1} = \Delta y_j + h \Delta f_j + \Delta \sigma_j \Delta W_{j+1}.$$

Following the techniques in Section 3, there exists $C_3 > 0$ such that

(114)
$$\mathbb{E}\left[|\Delta y_{j+1}|^2\right] \le (1+C_3h)\mathbb{E}\left[|\Delta y_j|^2\right] \le e^{C_3T}\mathbb{E}\left[|\Delta y_k|^2\right].$$

By the definition, we have $y_k^{k,x,u} = x$, then

(115)
$$\Delta y_k = y_k^{r,x,u} - x = h \sum_{j=r}^{k-1} f(t_j, y_j^{r,x,u}, u_j) + \sum_{j=r}^{k-1} [\sigma(t_j, y_j^{r,x,u}, u_j) \Delta W_{j+1}]$$

Since U_{ad} is compact, by the independence of the increments of the Brownian motion and (H1), there exist $C_4 > 0$ and $C_5 > 0$ such that

(116)

$$\mathbb{E}\left[|\Delta y_{k}|^{2}\right] \leq C_{4}\left[h^{2}(k-r)\sum_{j=r}^{k-1}\mathbb{E}[|f(t_{j},y_{j}^{r,x,u},u_{j})|^{2}] + h\sum_{j=r}^{k-1}\mathbb{E}[|\sigma(t_{j},y_{j}^{r,x,u},u_{j})|^{2}]\right] \\
\leq C_{5}h|k-r|\left[1+\max_{j=r,\dots,k-1}\mathbb{E}[|y_{j}^{r,x,u}|^{2}]\right] \\
\leq C_{6}h|k-r|\left[1+|x|^{2}\right],$$

where the last inequality holds by Lemma 3.1. We have

(117)
$$|J_r^h(x,u) - J_k^h(x,u)| = \left| h \sum_{j=r}^{k-1} \mathbb{E}[\ell(t_j, y_j^{r,x,u}, u_j)] + h \sum_{j=k}^{N-1} \mathbb{E}[\Delta \ell_j] + \mathbb{E}[\Delta g] \right|,$$

and also,

(118)
$$|V^{r}(x) - V^{k}(x)| \leq \sup_{u \in \mathcal{U}_{ad}^{h}} |J_{r}^{h}(x,u) - J_{k}^{h}(x,u)|$$

By (H2), Lemma 3.1 and since U_{ad} is compact, there exists $C_7 > 0$ such that

(119)
$$h\left|\sum_{j=r}^{k-1} \mathbb{E}[\ell(t_j, y_j^{r, x, u}, u_j)]\right| \le h \sum_{j=r}^{k-1} L \mathbb{E}\left[1 + |y_j^{r, x, u}| + |u_j|\right]^2 \le h|k - r|C_7\left[1 + |x|^2\right].$$

On the other hand, as in (109), by Lemma 3.1 and (116), we obtain the existence of $C_8 > 0$ such that

(120)
$$\mathbb{E}\left[\Delta \ell_{j}\right] \leq C_{8}\left[1+|x|^{2}\right]h^{\frac{1}{2}}|k-r|^{\frac{1}{2}},$$

and a similar estimate holds for $\mathbb{E}[\Delta g]$. Therefore, combining (117)-(120) we get the result. \Box

Our aim now is study the semiconcavity of V and of its discrete version $\{V^k ; k = 0, ..., N\}$. Recall that $\varphi : \mathbb{R}^n \to \mathbb{R}$ is semi-concave with constant K > 0 if for all $\lambda \in [0, 1]$

(121)
$$\lambda\varphi(x) + (1-\lambda)\varphi(y) - \varphi(\lambda x + (1-\lambda)y) \le K\lambda(1-\lambda)|x-y|^2, \quad \forall x, y \in \mathbb{R}^n.$$

We will need the following additional assumptions:

(H3) There exists K > 0 such that g is semi-concave with constant K and ℓ is also semi-concave with constant K, uniformly in $[0, T] \times U_{ad}$, i.e. for all $y, \bar{y} \in \mathbb{R}^n$,

(122)
$$\lambda\ell(t,y,u) + (1-\lambda)\ell(t,\bar{y},u) - \ell(t,\lambda y + (1-\lambda)\bar{y},u) \le K\lambda(1-\lambda)|y-\bar{y}|^2, \quad \forall \lambda \in [0,1],$$

and

(123)
$$\lambda g(y) + (1-\lambda)g(\bar{y}) - g(\lambda y + (1-\lambda)\bar{y}) \le K\lambda(1-\lambda)|y-\bar{y}|^2, \quad \forall \lambda \in [0,1].$$

(H4) For $\varphi = f, \sigma$, and for almost all $t \in [0, T]$, the map $(y, u) \mapsto \varphi(t, y, u)$ is C^2 and there exists a constant L such that for all $y \in \mathbb{R}^n$ and $u \in U_{ad}$,

(124)
$$|\varphi_{yy}(t,y,u)| + |\varphi_{yu}(t,y,u)| + |\varphi_{uu}(t,y,u)| \le L.$$

Under these additional assumption we prove now a local version of (121) for V and $\{V^k; k = 0, \ldots, N\}$. The following proof is similar to [28, Proposition 4.5, p.187].

Theorem 5.2. Under assumptions **(H1)-(H4)**, the functions V and V^k are locally semi-concave, *i.e.* for all $\bar{x} \in \mathbb{R}^n$ and $\delta > 0$, there exists a constant $K_{\bar{x},\delta} > 0$ such that, for all $s \in [0,T]$, $k = 0, \ldots, N$ and for all $\lambda \in [0,1]$, we have

(125)
$$\lambda V(s,x) + (1-\lambda)V(s,\bar{x}) - V(s,\lambda x + (1-\lambda)\bar{x}) \le K_{\bar{x},\delta}\lambda(1-\lambda)|x-\bar{x}|^2, \quad \forall x \in B_{\delta}(\bar{x})$$

and

(126)
$$\lambda V^{k}(x) + (1-\lambda)V^{k}(\bar{x}) - V^{k}(\lambda x + (1-\lambda)\bar{x}) \le K_{\bar{x},\delta}\lambda(1-\lambda)|x-\bar{x}|^{2}, \quad \forall x \in B_{\delta}(\bar{x})$$

where $B_{\delta}(\bar{x}) := \{x \in \mathbb{R}^n : |x - \bar{x}| < \delta\}.$

Proof. Let $x, \bar{x} \in \mathbb{R}^n$ and $\lambda \in [0, 1]$, define $x^{\lambda} := \lambda x + (1 - \lambda)\bar{x}$. For any $\varepsilon > 0$, there exists $u_{\varepsilon} \in \mathcal{U}_{ad}^s$ such that

(127)
$$J^{s,x^{\lambda}}(u_{\varepsilon}) - \varepsilon < V(s,x^{\lambda}).$$

For notational convenience, we denote $y^{\xi}(t) = y^{s,\xi}_{u_{\varepsilon}}(t), \ \ell(y^{\xi}(t)) = \ell(t, y^{s,\xi}_{u_{\varepsilon}}(t), u_{\varepsilon}(t))$ and $g(y^{\xi}) = g(y^{s,\xi}_{u_{\varepsilon}}(T))$ for $\xi = x, \bar{x}, x^{\lambda}$. Then, we have

$$\lambda V(s,x) + (1-\lambda)V(s,\bar{x}) - V(s,x^{\lambda}) \leq \lambda J^{s,x}(u_{\varepsilon}) + (1-\lambda)J^{s,\bar{x}}(u_{\varepsilon}) - J^{s,x^{\lambda}}(u_{\varepsilon}) + \varepsilon$$

$$\leq \mathbb{E}\left[\int_{s}^{T} [\lambda\ell(y^{x}) + (1-\lambda)\ell(y^{\bar{x}}) - \ell(y^{x^{\lambda}})]dt\right]$$

$$+ \mathbb{E}\left[\lambda g(y^{x}) + (1-\lambda)g(y^{\bar{x}}) - g(y^{x^{\lambda}})\right] + \varepsilon.$$

By the semi-concavity assumption **(H3)** we obtain, (129)

$$\mathbb{E}\left[\int_{s}^{T} [\lambda\ell(y^{x}) + (1-\lambda)\ell(y^{\bar{x}}) - \ell(y^{x^{\lambda}})] dt\right] = \mathbb{E}\left[\int_{s}^{T} [\lambda\ell(y^{x}) + (1-\lambda)\ell(y^{\bar{x}}) - \ell(\lambda y^{x} + (1-\lambda)y^{\bar{x}})] dt\right] \\ + \mathbb{E}\left[\int_{s}^{T} [\ell(\lambda y^{x} + (1-\lambda)y^{\bar{x}}) - \ell(y^{x^{\lambda}})] dt\right] \\ \leq K\lambda(1-\lambda)T\mathbb{E}\left[\sup_{t\in[s,T]} |y^{x}(t) - y^{\bar{x}}(t)|^{2}\right] \\ + \mathbb{E}\left[\int_{s}^{T} [\ell(\lambda y^{x} + (1-\lambda)y^{\bar{x}}) - \ell(y^{x^{\lambda}})] dt\right].$$

By [22, Proposition 2.1], there exists C_0 such that

(130)
$$\mathbb{E}\left[\sup_{t\in[s,T]}|y^{x}(t)-y^{\bar{x}}(t)|^{2}\right] \leq C_{0}|x-\bar{x}|^{2}$$

Now, define $\Delta y(t) := \lambda y^x(t) + (1-\lambda)y^{\bar{x}}(t) - y^{x^{\lambda}}(t)$ for all $t \in [s, T]$. By **(H2)**, and the compactness of U_{ad} , there exists $C_1 > 0$ such that,

(131)
$$\begin{aligned} |\ell(\lambda y^{x}(t) + (1-\lambda)y^{\bar{x}}(t)) - \ell(y^{x^{\lambda}}(t))| &\leq \int_{0}^{1} |\ell_{y}(y^{x^{\lambda}}(t) + \xi \Delta y(t))| |\Delta y(t)| d\xi \\ &\leq C_{1}[1 + |y^{x^{\lambda}}(t)| + |\Delta y(t)|] |\Delta y(t)|. \end{aligned}$$

We can obtain a similar estimate for g. By (H4), there exists $C_2 > 0$ such that

(132)
$$\mathbb{E}\left[\sup_{t\in s,T} |\Delta y(t)|^2\right] \le C_2 \lambda^2 (1-\lambda)^2 |x-\bar{x}|^4.$$

Now, returning to (131), by the Cauchy-Schwartz inequality, [22, Proposition 2.1] and the above equation, there exists $C_3 > 0$ such that

(133)

$$\mathbb{E}\left[|y^{x^{\lambda}}(t)||\Delta y(t)|\right] \leq (\mathbb{E}|y^{x^{\lambda}}(t)|^{2})^{\frac{1}{2}}(\mathbb{E}|\Delta y(t)|^{2})^{\frac{1}{2}} \\
\leq C_{3}\left[1+|x^{\lambda}|\right]\lambda(1-\lambda)|x-\bar{x}|^{2} \\
\leq C_{3}\left[1+|\bar{x}|+|x-\bar{x}|\right]\lambda(1-\lambda)|x-\bar{x}|^{2}$$

Since $|x - \bar{x}|^4 \leq \delta^2 |x - \bar{x}|^2$, for all $x \in B_{\delta}(\bar{x})$, combining (129)-(133), we can complete the proof of (125).

Now, for the discrete value, we follow similar arguments. There exists $u_{\varepsilon} \in \mathcal{U}_k^h$ such that

(134)
$$J_k^h(x^{\lambda}, u_{\varepsilon}) - \varepsilon \le V^k(x^{\lambda}).$$

Denoting
$$y_{j}^{\xi} = y_{j}^{k,\xi,u_{\varepsilon}}$$
 and $\ell(y_{j}^{\xi}) = \ell(t_{j}, y_{j}^{\xi}, u_{\varepsilon,j})$ for $\xi = x, \bar{x}, x^{\lambda}$ and $j = k, \dots, N$, we have
 $\lambda V^{k}(x) + (1-\lambda)V^{k}(\bar{x}) - V^{k}(x^{\lambda}) \leq \lambda J_{k}^{h}(x, u_{\varepsilon}) + (1-\lambda)J_{k}^{h}(\bar{x}, u_{\varepsilon}) - J_{k}^{h}(x^{\lambda}, u_{\varepsilon}) + \varepsilon$
(135)
$$\leq \mathbb{E} \left[h \sum_{j=k}^{N-1} [\lambda \ell(y_{j}^{x}) + (1-\lambda)\ell(y_{j}^{\bar{x}}) - \ell(y_{j}^{x^{\lambda}})] \right] + \mathbb{E} \left[\lambda g(y_{N}^{x}) + (1-\lambda)g(y_{N}^{\bar{x}}) - g(y_{N}^{x^{\lambda}}) \right] + \varepsilon.$$

As in (129), by the semi-concavity assumption **(H3)** we obtain, (136) $\mathbb{E}\left[h\sum^{N-1}[\lambda\ell(a^{x}) + (1-\lambda)\ell(a^{\bar{x}}) - \ell(a^{x^{\lambda}})]\right] \leq K\lambda(1-\lambda)T$

$$\mathbb{E}\left[h\sum_{j=k}^{N-1} [\lambda\ell(y_j^x) + (1-\lambda)\ell(y_j^{\bar{x}}) - \ell(y_j^{x^{\lambda}})]\right] \leq K\lambda(1-\lambda)T\max_{j=k,\dots,N} \mathbb{E}\left[|y_j^x - y_j^{\bar{x}}|^2\right] \\ + \mathbb{E}\left[h\sum_{j=k}^{N-1} [\ell(\lambda y_j^x + (1-\lambda)y_j^{\bar{x}}) - \ell(y_j^{x^{\lambda}})]\right].$$

By Lemma 4.1, there exists $C_0 > 0$ such that

(137)
$$\max_{j=k,\dots,N} \mathbb{E}\left[|y_j^x - y_j^{\bar{x}}|^2\right] \le C_0 |x - \bar{x}|^2.$$

In order to estimate the last term in (136) we set $\Delta y_j := \lambda y_j^x + (1-\lambda)y_j^{\bar{x}} - y_j^{x^{\lambda}}$. By **(H2)** and since U_{ad} is compact, there exists $C_1 > 0$ such that

(138)
$$\mathbb{E}\left[\ell(\lambda y_j^x + (1-\lambda)y_j^{\bar{x}}) - \ell(y_j^{x^{\lambda}})\right] \leq \mathbb{E}\left[\int_0^1 |\ell_y(y_j^{x^{\lambda}} + \xi \Delta y_j)||\Delta y_j|d\xi\right] \\ \leq C_1 \mathbb{E}\left[[1 + |y_j^{x^{\lambda}}| + |\Delta y_j|]|\Delta y_j|\right].$$

We have,

(139)

$$\begin{aligned} \Delta y_{j+1} &= \Delta y_j + h \left[f(\lambda y_j^x + (1-\lambda)y_j^{\bar{x}}) - f(y_j^{x^{\lambda}}) \right] + \left[\sigma(\lambda y_j^x + (1-\lambda)y_j^{\bar{x}}) - \sigma(y_j^{x^{\lambda}}) \right] \Delta W_{j+1}. \\ &+ h \left[\lambda f(y_j^x) + (1-\lambda)f(y_j^{\bar{x}}) - f(\lambda y_j^x + (1-\lambda)y_j^{\bar{x}}) \right] \\ &+ \left[\lambda \sigma(y_j^x) + (1-\lambda)\sigma(y_j^{\bar{x}}) - \sigma(\lambda y_j^x + (1-\lambda)y_j^{\bar{x}}) \right] \Delta W_{j+1}. \end{aligned}$$

By the Young's inequality and the Itô isometry, there exists $C_2 > 0$ such that,

(140)

$$\mathbb{E}\left[|\Delta y_{j+1}|^{2}\right] \leq \left[1 + C_{2}h\right]\mathbb{E}\left[|\Delta y_{j}|^{2}\right] + C_{2}h\mathbb{E}\left[|f(\lambda y_{j}^{x} + (1 - \lambda)y_{j}^{\bar{x}}) - f(y_{j}^{x^{\lambda}})|^{2}\right] \\
+ C_{2}h\mathbb{E}\left[|\sigma(\lambda y_{j}^{x} + (1 - \lambda)y_{j}^{\bar{x}}) - \sigma(y_{j}^{x^{\lambda}})|^{2}\right] \\
+ C_{2}h\mathbb{E}\left[|\lambda f(y_{j}^{x}) + (1 - \lambda)f(y_{j}^{\bar{x}}) - f(\lambda y_{j}^{x} + (1 - \lambda)y_{j}^{\bar{x}})|^{2}\right] \\
+ C_{2}h\mathbb{E}\left[|\lambda \sigma(y_{j}^{x}) + (1 - \lambda)\sigma(y_{j}^{\bar{x}}) - \sigma(\lambda y_{j}^{x} + (1 - \lambda)y_{j}^{\bar{x}})|^{2}\right].$$

By (H1), we obtain

(141)
$$\mathbb{E}\left[|f(\lambda y_{j}^{x} + (1-\lambda)y_{j}^{\bar{x}}) - f(y_{j}^{x^{\lambda}})|^{2}\right] + \mathbb{E}\left[|\sigma(\lambda y_{j}^{x} + (1-\lambda)y_{j}^{\bar{x}}) - \sigma(y_{j}^{x^{\lambda}})|^{2}\right] \leq 2L^{2}\mathbb{E}\left[|\Delta y_{j}|^{2}\right].$$

Now, for the last two terms in (140) we have,

(142)

$$\begin{aligned} |\lambda f(y_{j}^{x}) + (1-\lambda)f(y_{j}^{x}) - f(\lambda y_{j}^{x} + (1-\lambda)y_{j}^{x})| \\ &= |\lambda \int_{0}^{1} f_{y}(\lambda y_{j}^{x} + (1-\lambda)y_{j}^{\bar{x}} + \xi(1-\lambda)(y_{j}^{x} - y_{j}^{\bar{x}}))(1-\lambda)(y_{j}^{x} - y_{j}^{\bar{x}})d\xi \\ &+ (1-\lambda) \int_{0}^{1} f_{y}(\lambda y_{j}^{x} + (1-\lambda)y_{j}^{\bar{x}} + \xi\lambda(y_{j}^{\bar{x}} - y_{j}^{x}))\lambda(y_{j}^{\bar{x}} - y_{j}^{x})d\xi| \\ &\leq L\lambda(1-\lambda)|y_{j}^{x} - y_{j}^{\bar{x}}|^{2}, \end{aligned}$$

where the last inequality holds by (H4). Analogous estimates are satisfied by σ . By Lemma 4.1, we can conclude that there exists $C_3 > 0$ and $C_4 > 0$ such that,

(143)
$$\mathbb{E}\left[|\Delta y_{j+1}|^2\right] \leq [1+C_3h]\mathbb{E}\left[|\Delta y_j|^2\right] + C_4h\lambda^2(1-\lambda)^2|x-\bar{x}|^4.$$
$$\leq e^{C_3T}C_4\lambda^2(1-\lambda)^2|x-\bar{x}|^4.$$

By the Cauchy-Schwarz inequality, and the above inequality, there exists $C_5 > 0$ such that

(144)
$$\sup_{j=k,\dots,N} \mathbb{E}\left[|\Delta y_j|\right] \le C_5 \lambda (1-\lambda) |x-\bar{x}|^2$$

In order to estimate (138), by the Cauchy-Schwarz inequality, Lemma 3.1 and the previous bounds, there exists $C_6 > 0$ such that,

(145)

$$\mathbb{E}\left[|y_{j}^{x^{\lambda}}||\Delta y_{j}|\right] \leq (\mathbb{E}[|y_{j}^{x^{\lambda}}|^{2}])^{\frac{1}{2}}(\mathbb{E}|\Delta y_{j}|^{2})^{\frac{1}{2}} \\
\leq C_{6}[1+|x^{\lambda}|]\lambda(1-\lambda)|x-\bar{x}|^{2} \\
\leq C_{6}[1+|\bar{x}|+|x-\bar{x}|]\lambda(1-\lambda)|x-\bar{x}|^{2}.$$

Since $|x - \bar{x}|^4 \leq \delta^2 |x - \bar{x}|^2$, for all $x \in B_{\delta}(\bar{x})$, combining (138), (144) and (145), we deduce that there exists $C_{\bar{x},\delta} > 0$, which depends on \bar{x} and δ , such that

(146)
$$\mathbb{E}\left[h\sum_{j=k}^{N-1} [\lambda\ell(y_j^x) + (1-\lambda)\ell(y_j^{\bar{x}}) - \ell(y_j^{x^{\lambda}})]\right] \le C_{\bar{x},\delta}\lambda(1-\lambda)|x-\bar{x}|^2.$$

Similar estimates hold for the term involving g in (135), and then by (136), (137) and (146) we can conclude that (126) holds true.

Remark 5.3. If in addition to the above assumptions, we assume that the cost functionals ℓ and g are Lipschitz or f and σ are affine, then similar arguments as those in the previous proof (see [28, Proposition 4.5, p.187]) show that V and V^k satisfy (121) for some K (independent of h in the case of the discrete value function).

Now we can define for each $h = \frac{T}{N}$, the discrete value function, $V^h : [0,T] \times \mathbb{R}^n \to \mathbb{R}$ as a linear interpolation in time of the functions V^k , i.e.

(147)
$$V^{h}(t,x) := \alpha V^{k}(x) + (1-\alpha)V^{k+1}(x),$$

for $t = \alpha t_k + (1 - \alpha)t_{k+1}$, $\alpha \in [0, 1)$. Combining Theorem 5.1 and Theorem 5.2, we easily obtain the following result.

Theorem 5.4. Under assumptions (H1) and (H2), for each $h = \frac{T}{N}$ the discrete value function V^h is $\frac{1}{2}$ -Hölder continuous in time. If in addition, we assume that (H3) and (H4) hold, then V^h is locally semi-concave in the second variable.

Proof. Let $s, t \in [0, T]$ with s < t. There exist $k_s, k_t \in \{0, \ldots, N-1\}$ such that $s \in [t_{k_s}, t_{k_s+1})$ and $t \in [t_{k_t}, t_{k_t+1})$. Then, there exists $\alpha_i \in [0, 1)$, such that $i = \alpha_i t_{k_i} + (1 - \alpha_i) t_{k_i+1}$, for i = s, t. If $k_s = k_t$, by the definition of V^h we obtain, for all $x \in \mathbb{R}^n$,

$$\begin{aligned} (148) \\ |V^{h}(s,x) - V^{h}(t,x)| &\leq |\alpha_{s}V^{k_{s}}(x) + (1-\alpha_{s})V^{k_{s}+1}(x) - \alpha_{t}V^{k_{s}}(x) - (1-\alpha_{t})V^{k_{s}+1}(x)| \\ &\leq |\alpha_{s} - \alpha_{t}||V^{k_{s}}(x) - V^{k_{s}+1}(x)| \\ &\leq C[1+|x|^{2}]|\alpha_{s} - \alpha_{t}|h^{\frac{1}{2}}, \end{aligned}$$

where the last inequality holds by Theorem 5.1. Since $|s - t| = |\alpha_s - \alpha_t|h$ and $|\alpha_s - \alpha_t| < 1$, we deduce that

(149)
$$|V^{h}(s,x) - V^{h}(t,x)| \le C[1+|x|^{2}]|s-t|^{\frac{1}{2}}$$

Now, assume $k_s < k_t$. Then,

(150)
$$|s-t| = [\alpha_s + (k_t - k_s - 1) + (1 - \alpha_t)]h.$$

And again, by Theorem 5.1 we obtain, (151)

$$\begin{aligned} |V^{h}(s,x) - V^{h}(t,x)|^{2} &\leq 3 \left[|\alpha_{s}V^{k_{s}}(x) + (1-\alpha_{s})V^{k_{s}+1}(x) - V^{k_{s}+1}(x)|^{2} + |V^{k_{s}+1}(x) - V^{k_{t}}(s)|^{2} \right. \\ &\quad + |V^{k_{t}}(x) - \alpha_{t}V^{k_{t}}(x) + (1-\alpha_{t})V^{k_{t}+1}(x)|^{2} \right] \\ &\leq 3 \left[|\alpha_{s}|^{2}|V^{k_{s}}(x) - V^{k_{s}+1}(x)|^{2} + |V^{k_{s}+1}(x) - V^{k_{t}}(s)|^{2} \right. \\ &\quad + |1-\alpha_{t}|^{2}|V^{k_{t}}(x) - V^{k_{t}+1}(s)|^{2} \right] \\ &\leq 3C^{2} \left[1+|x|^{2} \right]^{2} \left[|\alpha_{s}|^{2}h + (k_{t}-k_{s}-1)h + |1-\alpha_{t}|^{2}h \right] \\ &\leq 3C^{2} \left[1+|x|^{2} \right]^{2} \left[\alpha_{s} + (k_{t}-k_{s}-1) + (1-\alpha_{t}) \right] h, \end{aligned}$$

where the last inequality holds since $\alpha_s, (1 - \alpha_t) \in [0, 1]$. Finally, by (149) and (151), for all $x \in \mathbb{R}^n$ and $s, t \in [0, T]$ we have

(152)
$$|V^{h}(s,x) - V^{h}(t,x)| \leq \sqrt{3}C[1+|x|^{2}]|s-t|^{\frac{1}{2}}.$$

Since the constant $K_{\bar{x},\delta}$ in Theorem 5.2 is independent of $k = 0, \ldots, N$, for $t = \alpha t_k + (1 - \alpha)t_{k+1}$, and for all $\lambda \in [0, 1]$, we have (153)

$$\begin{split} \lambda \dot{V}^{h}(t,x) + (1-\lambda)V^{h}(t,\bar{x}) - V^{h}(t,\lambda x + (1-\lambda)\bar{x}) \\ &= \alpha \left[\lambda V^{k}(x) + (1-\lambda)V^{k}(\bar{x}) - V^{k}(\lambda x + (1-\lambda)\bar{x}) \right] \\ &+ (1-\alpha) \left[\lambda V^{k+1}(x) + (1-\lambda)V^{k+1}(\bar{x}) - V^{k+1}(\lambda x + (1-\lambda)\bar{x}) \right] \\ &\leq K_{\bar{x},\delta}\lambda(1-\lambda)|x-\bar{x}|^{2}, \end{split}$$

for all $x \in B_{\delta}(\bar{x})$. The result follows.

6. Convergence

In this section we will analyse the relationship between the value of the discrete and the continuous problems. As the time step h tends to zero we will prove that V^h converges to V and also that any sequence of solutions of the discrete problems, extended as piecewise constant processes in [0, T], is a minimizing sequence for the continuous problem. In particular, we can take as minimizing sequence the one consisting on the discrete time feedback controls constructed in Proposition 4.8 and Remark 4.9. Finally, under some convexity assumptions, we can prove the weak convergence of the discrete optimal controls to a solution of the continuous problem.

Throughout this section we will assume that (H1)-(H2) hold and, as in the previous section, we suppose that U_{ad} is compact. We begin by providing an estimate of the difference between the cost

functions of the discrete and the continuous problems. In what follows, for any k = 0, ..., N - 1and $x \in \mathbb{R}^n$, we extend $J_k^h(x, \cdot)$ to $\prod_{i=0}^{N-1} L_{\mathcal{F}_{t_i}}^2$ using the same r.h.s. as in (39).

Lemma 6.1. Let $u^h \in \prod_{i=0}^{N-1} L^2_{\mathcal{F}_{t_i}}$ and define the control in \mathcal{U}_{ad} , still denoted by u^h , as $u^h(t) := u^h_k$ for all $t \in [t_k, t_{k+1})$. Then, for all $k = 0, \ldots, N-1$ there exists C > 0 independent of u^h and k such that

(154)
$$\left| J_k^h(x, u^h) - J^{t_k, x}(u^h) \right| \le C \left[|x|^2 + 1 \right] h^{\frac{1}{2}} + C\overline{\omega}(h).$$

Proof. For notational convenience we will assume that k = 0 and, since x is fixed, we denote $J^h(u^h) = J_0^h(x, u^h)$ and $J(u^h) = J^{0,x}(u^h)$. Let \tilde{y}^h be the continuous solution of the state equation with respect to the control u^h , and $y^h = (y_k^h)_{k=0}^N$ the discrete state associated with u^h . We have (155)

$$\left| J(u^{h}) - J^{h}(u^{h}) \right| \leq \left| \mathbb{E} \sum_{k=0}^{N-1} \int_{t_{k}}^{t_{k+1}} \left[\ell(t, \tilde{y}^{h}(t), u_{k}^{h}) - \ell(t_{k}, y_{k}^{h}, u_{k}^{h}) \right] \mathrm{d}t \right| + \left| \mathbb{E} \left[g(\tilde{y}^{h}(t_{N})) - g(y_{N}^{h}) \right] \right|,$$

and

(156)
$$\left| \mathbb{E} \int_{t_k}^{t_{k+1}} \left[\ell(t, \tilde{y}^h(t), u_k^h) - \ell(t_k, y_k^h, u_k^h) \right] \mathrm{d}t \right| \leq \mathbb{E} \left| \int_{t_k}^{t_{k+1}} \left[\ell(t, \tilde{y}^h(t), u_k^h) - \ell(t, y_k^h, u_k^h) \right] \mathrm{d}t \right| + \mathbb{E} \int_{t_k}^{t_{k+1}} \left| \ell(t, y_k^h, u_k^h) - \ell(t_k, y_k^h, u_k^h) \right| \mathrm{d}t.$$

By (H1), for the last term we obtain,

(157)
$$\mathbb{E}\int_{t_k}^{t_{k+1}} \left| \ell(t, y_k^h, u_k^h) - \ell(t_k, y_k^h, u_k^h) \right| \mathrm{d}t \le h\overline{\omega}(h)$$

and for the first one, by (H2) we have

(158)
$$\mathbb{E} \left| \int_{t_k}^{t_{k+1}} \left[\ell(t, \tilde{y}^h(t), u_k^h) - \ell(t, y_k^h, u_k^h) \right] dt \right|$$
$$\leq \mathbb{E} \int_{t_k}^{t_{k+1}} \int_0^1 \left| \ell_y(t, \tilde{y}^h(t) + s(y_k^h - \tilde{y}^h(t)), u_k^h) \right| \left| \tilde{y}^h(t) - y_k^h \right| ds dt$$
$$\leq \mathbb{E} \int_{t_k}^{t_{k+1}} L \left[\left[\left| \tilde{y}^h(t) \right| + \left| u_k^h \right| + 1 \right] \left| \tilde{y}^h(t) - y_k^h \right| + \left| \tilde{y}^h(t) - y_k^h \right|^2 \right] dt.$$

Since U_{ad} is compact, by the Cauchy-Schwarz inequality, [22, Proposition 2.1] and Corollary 3.3, there exists $C_0 > 0$ such that (159)

$$\int_{t_k}^{(100)} \mathbb{E}[|\tilde{y}^h(t)||\tilde{y}^h(t) - y^h_k|] \mathrm{d}t \le \int_{t_k}^{t_{k+1}} [\mathbb{E}[|\tilde{y}^h(t)|^2]]^{\frac{1}{2}} [\mathbb{E}[|\tilde{y}^h(t) - y^h_k|^2]]^{\frac{1}{2}} \mathrm{d}t \le C_0[|x|^2 + 1]h^{\frac{3}{2}} + C_0h\overline{\omega}(h),$$

and also (160)

$$\int_{t_k}^{t_{k+1}} \mathbb{E}[|u_k^h| |\tilde{y}^h(t) - y_k^h|] \mathrm{d}t \le \int_{t_k}^{t_{k+1}} [\mathbb{E}[|u_k^h|^2]]^{\frac{1}{2}} [\mathbb{E}[|\tilde{y}^h(t) - y_k^h|^2]]^{\frac{1}{2}} \mathrm{d}t \le C_0[|x|^2 + 1]h^{\frac{3}{2}} + C_0h\overline{\omega}(h).$$

By (158)-(160) and Corollary 3.3, there exists $C_1 > 0$ such that

(161)
$$\left| \mathbb{E} \int_{t_k}^{t_{k+1}} \left[\ell(t, \tilde{y}^h(t), u_k^h) - \ell(t, y_k^h, u_k^h) \right] \mathrm{d}t \right| \le C_1[|x|^2 + 1]h^{\frac{3}{2}} + C_1h\overline{\omega}(h).$$

Arguing as before we can prove that

(162)
$$\mathbb{E}\left[|g(\tilde{y}^{h}(t_{N})) - g(y_{N}^{h})|\right] \leq C_{1}\left[|x|^{2} + 1\right]h^{\frac{1}{2}} + C_{1}\overline{\omega}(h).$$

Then, we conclude that there exists C > 0 such that

(163)
$$\left| J(u^h) - J^h(u^h) \right| \le C \left[|x|^2 + 1 \right] h^{\frac{1}{2}} + C\overline{\omega}(h).$$

Consider a sequence $(N_j)_{j\in\mathbb{N}} \subset \mathbb{N}$ such that $N_j \to \infty$ as $j \to \infty$ and define $h_j = T/N_j$ and $t_k = kh_j$ $(k = 0, \ldots, N_j)$. Let $x \in \mathbb{R}^n$, $t \in (0, T]$ and $(\varepsilon_j)_{j\in\mathbb{N}}$ such that $\varepsilon_j \ge 0$ and $\lim_{j\to\infty} \varepsilon_j = 0$. Let $(\bar{u}^{h_j})_j$ be a sequence of ε_j -optimal controls for the discrete problems associated with $V^{k_j+1}(x)$, where $k_j \in \{0, \ldots, N_j - 1\}$ is such that $t \in (t_{k_j}, t_{k_{j+1}}]$. Let us define

(164)
$$\tilde{u}^{h_j}(s) = \begin{cases} \bar{u}^{h_j}_{k_j+1,} & s \in [t, t_{k_j+1}), \\ \bar{u}^{h_j}_m, & s \in [t_m, t_{m+1}), \\ m = k_j + 1, \cdots, N_j - 1. \end{cases}$$

In the case t = 0 we define $\tilde{u}^{h_j}(s) = \bar{u}^{h_j}_m$, for all $s \in [t_m, t_{m+1})$ and $m = 0, \dots, N_j - 1$, where \bar{u}^{h_j} is an ε_j -optimal control for the discrete problem associated with $V^0(x)$. Note that by definition $\tilde{u}^{h_j} \in \mathcal{U}^t_{ad}$. We point out that \tilde{u}^{h_j} depends on t, but for notational convenience we have omitted this dependence. Now we prove the main result of this section.

Theorem 6.2. Under the above notations we have

(165)
$$V(t,x) = \lim_{j \to \infty} V^{h_j}(t,x), \quad \forall \ (t,x) \in [0,T] \times \mathbb{R}^n,$$

where V^{h_j} was defined in (147) and

(166)
$$V(t,x) = \lim_{j \to \infty} J^{t,x}(\tilde{u}^{h_j}).$$

In addition, if $K \subset \mathbb{R}^n$ is a compact set, the sequence $(V^{h_j})_j$ converges uniformly to V on $[0,T] \times K$.

Proof. Let us first show the pointwise convergence in (165). Let $t \in [0,T]$ and $x \in \mathbb{R}^n$ be fixed. For each h_j , we consider the partition of [0,T] given by $\{t_0, t_1 \cdots, t_{N_j}\}$ where $t_k = kh_j$, for $k = 0, \cdots, N_j$. Thus, if $t \in (0,T]$ for all $j \in \mathbb{N}$ there exists k_j such that $t \in (t_{k_j}, t_{k_j+1}]$. If t = 0, we denote $t_{k_j+1} = 0$. Let ε be a positive number, then there exists an $\frac{\varepsilon}{2}$ -optimal control $\bar{u}_{\varepsilon} \in \mathcal{U}_{ad}^t$ such that

(167)
$$J^{t,x}(\bar{u}_{\varepsilon}) \le V(t,x) + \frac{\varepsilon}{2}$$

For all j large enough we have

(168)
$$J^{t_{k_j+1},x}(\bar{u}_{\varepsilon}) \le V(t_{k_j+1},x) + \varepsilon$$

Indeed, by (167) and Theorem 5.1 there exists $C_0 > 0$, independent of h_j , such that,

(169)
$$J^{t_{k_{j}+1},x}(\bar{u}_{\varepsilon}) = J^{t_{k_{j}+1},x}(\bar{u}_{\varepsilon}) - J^{t,x}(\bar{u}_{\varepsilon}) + J^{t,x}(\bar{u}_{\varepsilon})$$
$$\leq C_{0} \left[1 + |x|^{2}\right] h_{j}^{\frac{1}{2}} + V(t,x) + \frac{\varepsilon}{2}$$
$$\leq C_{0} \left[1 + |x|^{2}\right] 2h_{j}^{\frac{1}{2}} + V(t_{k_{j}+1},x) + \frac{\varepsilon}{2}$$

Let $(\varepsilon_j)_{j\in\mathbb{N}}$ be a decreasing sequence of positive numbers that converges to 0. Then, there exists an ε_j -optimal control, $\bar{u}^{h_j} \in \mathcal{U}_{k_j+1}^{h_j}$ for each $V^{h_j}(t_{k_j+1}, x)$, i.e.

(170)
$$V^{h_j}(t_{k_j+1}, x) \le J^{h_j}_{k_j+1}(x, \bar{u}^{h_j}) \le V^{h_j}(t_{k_j+1}, x) + \varepsilon_j$$

Since U_{ad} is compact, by a result of Krylov (see [17, Lemma 6, Section 3.2, p.143]), for any $\varepsilon' > 0$, there exists $N_{\varepsilon'}$ such that for all $j \ge N_{\varepsilon'}$ there exists $u^{h_j} \in \mathbb{H}^2_{\mathbb{F}}$ constant in each interval of the partition $\{t, t_{k_j+1}, ..., t_{N_j}\}$, such that

(171)
$$\|u^{h_j} - \bar{u}_{\varepsilon}\|_{\mathbb{H}^2_{\pi}} < \varepsilon'.$$

It is clear that $u^{h_j} = (u_t^{h_j}, u_{k_j+1}^{h_j}, \cdots, u_{N_j}^{h_j})$ belongs to $L^2_{\mathcal{F}_t} \times \prod_{i=k_j+1}^{N-1} L^2_{\mathcal{F}_{t_i}}$. We can define $\hat{u}^{h_j} = (u_{k_j+1}^{h_j}, \cdots, u_{N_j}^{h_j}) \in \prod_{i=k_j+1}^{N-1} L^2_{\mathcal{F}_{t_i}}$, then

(172)
$$|J^{t,x}(\bar{u}_{\varepsilon}) - J^{h_j}_{k_j+1}(x,\hat{u}^{h_j})| \leq |J^{t,x}(\bar{u}_{\varepsilon}) - J^{t,x}(u^{h_j})| + |J^{t,x}(u^{h_j}) - J^{t_{k_j+1},x}(\hat{u}^{h_j})| + |J^{t_{k_j+1},x}(\hat{u}^{h_j}) - J^{h_j}_{k_i+1}(x,\hat{u}^{h_j})|.$$

By (171) and the continuity of $J^{t,x}$ in \mathcal{U}_{ad} we deduce the first term in the r.h.s. goes to zero when j goes to infinity. By Theorem 5.1, and Lemma 6.1, there exists $C_1 > 0$ such that,

(173)
$$|J^{t,x}(u^{h_j}) - J^{t_{k_j+1},x}(\hat{u}^{h_j})| \le C_1[1+|x|^2]h_j^{\frac{1}{2}},$$

and

(174)
$$|J^{t_{k_j+1},x}(\hat{u}^{h_j}) - J^{h_j}_{k_j+1}(x,\hat{u}^{h_j})| \le C_1 \left[1 + |x|^2\right] \left[h^{\frac{1}{2}} + \overline{\omega}(h_j)\right].$$

Therefore, we can conclude that for j large enough we have,

(175)
$$|J^{t,x}(\bar{u}_{\varepsilon}) - J^{h_j}_{k_j+1}(x,\hat{u}^{h_j})| < \varepsilon.$$

As we saw in Remark 4.7, the value $V^{h_j}(t_{k_j+1}, x)$ is the same as if we minimize over the set of controls $\prod_{i=k_j+1}^{N_j-1} L^2_{\mathcal{F}_{t_i}}$ and, since \hat{u}^{h_j} belongs to this set, we have

(176)
$$V^{h_j}(t_{k_j+1}, x) \le J^{h_j}_{k_j+1}(x, \hat{u}^{h_j}) \le J^{t, x}(\bar{u}_{\varepsilon}) + \varepsilon \le V(t, x) + 2\varepsilon,$$

where in the last two inequalities we have used (175) and (167). On the other hand, Theorem 5.1 implies that there exists $C_2 > 0$ such that

(177)
$$V(t,x) \le C_2 \left[1 + |x|^2\right] h_j^{\frac{1}{2}} + V(t_{k_j+1},x).$$

Finally, Lemma 6.1 and (170) yield the existence of $C_3 > 0$ such that

(178)
$$V(t_{k_j+1}, x) \leq J^{t_{k_j+1}, x}(\bar{u}^{h_j}) \leq J^{h_j}_{k_j+1}(x, \bar{u}^{h_j}) + C_3 \left[[1+|x|^2] h_j^{\frac{1}{2}} + \overline{\omega}(h_j) \right] \\ \leq V^{h_j}(t_{k_j+1}, x) + \varepsilon_j + C_3 \left[[1+|x|^2] h_j^{\frac{1}{2}} + \overline{\omega}(h_j) \right].$$

Combining the last three inequalities and using Theorem 5.4, we get the existence of C > 0 such that for j large enough,

(179)
$$|V(t,x) - V^{h_j}(t,x)| \leq |V(t,x) - V^{h_j}(t_{k_j+1},x)| + |V^{h_j}(t_{k_j+1},x) - V^{h_j}(t,x)| \\ \leq \varepsilon_j + 2\varepsilon + C \left[[1 + |x|^2] h_j^{\frac{1}{2}} + \overline{\omega}(h_j) \right].$$

Letting $j \uparrow \infty$ and using that $\varepsilon > 0$ is arbitrary we obtain (165).

Now, let us prove (166). Combining Theorem 5.1 and Lemma 6.1, we get the existence of C > 0 such that

$$(180) | |J^{t,x}(\tilde{u}^{h_j}) - J^{h_j}_{k_j+1}(x, \bar{u}^{h_j})| \leq |J^{t,x}(\tilde{u}^{h_j}) - J^{t_{k_j+1},x}(\tilde{u}^{h_j})| + |J^{t_{k_j+1},x}(\bar{u}^{h_j}) - J^{h_j}_{k_j+1}(x, \bar{u}^{h_j})| \\ \leq C [1 + |x|] h_j^{\frac{1}{2}} + C\overline{\omega}(h_j).$$

By (178) and (165), we conclude

(181)
$$\lim_{j \to \infty} J^{t,x}(\tilde{u}^{h_j}) = \lim_{j \to \infty} J^{h_j}_{k_j+1}(x, \bar{u}^{h_j}) = V(t, x).$$

In order to prove the last assertion of the theorem, let $K \subset \mathbb{R}^n$ be a compact set. By Theorem 5.1 and Lemma 4.2, we deduce that the sequence $(V^{h_j})_j$ is uniformly bounded and uniformly equicontinuous on $[0, T] \times K$. Then, by the Ascoli-Arzelá theorem, and the pointwise convergence (165), we deduce that the sequence uniformly converges to V on $[0, T] \times K$.

Remark 6.3. Relation (166) shows that (\tilde{u}^{h_j}) is a minimizing sequence for the optimal control problem associated with V(t, x). In particular, we can take as (\tilde{u}^{h_j}) the sequence of discrete time feedback controls constructed in Remark 4.9.

The following result shows that under some convexity assumptions, we have convergence of (\tilde{u}^{h_j}) to an optimal solution of the continuous problem.

Corollary 6.4. Suppose in addition that U_{ad} is a convex set and $J^{t,x}$ is a convex functional. Then, there exists at least one weak limit point of (\tilde{u}^{h_j}) , and any limit point $u^* \in \mathcal{U}_{ad}^t$ satisfies,

(182)
$$J^{t,x}(u^*) = V(t,x).$$

If in addition, J is strongly convex, then the whole sequence $(\tilde{u}^{h_j})_{j\in\mathbb{N}}$ strongly converges to the unique $u \in \mathcal{U}_{ad}^t$ that verifies (182).

Proof. First, note that since U_{ad} is compact, the space \mathcal{U}_{ad}^t is bounded in $\mathbb{H}_{\mathbb{F}}^2$. Using that the convexity and continuity of $J^{t,x}$ imply its weak lower semi-continuity, classical arguments yield the existence of at least one optimal control \bar{u} for V(t,x).

Since \tilde{u}^{h_j} is a bounded sequence in $\mathbb{H}^2_{\mathbb{F}}$, there exists a subsequence (still denoted \tilde{u}^{h_j}) which converges weakly to $u^* \in \mathbb{H}^2_{\mathbb{F}}$. By the weak lower semi-continuity and equation (166) we have

(183)
$$J^{t,x}(u^*) \le \liminf_{j \to \infty} J^{t,x}(\tilde{u}^{h_j}) = V(t,x).$$

Finally, if $J^{t,x}$ is strongly convex, the strong convergence follows from the classical argument stating that a minimizing sequence of a strongly convex problem converge strongly to the unique optimizer of the problem (see e.g. [[4], Proof of Lemma 2.33(ii)]).

References

- C. Aliprantis and K. Border. Infinite dimensional analysis. A hitchhiker's guide. Springer, Berlin, third edition, 2006.
- [2] G. Barles and P. Souganidis. Convergence of approximation schemes for fully nonlinear second order equations. Asymptotic Analysis, 4:271–283, 1991.
- [3] D. P. Bertsekas and S. E. Shreve. Stochastic optimal control : the discrete time case. Academic Press New York, 1978.
- [4] J. F. Bonnans and A. Shapiro. Perturbation analysis of optimization problems. Springer Series in Operations Research. Springer-Verlag, New York, 2000.
- [5] B. Bouchard and N. Touzi. Weak dynamic programming principle for viscosity solutions. SIAM Journal on Control and Optimization, 49(3):948–962, 2011.
- [6] D. L. Burkholder, B. J. Davis, and R. F. Gundy. Integral inequalities for convex functions of operators on martingales. In Proceedings of the Sixth Berkeley Symposium on Mathematical Statistics and Probability, Volume 2: Probability Theory, pages 223–240, Berkeley, Calif., 1972. University of California Press.
- [7] N. Christopeit. Discrete approximation of continuous time stochastic control systems. SIAM Journal on Control and Optimization, 21(1):17–40, 1983.
- [8] D. S. Clark. Short proof of a discrete Gronwall inequality. Discrete Applied Mathematics, 16(3):279 281, 1987.
- [9] E. B. Dynkin and A. A. Yushkevich. Controlled Markov processes, volume 235 of Grundlehren der Mathematischen Wissenschaften [Fundamental Principles of Mathematical Sciences]. Springer-Verlag, Berlin-New York, 1979. Translated from the Russian original by J. M. Danskin and C. Holland.
- [10] W. H. Fleming and R. W. Rishel. Deterministic and stochastic optimal control. Springer-Verlag, Berlin-New York, 1975. Applications of Mathematics, No. 1.
- [11] W. H. Fleming and H. M. Soner. Controlled Markov processes and viscosity solutions, volume 25 of Applications of Mathematics (New York). Springer-Verlag, New York, 1993.
- [12] W. H. Fleming and H. M. Soner. Controlled Markov processes and viscosity solutions, volume 25 of Stochastic Modelling and Applied Probability. Springer, New York, second edition, 2006.
- [13] I. I. Gikhman and A. V. Skorohod. Controlled stochastic processes. Springer-Verlag, New York-Heidelberg, 1979. Translated from the Russian by Samuel Kotz.
- [14] N. Ikeda and S. Watanabe. Stochastic Differential Equations and Diffusion Processes. North Holland-Kodansha Publishing, 1981.
- [15] N. Krylov. Approximating value functions for controlled degenerate diffusion processes by using piece-wise constant policies. *Electron. J. Probab.*, 4:1–19, 1999.
- [16] N. V. Krylov. Mean value theorems for stochastic integrals. Ann. Probab., 29(1):385–410, 2001.
- [17] N. V. Krylov. Controlled diffusion processes, volume 14. Springer Science & Business Media, 2008.
- [18] H. Kushner. Probability methods for approximations in stochastic control and for elliptic equations. Academic Press, New York, 1977. Mathematics in Science and Engineering, Vol. 129.
- [19] P.-L. Lions. Optimal control of diffusion processes and Hamilton-Jacobi-Bellman equations. I. The dynamic programming principle and applications. Comm. Partial Differential Equations, 8(10):1101–1174, 1983.
- [20] P.-L. Lions. Optimal control of diffusion processes and Hamilton-Jacobi-Bellman equations. II. Viscosity solutions and uniqueness. Comm. Partial Differential Equations, 8(11):1229–1276, 1983.
- [21] P.-L. Lions. Optimal control of diffusion processes and Hamilton-Jacobi-Bellman equations. III. Regularity of the optimal cost function. In Nonlinear partial differential equations and their applications. Collège de France seminar, Vol. V (Paris, 1981/1982), volume 93 of Res. Notes in Math., pages 95–205. Pitman, Boston, MA, 1983.

- [22] L. Mou and J. Yong. A variational formula for stochastic controls and some applications. Pure Appl. Math. Q., 3(2, Special Issue: In honor of Leon Simon. Part 1):539–567, 2007.
- [23] M. Nisio. Stochastic control theory. Dynamic programming principle. 2nd ed. Tokyo: Springer, 2nd ed. edition, 2015.
- [24] L. Pontryagin, V. Boltyanskii, R. Gamkrelidze, and E. Mishchenko. The mathematical theory of optimal processes. Gordon & Breach Science Publishers, New York, 1986. Reprint of the 1962 English translation.
- [25] M. L. Puterman. Markov decision processes: discrete stochastic dynamic programming. Wiley Series in Probability and Mathematical Statistics: Applied Probability and Statistics. John Wiley & Sons, Inc., New York, 1994. A Wiley-Interscience Publication.
- [26] S. Srivastava. A Course on Borel Sets. Springer-Verlag New York, 1998.
- [27] N. Touzi. Optimal stochastic control, stochastic target problems, and backward SDE, volume 29 of Fields Institute Monographs. Springer, New York; Fields Institute for Research in Mathematical Sciences, Toronto, ON, 2013. With Chapter 13 by Angès Tourin.
- [28] J. Yong and X. Zhou. Stochastic controls, Hamiltonian systems and HJB equations. Springer-Verlag, New York, Berlin, 2000.
- [29] A. A. Yushkevich and R. Y. Chitashvili. Controlled random sequences and Markov chains. Russian Mathematical Surveys, 37(6):239, 1982.

CENTRE DE MATHÉMATIQUES APPLIQUÉES, ECOLE POLYTECHNIQUE, INRIA-SACLAY, CNRS, UNIVERSITÉ PARIS-SACLAY, 91128 PALAISEAU, FRANCE.

CIFASIS - CENTRO INTERNACIONAL FRANCO ARGENTINO DE CIENCIAS DE LA INFOR-MACIÓN Y DE SISTEMAS - CONICET - UNR - AMU, S2000EZP ROSARIO, ARGENTINA

INSTITUT DE RECHERCHE XLIM-DMI, UMR-CNRS 7252, FACULTÉ DES SCIENCES ET TECH-NIQUES, UNIVERSITÉ DE LIMOGES, 87060 LIMOGES, FRANCE