



**HAL**  
open science

# Feedback stabilization of homogeneous polynomial systems

Abderrahman Iggidr, Rachid Outbib

► **To cite this version:**

Abderrahman Iggidr, Rachid Outbib. Feedback stabilization of homogeneous polynomial systems. *Nonlinear Control Systems Design 1995*, Elsevier, pp.137–141, 1995, 10.1016/b978-0-08-042371-5.50028-9 . hal-01862879

**HAL Id: hal-01862879**

**<https://inria.hal.science/hal-01862879>**

Submitted on 30 Aug 2018

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# FEEDBACK STABILIZATION OF HOMOGENEOUS POLYNOMIAL SYSTEMS

A. IGGIDR\* and R. OUTBIB\*

\*INRIA Lorraine (CONGE Project) & University of Metz.  
4, rue Marconi, 57070 METZ - FRANCE.  
e-mail: {iggidr,outbib}@ilm.loria.fr

**Abstract.** The propose of this paper is to drive a simple necessary and sufficient stabilizability condition for a class of multi-inputs polynomial systems. This result represents a generalization of the main theorems of (Iggidr and Vivalda, 1992). The stabilizing feedbacks are explicitly given.

**Key Words.** Stabilization, feedback, dilations, homogeneous systems.

## 1. INTRODUCTION

The stabilization problem of nonlinear control systems by means of smooth feedback is one of the most important problem in control theory. It has attracted the interest of an increasing number of authors in the last decay. The local stabilizability of nonlinear systems has been extensively studied and a necessary and sufficient stabilizability condition for two-dimensional systems has been given in (Dayawansa *et al.*, 1990). However, the global problem, even for low dimensional systems, is still an open problem. Many interesting results have been published (Andreini *et al.*, 1988; Byrnes and Isidori, 1989; Jurdjevic and Quinn, 1978; Kokotovic and Sussmann, 1989; Saberi *et al.*, 1990; Sontag, 1989; Sontag, 1990; Seibert and Suarez, 1991) but they are, generally, difficult to apply for a given system because they are based on the construction of auxiliary functions such Lyapunov functions or Lyapunov control function. In this paper we solve, completely, the stabilization problem for the class of systems considered.

More precisely we consider a nonlinear control system

$$\begin{cases} \dot{x} = X(x) + Bu \\ x \in \mathbb{R}^n, u \in \mathbb{R}^{n-1} \end{cases} \quad (1)$$

where  $X$  is a polynomial vector field, which is homogeneous of degree  $k \in \mathbb{N}$  with respect to a family of dilations (see definition below) and  $B$  is an  $n \times (n - 1)$  matrix of rank  $n - 1$ . We shall say that (1) is globally smoothly asymptotically stabilizable (G.S.A.S) if there exists a smooth ( $C^\infty$ ) feedback such that  $u(0) = 0$  and the origin is a globally asymptotically stable equilibrium point

for the (closed-loop) system

$$\dot{x} = X(x) + Bu(x) \quad (2)$$

In this communication, we give a necessary and sufficient condition for (1) to be G.S.A.S and we construct explicitly the stabilizing feedback which turns to be also polynomial. This result is a generalization of (Iggidr and Vivalda, 1992) that concerns the case where  $X$  is homogeneous with respect to the standard dilation. We can remark that for this class of nonlinear control systems, the stabilizability by feedback is equivalent to the null controllability. Homogeneous systems are also considered in (Hermes, 1990; Hermes, 1991; Kawski, 1990; Kawski, 1989).

To illustrate the methodology developed in this article, we consider the following examples :

### Example 1

$$\begin{cases} \dot{x} = x^8 + x^6y - x^2y^3 - y^4 \\ \dot{y} = u \\ (x, y) \in \mathbb{R}^2, u \in \mathbb{R} \end{cases} \quad (3)$$

is G.S.A.S thanks to the feedback law

$$u(x, y) = x^2 + y + (x^4 + x^2y + 2y^2) \times (x^2 - y) (x + 2x^3 + 2xy)$$

One can remark that for this system the condition of (Boothby and Marino, 1989; Boothby, 1990) is not met so the result of Boothby-Marino (Boothby

and Marino, 1989; Boothby, 1990) can not be applied even to achieve the local stabilization.

### Example 2

$$\begin{cases} \dot{x} = x^6 + x^2y^2 + y^3 \\ \dot{y} = u \\ (x, y) \in \mathbb{R}^2, u \in \mathbb{R} \end{cases} \quad (4)$$

This system satisfies the condition of theorem 1 so it can be stabilized by the feedback law given in proposition 1.

### Example 3

$$\begin{cases} \dot{x} = x^6 + x^3y + y^2 \\ \dot{y} = u \\ (x, y) \in \mathbb{R}^2, u \in \mathbb{R} \end{cases} \quad (5)$$

is not stabilizable.

## 2. NOTATIONS AND PRELIMINARIES

In this paper,  $\langle x, y \rangle$  is the usual scalar product and for  $n-1$  vectors  $x_1, \dots, x_{n-1}$  of  $\mathbb{R}^n$ , we will denote by  $x_1 \wedge \dots \wedge x_{n-1}$  their vectorial product i.e. the unique vector satisfying  $\forall x \in \mathbb{R}^n$

$$\det(x_1, \dots, x_{n-1}, x) = \langle x_1 \wedge \dots \wedge x_{n-1}, x \rangle$$

Let  $b_2, \dots, b_n$  be the column vectors of B and define  $b_1 = b_2 \wedge \dots \wedge b_n$ . Since B is of rank  $n-1$ ,  $(b_1, b_2, \dots, b_n)$  is a basis of  $\mathbb{R}^n$ .

#### Families of dilations.

For positive integers  $r_1 \leq r_2 \leq \dots \leq r_n$  and for a given coordinates  $(x_1, \dots, x_n)$  on  $\mathbb{R}^n$ , a one-parameter family of dilations parametrized by  $\lambda \in \mathbb{R}$  is

$$\begin{aligned} \Delta_\lambda : \mathbb{R}^n &\rightarrow \mathbb{R}^n \\ (x_1, \dots, x_n) &\mapsto (\lambda^{r_1}x_1, \dots, \lambda^{r_n}x_n) \end{aligned}$$

A function  $\psi : \mathbb{R}^n \rightarrow \mathbb{R}$  is  $\Delta_\lambda$ -homogeneous of order  $k$  if  $\psi \circ \Delta_\lambda = \lambda^k \psi$ .

Throught this paper, we shall say that a vector field

$$X(x) = \sum_{i=1}^n X_i(x) \frac{\partial}{\partial x_i}$$

is  $\Delta_\lambda$ -homogeneous of order  $k$ , written  $X \in \mathcal{H}_k$ , if all its compenents  $X_i$  are homogeneous functions of degree  $k$  with respect to the same dilation.

In this paper, we consider only dilations for which  $r_1 = 1$ . A complete study for arbitrary integers  $r_1, \dots, r_n$  as well as the application to the local stabilization of analytic systems will be published in a forthcoming paper.

## 3. STABILIZATION OF ODD HOMOGENEOUS VECTOR FIELDS

*Theorem 1* The control system (1), where  $X$  is an odd homogeneous vector field, is G.S.A.S if and only if, the following assumption holds :

(a) there exists  $\alpha = (\alpha_2, \dots, \alpha_n)^T \in \mathbb{R}^{n-1}$  such that  $\langle X(b_1 + B\alpha), b_1 \rangle < 0$

*Proof:* Let  $(x_1, \dots, x_n)$  be the coordinates of  $x$  in the basis  $(b_1, b_2, \dots, b_n)$ . In this basis, the system (1) is given by :

$$\begin{cases} \dot{x}_1 = \langle X(x), b_1 \rangle = P_1(x) \\ \dot{x}_2 = P_2(x) + u_2 \\ \vdots \\ \dot{x}_n = P_n(x) + u_n \end{cases} \quad (6)$$

where  $P_i$  are homogeneous polynomial functions of degree  $k$ .

The condition (a) is sufficient, to prove this we establishe the following result

*Proposition 1* If (a) holds then the system (6) is G.S.A.S and the stabilizing feedback is given by :

$$\begin{aligned} u_i(x) &= \alpha_i x_1^{r_i-1} P_1(x) - x_1 g_i(x) \\ &\quad - (x_i - \alpha_i x_1^{r_i}) - P_i(x) \end{aligned} \quad (7)$$

for  $i \in \{2, \dots, n\}$ , where:

$$\begin{aligned} g_i(x) &= \int_0^1 \frac{\partial P_1}{\partial x_i}(x_1, tx_2 + (1-t)\alpha_2 x_1^{r_2}, \dots \\ &\quad \dots, tx_n + (1-t)\alpha_n x_1^{r_n}) dt \end{aligned} \quad (8)$$

*Proof:* Let

$$\begin{aligned} \varphi(t) &= P_1(x_1, tx_2 + (1-t)\alpha_2 x_1^{r_2}, \dots \\ &\quad \dots, tx_n + (1-t)\alpha_n x_1^{r_n}) \\ &= P_1(x_1, t(x_2 - \alpha_2 x_1^{r_2}) + \alpha_2 x_1^{r_2}, \dots \\ &\quad \dots, t(x_n - \alpha_n x_1^{r_n}) + \alpha_n x_1^{r_n}) \end{aligned}$$

we have:

$$\begin{aligned} \varphi(1) &= P_1(x_1, x_2, \dots, x_n) = P_1(x) \\ \varphi(0) &= P_1(x_1, \alpha_2 x_1^{r_2}, \dots, \alpha_n x_1^{r_n}) \\ \varphi(1) &= \varphi(0) + \int_0^1 \varphi'(t) dt \end{aligned}$$

So, we can write :

$$\begin{aligned} P_1(x_1, x_2, \dots, x_n) &= P_1(x_1, \alpha_2 x_1^{r_2}, \dots, \alpha_n x_1^{r_n}) \\ &\quad + \sum_{i=2}^n (x_i - \alpha_i x_1^{r_i}) g_i(x) \end{aligned}$$

Now, introduce the positive definite function :

$$V(x_1, x_2, \dots, x_n) = \frac{1}{2} \left( x_1^2 + \sum_{i=2}^n (x_i - \alpha_i x_1^{r_i})^2 \right)$$

the derivative of V along trajectories of (6-7) is

$$\begin{aligned} \dot{V} &= x_1 P_1(x) + \sum_{i=2}^n (x_i - \alpha_i x_1^{r_i}) \left( P_i(x) + u_i(x) - \alpha_i x_1^{r_i-1} P_1(x) \right) \\ &= x_1 P_1(x) - x_1 \sum_{i=2}^n (x_i - \alpha_i x_1^{r_i}) g_i(x) \\ &\quad - \sum_{i=2}^n (x_i - \alpha_i x_1^{r_i})^2 \\ &= x_1 P_1(x_1, \alpha_2 x_1^{r_2}, \dots, \alpha_n x_1^{r_n}) \\ &\quad - \sum_{i=2}^n (x_i - \alpha_i x_1^{r_i})^2 \\ &= x_1^{k+1} P_1(1, \alpha_2, \dots, \alpha_n) \\ &\quad - \sum_{i=2}^n (x_i - \alpha_i x_1^{r_i})^2 \end{aligned}$$

(where  $k$  is the degree of  $P_1$ ,  $k$  is odd). So,  $\dot{V}(x) < 0$  for all nonzero  $x$  and global stability is assured and this completes the proof of the proposition.

Let us prove that (a) is a necessary condition for the existence of a stabilizing feedback.

Suppose that  $P_1(1, x_2, \dots, x_n) \geq 0$  for any  $(x_2, \dots, x_n) \in \mathbb{R}^{n-1}$  then for any  $x_1$  positive and any  $(x_2, \dots, x_n) \in \mathbb{R}^{n-1}$  :

$$P_1(x_1, x_2, \dots, x_n) = x_1^k P_1 \left( 1, \frac{x_2}{x_1^{r_2}}, \dots, \frac{x_n}{x_1^{r_n}} \right) \geq 0$$

This shows the origin cannot be reachable from any point of the open half space  $\{x_1 > \alpha > 0\}$ . The proof of theorem 1 is now completed. ■

#### 4. STABILIZATION OF EVEN HOMOGENEOUS VECTOR FIELDS

*Theorem 2* The control system (1) is G.S.A.S if and only if the even homogeneous polynomial  $\langle X(x), b_1 \rangle$  takes both positive and negative values.

*Proof:*  $X$  is a homogeneous polynomial vector field of degree  $k = 2p \in \mathbb{N}^*$

Let  $(x_1, \dots, x_n)$  be the coordinates of  $x$  in the basis  $(b_1, b_2, \dots, b_n)$ . In this basis, the system (1)

is given by :

$$\begin{cases} \dot{x}_1 = \langle X(x), b_1 \rangle = P_1(x) \\ \dot{x}_2 = P_2(x) + u_2 \\ \vdots \\ \dot{x}_n = P_n(x) + u_n \end{cases} \quad (9)$$

where  $P_i$  are homogeneous polynomial functions of degree  $2p$ .

If  $P_1(x)$  does not change its sign, then the map  $f : \mathbb{R}^n \times \mathbb{R}^{n-1} \rightarrow \mathbb{R}^n$  defined by :

$$f(x, u) = \left( \langle X(x), b_1 \rangle, P_2(x) + u_2, \dots, P_n(x) + u_n \right)^T$$

cannot be onto an open neighborhood of the origin in  $\mathbb{R}^n$ , so (9) cannot be stabilizable by virtue of BROCKETT'S theorem (Brockett, 1983), moreover the origin cannot be reachable from any point of the half-space  $x_1 > \alpha > 0$  (or  $x_1 < \beta < 0$ ).

Now suppose that  $P_1(x)$  changes its sign, without loss of generality we can assume that  $P_1$  takes both positive and negative values in the plane  $(x_1, x_2)$  (if not one has to make first a linear change of coordinates, see (Iggidr and Vivalda, 1992)).

we can write

$$P_1(x) = Q(x_1, x_2) + R(x_1, \dots, x_n)$$

where

$$R(x) = \sum_{i=3}^n x_i R_i(x_1, \dots, x_n)$$

and

$$Q(x_1, x_2) = P_1(x_1, x_2, 0, \dots, 0)$$

are homogeneous of degree  $2p$ .

$Q(x_1, x_2)$  changes its sign, so it can be written :

$$Q(x_1, x_2) = L_1^{s_1} L_2^{s_2} \dots L_q^{s_q} \Phi(x_1, x_2)$$

where the polynomial functions  $L_i$  are of the form  $L_i = a_i x_1^{r_i} + b_i x_2$  and are linearly independant and  $\Phi(x_1, x_2)$  is a definite polynomial function.

At last, two exponents  $s_i$  are odd ( because  $Q(x_1, x_2)$  takes positive and negative values ); we can assume that  $i = 1$  and  $j = 2$ . Since  $L_1$  and  $L_2$  are linearly independant, we can suppose that  $L_1 = a_1 x_1^{r_2} + b_1 x_2$  with  $b_1 \neq 0$

Let us consider the following feedback :

$$\begin{cases} u_2(x) = -P_2(x) - \frac{1}{b_1} \left( a_1 r_2 x_1^{r_2-1} P_1(x) \right. \\ \quad \left. + x_1 L_2^{s_2} L_3^{s_3} \cdots L_q^{s_q} \Phi(x_1, x_2) + L_1^{s_1} \right) \\ u_3(x) = -x_3 - P_3(x) - x_1 R_3(x) \\ \vdots \\ u_n(x) = -x_n - P_n(x) - x_1 R_n(x) \end{cases} \quad (10)$$

and the function

$$V = \frac{1}{2} x_1^2 + \frac{1}{s_1 + 1} L_1^{s_1+1} + \frac{1}{2} x_3^2 + \cdots + \frac{1}{2} x_n^2$$

$V$  is smooth (polynomial), positive definite and proper.

Along the trajectories of the closed-loop system, one has

$$\dot{V} = \frac{dV(x(t))}{dt} = \langle \nabla V(x), X(x) \rangle$$

where  $X(x)$  is the closed-loop system with the feedback above(10)

$$\nabla V(x) = \begin{pmatrix} x_1 + r_2 a_1 x_1^{r_2-1} L_1^{s_1} \\ b_1 L_1^{s_1} \\ x_3 \\ \vdots \\ x_n \end{pmatrix}$$

$$\begin{aligned} \dot{V} &= (x_1 + r_2 a_1 x_1^{r_2-1} L_1^{s_1}) P_1(x) \\ &\quad + b_1 L_1^{s_1} (P_2(x) + u_2(x)) \\ &\quad + \sum_{i=3}^n x_i (P_i(x) + u_i(x)) \\ &= (x_1 + a_1 r_2 x_1^{r_2-1} L_1^{s_1}) P_1(x) \\ &\quad - L_1^{s_1} \left( a_1 r_2 x_1^{r_2-1} P_1(x) \right. \\ &\quad \left. + x_1 L_2^{s_2} L_3^{s_3} \cdots L_q^{s_q} \Phi(x_1, x_2) + L_1^{s_1} \right) \\ &\quad - \sum_{i=3}^n x_i^2 - x_1 \sum_{i=3}^n x_i R_i \\ &= x_1 P_1(x) \\ &\quad - L_1^{s_1} \left( x_1 L_2^{s_2} L_3^{s_3} \cdots L_q^{s_q} \Phi(x_1, x_2) \right) \\ &\quad - L_1^{2s_1} - \sum_{i=3}^n x_i^2 - x_1 \sum_{i=3}^n x_i R_i \\ &= x_1 P_1(x) - x_1 Q(x) - x_1 R(x) \\ &\quad - L_1^{2s_1} - \sum_{i=3}^n x_i^2 \end{aligned}$$

So

$$\dot{V} = -L_1^{2s_1} - \sum_{i=3}^n x_i^2 \leq 0 \quad (11)$$

If we let  $E = \{x \in \mathbb{R}^n / \dot{V}(x) = 0\}$  then by LASALLE'S invariance theorem ((Lasalle and Lefschetz, 1961), pp.66) all integral curves of the closed-loop system tend to the largest subset  $\Omega$  of  $E$  wich is invariant by the vector field corresponding to the closed-loop system, the proof will be finished if we show that  $\Omega = \{0\}$ .

We have

$$E = \{x \in \mathbb{R}^n \mid a_1 x_1^{r_2} + b_1 x_2 = 0, \\ x_3 = 0, \dots, x_n = 0\}$$

is a curve in  $\mathbb{R}^n$ . For  $x \in E$ , the closed-loop system is given by :

$$\begin{cases} \dot{x}_1 = 0 \\ \dot{x}_2 = -\frac{1}{b_1} x_1 L_2^{s_2} L_3^{s_3} \cdots L_q^{s_q} \Phi(x_1, x_2) \\ \dot{x}_3 = -x_1 R_3(x_1, x_2, 0, \dots, 0) \\ \vdots \\ \dot{x}_n = -x_1 R_n(x_1, x_2, 0, \dots, 0) \end{cases} \quad (12)$$

and it is easy to show that  $\Omega = \{0\}$ . Thus, the theorem is established.

## 5. REFERENCES

- Andreini, A., A. Bacciotti and G. Stefani (1988). Global stabilizability of homogeneous vector fields of odd degree. *Systems & Control Letters* **10**, 251–256.
- Boothby, W. and R. Marino (1989). Feedback stabilization of planar nonlinear systems. *Systems & Control Letters* **12**, 87–92.
- Boothby, W.M. (1990). Stabilization of planar single input systems by smooth feedback. In: *Colloque international sur l'analyse des systèmes contrôlés*. Lyon.
- Brockett, R.W. (1983). *Asymptotic stability and feedback stabilization*. pp. 181–191. Brockett, Milmann, Sussmann.
- Byrnes, C. and A. Isidori (1989). New results and examples in nonlinear feedback stabilization. *Systems & Control Letters* **12**, 437–442.
- Dayawansa, W.P., C.F. Martin and G. Knowles (1990). Asymptotic stabilization of a class of smooth two-dimensional systems. *SIAM J. Control and Optimization* **28**, 1321–1349.
- Hermes, H. (1990). Homogeneous coordinates and continuous stabilizing feedback controls. In: *Differential Equations. Stability and Control*. S. Elaydi.
- Hermes, H. (1991). Nilpotent and high-order approximations of vector field systems. *SIAM REVIEW* **33(2)**, 238–264.
- Iggidr, A. and J.C. Vivalda (1992). Global stabilization of homogeneous polynomial systems

- in  $\mathbb{R}^n$ . *Nonlinear Analysis TMA* **18(12)**, 1181–1186.
- Jurdjevic, V. and J.P. Quinn (1978). Controllability and stability. *Journal of Differential Equations* **28**, 381–389.
- Kawski, M. (1989). Homogeneous feedback laws in dimension three.. In: *the 28th IEEE C.D.C.*
- Kawski, M. (1990). Stabilization of nonlinear systems in the plane. *Systems & Control Letters* **12**, 169–175.
- Kokotovic, P.V. and H.J. Sussmann (1989). A positive real condition for global stabilization of nonlinear systems. *Systems & Control Letters* **13**, 125–133.
- Lasalle, J. and S. Lefschetz (1961). *Stability by Liapunov's direct method with applications*. Academic Press. New-York.
- Saberi, A., P.V. Kokotovic and H.J. Sussmann (1990). Global stabilization of partially linear composite systems. *SIAM J. Control and Optimization* **28**, 1491–1503.
- Seibert, P. and R. Suarez (1991). Global stabilization of a certain class of nonlinear systems. *Systems & Control Letters* **16**, 17–23.
- Sontag, E.D. (1989). A universal construction of arstein's theorem on nonlinear stabilization. *Systems & Control Letters* **13**, 117–123.
- Sontag, E.D. (1990). Feedback stabilization of nonlinear systems. In: *Robust Control of Linear Systems and Nonlinear Control* (Ran A.C.M Kaashoek M.A, van Schuppen J.H, Ed.). pp. 61–81. Birkhauser.