

# **Optimal bacterial resource allocation**

Agustin Gabriel Yabo, Jean-Baptiste Caillau, Jean-Luc Gouzé

# **To cite this version:**

Agustin Gabriel Yabo, Jean-Baptiste Caillau, Jean-Luc Gouzé. Optimal bacterial resource allocation. DCO 2021 - International Conference on Dynamic Control and Optimization, Feb 2021, Aveiro, Portugal.  $hal-03528000$ 

# **HAL Id: hal-03528000 <https://inria.hal.science/hal-03528000v1>**

Submitted on 17 Jan 2022

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# **Optimal bacterial resource allocation**

## **Jean-Baptiste Caillau** Université Côte d'Azur, CNRS, Inria, LJAD

Joint work with

## **Jean-Luc Gouzé** Inria

**Agustín Yabo** Université Côte d'Azur, Inria

## **Dynamic Control and Optimization**

Aveiro, February 2021



# **Honouring Andrey V. Sarychev's 65**

#### **Encounter first with the Portuguese team**



Geometric control summer school, Bedlewo (2003)

"Even if he falls asleep during a talk, he will ask THE good question!"

Then Trieste, Dijon, Moscow, Paris... (often with Bernard)

## **Two seminal papers (among many others)**

#### **Second order optimality conditions (smooth case)**

.<br>2. Martin USSR Sbornik (1989), Indian Math. USSR Sbornik (1987), No. 3<br>2. Mol. 41 (1987), No. 3

UDC <sup>5</sup>19.3

THE INDEX OF<br>THE SECOND VARIATION OF A CONTROL SYSTEM

A. V. <sup>S</sup>ARYCEV

ABSTRACT. The constancy of sign of the second variation of a nonlinear control system is<br>investigated. Sufficient conditions for controllability of second order and also sufficient investigated. Sufficient conditions for controllability of second court and also sufficient conditions for <sup>o</sup>ptimality wit<sup>h</sup> respec<sup>t</sup> to fast action of the <sup>e</sup>xtremals of <sup>t</sup>his system analogous to the <sup>L</sup>egendr<sup>e</sup> Jacobi conditions of the <sup>c</sup>lassical <sup>c</sup>alculus of variation are obtained. <sup>B</sup>ibliography: 6 <sup>t</sup>itles.

The paper is devoted to an investigation of controllability and optimality of nonlinear systems. <sup>T</sup>h<sup>e</sup> investigation of th<sup>e</sup> second variation of th<sup>e</sup> system gives <sup>e</sup>ssential informa <sup>t</sup>ion onth<sup>e</sup> behavior of a control system in a neighborhoo<sup>d</sup> of a given <sup>e</sup>xtremal. <sup>T</sup>h<sup>e</sup> Morse index is the most important invariant of the second variation. The second variation of a control system has previously been studied by many authors; we note, in particular, the papers [1] and [2]. In the present paper a modification of the concept of a conjugate point of an extremal is considered. The structure of the set of conjugate points is investigated depending on whether or not the given extremal satisfies a strong regularity condition. In both cases a constructive method of finding the set of conjugate points and a method for computing the Morse index of the second variation are given.

We consider the problem of fast action

$$
\begin{aligned}\n\dot{x} &= f(x, u), \\
x(0) &= 0, \quad x(T) = x_1, \\
T &\rightarrow \min. \n\end{aligned} \n\tag{3}
$$

Here the phase vector  $x \in \mathbb{R}^n$ , f is a vector field which is smooth (of class  $C^{\infty}$ ) in  $x$  and twice continuously differentiable with respect to the parameter  $u \in \mathbb{R}'$ , and the control  $u(\cdot)$  is a measurable, essentially bounded function,  $u(\cdot) \in L^*$ . We call the control  $u(\cdot)$ admissible for the system  $(1)$  - $(2)$  on the interval  $[0, T]$  if the solution of the equation

$$
x = f(x, u(t))
$$

 $x = f(x, u(t))$ <br>with initial condition  $x(0) = 0$  assumes the value  $x_1$  at time T. Let  $\hat{u}(\cdot)$  be an admissible control on [0, T] to be checked for optimality in problem (1)-(3). We rewrite the differential <sup>e</sup>quation (1) in th<sup>e</sup> form

> $\hat{x} = f(x, \hat{u}(t)) + (f(x, u) - f(x, \hat{u}(t))) = f_t(x) + \delta f_t(x, v).$ 383

19<sup>80</sup> <sup>M</sup>athematic<sup>s</sup> <sup>S</sup>ubjec<sup>t</sup> <sup>C</sup>lassification. Primary <sup>4</sup>9B10, 93BO5.

© 19<sup>82</sup> American Mathematical Society

Leads to numerically computable conjugacy conditions

## **Two seminal papers (among many others)**

#### **Second order optimality conditions (bang-bang case)**

SIAM J. CONTROL <sup>O</sup>PTIM. ∞c 1997 Society for Industrial and Applied Mathematics Vol. 35, No. 1, pp. 315–340, January 1997 018

#### FIRST- AND SECOND-ORDER SUFFICIENT OPTIMALITY CONDITIONS FOR BANG-BANG CONTROLS§

ANDREI V. SARYCHEV†<br>**Abstract**. We study L+-local optimality of a given control (i-) in the time-optimal control prob-Abstract. We study *L*1-local optimality of a given control ˜*u*(*·*) in the time-optimal control problem for an a±ne control system. We start with the necessary optimality condition—the Pontryagin maximum principle, which selects the candidates for minimizers, the extremal controls. Generally evitching points. In the present paper we treat only pure bang-bang extremals. We introduce ex systeming points. In the present paper we treat only pure tang-bang extremans. We introduce our<br>traded first and second variations along a bang-bang extremal and establish first- and second-order<br>sufficient optimality cond

Key words. optimal control problem, Pontryagin maximum principle, bang-bang extremals, sufficient optimality conditions

AMS subject classifications. 49K30, 93C10

PII. S0363012993246191

1. Introduction. We consider a nonlinear time-optimal control problem:

- (1.1)  $t \rightarrow \min$ ,
- (1.2)  $\dot{q} = f(q) + G(q)u(\tau), q(0) = q_0, q \in M, u \in U$

(1.3)  $q(t) = q_1$ ,

for an affine control system (1.2) with end-point condition (1.3) on a  $C^{\infty}$ -smooth *n*-dimensional manifold *M*. Here  $G(q) = (g^1(q), \ldots, g^r(q))$  and  $f(q), g^1(q), \ldots, g^r(q)$ are *C*1-smooth vector fields on *M*; admissible controls *u*(ø )=(*u*1(ø )*,...,ur*(ø )) are measurable and take their values in a convex compact polyhedron  $U \subset R'$ .

We set the problem of *L<sub>2</sub>*-local optimality according to the following definition. DEFINITION 1.1. *A pair*  $(ii(.)$ ,  $a(.)$ ) *meeting* (1.2)–(1.3) for  $t = T$  *is called L*  $locally$  *optimal if there exist*  $\Delta > 0$  and a  $ballU \supset \bar{u}(\cdot)$  in  $L^r_1[0,T]$  such that no admis*sible control from <i>U* can steer the system (1.2) *from*  $q_0$  to  $q_1$  in time  $T' \in [T - \Delta, T)$ .

A first-order optimality condition for the problem (1.1)–(1.3) is provided by the Pontryagin maximum principle (see [7]). If a pair  $(\hat{u}(\cdot), \hat{q}(\cdot))$  meets this principle for Powiryagen maximum principle (see [7]). It a pair  $(u(\cdot), q(\cdot))$  meets this principle for<br>some covector function (Hamiltonian multiplier)  $\zeta(\cdot)$ , then the triple  $(\tilde{u}(\cdot), \tilde{q}(\cdot), \tilde{\zeta}(\cdot))$ is called a *Pontryagin extremal* and ˜*u*(*·*) is called the *extremal control*. There can exist diÆerent Pontryagin extremals with diÆerent ˜≥(*·*) corresponding to the same extremal control ˜*u*(*·*).

In what follows we assume that the extremal control  $\hat{u}(\cdot)$  is a piecewise  $C^1\text{-smooth}$ function of  $\tau$ . Then due to the Pontryagin maximum principle the domain  $[0,T]$  of *u*<sup> $(i)$ </sup> can be subdivided into subintervals  $0 = \tau_0 < \tau_1 < \cdots < \tau_m < \tau_{m+1} = T$  in such way that for each  $\tau \in (\tau_i, \tau_{i+1})$  the maximality condition of the Pontryagin maximum principle is fulfilled on a *k*<sub>i</sub>-dimensional  $(k_i \geq 0)$  face *W<sub>i</sub>* of the polyhedron *U*. The

\*Received by the editors March 26, 1993; accepted for publication (in revised form) November 27, 1995. This reveals was supported in part by the A, von Humboldt Foundation. Germany. 27, 1995. This research was supported in part by the A. von Humboldt Foundation, Germany. A version of this paper was presented at the 35th IEEE Conference on Decision and Control, Kobe, Japan, December 11–13, 1996.

http://www.siam.org/journals/sicon/35-1/24619.html *†*Department of Mathematics, University of Aveiro, 3810, Aveiro, Portugal (ansar@mat.ua.pt).

Paved the way for further analysis (Poggiolini, Stefanni et al)

# **Model definition**

#### **Optimal control of microbial cells (ANR Maximic, PI H. de Jong)**



- $\triangleright$  Self-replicator model: biomass maximisation (Giordano et al'16)
- Genetic engineering of a strain of bacteria: light-induced control of growth
- New pathway to produce a metabolite of interest (Egorov et al'18)

 $\triangleright$  Competition between biomass maximisation and metabolite production Yabo, A.; Caillau, J.-B.; Gouzé, J.-L. Optimal bacterial resource allocation: metabolite production in continuous bioreactors. Math. Biosci. Eng. **17** (2020), no. 6, 7074–7100

## **Model definition**

**Self-replicator model**



The model represents three chemical macroreactions between substrate (S), precursors (P), genetic machinery/ribosomes (R), metabolic machinery (M) and produced metabolite (X):

$$
S \xrightarrow{V_M} P
$$
  
\n
$$
P \xrightarrow{V_R} \alpha R + (1-\alpha) M
$$
  
\n
$$
P \xrightarrow{V_X} X
$$

New control:  $u(t) := \alpha(t)I(t)$ 

## **Model definition**

#### **Continuous stirred-tank reactor dynamics**

In terms of concentrations s, p, r, x (and using  $m + r = 1$ ) in the CSTR,

$$
S_1: \left\{\begin{array}{l}\n\dot{s} = D(s_{in} - s) - v_M(s, 1 - r)\mathcal{V}, \\
\dot{p} = v_M(s, 1 - r) - v_X(p, 1 - r) - \mu(p, r)(p + 1), \\
\dot{r} = (u - r)\mu(p, r), \\
\dot{x} = v_X(p, 1 - r)\mathcal{V} - Dx, \\
\dot{\mathcal{V}} = (\mu(p, r) - D)\mathcal{V},\n\end{array}\right.
$$

where  $\mathscr V$  is the volume of the cell population, D is the dilution rate,  $s_{in}$  is the substrate inflow, and

$$
\mu(p,r):=\beta\,v_R(p,r)
$$

 $(\beta =$ inverse of cytoplasmic density) is the growth rate of the bacterial population.

**Assumption.** The synthesis rates  $v_M$ ,  $v_R$  and  $v_X$  are monotone increasing kinetics (e.g. Michaelis-Menten,  $v_R(p,r) := k_R rp/(K_R + p)$ ) and

$$
v_X(p,1-r)=c(r)v_R(p,r).
$$

**Mass conservation**

**Proposition.** The set

$$
\Gamma=\Big\{(s,\rho,r,x,\mathscr{V})\in\textbf{R}^5\,:\,s_\textit{in}\geq s\geq 0,\,\rho\geq 0,x\geq 0,1\geq r\geq 0,\,\mathscr{V}\geq 0\}
$$

is positively invariant for the initial value problem.

We assume  $\mathcal{V}(0) > 0$  and  $r(0) > 0$  (no growth otherwise).

**Proposition.** The  $\omega$ -limit set of any solution of system  $S_1$  with constant input  $u(t) = \overline{u}$  lies in the set

$$
\Omega:=\left\{(s,p,r,x,\mathscr{V})\in\mathbf{R}^5:s+\left(p+\frac{r}{\overline{u}}\right)\mathscr{V}+x=s_{in}\right\}.
$$

This result is used to define a limit system and reduce the dimension by two.

#### **Limiting system**

As  $r(t) \rightarrow \overline{u}$  when  $t \rightarrow \infty$  and since x can be eliminated  $(\Omega)$ , we define

$$
S'_1: \left\{\begin{array}{l} \dot{s} = D(s_{in}-s) - \overline{v}_M(s)\mathscr{V}, \\ \dot{p} = \overline{v}_M(s) - \overline{\mu}(\rho)(p+\overline{c}+1), \\ \dot{\mathscr{V}} = (\overline{\mu}(p)-D)\mathscr{V}, \end{array}\right.
$$

where

$$
\overline{v}_M(s) := v_M(s, 1 - \overline{u}), \quad \overline{v}_R(p) := v_R(p, \overline{u}), \quad \overline{v}_X(p) := v_X(p, 1 - \overline{u}), \overline{\mu}(p) := \mu(p, \overline{u}), \quad \overline{c} := c(\overline{u}).
$$

We study the local and global stability properties of this reduced system.

#### **Local stability**

#### **Theorem.** Define

$$
\overline{f}(p) := \overline{v}_R(p) + \overline{v}_X(p) + \overline{\mu}(p)p = \overline{\mu}(p)(p + \overline{c} + 1),
$$

and let  $p_w$  be the solution of  $\overline{f}(p) = \overline{v}_M(s_{in})$ . Then,

- If  $\overline{\mu}(p_w) > D$ :
	- $\blacktriangleright$  The interior equilibrium  $E_i$  exists, is unique and locally stable.
	- $\blacktriangleright$  The washout equilibrium  $E_w$  exists, is unique and locally unstable.
- If  $\overline{\mu}(p_w) < D$ :
	- $\blacktriangleright$  The interior equilibrium  $E_i$  does not exist.
	- The washout equilibrium  $E_w$  exists, is unique and locally stable.
- The interior equilibrium  $E_i := (s_i, p_i, \mathcal{V}_i)$  with

$$
\overline{\mu}(p_i) = D, \quad \overline{\nu}_M(s_i) = \overline{f}(p_i), \quad \gamma_i := \frac{D(s_{in} - s_i)}{\overline{\nu}_M(s_i)}.
$$

The washout equilibrium is  $E_w := (s_{in}, p_w, 0)$ .

**Sketch of proof.** If  $\overline{\mu}(p_w) \ge D$ ,

$$
J_i = \begin{bmatrix} -D - \overline{v}'_M(s) \mathscr{V}_i & 0 & -\overline{v}_M(s) \\ \overline{v}'_M(s) & \overline{f}'(p) & 0 \\ 0 & \overline{\mu}'(p) \mathscr{V}_i & 0 \end{bmatrix},
$$

and the characteristic polynomial is

$$
P_i(\lambda)=(\lambda+D)(\lambda^2+\lambda\underbrace{(D+\nabla_M(s)\mathscr{V}_i+(\rho+\overline{c}+1)\overline{\mu}'(\rho))}_{>0}+\underbrace{\overline{\nu}_M'(s)\mathscr{V}_i(\rho+\overline{c}+1)\overline{\mu}'(\rho))}_{>0}
$$

which, by Routh-Hurwitz criterion, implies that all eigenvalues have negative real part. If  $\overline{\mu}(p_w) < D$ ,

$$
J_w = \begin{bmatrix} -D & 0 & -\overline{c} \\ \overline{v}'_M(s) & -\overline{f}'(p) & 0 \\ 0 & 0 & \overline{\mu}(p_w) - D \end{bmatrix}
$$

with characteristic polynomial

$$
P_w(\lambda)=(\lambda+D)(\lambda+\overline{f}'(p))(\lambda-\overline{\mu}(p_w)+D). \quad \Box
$$

**Global analysis**

**Proposition.** The  $\omega$ -limit set of any solution of the limiting system  $S'_1$  lies in the set

$$
\Omega':=\left\{\left(\boldsymbol{\mathsf{s}},\boldsymbol{\mathsf{p}},\boldsymbol{\mathscr{V}}\right)\in\mathbf{R}^3\,:\,\boldsymbol{\mathsf{s}}+\left(\boldsymbol{\mathsf{p}}+\overline{\boldsymbol{\mathsf{c}}}+\boldsymbol{1}\right)\boldsymbol{\mathscr{V}}=\boldsymbol{\mathsf{s}}_{\mathsf{in}}\right\}
$$

As  $s = s_{in} - \mathcal{V}(p + \overline{c} + 1)$ , one can further reduce  $S'_1$  to

$$
S_1'' : \left\{ \begin{array}{l} \dot{p} = \overline{v}_M(s(\cdot)) - \overline{\mu}(p)(p + \overline{c} + 1), \\ \dot{\psi} = (\overline{\mu}(p) - D)\mathscr{V}. \end{array} \right.
$$

**Proposition.** Every solution of the limiting system  $S_1''$  converges to

 $\blacktriangleright E_i^* := (p_i, \mathcal{V}_i)$  if  $\overline{\mu}(p_w) \geq D$ ,  $\blacktriangleright E^*_w := (p_w, 0)$  if  $\overline{\mu}(p_w) < D$ .

**Sketch of proof.** Bendixson-Dulac criterion allows to discard periodic orbits and cycles of equilibria as

$$
\frac{\partial}{\partial \rho}\dot{\rho} + \frac{\partial}{\partial \mathscr{V}}\dot{\mathscr{V}} = \frac{\partial}{\partial \rho}\overline{v}_M(s(\cdot)) - \overline{\mu}(\rho) - \overline{\mu}'(\rho)(\rho + \overline{c} + 1) + \overline{\mu}(\rho) - D
$$

$$
= \overline{v}'_M(s(\cdot))\frac{\partial s(\cdot)}{\partial \rho} - \overline{\mu}'(\rho)(\rho + \overline{c} + 1) - D < 0. \quad \Box
$$



Results on asymptotically autonomous systems (Thieme'92) eventually allow to relate the asymptotic behaviour of the 2-dimensional limiting system  $S_1^{\prime\prime}$  to the behaviour of the full 5-dimensional system  $S_1$ .

**Theorem.** Every solution of system  $S_1$  converges to

ighthropoletic the extended interior equilibrium  $\hat{E}_i := (s_i, p_i, \overline{u}, x_i, \mathcal{V}_i), x_i := \overline{c} \mathcal{V}_i$ , if  $\overline{\mu}(p_w) \geq D$ ,

In the extended washout equilibrium  $\hat{E}_w := (s_{in}, p_w, \overline{u}, 0, 0)$  otherwise.

#### **Metabolite production**

Maximisation of the metabolite X is considered over a finite time horizon:

$$
\text{maximize } D \mathscr{V}_{\text{ext}} \int_0^T x(t) \, \mathrm{d}t,
$$

resorting to  $(q := (s, p, r, x, \mathscr{V}) \in \mathbb{R}^5)$ 

(OCP): 
$$
\begin{cases} \text{maximize} & \int_0^T x(t) dt \\ \text{subject to} & \dot{q}(t) = F(q(t), u(t)), \\ & q(0) = q_0, q(T) \text{ free}, \\ & u(t) \in [0, 1]. \end{cases}
$$

**Proposition.** Existence holds.

#### **Extremal flow**

We write the (normal) Hamiltonian in terms of state  $q := (s, p, r, x, \mathcal{V})$  and costate  $\lambda := (\lambda_s, \lambda_p, \lambda_r, \lambda_x, \lambda_y)$ :

$$
H(q,\lambda,u)=-\lambda^0x+\langle\lambda,F(q,u)\rangle,
$$

where F is the right-hand side of  $S_1$ . As the dynamics is control-affine,  $H = H_0 + uH_1$  with

$$
H_0 = \lambda_s (D(s_{in} - s) - v_M(s, 1 - r)\mathcal{V}) + \lambda_p \Big( v_M(s, 1 - r) - v_X(p, 1 - r) - \mu(p, r)(p + 1) \Big) - r\lambda_r \mu(p, r) + \lambda_x (v_X(p, 1 - r)\mathcal{V} - Dx) + \lambda_{\mathcal{V}} (\mu(p, r) - D)\mathcal{V} - \lambda^0 x, H_1 = \lambda_r \mu(p, r).
$$

By virtue of Pontrjagin's maximum principle, a.e. one has

$$
u(t) = \begin{cases} 0 & \text{if } H_1(q(t), \lambda(t)) < 0, \\ 1 & \text{if } H_1(q(t), \lambda(t)) > 0, \end{cases}
$$

and the control is singular if  $H_1$  vanishes along a whole subarc.

#### **Singular arcs**

Along a singular arc

$$
0=\dot{H}_1=\frac{\partial H_1}{\partial q}\dot{q}+\frac{\partial H_1}{\partial \lambda}\dot{\lambda}=\sum_{i=1}^n\left(\frac{\partial H}{\partial \lambda_i}\frac{\partial H_1}{\partial q_i}-\frac{\partial H}{\partial q_i}\frac{\partial H_1}{\partial \lambda_i}\right)=\{H,H_1\}=\{H_0,H_1\}:=H_{01}
$$

and

$$
0 = \dot{H}_{01} = H_{001} + uH_{101}.
$$

**Proposition.** Singular arcs are at least of order two.

$$
H_{101} = \mu(p,r) \left[ \lambda_r \mu_r(p,r) + \lambda_r \frac{\partial}{\partial r} \left( \mu_r(p,r) \dot{r} + \mu_p(p,r) \dot{p} \right) \right]
$$

$$
- \lambda_r \mu_r(p,r) \frac{\partial H_{01}}{\partial \lambda_r} - \lambda_r \mu_p(p,r) \frac{\partial H_{01}}{\partial \lambda_p}
$$

which is also equal to 0 when  $H_1 = 0$ .  $\Box$ 

In the case of an order two singular control  $(H_{10001} < 0$  along the arc, generalized Legendre-Clebsch condition)

$$
u=-\frac{H_{00001}}{H_{10001}}\cdot
$$

Although the order is local  $(H<sub>101</sub>$  is not everywhere zero), one expects connection between bang and singular arcs through Fuller phenomenon.



#### Fuller phenomenon

## Generalized Legendre-Clebsch condition



**Turnpike property**



A Lagrange pair  $(\overline{q},\overline{u},\overline{\lambda})$  of  $(SP)_X$  defines a hyperbolic equilibrium of the Hamiltonian singular flow on  $\Sigma'' := \{(q,\lambda) | H_1 = H_{01} = H_{001} = H_{00001} = 0\},\$ 

$$
H_{\sf s}(q,\lambda):=H(q,\lambda,u_{\sf s}(q,\lambda)),\quad u_{\sf s}(q,\lambda):=-\frac{H_{00001}}{H_{10001}}(q,\lambda).
$$

See Trélat-Zuazua'14, Pighin'16 in the regular case, ongoing work with S. Maslovskaya, W. Djema, J.-B. Pomet in the singular case

# **Static optimisation**

#### **Metabolite production vs. biomass maximisation**

Maximisation is now performed wrt. the static control  $\overline{u}$  plus the dilutation rate D of the CSTR:



**Proposition.** Any solution of the two static problems lies in the region of existence of the interior equilibrium,  $\overline{\mu}(p_w) > D$ .

# **Static optimisation**

## **Discussion**



- ▶ 20% decrease of biomass  $(V)$  but 500% increase of produced metabolite  $(X)$
- $\triangleright$  Difference between static and "gold standard" dynamic optimisation negligible for large fixed final time  $(< 1\%)$
- $\triangleright$  Richer models: ubiquity of Fuller and (singular) turnpike phenomena
- $\triangleright$  Second order conditions in the Fuller case: preliminary approach in Agrachev-Beschastnyi'2020
- Reproducible research:  $ct$  (= control toolbox) initiative [ct.gitlabpages.inria.fr/gallery](https://ct.gitlabpages.inria.fr/gallery/bacteria/bacteria.html)

# **Standing on the shoulders of giants**

**Revaz Valerianovich Gamkrelidze** (born February 4, 1927)

