

Centrohermitian solutions of a factorization problem arising in vibration analysis. Part I: Lee's transformation

Elisa Hubert, Yacine Bouzidi, Roudy Dagher, Alban Quadrat

▶ To cite this version:

Elisa Hubert, Yacine Bouzidi, Roudy Dagher, Alban Quadrat. Centrohermitian solutions of a factorization problem arising in vibration analysis. Part I: Lee's transformation. ECC 2021 - European Control Conference, Jun 2021, Delft (Virtual), Netherlands. 10.23919/ECC54610.2021.9655069 . hal-03530244

HAL Id: hal-03530244 https://inria.hal.science/hal-03530244

Submitted on 17 Jan2022

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Centrohermitian Solutions of a Factorization Problem Arising in Vibration Analysis. Part I: Lee's Transformation

Elisa Hubert¹, Yacine Bouzidi², Roudy Dagher³ and Alban Quadrat⁴

Abstract— Motivated by an application of vibration analysis to gearbox fault surveillance, a new demodulation approach for gearbox vibration signals has recently been developed. Within this approach, the demodulation problem yields the study of a rank factorization problem for centrohermitian matrices. In this paper, using the properties of centrohermitian matrices, we first show that the rank factorization problem for centrohermitian matrices can be transformed into a rank factorization problem for real matrices. Based on previous works, we then show how to parametrize a class of centrohermitian solutions of the rank factorization problem that is important in practice.

Notation. In what follows, let \Bbbk denote a field (e.g., $\Bbbk = \mathbb{Q}$, \mathbb{R} , \mathbb{C}), $\Bbbk^{n \times m}$ the \Bbbk -vector space formed by all the $n \times m$ matrices with entries in \Bbbk and I_n the identity matrix of $\Bbbk^{n \times n}$. We also denote by J_n the $n \times n$ exchange matrix, namely, the matrix formed by 1 on the second diagonal (i.e., the antidiagonal) and 0 elsewhere. If $\Bbbk = \mathbb{C}$, then \overline{M} (resp., M^*) denotes the *conjugate matrix* (resp., the *adjoint*, namely, the *conjugate transpose*) of M. Finally, if $M \in \Bbbk^{n \times m}$, then we can consider the following \Bbbk -linear maps

and denote their kernels (resp., images) respectively by $\ker_{\mathbb{k}}(M)$ and $\ker_{\mathbb{k}}(.M)$ (resp., $\operatorname{im}_{\mathbb{k}}(M)$) and $\operatorname{im}_{\mathbb{k}}(.M)$).

I. STATEMENT OF THE PROBLEM

We first introduce the concept of a *centrohermitian* matrix. Definition 1 ([12], [5]): A matrix $M \in \mathbb{C}^{n \times m}$ is called *centrohermitian* if $J_n \overline{M} J_m = M$. The set of all the centrohermitian matrices of $\mathbb{C}^{n \times m}$ is denoted by $CH_{n,m}$.

Using $J_1 = 1$, a vector $u \in \mathbb{C}^{n \times 1}$ (resp., $v \in \mathbb{C}^{1 \times m}$) is centrohermitian if $J_n \overline{u} = u$ (resp., $\overline{v} J_m = v$).

The next examples show that centrohermitian vectors and matrices naturally appear while considering Fourier analysis of real signals (e.g., gearbox vibration signals) [6], [7].

Example 1: If $s : \mathbb{R} \to \mathbb{R}$ is a *T*-periodic integrable function, then *s* can be expressed by its *Fourier series* [13]

$$\forall \ t \in \mathbb{R}, \quad s(t) = \sum_{j \in \mathbb{Z}} c_j(s) \ e^{\frac{2\pi i j t}{T}}$$

whose Fourier coefficients are defined by:

$$\forall j \in \mathbb{Z}, \quad c_j(s) = \frac{1}{T} \int_0^T s(t) e^{-\frac{2\pi i j t}{T}} dt.$$
 (1)

¹Elisa Hubert is with University of Lyon, UJM-St-Etienne, LASPI, 42334 Saint-Etienne, France elisa.hubert@wanadoo.fr

²Yacine Bouzidi bouzidi.yacine@gmail.com

 3Roudy Dagher is with Inria Lille - Nord Europe, 59650 Villeneuve d'Ascq, France <code>roudy.dagher@inria.fr</code>

⁴Alban Quadrat is with Inria Paris, Ouragan project, IMJ - PRG, Sorbonne University, 75252 Paris, France alban.quadrat@inria.fr

If $r \in \mathbb{Z} \setminus \{0\}$, then we can define the column vector

$$c = (c_r(s) \dots c_0(s) \dots c_{-r}(s))^T \in \mathbb{C}^{(2r+1) \times 1}$$

formed with the first Fourier coefficients $c_j(s)$ of s centered around 0. Since s is supposed to be real, using (1), we have

$$\forall j \in \mathbb{Z}, \quad \overline{c_j(s)} = c_{-j}(\overline{s}) = c_{-j}(s), \tag{2}$$

which shows that c is a centrohermitian column vector.

By Definition 1, a matrix M is centrohermitian if M is equal to the matrix obtained by reversing the rows and columns of \overline{M} . For instance, the following matrix

$$M = \begin{pmatrix} a & b & c \\ d & e & \overline{d} \\ \overline{c} & \overline{b} & \overline{a} \end{pmatrix},$$

where $a, b, c, d \in \mathbb{C}$ and $e \in \mathbb{R}$, is centrohermitian.

Example 2: We consider again Example 1. If we simply denote by c_j the j^{th} Fourier coefficient $c_j(s)$ of s and fix $p, q \in \mathbb{Z}_{>0}$, then we can form the following complex matrix

$$M = \begin{pmatrix} c_{q\,(2\,p+1)+p} & \dots & c_{p} & \dots & c_{-q\,(2\,p+1)+p} \\ \vdots & \vdots & & \vdots \\ c_{q\,(2\,p+1)} & \dots & c_{0} & \dots & c_{-q\,(2\,p+1)} \\ \vdots & & \vdots & & \vdots \\ c_{q\,(2\,p+1)-p} & \dots & c_{-p} & \dots & c_{-q\,(2\,p+1)-p} \end{pmatrix}$$

with the Fourier coefficients c_j for $0 \le |j| \le q (2p+1) + p$. Using (2), we can check that M is a centrohermitian matrix.

In [6], [7], it was shown that the *gearbox spectrum* can be represented by a centrohermitian matrix M and the problem of separating the time vibration signal into its main components amounts to estimating centrohermitian vectors u and v_1, \ldots, v_r that solve the following problem.

The centrohermitian rank factorization problem:

Let $D_1, \ldots, D_r \in CH_{n,n} \setminus \{0\}$ and $M \in CH_{n,m} \setminus \{0\}$. Determine – when they exist – vectors $u \in CH_{n,1}$ and $v_1, \ldots, v_r \in CH_{1,m}$ satisfying:

$$M = \sum_{i=1}^{r} D_i u v_i. \tag{3}$$

Remark 1: If a solution of (3) exists, then we have $M w = \sum_{i=1}^{r} D_i u(v_i w)$ for all $w \in \mathbb{k}^{m \times 1}$, which implies that $\operatorname{im}_{\mathbb{k}}(M) \subseteq \operatorname{span}_{\mathbb{k}}\{D_1 u, \ldots, D_r u\}$, and thus, we get:

 $\operatorname{rank}_{\Bbbk}(M) \leq \dim_{\Bbbk}(\operatorname{span}_{\Bbbk}\{D_1 \, u, \dots, D_r \, u\}) \leq \min\{r, n\}.$

The centrohermitian rank factorization problem can be generalized by considering general matrices M, D_1, \ldots, D_r and general vectors u and v_1, \ldots, v_r as follows.

The rank factorization problem:

Let $D_1, \ldots, D_r \in \mathbb{k}^{n \times n} \setminus \{0\}$ and $M \in \mathbb{k}^{n \times m} \setminus \{0\}$. Determine – when they exist – vectors $u \in \mathbb{k}^{n \times 1}$ and $v_1, \ldots, v_r \in \mathbb{k}^{1 \times m}$ satisfying (3).

The rank factorization problem was solved for r = 1 and $D_1 = I_n$ in [7], and for r = 2 and $D_1 = I_n$ in [8]. In [9], the problem was solved with the assumption that the row vectors v_i 's are k-linearly independent, i.e., that the matrix $v := (v_1^T \ldots v_r^T)^T$ has full row rank. In our application, the vector $v_i \in \mathbb{k}^{1 \times n}$ contains the first $(n/2)^{\text{th}}$ harmonics of a time signal (see Example 1). Hence, the assumption that v has full row rank means that the truncation of the underlying time signals at their first $(n/2)^{\text{th}}$ harmonics are k-linear independent. Based on *module theory* and *computer algebra*, local closed-form solutions were obtained in [10].

The goal of this paper is to show that the centrohermitian rank factorization problem can be reduced to the rank factorization for real matrices and real vectors. Hence, using the results obtained in [7], [9], [10], we can effectively solve the centrohermitian rank factorization problem when the row vectors v_i 's are supposed to be \mathbb{C} -linearly independent.

II. CENTROHERMITIAN MATRICES

If $M_1, M_2 \in \mathbb{C}^{t \times s}, m_1 \in \mathbb{C}^{t \times 1}, m_2 \in \mathbb{C}^{1 \times s}$ and $m_3 \in \mathbb{R}$, then we can check that a centrohermitian matrix $M \in \mathbb{C}^{n \times m}$ has one of the following 4 forms [12]:

1) If n = 2t and m = 2s, then:

$$M = \begin{pmatrix} M_1 & M_2 J_s \\ J_t \overline{M_2} & J_t \overline{M_1} J_s \end{pmatrix}.$$

2) If n = 2t and m = 2s + 1, then:

$$M = \begin{pmatrix} M_1 & m_1 & M_2 J_s \\ J_t \overline{M_2} & J_t \overline{m_1} & J_t \overline{M_1} J_s \end{pmatrix}$$

3) If n = 2t + 1 and m = 2s, then:

$$M = \begin{pmatrix} M_1 & M_2 J_s \\ m_2 & \overline{m_2} J_s \\ J_t \overline{M_2} & J_t \overline{M_1} J_s \end{pmatrix}.$$

4) If n = 2t + 1 and m = 2s + 1, then:

$$M = \begin{pmatrix} M_1 & m_1 & M_2 J_s \\ m_2 & m_3 & \overline{m_2} J_s \\ J_t \overline{M_2} & J_t \overline{m_1} & J_s \overline{M_1} J_s \end{pmatrix}.$$

We state again a few results on centrohermitian matrices. Clearly, if $M \in \mathbb{C}^{n \times m}$ is a centrohermitian matrix, so are:

$$\overline{M}, M^T, M^{\star}, J_n M, M J_m$$

Using $J_m^2 = I_m$, the product of two centrohermitian matrices $A \in \mathbb{C}^{n \times m}$ and $B \in \mathbb{C}^{m \times p}$ is then also centrohermitian:

$$A B = J_n \overline{A} J_m^2 \overline{B} J_p = J_n \overline{AB} J_p.$$

Hence, the set $CH_{n,n}$ of all the centrohermitian matrices of $\mathbb{C}^{n \times n}$ is stable under addition, multiplication by reals and multiplication, i.e., $CH_{n,n}$ has an \mathbb{R} -algebra structure. Finally, if $M \in CH_{n,n}$ is non-singular, then $M^{-1} \in CH_{n,n}$.

Theorem 1 ([5], [12]): If M is a centrohermitian, then so is its Moore-Penrose inverse M^+ .

In what follows, we state Lee's theorem [12] which explicitly characterizes $CH_{n,m}$. To do that, we first introduce a few more definitions and simple results.

Definition 2 ([12]): The matrix $Q \in \mathbb{C}^{n \times m}$ is called *J*-real if we have:

$$J_n \overline{Q} = Q.$$

Hence, Q is J-real iff its columns are centrohermitian. Example 3: The following complex matrices are J-real:

$$Q_{2t} = \frac{1}{\sqrt{2}} \begin{pmatrix} I_t & i I_t \\ J_t & -i J_t \end{pmatrix} \in \mathbb{C}^{2t \times 2t}, \quad Q_1 = 1,$$
$$Q_{2t+1} = \frac{1}{\sqrt{2}} \begin{pmatrix} I_t & 0 & i I_t \\ 0 & \sqrt{2} & 0 \\ J_t & 0 & -i J_t \end{pmatrix} \in \mathbb{C}^{(2t+1) \times (2t+1)}.$$

We note that both matrices Q_{2t} and Q_{2t+1} are also *unitary*:

$$Q_{2t}^{\star} Q_{2t} = Q_{2t} Q_{2t}^{\star} = I_{2t},$$
$$Q_{2t+1}^{\star} Q_{2t+1} = Q_{2t+1} Q_{2t+1}^{\star} = I_{2t+1}.$$

Let $U \in \mathbb{C}^{m \times m}$ and $V \in \mathbb{C}^{n \times n}$ be two non-singular *J*-real matrices. Using $J_m^2 = I_m$, then we have:

$$\overline{U} = J_m \left(J_m \,\overline{U} \right) = J_m \, U,$$
$$J_n \,\overline{V} = V \iff V^{-1} \, J_n \,\overline{V} = I_n \iff \overline{V^{-1}} = \overline{V}^{-1} = V^{-1} \, J_n$$

If $M \in CH_{n,m}$ and $\varphi(M) := V^{-1} M U$, then we have

$$\overline{\varphi(M)} = \overline{V^{-1}} \,\overline{M} \,\overline{U} = (V^{-1} \,J_n) \,(J_n \,M \,J_m) \,(J_m \,U)$$
$$= V^{-1} \,M \,U = \varphi(M),$$

which shows that $\varphi(M) \in \mathbb{R}^{n \times m}$, i.e., $\varphi(M)$ is a real matrix. Now, if $N \in \mathbb{R}^{n \times m}$, then we have

$$J_n \overline{(V N U^{-1})} J_m = J_n \overline{V} N \overline{U}^{-1} J_m = V N U^{-1},$$

which shows that $V N U^{-1}$ is a centrohermitian matrix.

These two results show the following important result.

Theorem 2 ([12]): Let $U \in \mathbb{C}^{m \times m}$ and $V \in \mathbb{C}^{n \times n}$ be two non-singular J-real matrices. Then, the \mathbb{R} -linear application

$$\begin{array}{cccc} \varphi : \mathbb{C}^{n \times m} & \longrightarrow & \mathbb{C}^{n \times m} \\ M & \longmapsto & V^{-1} M U, \end{array} \tag{4}$$

bijectively maps $CH_{n,m}$ onto $\mathbb{R}^{n \times m}$, i.e.:

- $\varphi(\operatorname{CH}_{n,m}) = \mathbb{R}^{n \times m}$,
- $\forall N \in \mathbb{R}^{n \times m}, \exists ! M \in CH_{n,m}(\mathbb{C}) : N = V^{-1} M U.$

Hence, $\operatorname{CH}_{n,m} = \varphi^{-1}(\mathbb{R}^{n \times m})$, i.e., $M \in \operatorname{CH}_{n,m}$ iff there exists a unique $N \in \mathbb{R}^{n \times m}$ such that $N = V^{-1} M U$.

Finally, if m = n, then φ isomorphically maps the ring $CH_{n,n}$ onto the ring $\mathbb{R}^{n \times n}$ and φ is a *ring automorphism*.

Example 4: Let Q_n (resp., Q_m) be defined as in Example 3. Then, $Q_n^{-1} = Q_n^*$ since Q_n is unitary. If $u \in \mathbb{C}^{n \times 1}$ is a centrohermitian column vector, i.e., $u \in CH_{n,1}$, then, by

Theorem 2, $u_{\varphi} := Q_n^{\star} u$ is a real vector, i.e., $u_{\varphi} \in \mathbb{R}^{n \times 1}$. Similarly, if $v_i \in CH_{1,m}$, then $v_{i,\varphi} := v_i Q_m \in \mathbb{R}^{1 \times m}$.

. .

Example 5: Let us consider the following matrix:

$$M = \begin{pmatrix} \frac{45}{2} + 5i & 10 - 15i & 15i & \frac{45}{2} + 10i \\ \frac{5}{2}\sqrt{2} - \frac{15}{2}\sqrt{2}i & 10\sqrt{2} & 10\sqrt{2} & \frac{5}{2}\sqrt{2} + \frac{15}{2}\sqrt{2}i \\ \frac{45}{2} - 10i & -15i & 10 + 15i & \frac{45}{2} - 5i \end{pmatrix}$$

Clearly, $M \in CH_{3,4}$. With the notations of Example 3, i.e.,

$$Q_{3} = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 0 & i \\ 0 & \sqrt{2} & 0 \\ 1 & 0 & -i \end{pmatrix},$$
$$Q_{4} = \frac{1}{\sqrt{2}} \begin{pmatrix} I_{2} & i I_{2} \\ J_{2} & -i J_{2} \end{pmatrix},$$

we then have $Q_3^{-1} = Q_3^{\star}$ and:

$$\varphi(M) = Q_3^{\star} M Q_4 = \begin{pmatrix}
45 & 10 & 5 & 30 \\
5 & 20 & 15 & 0 \\
15 & 0 & 0 & 10
\end{pmatrix} \in \mathbb{R}^{3 \times 4}.$$

Note that Theorem 2 yields $\dim_{\mathbb{R}}(CH_{n,m}) = n m$.

If λ is an eigenvalue of $M \in CH_{n,n}$ with as x an associated eigenvector, then $M x = \lambda x$ yields $\overline{M} \overline{x} = \overline{\lambda} \overline{x}$, and thus, $M(J_n \overline{x}) = \overline{\lambda} (J_n \overline{x})$, which shows that $\overline{\lambda}$ is also an eigenvalue of M with $J_n \overline{x}$ as an associated eigenvector.

Theorem 2 shows that a centrohermitian matrix is similar to a real matrix. Hence, the spectral theory of centrohermitian matrices corresponds to the one of real matrices.

Theorem 3 ([12]): If M is centrohermitian and λ is an eigenvalue of M of algebraic multiplicity k, then $\overline{\lambda}$ is an eigenvalue of M of algebraic multiplicity k. In particular, if $M \in CH_{n,n}$ with n odd, then M always has a real eigenvalue. The characteristic polynomial of $M \in CH_{n,n}$ has thus all real coefficients, and thus, $\det(M) \in \mathbb{R}$.

Example 6: Let us consider the centrohermitian matrix:

$$M = \begin{pmatrix} 9+18i & -225 & 9+198i \\ 0 & 0 & 0 \\ 9-198i & -225 & 9-18i \end{pmatrix} \in \mathbb{C}^{3\times 3}.$$

Let us consider the J-real matrix Q_3 defined in Example 5. Then, we have $Q_3^{-1} = Q_3^{\star}$ and:

$$\varphi(M) = Q_3^{\star} M Q_3 = \begin{pmatrix} 18 & -225\sqrt{2} & 180 \\ 0 & 0 & 0 \\ 216 & 0 & 0 \end{pmatrix} \in \mathbb{R}^{3 \times 3}.$$

The characteristic polynomial $p(\lambda) = \lambda (\lambda^2 - 18 \lambda - 38880)$ of *M* has real coefficients and det(*M*) = 0 $\in \mathbb{R}$.

Using Theorem 2, we obtain the following consequence.

Proposition 1 ([4]): Let $M \in CH_{n,m}$, $Q_m \in \mathbb{C}^{m \times m}$ and $Q_n \in \mathbb{C}^{n \times n}$ be two J-real and unitary matrices (e.g., as defined in Example 3), and $M_{\varphi} := Q_n^{\star} M Q_m \in \mathbb{R}^{n \times m}$. Let $M_{\varphi} = U_{\varphi} \Sigma V_{\varphi}^T$ be a Singular Value Decomposition (SVD) of M_{φ} , where $U_{\varphi} \in \mathbb{R}^{n \times n}$ and $V_{\varphi} \in \mathbb{R}^{m \times m}$ are two orthogonal matrices and Σ is the diagonal matrix formed by the singular values of M_{φ} . Then, a SVD of M is given by:

$$M = (Q_n U_{\varphi}) \Sigma (Q_m V_{\varphi})^{\star}.$$

Hence, the singular values of M are equal to those of M_{φ} and the left and right singular vectors of M are centrohermitian.

III. TRANSFORMING THE CENTROHERMITIAN RANK FACTORIZATION PROBLEM INTO A REAL RANK FACTORIZATION PROBLEM

In this section, we use Theorem 2 to study the centrohermitian rank factorization problem stated in Section I.

Let $Q_m \in \mathbb{C}^{m \times m}$ and $Q_n \in \mathbb{C}^{n \times n}$ be two *J*-real and unitary matrices (e.g., as defined in Example 3). Since *M* and D_1, \ldots, D_r are centrohermitian matrices, using Theorem 2, we can define the following real matrices:

$$\begin{cases} M_{\varphi} := Q_n^{\star} M Q_m \in \mathbb{R}^{n \times m}, \\ D_{i\varphi} := Q_n^{\star} D_i Q_n \in \mathbb{R}^{n \times n}, \quad i = 1, \dots, r. \end{cases}$$

Note that we have:

$$\operatorname{rank}_{\mathbb{C}}(M) = \operatorname{rank}_{\mathbb{C}}(M_{\varphi}) = \operatorname{rank}_{\mathbb{R}}(M_{\varphi}).$$

Let us suppose that the centrohermitian rank factorization problem (3) admits a centrohermitian solution u, v_1, \ldots, v_r . Again, by Theorem 2, we have the following real vectors:

$$\begin{cases} u_{\varphi} := Q_n^{\star} u \in \mathbb{R}^{n \times 1}, \\ v_{i\varphi} := v_i Q_m \in \mathbb{R}^{1 \times m}, \quad i = 1, \dots, r. \end{cases}$$

See also Example 4. Substituting $M = Q_n M_{\varphi} Q_m^*$ and $D_i = Q_n D_{i\varphi} Q_n^*$ for $i = 1, \ldots, r$ into (3), we then obtain

$$Q_n M_{\varphi} Q_m^{\star} = \sum_{i=1}^r Q_n D_{i\varphi} Q_n^{\star} u v_i$$

$$\Leftrightarrow \quad M_{\varphi} = \sum_{i=1}^r D_{i\varphi} (Q_n^{\star} u) (v_i Q_m)$$

$$\Leftrightarrow \quad M_{\varphi} = \sum_{i=1}^r D_{i\varphi} u_{\varphi} v_{i\varphi},$$

which shows that the rank factorization problem for the real matrices M_{φ} and $D_{i\varphi}$, $i = 1, \ldots, r$, then admits a real solution $(u_{\varphi}, v_{1\varphi}, \ldots, v_{r\varphi})$.

Conversely, if there exists a real solution $u_{\varphi} \in \mathbb{R}^{n \times 1}$, $v_{i\varphi} \in \mathbb{R}^{1 \times m}$, $i = 1, \ldots, r$, of the rank factorization problem

$$M_{\varphi} = \sum_{i=1}^{r} D_{i\varphi} \, u_{\varphi} \, v_{i\varphi}, \tag{5}$$

then, by Theorem 2 (see also Example 4), the vectors

$$\begin{cases} u := Q_n \, u_{\varphi} \in \operatorname{CH}_{n,1}, \\ v_i := v_{i\varphi} \, Q_m^{\star} \in \operatorname{CH}_{1,m}, \quad i = 1, \dots, r \end{cases}$$

satisfy (3), i.e., they define a centrohermitian solution of the centrohermitian rank factorization problem (3).

The above results prove the following new result.

Theorem 4: Let $M \in CH_{n,m}$, $D_i \in CH_{n,n}$, i = 1, ..., r, $Q_m \in \mathbb{C}^{m \times m}$ and $Q_n \in \mathbb{C}^{n \times n}$ be two *J*-real and unitary matrices (e.g., as defined in Example 3), and:

$$\begin{cases} M_{\varphi} := Q_n^{\star} M Q_m \in \mathbb{R}^{n \times m}, \\ D_{i\varphi} := Q_n^{\star} D_i Q_n \in \mathbb{R}^{n \times n}, \quad i = 1, \dots, r. \end{cases}$$
(6)

Then, the centrohermitian rank factorization problem (3) admits a solution $(u, v_1, \ldots, v_r) \in CH_{n,1} \times CH_{1,m}^r$ if and only if the rank factorization problem (5) admits a solution $(u_{\varphi}, v_{1\varphi}, \ldots, v_{r\varphi}) \in \mathbb{R}^{n \times 1} \times (\mathbb{R}^{1 \times m})^r$. Finally, the bijections between the two sets of solutions is given by:

$$\begin{array}{rcl} \operatorname{CH}_{n,1} \times \operatorname{CH}_{1,m}^r &\longmapsto & \mathbb{R}^{n \times 1} \times \left(\mathbb{R}^{1 \times m}\right)^r \\ & (u, v_1, \dots, v_r) &\longmapsto & (Q_n^{\star} \, u, v_1 \, Q_m, \dots, v_r \, Q_m), \\ \\ \mathbb{R}^{n \times 1} \times \left(\mathbb{R}^{1 \times m}\right)^r &\longmapsto & \operatorname{CH}_{n,1} \times \operatorname{CH}_{1,m}^r \\ & (u_{\varphi}, v_{1\varphi}, \dots, v_{r\varphi}) &\longmapsto & (Q_n \, u_{\varphi}, v_{1\varphi} \, Q_m^{\star}, \dots, v_{r\varphi} \, Q_m^{\star}) \,. \end{array}$$

$$\operatorname{IV.} \text{ A class of solutions of the centrohermitian}$$

RANK FACTORIZATION PROBLEM

Theorem 4 shows that centrohermitian solutions of the centrohermitian rank factorization problem are in a one-toone correspondence with real solutions of the rank factorization problem (i.e., $\mathbb{k} = \mathbb{R}$). As stated in Section I, a class of solutions of the rank factorization problem (namely, the solutions such that $v = (v_1^T \dots v_r^T)^T$ has full row rank) – important in practice – can be explicitly parametrized [9], [10]. Hence, we can parametrize the class of centrohermitian solutions of the centrohermitian rank factorization problem for which v has full row rank. Let us explain how to do it.

Let us state again results on the rank factorization problem (see Section I) obtained in [9], [10]. Let \Bbbk be a field (e.g., $k = \mathbb{Q}, \mathbb{R}, \mathbb{C}$), $M \in \mathbb{k}^{n \times m}$ and $l := \operatorname{rank}_{\mathbb{k}}(M)$. Stacking a basis of $\operatorname{im}(M) := M \mathbb{k}^{m \times 1}$ into a full column rank matrix $X \in \mathbb{k}^{n \times l}$, there exists a unique $Y \in \mathbb{k}^{l \times m}$ such that:

$$M = X Y. (7)$$

Denoting

$$\begin{cases} A(u) := (D_1 u \dots D_r u) \in \mathbb{k}^{n \times r}, \\ v := (v_1^T \dots v_r^T)^T \in \mathbb{k}^{r \times m}, \end{cases}$$

then (3) can be rewritten as follows:

$$A(u)v = M. (8)$$

The bilinear structure of (8) implies that $(\lambda u, \lambda^{-1} v)$ is a solution for all solutions (u, v) and for all $\lambda \in \mathbb{R} \setminus \{0\}$. Hence, if a solution exists for the rank factorization problem, then it is not unique. Moreover, we note that (8) is equivalent to the existence of $u \in \mathbb{R}^{n \times 1}$ such that $\operatorname{im}_{\mathbb{R}}(M) \subseteq \operatorname{im}_{K}(A(u))$.

In what follows, we shall investigate the class of solutions (u, v) of (8) defined by a full row rank matrix v. If such a solution of (8) exists, then v admits a right inverse since v has full row rank, i.e., there exists $t \in \mathbb{k}^{m \times r}$ such that $v t = I_r$. Hence, (8) yields A(u) = M t, which shows that $\operatorname{im}_K(A(u)) \subseteq \operatorname{im}_{\mathbb{k}}(M)$, and thus, we obtain:

$$\operatorname{im}_{\Bbbk}(A(u).) = \operatorname{im}_{\Bbbk}(M.). \tag{9}$$

Thus, the existence of a solution (u, v) of (8), where v has full row rank, yields (9). Hence, let us focus on the existence of $u \in \mathbb{k}^{n \times 1}$ satisfying (9). We note that (9) is equivalent to:

$$\exists u \in \mathbb{k}^{n \times 1} \begin{cases} D_i u \in \operatorname{im}_{\mathbb{k}}(M.), \ i = 1, \dots, r, \\ \operatorname{rank}_{\mathbb{k}}(D_1 u \dots D_r u) = \operatorname{rank}_{\mathbb{k}}(M) = l. \end{cases}$$
(10)

We note that v has been eliminated, i.e., we have transformed the polynomial problem (8) into a pure linear algebra problem (10). This last problem can easily be solved as follows.

If $\operatorname{im}_{\Bbbk}(M.) = \Bbbk^{n \times 1}$, then we let L := 0. Else let $L \in \Bbbk^{p \times n}$ be such that $\operatorname{ker}_{\Bbbk}(L.) = \operatorname{im}_{\Bbbk}(M.)$. The first condition of (10) is equivalent to the following linear system on u:

$$\begin{cases} (L D_1) u = 0, \\ \vdots \\ (L D_r) u = 0. \end{cases}$$
(11)

If the only solution of (11) is u = 0, then (9) has no solution since A(0) = 0 and $M \neq 0$. Hence, let $Z \in \mathbb{k}^{n \times d}$ be a full column matrix whose columns form a basis of the k-vector space (11). Note that if $\operatorname{im}_{\mathbb{k}}(M.) = \mathbb{k}^{n \times 1}$, and thus, L = 0, then we get $Z = I_n$. Hence, the vectors $u = Z \psi$ satisfy the first condition of (10) for all $\psi \in \mathbb{k}^{d \times 1}$. Now, we note that $D_i Z \psi \in \operatorname{im}_{\mathbb{k}}(M.) = \operatorname{im}_{\mathbb{k}}(X.)$ for all $\psi \in \mathbb{k}^{d \times 1}$ and $i = 1, \ldots, r$, which shows the existence of unique matrices $W_i \in \mathbb{k}^{l \times d}$ satisfying the following identities:

$$D_i Z = X W_i, \quad i = 1, \dots, r.$$

Let us note:

$$\forall \ \psi \in \mathbb{k}^{d \times 1}, \quad B(\psi) := (W_1 \ \psi \ \dots \ W_r \ \psi) \in \mathbb{k}^{l \times r}.$$

By assumption, $l := \operatorname{rank}_{\Bbbk}(M) \leq r$ (see Remark 1), which shows that *B* is a wide matrix. The second condition of (10) then becomes $A(Z\psi) = (D_1 Z\psi \dots D_r Z\psi) = X B(\psi)$ for all $\psi \in \mathbb{k}^{d \times 1}$. Since *X* has full column rank, we get:

$$\operatorname{rank}_{\Bbbk} A(Z\psi) = \operatorname{rank}_{\Bbbk} B(\psi).$$

The second condition of (10) is equivalent to $\psi \in \mathcal{P}$, where:

$$\mathcal{P} := \{ \psi \in \mathbb{k}^{d \times 1} \mid \operatorname{rank}_{\mathbb{k}} B(\psi) = l \}.$$
(12)

If $\psi \in \mathcal{P}$, then using (7) and the fact that X has full column rank, then we obtain:

$$A(Z\psi)v = M \iff X B(\psi)v = X Y \iff B(\psi)v = Y.$$
(13)

Moreover, since $\operatorname{rank}_{\mathbb{k}}B(\psi) = l$, $B(\psi) \in \mathbb{k}^{l \times r}$ and $l \leq r$, $B(\psi)$ has full row rank, which shows that $B(\psi)$ admits a right inverse $E_{\psi} \in \mathbb{k}^{r \times l}$, i.e., $B(\psi) E_{\psi} = I_l$. Hence, $v = E_{\psi} Y$ is a particular solution of (13). If $C_{\psi} \in \mathbb{k}^{r \times (r-l)}$ is a full column matrix whose columns form a basis of $\ker_{\mathbb{k}}(B(\psi).)$, then the general solution of (13) is given by:

$$\forall Y' \in \mathbb{k}^{(r-l) \times m}, \quad v = (E_{\psi} \quad C_{\psi}) \begin{pmatrix} Y \\ Y' \end{pmatrix}.$$

Finally, we note that $(E_{\psi} \quad C_{\psi})$ is invertible, i.e., is a nonsingular matrix, which shows that v has full row rank iff so has the matrix $(Y^T \quad {Y'}^T)^T \in \mathbb{k}^{r \times m}$. We get the theorem.

Theorem 5 ([9]): With the above notations, (9) holds iff (12) is not empty. If so, then for every $\psi \in \mathcal{P}$,

$$\forall Y' \in \mathbb{k}^{(r-l) \times m}, \quad \left\{ \begin{array}{ll} u = Z \,\psi, \\ v = (E_{\psi} \quad C_{\psi}) \left(\begin{array}{c} Y \\ Y' \end{array} \right), \end{array} \right.$$

are solutions of (8), and thus, solutions of (3). Finally, v has full row rank iff so has $(Y^T \quad {Y'}^T)^T \in \mathbb{k}^{r \times m}$.

Set $C_r^l := r!/(l! (r-l)!)$ and let $\{m_k(\psi)\}_{k=1,\ldots,C_r^l}$ denote the set of all $l \times l$ -minors of $B(\psi)$. Note that the m_k 's are either 0 or homogeneous polynomials of degree l, namely:

$$\forall \lambda \in \mathbb{k} \setminus \{0\}, \quad \mathsf{m}_k(\lambda x) = \lambda^l \, \mathsf{m}_k(x), \quad k = 1, \dots, C_r^l.$$

Hence, we clearly have:

$$\mathcal{P} = \mathbb{k}^{d \times 1} \setminus \left\{ \psi \in \mathbb{k}^{d \times 1} \mid \mathsf{m}_k(\psi) = 0, \, k = 1, \dots, C_r^l \right\}.$$

Since C_r^l grows exponentially with r, a more efficient characterization of \mathcal{P} was obtained in [10] based on module theory and computer algebra (*Gröbner bases* [3], [10]).

According to Theorem 4, a particular class of solutions of the centrohermitian rank factorization problem can be obtained by applying Theorem 5 to (6) with $\mathbb{k} = \mathbb{R}$. Hence, we obtain the following new result.

Corollary 1: Let Q_n and Q_m be two J-real unitary matrices (e.g., as defined in Example 3), $M \in CH_{n,m}$ and $D_i \in CH_{n,n}$ for i = 1, ..., r, and $M_{\varphi} \in \mathbb{R}^{n \times m}$ and $D_{i\varphi} \in \mathbb{R}^{n \times n}$, i = 1, ..., r, defined by (6). Moreover, if

$$\begin{cases} u_{\varphi} = Z_{\varphi} \psi, \\ v_{\varphi} = (E_{\varphi\psi} \quad C_{\varphi\psi}) \begin{pmatrix} Y \\ Y' \end{pmatrix}, \end{cases}$$

denotes the solutions of the rank factorization problem (5) for $\mathbb{k} = \mathbb{R}$ – defined by Theorem 5 – where $Y' \in \mathbb{R}^{(r-l) \times m}$ and $\psi \in \mathcal{P} := \{\psi \in \mathbb{R}^{d \times 1} \mid \operatorname{rank}_{\mathbb{R}} \mathcal{B}_{\varphi}(\psi) = l\}$, then

$$\begin{cases}
 u = Q_n u_{\varphi}, \\
 v = v_{\varphi} Q_m^{\star},
\end{cases}$$
(14)

is a centrohermitian solution of (3). Finally, v has full row rank iff so has $(Y^T \quad {Y'}^T)^T \in \mathbb{R}^{r \times m}$.

The last point of Corollary 1 comes from the fact that $\lambda v = \lambda v_{\varphi} Q_m^* = 0$ iff $\lambda v_{\varphi} = 0$, and thus, we get $\lambda = 0$ iff v_{φ} has full row rank, which is characterized in Theorem 5.

Example 7: We consider again the matrix $M \in CH_{3,4}$ defined in Example 5. Let us consider the following matrices:

$$D_{1} = \frac{1}{2} \begin{pmatrix} -i & 0 & i \\ 0 & 0 & 0 \\ -i & 0 & i \end{pmatrix} \in CH_{3,3},$$
$$D_{2} = \frac{3i}{\sqrt{2}} \begin{pmatrix} 0 & 1 & 0 \\ 0 & 0 & 0 \\ 0 & -1 & 0 \end{pmatrix} \in CH_{3,3},$$
$$D_{3} = \frac{i}{\sqrt{2}} \begin{pmatrix} 0 & 0 & 0 \\ -1 & 0 & 1 \\ 0 & 0 & 0 \end{pmatrix} \in CH_{3,3},$$
$$D_{4} = \frac{1}{2} \begin{pmatrix} 1-3i & 0 & -1+3i \\ 0 & 0 & 0 \\ -1-3i & 0 & 1+3i \end{pmatrix} \in CH_{3,3}.$$

Using (6), we have:

$$\begin{split} D_{1\varphi} &= Q_3^{\star} \, D_1 \, Q_3 = \begin{pmatrix} 0 & 0 & 1 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{pmatrix} \in \mathbb{R}^{3 \times 3}, \\ D_{2\varphi} &= Q_3^{\star} \, D_2 \, Q_3 = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 3 & 0 \end{pmatrix} \in \mathbb{R}^{3 \times 3}, \\ D_{3\varphi} &= Q_3^{\star} \, D_3 \, Q_3 = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 1 \\ 0 & 0 & 0 \end{pmatrix} \in \mathbb{R}^{3 \times 3}, \\ D_{4\varphi} &= Q_3^{\star} \, D_4 \, Q_3 = \begin{pmatrix} 0 & 0 & 3 \\ 0 & 0 & 0 \\ 0 & 0 & 1 \end{pmatrix} \in \mathbb{R}^{3 \times 3}. \end{split}$$

Let M_{φ} denote the matrix $\varphi(M)$ defined in Example 5. Then, we can solve (5) using Theorem 5. We can easily check that $l := \operatorname{rank}_{\mathbb{R}}(M_{\varphi}) = \operatorname{rank}_{\mathbb{C}}(M) = 3 < r = 4$. We then get:

$$\begin{aligned} X_{\varphi} &= \begin{pmatrix} 45 & 10 & 5 \\ 5 & 20 & 15 \\ 15 & 0 & 0 \end{pmatrix} \in \mathbb{R}^{3 \times 3}, \\ Y_{\varphi} &= \frac{1}{3} \begin{pmatrix} 3 & 0 & 0 & 2 \\ 0 & 3 & 0 & 1 \\ 0 & 0 & 3 & -2 \end{pmatrix} \in \mathbb{R}^{3 \times 4}, \\ L_{\varphi} &= 0, \quad Z_{\varphi} &= I_{3}, \quad d_{\varphi} &= 3, \quad \psi = \begin{pmatrix} \psi_{1} \\ \psi_{2} \\ \psi_{3} \end{pmatrix} \in \mathbb{R}^{3 \times 1}, \\ W_{1\varphi} &= \frac{1}{10} \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & 3 \\ 0 & 0 & -4 \end{pmatrix}, \\ W_{2\varphi} &= \frac{1}{5} \begin{pmatrix} 0 & 1 & 0 \\ 0 & -13 & 0 \\ 0 & 17 & 0 \end{pmatrix}, \\ W_{3\varphi} &= \frac{1}{10} \begin{pmatrix} 0 & 0 & 0 \\ 0 & 0 & -1 \\ 0 & 0 & 2 \end{pmatrix}, \\ W_{4\varphi} &= \frac{1}{30} \begin{pmatrix} 0 & 0 & 2 \\ 0 & 0 & 1 \\ 0 & 0 & -2 \end{pmatrix}, \\ B_{\varphi}(\psi) &= \frac{1}{30} \begin{pmatrix} 0 & 6 & \psi_{2} & 0 & 2\psi_{3} \\ 9\psi_{3} & -78\psi_{2} & -3\psi_{3} & \psi_{3} \\ -12\psi_{3} & 102\psi_{2} & 6\psi_{3} & -2\psi_{3} \end{pmatrix}, \\ \mathcal{P} &= \mathbb{R}^{3 \times 1} \setminus \{(\psi_{1} \ \psi_{2} \ \psi_{3})^{T} \in \mathbb{R}^{3 \times 1} \mid \psi_{3} = 0\} \\ &= \mathbb{R} \times \mathbb{R} \times (\mathbb{R} \setminus \{0\}), \end{aligned}$$

$$E_{\psi_3} = \frac{1}{\psi_3} \begin{pmatrix} 0 & 10 & 3 \\ 0 & 0 & 0 \\ 5 & 20 & 15 \\ 15 & 0 & 0 \end{pmatrix}, \quad C = \begin{pmatrix} 9\psi_2 \\ \psi_3 \\ 0 \\ -3\psi_2 \end{pmatrix}.$$

$$\begin{aligned} \text{Real solutions of } M_{\varphi} &= \sum_{i=1}^{4} D_{i\varphi} \, u_{\varphi} \, v_{i\varphi} \text{ are then given by:} \\ \forall \, \psi \in \mathcal{P}, \quad \forall \, Y' = (y'_1 \quad y'_2 \quad y'_3 \quad y'_4) \in \mathbb{R}^{1 \times 4}, \\ u_{\varphi} &= Z_{\varphi} \, \psi = \psi, \\ v_{\varphi} &= E_{\psi_3} \, Y + C \, Y' = \\ \begin{pmatrix} 9 \, \psi_2 \, y'_1 & \frac{10}{\psi_3} + 9 \, \psi_2 \, y'_2 & \frac{5}{\psi_3} + 9 \, \psi_2 \, y'_3 & 9 \, \psi_2 \, y'_4 \\ \psi_3 \, y'_1 & \psi_3 \, y'_2 & \psi_3 \, y'_3 & \psi_3 \, y'_4 \\ \frac{5}{\psi_3} & \frac{20}{\psi_3} & \frac{15}{\psi_3} & 0 \\ \frac{15}{\psi_3} - 3 \, \psi_2 \, y'_1 & -3 \, \psi_2 \, y'_2 & -3 \, \psi_2 \, y'_3 & \frac{10}{\psi_3} - 3 \, \psi_2 \, y'_4 \end{aligned}$$

Moreover, v_{φ} has full row rank iff det $\begin{pmatrix} Y^T & {Y'}^T \end{pmatrix} \neq 0$, i.e., iff $Y' = (y'_1 \quad y'_2 \quad y'_3 \quad y'_4) \in \mathbb{R}^{1 \times 4}$ is chosen such that: $2y'_1 + y'_2 - 2y'_3 - 3y'_4 \neq 0.$ (15)

Now, using (14) (see Corollary 1), centrohermitian solutions of $M = \sum_{i=1}^{4} D_i u v_i$ are then defined by

$$\forall \ \psi \in \mathcal{P}, \quad \forall \ Y' = (y'_1 \quad y'_2 \quad y'_3 \quad y'_4) \in \mathbb{R}^{1 \times 4},$$

$$\begin{cases} u = Q_3 \ \psi = \begin{pmatrix} \frac{\sqrt{2}}{2} \psi_1 + \frac{\sqrt{2}}{2} i \psi_3 \\ \psi_2 \\ \frac{\sqrt{2}}{2} \psi_1 - \frac{\sqrt{2}}{2} i \psi_3 \end{pmatrix}, \\ v = \begin{pmatrix} v_1 \\ v_2 \\ v_3 \\ v_4 \end{pmatrix} = v_{\varphi} \ Q_4^*,$$

$$v_1 = \frac{1}{\sqrt{2} \psi_3}$$

 $(9 \psi_2 \psi_3 y'_1 - 9 \psi_2 \psi_3 y'_3 i - 5 i \quad 10 + 9 \psi_2 \psi_3 y'_2 - 9 \psi_2 \psi_3 y'_4 i$ $10 + 9 \psi_2 \psi_3 y'_2 + 9 \psi_2 \psi_3 y'_4 i \quad 9 \psi_2 \psi_3 y'_1 + 9 \psi_2 \psi_3 y'_3 i + 5 i),$

$$\begin{split} v_2 &= \frac{1}{2} \, \psi_3 \, (y_1' \, \sqrt{2} - y_3' \, \sqrt{2} \, i \quad y_2' \, \sqrt{2} - y_4' \, \sqrt{2} \, i \\ &\quad y_2' \, \sqrt{2} + y_4 \, \sqrt{2} \, i \quad y_1' \, \sqrt{2} + y_3' \, \sqrt{2} \, i), \\ v_3 &= \frac{5}{2 \, \psi_3} \, \left((1 - 3 \, i) \, \sqrt{2} \quad 4 \, \sqrt{2} \quad 4 \, \sqrt{2} \quad (1 + 3 \, i) \, \sqrt{2} \right), \\ v_4 &= \frac{1}{\sqrt{2} \, \psi_3} \left(15 - 3 \, \psi_2 \, \psi_3 \, y_1' + 3 \, \psi_2 \, \psi_3 \, y_3' \, i \\ &\quad -3 \, \psi_2 \, \psi_3 \, y_2' + 3 \, \psi_2 \, \psi_3 \, y_4' \, i - 10 \, i \\ &\quad -3 \, \psi_2 \, \psi_3 \, y_2' - 3 \, \psi_2 \, \psi_3 \, y_4' \, i + 10 \, i \\ &\quad 15 - 3 \, \psi_2 \, \psi_3 \, y_1' - 3 \, \psi_2 \, \psi_3 \, y_3' \, i). \end{split}$$

Finally, the matrix v has full row rank iff the row vector $Y' = (y'_1 \quad y'_2 \quad y'_3 \quad y'_4) \in \mathbb{R}^{1 \times 4}$ satisfies (15). All the results developed in this paper can be easily

All the results developed in this paper can be easily implemented using, e.g., the OREMODULES package [3].

V. CONCLUSION

In this paper, using the structure of centrohermitian matrices and Lee's theorem [12], we proved that the centrohermitian rank factorization problem can be reduced to a real rank factorization one. Using results of [9], [10], we then show how to parametrize a class of solutions which are important in practice. In [11], we develop an alternative approach to Lee's transformation based on the so-called *coinvolutory matrices*. This alternative approach brings new insights.

An important issue that will be investigated in a future publication is the following minimization problem

$$\min_{u \in \operatorname{CH}_{n,1}(\mathbb{C}), \, v_i \in \operatorname{CH}_{1,m}(\mathbb{C})} \left\| \sum_{i=1}^r D_i \, u \, v_i - M \right\|_{\operatorname{Frob}}, \quad (16)$$

where $||A||_{\text{Frob}} = \sqrt{\text{trace}(A^*A)}$ stands for the standard *Frobenius norm*. If U and V are two unitary matrices, using the *cyclic property* of the trace, then we have:

$$\begin{aligned} \|UAV\|_{\text{Frob}} &= \sqrt{\operatorname{trace}(V^*A^*U^*UAV)} \\ &= \sqrt{\operatorname{trace}(V^*A^*AV)} \\ &= \sqrt{\operatorname{trace}(VV^*A^*A)} \\ &= \sqrt{\operatorname{trace}(A^*A)} = \|A\|_{\text{Frob}} \,. \end{aligned}$$

Hence, using the fact that the matrices Q_n and Q_m in Theorem 4 are unitary, we then obtain

16)
$$\Leftrightarrow \min_{u_{\varphi} \in \mathbb{R}^{n \times 1}, v_{i_{\varphi}} \in \mathbb{R}^{1 \times m}} \left\| \sum_{i=1}^{r} D_{i_{\varphi}} u_{\varphi} v_{i_{\varphi}} - M_{\varphi} \right\|_{\text{Frob}}$$

which shows that (16) can be reduced to the search for real solutions to a polynomial optimization problem.

REFERENCES

- C. Capdessus. Aide au diagnostic des machines tournantes par traitement du signal. PhD thesis, University of Grenoble, 1992, https://hal.archives-ouvertes.fr/tel-02187906.
- [2] C. Capdessus, M. Sidahmed. Analyse des vibrations d'un engrenage : cepstre, corrélation, spectre. *Colloque francophone de traitement du* signal et des images (GRETSI), France, vol. 8, 365–372, 1991.
- [3] F. Chyzak, A. Quadrat, R. Robertz. OREMODULES: A symbolic package for the study of multidimensional linear systems. *Applications of Time-Delay Systems*, LNCIS 352, Springer, 233–264, 2007, https://who.rocq.inria.fr/Alban.Quadrat/OreModules.html.
- [4] M. Haardt, J. A. Nossek. Unitary ESPRIT: How to obtain increased estimation accuracy with a reduced computational burden. *IEEE Transactions on Signal Processing*, 43 (1995),
- [5] R. D. Hill, R. G. Bates, S. R. Waters. On Centrohermitian matrices. SIAM J. on Matrix Analysis and Applications, 11 (1990), 128–133.
- [6] E. Hubert. Amplitude and phase demodulation of multi-carrier signals: Application to gear vibration signals. PhD Thesis, Lyon Univ., 2019.
- [7] E. Hubert, A. Barrau, M. El Badaoui. New multi-carrier demodulation method applied to gearbox vibration analysis. Proceedings of *ICASSP* 2018, Calgary (Canada), 15–20/04/2018.
- [8] E. Hubert, Y. Bouzidi, R. Dagher, A. Barrau, A. Quadrat. Algebraic aspects of the exact signal demodulation problem. Proceedings of SSSC & TDS, Sinaia (Romania), 09-11/09/2019.
- [9] E. Hubert, A. Barrau, Y. Bouzidi, R. Dagher, A. Quadrat. On a rank factorisation problem arising in gearbox vibration analysis. Proceedings of the 21st IFAC World Congress, Germany, 12-17/07/2020.
- [10] E. Hubert, Y. Bouzidi, R. Dagher, A. Quadrat. Algebraic aspects of a rank factorization problem arising in vibration analysis. Proceedings of the *Maple Conference*, 02-06/11/2020.
- [11] E. Hubert, A. Barrau, Y. Bouzidi, R. Dagher, A. Quadrat. Centrohermitian solutions of a factorization problem arising in vibration analysis. Part II: A coninvolutory matrix approach. *ECC 2021*.
- [12] A. Lee. Centrohermitian and skew-centrohermitian matrices. *Linear Algebra and its Applications*, 29 (1980), 205–210.
- [13] A. V. Oppenheim, R. W. Schafer. Discrete-Time Signal Processing. Prentice Hall Signal Processing Series, 2nd ed., 1999.