



HAL
open science

Stability of homogeneous systems with distributed delay and time-varying perturbations

Alexander Aleksandrov, Denis Efimov, Emilia Fridman

► To cite this version:

Alexander Aleksandrov, Denis Efimov, Emilia Fridman. Stability of homogeneous systems with distributed delay and time-varying perturbations. *Automatica*, 2023, 153, pp.111058. 10.1016/j.automatica.2023.111058 . hal-03777752v1

HAL Id: hal-03777752

<https://inria.hal.science/hal-03777752v1>

Submitted on 15 Sep 2022 (v1), last revised 12 Jan 2024 (v2)

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



Distributed under a Creative Commons Attribution 4.0 International License

Stability of homogeneous systems with distributed delay and time-varying perturbations

Alexander Aleksandrov ^{a,b} Denis Efimov ^{c,d} Emilia Fridman ^e

^a*Saint Petersburg State University, 7-9 Universitetskaya nab., Saint Petersburg, 199034, Russia*

^b*Institute for Problems of Mechanical Engineering, Russian Academy of Sciences, Saint Petersburg 199178, Russia*

^c*Inria, Univ. Lille, CNRS, UMR 9189 - CRISTAL, F-59000 Lille, France*

^d*ITMO University, 49 av. Kronverkskiy, 197101 Saint Petersburg, Russia*

^e*School of Electrical Engineering, Tel-Aviv University, Tel-Aviv 69978, Israel*

Abstract

For a class of nonlinear systems with homogeneous right-hand sides of non-zero degree and distributed delays, the problem of stability robustness of the zero solution with respect to time-varying perturbations multiplied by a nonlinear functional gain is studied. It is assumed that the disturbance-free and delay-free system (that results after substitution of non-delayed state for the delayed one) is globally asymptotically stable. First, it is demonstrated that in the disturbance-free case the zero solution is either locally asymptotically stable or practically globally asymptotically stable, depending on the homogeneity degree of the delay-free counterpart. Second, using averaging tools several variants of the time-varying perturbations are considered and the respective conditions are derived evaluating the stability margins in the system. The results are obtained by a careful choice and comparison of Lyapunov–Krasovskii and Lyapunov–Razumikhin approaches. Finally, the obtained theoretical findings are illustrated on two mechanical systems.

1 Introduction

The problem of stability analysis for nonlinear time-delay systems influenced by time-varying perturbations is rather complex [Hale, 1977, Kolmanovskii and Myshkis, 1999, Gu et al., 2003, Richard, 2003, Fridman, 2014]. Despite that, nowadays it is gaining a practical importance with raising the internet of things and cyber-physical systems technologies [Karafyllis et al., 2016, Hetel et al., 2017]. There are two main methods for stability analysis of time-delay systems: Lyapunov–Krasovskii (LK) and Lyapunov–Razumikhin (LR) approaches [Fridman, 2014]. The former uses LK functionals (LKFs) and it has been proven to give the necessary and sufficient conditions of stability [Pepe et al., 2017, Efimov and Fridman, 2020], while the latter is based on usual Lyapunov function analysis (under additional restrictions), and it provides only sufficient conditions of stability, which however may be easier to check in applications. Both methods have

their own extensions to the input-to-state stability (ISS) verification [Teel, 1998, Fridman et al., 2008].

Distributed delays can be induced by communication network or realization of the control/estimation algorithms [Anan’evskii and Kolmanovskii, 1989, Feng and Lam, 2012, Feng et al., 2020], and their stability analysis requires special extensions of the previously mentioned methods [Xie et al., 2001, Solomon and Fridman, 2013]. The investigation becomes even more complex if there are external perturbations and we would like to evaluate the shape of admissible upper bound of the disturbance in terms of the delayed state (*i.e.*, evaluate the asymptotic gains in terms of ISS). The obtained bounds can be less conservative if the features of the time-varying perturbations are taken into account. For example, if the perturbations are periodic or almost periodic, then the averaging method has been proven to be very efficient [Bogoliubov and Mitropolsky, 1961, Khapaev, 1993].

Working in a nonlinear setting, it is useful to restrict the analysis to a particular class of models, and in this work we will focus on homogeneous dynamics, which in the delay-free case have a lot of useful properties helped them to gain

* Sections 6 and 7 were performed in Institute for Problems in Mechanical Engineering RAS and supported by the Ministry of Science and Higher Education of the Russian Federation (Project No. 075-15-2021-573).

popularity [Efimov and Polyakov, 2021], and there are also their extension to infinite-dimensional systems [Efimov et al., 2014, 2016]. It has been shown that for systems with discrete time-delays, if the delay-free counterparts (the systems with zero delay) are globally asymptotically stable at the origin, then for any delay value the original dynamics are locally asymptotically stable at the origin for positive homogeneity degree [Aleksandrov and Zhabko, 2012, 2014, Efimov et al., 2014] or practically globally asymptotically stable (we will call later this property uniform ultimate boundedness (UUB) of the solutions) for negative degree [Zimenko et al., 2017]. In above works, the LR method is used, and the LK approach has been developed to this case recently in [Aleksandrov et al., 2015, Efimov and Aleksandrov, 2021].

In this work, these results will be extended to the case of distributed delays, and next robust stability conditions will be developed evaluating the admissible shapes of perturbations without, and next with, the averaging approach.

The outline of this work is as follows. Preliminaries are given in Section 2. The considered analysis problem is described in Section 3. The general stability and robustness results are formulated in sections 4 and 5. Using the averaging approach, for particular classes of perturbations and the systems, the respective stability results are presented in sections 6 (for any sign of homogeneity degree) and 7 (for the positive degree of homogeneity). The illustrative examples are shown in Section 8.

2 Preliminaries

The real numbers are denoted by \mathbb{R} , and $|s|$ is an absolute value for $s \in \mathbb{R}$. Euclidean norm for a vector $x \in \mathbb{R}^n$ is defined as $\|x\|$. We denote by $C([a, b], \mathbb{R}^n)$, $-\infty < a < b < +\infty$ the Banach space of continuous functions $\phi : [a, b] \rightarrow \mathbb{R}^n$ with the uniform norm $\|\phi\|_C = \sup_{a \leq \varsigma \leq b} \|\phi(\varsigma)\|$.

A sequence of integers, $m, m+1, \dots, n$ for $m < n$ is further denoted by $\overline{m, n}$.

A continuous function $\sigma : \mathbb{R}_+ \rightarrow \mathbb{R}_+$ belongs to class \mathcal{K} if it is strictly increasing and $\sigma(0) = 0$; it belongs to class \mathcal{K}_∞ if it is also radially unbounded. A continuous function $\beta : \mathbb{R}_+ \times \mathbb{R}_+ \rightarrow \mathbb{R}_+$ belongs to class \mathcal{KL} if $\beta(\cdot, r) \in \mathcal{K}$ and $\beta(r, \cdot)$ is a strictly decreasing to zero for any fixed $r \in \mathbb{R}_+$.

The standard definitions of stability and related properties for time-delay systems can be found in [Hale, 1977, Kolmanovskii and Myshkis, 1999, Fridman, 2014], and for delay-free dynamics in [Khalil, 2002].

2.1 Useful inequalities

The *Young's inequality* claims that for any $\mathbf{a}, \mathbf{b} \in \mathbb{R}_+$ and $\gamma > 0, \delta > 0$ [Bacciotti and Rosier, 2001]:

$$\mathbf{a}^\gamma \mathbf{b}^\delta \leq \frac{1}{p} \mathbf{a}^{\gamma p} + \frac{p-1}{p} \mathbf{b}^{\frac{\delta p}{p-1}}$$

for any $p > 1$, while *Hölder's inequality* for any $f, g : I \rightarrow \mathbb{R}$ with $I \subset \mathbb{R}$ ensures that [Bacciotti and Rosier, 2001]:

$$\int_I |f(s)g(s)| ds \leq \left(\int_I |f(s)|^p ds \right)^{\frac{1}{p}} \left(\int_I |g(s)|^{\frac{p}{p-1}} ds \right)^{\frac{p-1}{p}}$$

for any $p > 1$.

Using the properties of homogeneous functions the following result can be obtained [Efimov and Aleksandrov, 2021]:

Lemma 1 *Let $\mathbf{a}, \mathbf{b} \in \mathbb{R}_+$ and $\ell > 0, \alpha > 0, \beta > 0, \gamma > 0, \delta > 0$ be given, then*

$$\mathbf{a}^\alpha + \mathbf{b}^\beta - \ell \mathbf{a}^\gamma \mathbf{b}^\delta \geq 0$$

provided that

- 1) $\max\{\mathbf{a}^\alpha, \mathbf{b}^\beta\} \geq \ell^{1-\frac{1}{\alpha}-\frac{1}{\beta}}$ and $\frac{\gamma}{\alpha} + \frac{\delta}{\beta} < 1$,
- 2) $\max\{\mathbf{a}^\alpha, \mathbf{b}^\beta\} \leq \ell^{1-\frac{1}{\alpha}-\frac{1}{\beta}}$ and $\frac{\gamma}{\alpha} + \frac{\delta}{\beta} > 1$.

2.2 Homogeneity

For any $r_i > 0, i = \overline{1, n}$ and $\lambda > 0$, define the *vector of weights* $\mathbf{r} = [r_1, \dots, r_n]$ and the *dilation matrix* $\Lambda_r(\lambda) = \text{diag}\{\lambda^{r_i}\}_{i=1}^n$; $r_{\min} = \min_{i=\overline{1, n}} r_i$ and $r_{\max} = \max_{i=\overline{1, n}} r_i$.

Definition 1 [Zubov, 1958, Efimov and Polyakov, 2021] *The function $h : \mathbb{R}^n \rightarrow \mathbb{R}$ is called \mathbf{r} -homogeneous, if for any $x \in \mathbb{R}^n$ the relation*

$$h(\Lambda_r(\lambda)x) = \lambda^\nu h(x)$$

holds for some $\nu \in \mathbb{R}$ and all $\lambda > 0$.

The vector field $f : \mathbb{R}^n \rightarrow \mathbb{R}^n$ is called \mathbf{r} -homogeneous, if for any $x \in \mathbb{R}^n$ the relation

$$f(\Lambda_r(\lambda)x) = \lambda^\nu \Lambda_r(\lambda) f(x)$$

holds for some $\nu \geq -r_{\min}$ and all $\lambda > 0$.

In both cases, the constant ν is called the degree of homogeneity.

For any $x \in \mathbb{R}^n$ and $\varpi \geq r_{\max}$, a *homogeneous norm* can be defined as follows

$$\|x\|_r = \left(\sum_{i=1}^n |x_i|^{\varpi/r_i} \right)^{1/\varpi}.$$

For all $x \in \mathbb{R}^n$, its Euclidean norm $\|x\|$ is related with the homogeneous one:

$$\underline{\sigma}_r(\|x\|_r) \leq \|x\| \leq \bar{\sigma}_r(\|x\|_r)$$

for some $\underline{\sigma}_r, \bar{\sigma}_r \in \mathcal{K}_\infty$ [Efimov et al., 2018]. In the following, due to this ‘‘equivalence’’, stability analysis with respect to the norm $\|x\|$ can be substituted with analysis for the norm $\|x\|_r$. The homogeneous norm has an important property: it is \mathbf{r} -homogeneous of degree 1, that is $\|\Lambda_r(\lambda)x\|_r = \lambda\|x\|_r$ for all $x \in \mathbb{R}^n$ and $\lambda > 0$.

3 Statement of the problem

Consider a nonlinear time-delay system without disturbances

$$\dot{x}(t) = F(x(t)) + \int_{t-\tau}^t G(x(s))ds, \quad (1)$$

where $x(t) \in \mathbb{R}^n$, vector fields $F(x)$ and $G(x)$ are continuous for $x \in \mathbb{R}^n$ and \mathbf{r} -homogeneous of the degree ν with respect to weights $\mathbf{r} = (r_1, \dots, r_n)$, $\nu + r_{\min} > 0$; $\tau = \text{const} > 0$ is the delay; the initial functions for (1) belong to the space $C([-\tau, 0], \mathbb{R}^n)$. Denote by x_t the restriction of a solution $x(t)$ to the segment $[t - \tau, t]$, i.e., $x_t : \xi \mapsto x(t + \xi)$, $\xi \in [-\tau, 0]$. The system (1) admits the zero solution.

Our objective is to derive the conditions of *asymptotic stability* for the zero solution (there exists $\beta \in \mathcal{KL}$ such that $\|x(t)\| \leq \beta(\|x_0\|_C, t)$ for all $t \geq 0$ and $\|x_0\|_C < \bar{\rho}$ for some $\bar{\rho} > 0$), or we will look for *UUB* conditions in (1) (there exist $\beta \in \mathcal{KL}$ and $\bar{\rho} > 0$ such that $\|x(t)\| \leq \beta(\|x_0\|_C, t) + \bar{\rho}$ for all $t \geq 0$ and $x_0 \in C([-\tau, 0], \mathbb{R}^n)$), depending on the sign ν of the homogeneity degree of F and G (see Section 4). Further, we will study, first, the impact on the dynamics of (1) of general non-stationary perturbations (in Section 5). Next, disturbances admitting averaging (e.g., periodic or almost periodic) with a nonlinear gain containing distributed delay (for all signs of homogeneity degree in Section 6 and an improvement for positive degree in Section 7).

The results of sections 6 and 7 in this paper are obtained with the aid of a special approach extending the averaging method (see [Fridman and Zhang, 2020, Zhang and Fridman, 2022]). Using this tool the conditions are derived under which the perturbations do not destroy the asymptotic stability or ultimate boundedness in (1).

4 Basic stability and UUB conditions

The main hypothesis for us is the asymptotic stability of the origin for the delay-free counterpart of (1), which is obtained after substitution of $x(t)$ in place of $x(s)$:

Assumption 1 *The zero solution of the auxiliary delay-free system*

$$\dot{x}(t) = F(x(t)) + \tau G(x(t)), \quad x(t) \in \mathbb{R}^n, \quad t \geq 0,$$

is asymptotically stable.

Remark 1 *In the case of linear system (1) with $F(x) = Ax$ and $G(x) = A_d x$, where A and $A_d \in \mathbb{R}^{n \times n}$, Assumption 1 means that $A + \tau A_d$ is Hurwitz, which guarantees the stability of the system provided that an additional condition holds (see Section 3.8 in [Fridman, 2014]). Surprisingly, for homogeneous systems with $\nu \neq 0$, Assumption 1 appears to be sufficient for stability of (1) (this will be demonstrated in Theorem 1 below).*

Remark 2 *It is well known (see [Zubov, 1958, Rosier, 1992]) that, under Assumption 1, the delay-free system admits a Lyapunov function $V(x)$ with the following properties:*

- (i) $V(x)$ is twice continuously differentiable for $x \in \mathbb{R}^n$;
- (ii) $V(x)$ is positive definite;
- (iii) $V(x)$ is \mathbf{r} -homogeneous of the degree $\mu > 2r_{\max}$;
- (iv) the function $(\partial V(x)/\partial x)^\top (F(x) + \tau G(x))$ is negative definite.

In [Aleksandrov et al., 2015, Efimov and Aleksandrov, 2021], an approach to the so-called complete-type LKF's construction for homogeneous systems with discrete delays was developed. In the present contribution, we will extend this approach to homogeneous systems with distributed delays.

Theorem 1 *Let Assumption 1 be fulfilled,*

- (i) *if $\nu > 0$, then the zero solution of (1) is asymptotically stable;*
- (ii) *if $\nu < 0$, then solutions of (1) are UUB.*

PROOF. Choose a LKF for (1) as follows:

$$\begin{aligned} \tilde{V}(t, x_t) = & V(x) + \left(\frac{\partial V(x)}{\partial x} \right)^\top \int_{t-\tau}^t (s + \tau - t) G(x(s)) ds \\ & + \int_{t-\tau}^t (\alpha + \beta(s + \tau - t)) |x(s)|_r^{\mu+\nu} ds, \end{aligned} \quad (2)$$

where α, β are positive parameters and $V(x)$ is a Lyapunov function satisfying the conditions specified in Remark 2.

Using properties of homogeneous functions (see [Efimov and Polyakov, 2021]), we arrive at the estimates

$$\begin{aligned} c_1 |x(t)|_r^\mu - c_3 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |x(s)|_r^{\nu+r_i} ds \\ + \alpha \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \leq \tilde{V}(t, x_t) \leq c_2 |x(t)|_r^\mu \\ + c_3 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |x(s)|_r^{\nu+r_i} ds + (\alpha + \beta\tau) \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds, \end{aligned}$$

where c_1, c_2, c_3 are positive constants.

Considering the derivative of the functional (2) along the solutions of (1) we obtain:

$$\begin{aligned} \dot{\tilde{V}} &= \left(\frac{\partial V(x(t))}{\partial x} \right)^\top (F(x(t)) + \tau G(x(t))) \\ &\quad + (\alpha + \beta\tau)|x(t)|_r^{\mu+\nu} - \alpha|x(t-\tau)|_r^{\mu+\nu} - \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \\ &+ \sum_{i,j=1}^n \frac{\partial^2 V(x(t))}{\partial x_i \partial x_j} \left(F_j(x(t)) + \int_{t-\tau}^t G_j(x(s)) ds \right) \int_{t-\tau}^t (s+\tau-t) G_i(x(s)) ds \\ &\leq -c_4|x(t)|_r^{\mu+\nu} + c_5 \sum_{i,j=1}^n |x(t)|_r^{\mu-r_i-r_j} \left(|x(t)|_r^{\nu+r_j} + \int_{t-\tau}^t |x(s)|_r^{\nu+r_j} ds \right) \\ &\quad \times \int_{t-\tau}^t |x(s)|_r^{\nu+r_i} ds + (\alpha + \beta\tau)|x(t)|_r^{\mu+\nu} - \alpha|x(t-\tau)|_r^{\mu+\nu} - \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds, \end{aligned}$$

where $c_4 > 0, c_5 > 0$.

Take $\alpha + \beta\tau < \frac{c_4}{4}$, then with the aid of Young's and Hölder's inequalities and Lemma 1, it is straightforward to prove the existence of positive numbers Δ_1, Δ_2 such that

(i) if $\nu > 0$, then

$$\begin{aligned} \frac{1}{2}c_1|x(t)|_r^\mu + \frac{1}{2}\alpha \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds &\leq \tilde{V}(t, x_t) \\ &\leq 2c_2|x(t)|_r^\mu + 2(\alpha + \beta\tau) \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds, \\ \dot{\tilde{V}} &\leq -\frac{1}{2}c_4|x(t)|_r^{\mu+\nu} - \frac{1}{2}\beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \end{aligned}$$

for $|x(t)|_r^\mu + \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds < \Delta_1$;

(ii) if $\nu < 0$, then these inequalities hold for $|x(t)|_r^\mu + \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds > \Delta_2$.

Hence (see [Efimov and Aleksandrov, 2021]), one can choose positive constants $h_1, h_2, \tilde{\Delta}_1, \tilde{\Delta}_2$ such that

$$\dot{\tilde{V}} \leq -h_1 \tilde{V}^{1+\frac{\nu}{\mu}}$$

for $\nu > 0$ in the domain where $\tilde{V} < \tilde{\Delta}_1$, and

$$\dot{\tilde{V}} \leq -h_2 \tilde{V}^{1+\frac{\nu}{\mu}}$$

for $\nu < 0$ in the domain $\tilde{V} > \tilde{\Delta}_2$. This completes the proof.

Note that the results of this work deal with non-zero homogeneity degree ν , which means that the linear systems (that are homogeneous with zero degree $\nu = 0$ [Efimov and Polyakov, 2021] and mostly studied in the literature [Fridman, 2014]) are not considered.

5 Stability of the perturbed system with distributed delay

Next, consider a perturbed system

$$\dot{x}(t) = F(x(t)) + \int_{t-\tau}^t G(x(s)) ds + \int_{t-\tau}^t R(s, x(s)) ds, \quad (3)$$

where vector function $R(t, x)$ is continuous for $t + \tau \geq 0$ and $x \in \mathbb{R}^n$. Here we do not introduce any additional constraint on the form of dependence of the perturbation R in the time argument t (this will be done in the next sections).

Assumption 2 *The inequalities*

$$|R_i(t, x)| \leq a|x|_r^{r_i+\lambda}, \quad i = \overline{1, n},$$

are valid for $t + \tau \geq 0, x \in \mathbb{R}^n$, where $a > 0, \lambda + r_{\min} > 0$ and $R_i(t, x)$ are components of the vector function $R(t, x)$.

This kind of upper estimates for R can be satisfied if, for example, for each fixed value of t the vector field R is r -homogeneous of the degree λ .

Theorem 2 *Let assumptions 1 and 2 be fulfilled, then*

(i) for $\nu > 0, \lambda > \nu$ the zero solution of (3) is asymptotically stable;

(ii) for $\nu < 0, \lambda < \nu$ solutions of (3) are UUB.

PROOF. Constructing a LKF candidate in the form (2) and considering its derivative along the solutions of the perturbed system, we obtain:

$$\begin{aligned} \dot{\tilde{V}} &= \Xi(x_t) + \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\tau}^t R(s, x(s)) ds \\ &+ \sum_{i,j=1}^n \frac{\partial^2 V(x(t))}{\partial x_i \partial x_j} \int_{t-\tau}^t R_j(s, x(s)) ds \int_{t-\tau}^t (s+\tau-t) G_i(x(s)) ds \\ &\leq -p_1|x(t)|_r^{\mu+\nu} + p_2 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |x(s)|_r^{\lambda+r_i} ds \\ &+ p_3 \sum_{i,j=1}^n |x(t)|_r^{\mu-r_i-r_j} \left(|x(t)|_r^{\nu+r_j} + \int_{t-\tau}^t |x(s)|_r^{\nu+r_j} ds \right. \\ &\quad \left. + \int_{t-\tau}^t |x(s)|_r^{\lambda+r_j} ds \right) \int_{t-\tau}^t |x(s)|_r^{\nu+r_i} ds \\ &+ (\alpha + \beta\tau)|x(t)|_r^{\mu+\nu} - \alpha|x(t-\tau)|_r^{\mu+\nu} - \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds, \end{aligned}$$

where $\Xi(x_t)$ is the derivative of (2) along the solutions of (1) and p_1, p_2, p_3 are positive constants. The subsequent proof is similar to that of Theorem 1.

To analyze the ISS conditions for (1) consider:

$$\dot{x}(t) = F(x(t)) + \int_{t-\tau}^t G(x(s)) ds + d(t), \quad (4)$$

where $d : \mathbb{R} \rightarrow \mathbb{R}^n$ is an exogenous measurable and essentially bounded input, robustness to that we would like to investigate.

Theorem 3 *Let Assumption 1 be fulfilled. Then*

- (i) for $\nu > 0$, (4) is locally ISS;
- (ii) for $\nu < 0$ (4) is practically ISS.

PROOF. As in Theorem 2, construct a LKF candidate in the form (2) and consider its derivative along the solutions of the system (4) under restrictions

$$(i) |d_i(t)| \leq \varrho_0 \tilde{V}^{\frac{r_i + \varrho_1}{\mu}}(t, x_t) \text{ with } \varrho_0 > 0 \text{ and } \varrho_1 > \nu \text{ for } \nu > 0,$$

$$(ii) |d_i(t)| \leq \varrho_0 \tilde{V}^{\frac{r_i + \varrho_2}{\mu}}(t, x_t) \text{ with } \varrho_0 > 0 \text{ and } -r_{\min} < \varrho_2 < \nu \text{ for } \nu < 0,$$

for all $i = \overline{1, n}$, then repeating the same computations as before we get the desired result since \tilde{V} verifies all conditions to be ISS-LKF [Fridman et al., 2008, Pepe et al., 2017] locally or practically, respectively.

The results of theorems 2 and 3 are related: the upper bound on R given in Assumption 2 provides an estimate on the asymptotic gain [Sontag, 2007, Dashkovskiy et al., 2011] (*i.e.*, the upper bound on admissible disturbances d not destroying stability of the origin), which is established in the proof of Theorem 3.

Remark 3 *Theorems 1–3 can be proven by applying the LR approach, as well.*

In the next section we will consider systems with non-stationary perturbations of a special form.

6 Stability and UUB analysis via averaging

In many cases the time dependence of perturbation has periodic or almost periodic nature, which can be effectively used in the analysis improving the results of Theorem 2.

6.1 Application of the Lyapunov–Krasovskii approach

Consider a perturbed system of the form

$$\dot{x}(t) = F(x(t)) + \int_{t-\tau}^t G(x(s))ds + B\left(\frac{t}{\varepsilon}\right) \int_{t-\tau}^t Q(x(s))ds, \quad (5)$$

where ε is a positive parameter, the matrix $B(t)$ is continuous for $t \in (-\infty, +\infty)$, vector function $Q(x)$ is continuous for $x \in \mathbb{R}^n$.

Assumption 3 *Let $\|B(t)\| \leq M$ for $t \in (-\infty, +\infty)$, $M = \text{const} > 0$.*

Remark 4 *Under Assumption 3, there exists a number $\delta \in [0, M]$ such that*

$$\frac{1}{\varepsilon} \left\| \int_{t-\varepsilon}^t B\left(\frac{\theta}{\varepsilon}\right) d\theta \right\| \leq \delta \quad (6)$$

for $t \geq 0$, $\varepsilon > 0$. For instance, $\delta = 0$ if all elements of $B(\cdot)$ are zero-mean 1-periodic signals.

Remark 5 *Under Assumption 3, the estimate*

$$\frac{1}{\varepsilon} \left\| \int_{t-\varepsilon}^t (\theta + \varepsilon - t) B\left(\frac{\theta}{\varepsilon}\right) d\theta \right\| \leq \frac{1}{2} \varepsilon M$$

holds for $t \geq 0$, $\varepsilon > 0$.

Assumption 4 *For any fixed $t \in (-\infty, +\infty)$, $B(t)Q(x)$ is r -homogeneous function of x of the degree $\sigma > -r_{\min}$.*

Under this hypothesis, Assumption 2 is satisfied for $R(t, x) = B(t)Q(x)$ with $\lambda = \sigma$.

Theorem 4 *Let assumptions 1, 3, 4 be fulfilled. Then one can choose positive numbers ε_0 and δ_0 such that if $0 < \varepsilon < \varepsilon_0$ and constant δ in the estimate (6) satisfies the condition $0 \leq \delta < \delta_0$, then*

(i) for $\nu > 0$, $\sigma \geq \nu$ the zero solution of (5) is asymptotically stable;

(ii) for $\nu < 0$, $\sigma \leq \nu$ solutions of (5) are UUB.

PROOF. Applying the approach proposed in [Fridman and Zhang, 2020], choose a LKF for (5) in the form

$$\begin{aligned} \tilde{W}(t, x_t) &= \tilde{V}(t, x_t) - \frac{1}{\varepsilon} \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \\ &\times \int_{t-\varepsilon}^t (\theta + \varepsilon - t) B\left(\frac{\theta}{\varepsilon}\right) d\theta \int_{t-\tau}^t Q(x(s))ds, \end{aligned}$$

where $V(x)$ is a Lyapunov function satisfying the conditions specified in Remark 2 and $\tilde{V}(t, x_t)$ is the functional (2) constructed in the proof of Theorem 1. Then

$$\begin{aligned} c_1 |x(t)|_r^\mu - c_3 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |x(s)|_r^{\nu+r_i} ds + \alpha \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \\ - \varepsilon \hat{c} \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |x(s)|_r^{\sigma+r_i} ds \leq \tilde{W}(t, x_t) \leq c_2 |x(t)|_r^\mu \\ + c_3 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |x(s)|_r^{\nu+r_i} ds + (\alpha + \beta\tau) \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \\ + \varepsilon \hat{c} \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |x(s)|_r^{\sigma+r_i} ds, \end{aligned}$$

where c_1, c_2, c_3, \hat{c} are positive constants.

Differentiating $\tilde{W}(t, x_t)$ along the solutions of (5), we obtain

$$\dot{\tilde{W}} = \left(\frac{\partial V(x(t))}{\partial x} \right)^\top (F(x(t)) + \tau G(x(t)))$$

$$\begin{aligned}
& +(\alpha + \beta\tau)|x(t)|_r^{\mu+\nu} - \alpha|x(t-\tau)|_r^{\mu+\nu} - \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \\
& + \sum_{i,j=1}^n \frac{\partial^2 V(x(t))}{\partial x_i \partial x_j} \left(F_j(x(t)) + \int_{t-\tau}^t G_j(x(s)) ds + \sum_{l=1}^n b_{jl} \left(\frac{t}{\varepsilon} \right) \int_{t-\tau}^t Q_l(x(s)) ds \right) \\
& \quad \left(\int_{t-\tau}^t (s+\tau-t) G_i(x(s)) ds - \frac{1}{\varepsilon} \right. \\
& \quad \left. \times \sum_{k=1}^n b_{ik} \left(\frac{\theta}{\varepsilon} \right) d\theta \int_{t-\tau}^t Q_k(x(s)) ds \right) \\
& \quad + \frac{1}{\varepsilon} \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\varepsilon}^t B \left(\frac{\theta}{\varepsilon} \right) d\theta \int_{t-\tau}^t Q(x(s)) ds \\
& \quad - \frac{1}{\varepsilon} \left(\frac{\partial V(x)}{\partial x} \right)^\top \int_{t-\varepsilon}^t (\theta + \varepsilon - t) B \left(\frac{\theta}{\varepsilon} \right) d\theta (Q(x(t)) - Q(x(t-\tau))) \\
& \leq -(c_4 - \alpha - \beta\tau)|x(t)|_r^{\mu+\nu} - \alpha|x(t-\tau)|_r^{\mu+\nu} - \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \\
& + c_5 \sum_{i,j=1}^n |x(t)|_r^{\mu-r_i-r_j} \left(|x(t)|_r^{\nu+r_j} + \int_{t-\tau}^t |x(s)|_r^{\nu+r_j} ds + \int_{t-\tau}^t |x(s)|_r^{\sigma+r_j} ds \right) \\
& \left(\int_{t-\tau}^t |x(s)|_r^{\nu+r_i} ds + \varepsilon \int_{t-\tau}^t |x(s)|_r^{\sigma+r_i} ds \right) + \delta c_6 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |x(s)|_r^{\sigma+r_i} ds \\
& \quad + \varepsilon c_7 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \left(|x(t)|_r^{\sigma+r_i} + |x(t-\tau)|_r^{\sigma+r_i} \right),
\end{aligned}$$

where $c_i > 0$, $i = \overline{4, 7}$.

Similarly to the proof of Theorem 1, with the aid of Young's and Hölder's inequalities and Lemma 1, it can be shown that if $\alpha + \beta\tau < c_4/4$ and ε, δ are sufficiently small, then

(i) in the case where $\nu > 0$, $\sigma \geq \nu$ there exists $\Delta_1 > 0$ such that

$$\begin{aligned}
& \frac{1}{2} c_1 |x(t)|_r^\mu + \frac{1}{2} \alpha \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \leq \widetilde{W}(t, x_t) \\
& \leq 2c_2 |x(t)|_r^\mu + 2(\alpha + \beta\tau) \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds, \\
& \dot{\widetilde{W}} \leq -\frac{1}{2} c_4 |x(t)|_r^{\mu+\nu} - \frac{1}{2} \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds
\end{aligned}$$

for $|x(t)|_r^\mu + \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds < \Delta_1$;

(ii) in the case where $\nu < 0$, $\sigma \leq \nu$ there exists $\Delta_2 > 0$ such that these inequalities hold for $|x(t)|_r^\mu + \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds > \Delta_2$.

This completes the proof.

Remark 6 It is worth noticing that we failed to prove Theorem 4 on the basis of the LR approach.

6.2 Application of the LR approach

Next, consider a perturbed system of the form

$$\dot{x}(t) = F(x(t)) + \int_{t-\tau}^t G(x(s)) ds + \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) Q(x(s)) ds, \quad (7)$$

where again ε is a positive parameter, the matrix $B(t)$ is continuous for $t \in (-\infty, +\infty)$, and vector function $Q(x)$ is continuous for $x \in \mathbb{R}^n$.

Theorem 5 Let assumptions 1, 3, 4 be fulfilled. Then there exist positive numbers ε_0 and δ_0 such that if $0 < \varepsilon < \varepsilon_0$ and constant δ in the estimate (6) satisfies the condition $0 \leq \delta < \delta_0$, then

(i) for $\nu > 0$, $\sigma \geq \nu$ the zero solution of (7) is asymptotically stable;

(ii) for $\nu < 0$, $\sigma \leq \nu$ solutions of (7) are UUB.

PROOF. The system (7) can be rewritten as follows:

$$\begin{aligned}
\dot{x}(t) = & F(x(t)) + \tau G(x(t)) + \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) ds Q(x(t)) \quad (8) \\
& + \int_{t-\tau}^t (G(x(s)) - G(x(t))) ds \\
& + \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) (Q(x(s)) - Q(x(t))) ds.
\end{aligned}$$

It should be noted that the condition (6) is equivalent to the following one:

$$\left\| \int_{t-1}^t B(u) du \right\| \leq \delta$$

for $t \geq 0$. Therefore,

$$\left\| \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) ds \right\| = \varepsilon \left\| \int_{t/\varepsilon-\tau/\varepsilon}^{t/\varepsilon} B(u) du \right\| \leq \tau\delta + \varepsilon M.$$

Let $V(x)$ be a Lyapunov function possessing the properties specified in Remark 2. Differentiating this function along the solutions of (8), we obtain

$$\begin{aligned}
\dot{V} = & \left(\frac{\partial V(x(t))}{\partial x} \right)^\top (F(x(t)) + \tau G(x(t))) + \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) ds Q(x(t)) \\
& + \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\tau}^t (G(x(s)) - G(x(t))) ds \\
& + \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) (Q(x(s)) - Q(x(t))) ds \\
& \leq -c_1 |x(t)|_r^{\mu+\nu} + c_2 (\tau\delta + \varepsilon M) |x(t)|_r^{\mu+\sigma} \\
& + c_3 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |G_i(x(s)) - G_i(x(t))| ds \\
& + c_4 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |H_i(s, x(s)) - H_i(s, x(t))| ds
\end{aligned}$$

where $H_i(s, x)$ are components of the vector $B(s/\varepsilon) Q(x)$ and c_1, c_2, c_3, c_4 are positive constants.

Assume that $x(t) \neq 0$ and the function $V(x)$ satisfies the LR condition $V(x(\xi)) \leq 2V(x(t))$ for $\xi \in [t-2\tau, t]$. Then $|x(\xi)|_r \leq m|x(t)|_r$ for $\xi \in [t-2\tau, t]$, $m = \text{const} > 1$, and

$$\begin{aligned}
& \int_{t-\tau}^t |G_i(x(s)) - G_i(x(t))| ds \\
& = |x(t)|_r^{\nu+r_i} \int_{t-\tau}^t |G_i(z(t) + \Delta z(t, \xi)) - G_i(z(t))| ds,
\end{aligned}$$

$$\begin{aligned} & \int_{t-\tau}^t |H_i(s, x(s)) - H_i(s, x(t))| ds \\ &= |x(t)|_r^{\sigma+r_i} \int_{t-\tau}^t |H_i(s, z(t) + \Delta z(t, \xi)) - H_i(s, z(t))| ds, \end{aligned}$$

where $z(t) = \Lambda_r^{-1}(|x(t)|_r)x(t)$, $\Delta z(t, \xi) = \Lambda_r^{-1}(|x(t)|_r)(x(\xi) - x(t))$, $i = \overline{1, n}$.

Using the Mean Value Theorem, it is direct to verify that there exists a number $\tilde{m} > 0$ such that

$$\|\Delta z(t, \xi)\| \leq \tilde{m}(|x(t)|_r^\nu + |x(t)|_r^\sigma).$$

Hence, if $\nu > 0$ and $\sigma > 0$ (if $\nu < 0$ and $\sigma < 0$), then

$$\begin{aligned} & \int_{t-\tau}^t |H_i(s, z(t) + \Delta z(t, \xi)) - H_i(s, z(t))| ds \rightarrow 0, \\ & \int_{t-\tau}^t |G_i(z(t) + \Delta z(t, \xi)) - G_i(z(t))| ds \rightarrow 0, \end{aligned}$$

as $|x(t)|_r \rightarrow 0$ (as $|x(t)|_r \rightarrow \infty$), $i = \overline{1, n}$.

Let $c_2(\tau\delta + \varepsilon M) < c_1/2$, then

(i) in the case where $\nu > 0$, $\sigma \geq \nu$ there exists $\Delta_1 > 0$ such that

$$\dot{V} \leq -\frac{1}{3}c_1|x(t)|_r^{\mu+\nu}$$

for $|x(t)|_r < \Delta_1$;

(ii) in the case where $\nu < 0$, $\sigma \leq \nu$ there exists $\Delta_2 > 0$ such that this estimate holds for $|x(t)|_r > \Delta_2$.

This completes the proof.

Remark 7 *It is worth noticing that we failed to prove Theorem 5 on the basis of the LK approach.*

In this section, under additional hypotheses imposed on time dependence of the perturbations, in theorems 4 and 5, the degree of perturbation σ can be bigger/smaller or equal to the degree of the delay-free system ν , while without these restrictions, in Theorem 2, only strict inequalities are allowed between λ (an analogue of σ) and ν .

7 A modification of the averaging technique for $\nu > 0$

In this section, a modified approach to a Lyapunov function and a LKF construction for the systems (5) and (7) will be proposed for the case $\nu > 0$. Using this approach, we will show that, under some additional constraints, less conservative asymptotic stability conditions than those in theorems 4 and 5 can be derived. Unlike results of the previous section, we do not assume that ε is sufficiently small. Moreover, the conditions will be obtained under which the asymptotic stability can be guaranteed even in the case where the degree of perturbations σ is less than one of the unperturbed system ν .

7.1 Application of the LR approach

Consider the system (5) under the following additional constraints.

Assumption 5 *Let $\nu > 0$, $\sigma > 0$ and the function $Q(x)$ be continuously differentiable for $x \in \mathbb{R}^n$.*

Theorem 6 *Let assumptions 1, 3, 4, 5 be fulfilled. Then one can choose positive number δ_0 such that if the constant δ in the estimate (6) satisfies the condition $0 < \delta < \delta_0$, then the zero solution of (5) is asymptotically stable for $\sigma \geq \nu$ and any $\varepsilon > 0$. In the case where*

$$\int_{t-1}^t B(s) ds = 0 \quad \text{for } t \geq 0 \quad (9)$$

the zero solution of (5) is asymptotically stable for $\sigma > \nu/2$ and any $\varepsilon > 0$.

PROOF. Choose a Lyapunov function candidate for (5) in the form

$$V_1(t, x) = V(x) - \frac{\tau}{\varepsilon} \left(\frac{\partial V(x)}{\partial x} \right)^\top \int_{t-\varepsilon}^t (s+\varepsilon-t) B \left(\frac{s}{\varepsilon} \right) ds Q(x),$$

where $V(x)$ is a Lyapunov function possessing the properties specified in Remark 2. Then

$$\begin{aligned} & c_1|x|_r^\mu - c_2|x|_r^{\mu+\sigma} \leq V_1(t, x) \leq c_3|x|_r^\mu + c_2|x|_r^{\mu+\sigma}, \\ & \dot{V}_1 = \left(\frac{\partial V(x(t))}{\partial x} \right)^\top (F(x(t)) + \tau G(x(t))) + \frac{\tau}{\varepsilon} \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \\ & \times \int_{t-\varepsilon}^t B \left(\frac{s}{\varepsilon} \right) ds Q(x(t)) + \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\tau}^t (G(x(s)) - G(x(t))) ds \\ & + \left(\frac{\partial V(x(t))}{\partial x} \right)^\top B \left(\frac{t}{\varepsilon} \right) \int_{t-\tau}^t (Q(x(s)) - Q(x(t))) ds \\ & - \frac{\tau}{\varepsilon} \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\varepsilon}^t (s+\varepsilon-t) B \left(\frac{s}{\varepsilon} \right) ds \frac{\partial Q(x(t))}{\partial x} (F(x(t)) \\ & + \int_{t-\tau}^t G(x(s)) ds + B \left(\frac{t}{\varepsilon} \right) \int_{t-\tau}^t Q(x(s)) ds) \\ & - \frac{\tau}{\varepsilon} \left(F(x(t)) + \int_{t-\tau}^t G(x(s)) ds + B \left(\frac{t}{\varepsilon} \right) \int_{t-\tau}^t Q(x(s)) ds \right)^\top \\ & \left(\frac{\partial^2 V(x(t))}{\partial x^2} \right)^\top \int_{t-\varepsilon}^t (s+\varepsilon-t) B \left(\frac{s}{\varepsilon} \right) ds Q(x(t)) \\ & \leq -c_4|x(t)|_r^{\mu+\nu} + c_5\delta|x(t)|_r^{\mu+\sigma} \\ & + c_6 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |G_i(x(s)) - G_i(x(t))| ds \\ & + c_7 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t |H_i(t, x(s)) - H_i(t, x(t))| ds \\ & + c_8 \sum_{i=1}^n |x(t)|_r^{\mu+\sigma-r_i} \left(|x(t)|_r^{\nu+r_i} + \int_{t-\tau}^t |x(s)|_r^{\mu+r_i} ds + \int_{t-\tau}^t |x(s)|_r^{\sigma+r_i} ds \right) \end{aligned}$$

where $H_i(t, x)$ are components of the vector $B(t/\varepsilon)Q(x)$ and $c_k > 0$, $k = \overline{1, 8}$. It should be noted that if the condition (9) is valid, then $\delta = 0$. The subsequent proof is similar to that of Theorem 5.

7.2 Application of the LK approach

Let us consider the system (7) once again.

Theorem 7 *Let assumptions 1, 3, 4, 5 be fulfilled. Then one can choose positive number δ_0 such that if the constant δ in the estimate (6) satisfies the condition $0 < \delta < \delta_0$, then the zero solution of (7) is asymptotically stable for $\sigma \geq \nu$ and any $\varepsilon > 0$. In the case where the condition (9) is valid the zero solution of (7) is asymptotically stable for $\sigma > \nu/2$ and any $\varepsilon > 0$.*

PROOF. Consider an LKF

$$\begin{aligned} \tilde{V}_1(t, x_t) &= \tilde{V}(t, x_t) \\ &+ \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\tau}^t (s + \tau - t) B \left(\frac{s}{\varepsilon} \right) Q(x(s)) ds \\ &- \frac{\tau}{\varepsilon} \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\varepsilon}^t (s + \varepsilon - t) B \left(\frac{s}{\varepsilon} \right) ds Q(x), \end{aligned}$$

where $V(x)$ is a Lyapunov function satisfying the conditions specified in Remark 2 and $\tilde{V}(t, x_t)$ is the functional (2) constructed in the proof of Theorem 1. We obtain

$$\begin{aligned} &c_1 |x(t)|_r^\mu - c_3 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \int_{t-\tau}^t (|x(s)|_r^{\nu+r_i} + |x(s)|_r^{\sigma+r_i}) ds \\ &+ \alpha \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds - c_4 |x(t)|_r^{\mu+\sigma} \leq \tilde{V}_1(t, x_t) \leq c_2 |x(t)|_r^\mu + c_3 \sum_{i=1}^n |x(t)|_r^{\mu-r_i} \\ &\times \int_{t-\tau}^t (|x(s)|_r^{\nu+r_i} + |x(s)|_r^{\sigma+r_i}) ds + (\alpha + \beta\tau) \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds + c_4 |x(t)|_r^{\mu+\sigma}, \\ \dot{\tilde{V}}_1 &= \left(\frac{\partial V(x(t))}{\partial x} \right)^\top (F(x(t)) + \tau G(x(t))) + \frac{\tau}{\varepsilon} \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\varepsilon}^t B \left(\frac{s}{\varepsilon} \right) ds \\ &\times Q(x(t)) + (\alpha + \beta\tau) |x(t)|_r^{\mu+\nu} - \alpha |x(t-\tau)|_r^{\mu+\nu} - \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \\ &+ \left(F(x(t)) + \int_{t-\tau}^t G(x(s)) ds + \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) Q(x(s)) ds \right)^\top \left(\frac{\partial^2 V(x(t))}{\partial x^2} \right)^\top \\ &\int_{t-\tau}^t (s + \varepsilon - t) \left(G(x(s)) + B \left(\frac{s}{\varepsilon} \right) Q(x(s)) \right) ds \\ &- \frac{\tau}{\varepsilon} \left(F(x(t)) + \int_{t-\tau}^t G(x(s)) ds + \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) Q(x(s)) ds \right)^\top \\ &\left(\frac{\partial^2 V(x(t))}{\partial x^2} \right)^\top \int_{t-\varepsilon}^t (s + \varepsilon - t) B \left(\frac{s}{\varepsilon} \right) ds Q(x(t)) \\ &- \frac{\tau}{\varepsilon} \left(\frac{\partial V(x(t))}{\partial x} \right)^\top \int_{t-\varepsilon}^t (s + \varepsilon - t) B \left(\frac{s}{\varepsilon} \right) ds \frac{\partial Q(x(t))}{\partial x} \\ &\left(F(x(t)) + \int_{t-\tau}^t G(x(s)) ds + \int_{t-\tau}^t B \left(\frac{s}{\varepsilon} \right) Q(x(s)) ds \right) \\ &\leq (\alpha + \beta\tau - c_5) |x(t)|_r^{\mu+\nu} + c_6 \delta |x(t)|_r^{\mu+\sigma} - \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \\ &+ c_7 \sum_{i,j=1}^n |x(t)|_r^{\mu-r_i-r_j} \left(|x(t)|_r^{\nu+r_j} + \int_{t-\tau}^t (|x(s)|_r^{\nu+r_j} + |x(s)|_r^{\sigma+r_j}) ds \right) \\ &\int_{t-\tau}^t (|x(s)|_r^{\nu+r_i} + |x(s)|_r^{\sigma+r_i}) ds \\ &+ c_8 \sum_{j=1}^n |x(t)|_r^{\mu+\sigma-r_j} \left(|x(t)|_r^{\nu+r_j} + \int_{t-\tau}^t (|x(s)|_r^{\nu+r_j} + |x(s)|_r^{\sigma+r_j}) ds \right), \end{aligned}$$

where $c_k > 0$, $k = \overline{1, 8}$.

Under constraint $\alpha + \beta\tau < c_5/4$, with the aid of Young's and Hölder's inequalities and Lemma 1, it is easy to prove that if one of the following conditions is valid:

(i) $\delta > 0$ and $\sigma \geq \nu$;

(ii) $\delta = 0$ and $\sigma > \nu/2$,

then there exists a positive number Δ such that

$$\begin{aligned} &\frac{1}{2} c_1 |x(t)|_r^\mu + \frac{1}{2} \alpha \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \leq \tilde{V}_1(t, x_t) \\ &\leq 2c_2 |x(t)|_r^\mu + 2(\alpha + \beta\tau) \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds, \\ \dot{\tilde{V}}_1 &\leq -\frac{1}{2} c_5 |x(t)|_r^{\mu+\nu} - \frac{1}{2} \beta \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds \end{aligned}$$

for $|x(t)|_r^\mu + \int_{t-\tau}^t |x(s)|_r^{\mu+\nu} ds < \Delta$. This completes the proof.

Remark 8 *Note that the LR approach is used in this section for the system (5) (it was the LK method in Section 7), while for the system (7) the situation is opposite.*

8 Examples

8.1 Vector Rayleigh equation

Assume that behavior of a mechanical system is modeled by the equation

$$\ddot{x}(t) + \frac{\partial W(\dot{x}(t))}{\partial \dot{x}} + \frac{\partial \Pi(x(t))}{\partial x} + \int_{t-\tau}^t \frac{\partial \tilde{\Pi}(x(s))}{\partial x} ds = 0, \quad (10)$$

where $x(t) \in \mathbb{R}^n$, $W(\dot{x})$ is a continuously differentiable for $\dot{x} \in \mathbb{R}^n$ positive definite homogeneous of the degree $\lambda + 1 > 1$ function with respect to the standard dilation (*i.e.*, $\mathbf{r} = (1, \dots, 1)$), $\Pi(x)$ and $\tilde{\Pi}(x)$ are continuously differentiable for $x \in \mathbb{R}^n$ homogeneous of the degree $\rho + 1 > 1$ functions with respect to the standard dilation.

The system (10) is a vector type Rayleigh equation [Rayleigh, 1945] describing the dynamics of mechanical systems with dissipative and potential forces, whereas the term $\int_{t-\tau}^t \partial \tilde{\Pi}(x(s)) / \partial x ds$ can be interpreted as an integral part of a PID-like regulator (see [Formal'sky, 1997, Radaideh and Hayajneh, 2002]).

Let $\lambda = 2\rho/(\rho + 1)$, then the corresponding first-order system

$$\begin{aligned} \dot{x}(t) &= y(t), \quad \dot{y}(t) = -\frac{\partial W(y(t))}{\partial \dot{x}} - \frac{\partial \Pi(x(t))}{\partial x} \\ &- \int_{t-\tau}^t \frac{\partial \tilde{\Pi}(x(s))}{\partial x} ds \end{aligned}$$

is \mathbf{r} -homogeneous of the degree $(\rho - 1)/2$ with respect to the dilation $\mathbf{r} = (r_1, \dots, r_{2n})$, where $r_i = 1$ for $i = \overline{1, n}$, and $r_i = (\rho + 1)/2$ for $i = n + 1, 2n$.

In addition, assume that the function $\Pi(x) + \tau \tilde{\Pi}(x)$ is positive definite. It is known (see [Rouche et al., 1977]) that,

under this assumption, the zero solution of the auxiliary system

$$\dot{x}(t) = y(t), \quad \dot{y}(t) = -\frac{\partial W(y(t))}{\partial \dot{x}} - \frac{\partial \Pi(x(t))}{\partial x} - \tau \frac{\partial \tilde{\Pi}(x(t))}{\partial x}$$

is asymptotically stable.

Applying Theorem 1, we obtain that

(i) for $\rho > 1$ the equilibrium position $x = \dot{x} = 0$ of (10) is asymptotically stable;

(ii) for $\rho < 1$ solutions of (10) are UUB.

Next, consider the associated perturbed system:

$$\begin{aligned} \ddot{x}(t) + \frac{\partial W(\dot{x}(t))}{\partial \dot{x}} + \frac{\partial \Pi(x(t))}{\partial x} + \int_{t-\tau}^t \frac{\partial \tilde{\Pi}(x(s))}{\partial x} ds \\ + B\left(\frac{t}{\varepsilon}\right) \int_{t-\tau}^t Q(x(s)) ds = 0, \end{aligned} \quad (11)$$

where as before we assume that ε is a positive parameter, the matrix $B(t)$ is continuous and bounded for $t \in (-\infty, +\infty)$, vector function $Q(x)$ is continuous for $x \in \mathbb{R}^n$ and homogeneous of the order $\eta > 0$ with respect to the standard dilation.

Using Theorem 4, we obtain that there exist positive numbers ε_0 and δ_0 such that if $0 < \varepsilon < \varepsilon_0$ and constant δ in the estimate (6) satisfies the condition $0 \leq \delta < \delta_0$, then

(i) for $\eta \geq \rho > 1$ the zero solution of (11) is asymptotically stable;

(ii) for $\eta \leq \rho < 1$ solutions of (11) are UUB.

8.2 Damping angular motions of a rigid body

It is worth noting that the approaches developed in this paper can be applied to strongly nonlinear systems that are not homogeneous. To illustrate this case, consider the problem of damping the angular motions of a rigid body.

Let a rigid body be rotating in an inertial space with angular velocity $\omega(t) \in \mathbb{R}^3$ around its center of inertia C . Denote by $Cxyz$ the principal central axes of inertia of the body. The attitude motion of the body under the action of a torque M is modeled by the Euler equations

$$J\dot{\omega}(t) + \omega(t) \times J\omega(t) = M,$$

where $J = \text{diag}\{A_1, A_2, A_3\}$ is the body inertia tensor in the axes $Cxyz$ [Merkin, 1997].

Let the torque M be of the form

$$M = F(\omega(t)) + \int_{t-\tau}^t (D + B(s))U(\omega(s))ds,$$

where $F(\omega) \in \mathbb{R}^3$ is a continuous for $\omega \in \mathbb{R}^3$ homogeneous of the degree $\rho > 1$ with respect to the standard dilation

function, $U(\omega) \in \mathbb{R}^3$ is a control vector, $D \in \mathbb{R}^{3 \times 3}$ is a constant matrix, $B(t) \in \mathbb{R}^{3 \times 3}$ is a continuous for $t \in (-\infty, +\infty)$ matrix that characterizes control deviations from a prescribed values caused by non-stationary disturbances, τ is a positive constant delay.

We are going to design a control law $U(\omega)$ providing the asymptotic stability of the equilibrium position $\omega = 0$ of the body.

With the aid of arguments similar to those used in the proof of Theorem 7, it is easy to verify that, under the following conditions:

(i) the matrix $B(t)$ is bounded for $t \in (-\infty, +\infty)$;

(ii) $\left\| \int_{t-1}^t B(s)ds \right\| \leq \delta$ for $t \geq 0$, where δ is a sufficiently small positive constant;

(iii) $U(\omega)$ is continuously differentiable for $\omega \in \mathbb{R}^3$;

(iv) $U(\omega)$ is homogeneous function of the degree ρ with respect to the standard dilation;

(v) the function $\omega^\top (F(\omega) + \tau DU(\omega))$ is negative definite,

the equilibrium position $\omega = 0$ of the corresponding closed-loop system is asymptotically stable.

9 Conclusion

For a nonlinear system with distributed delay and homogeneous right-hand side (in the delay-free setting), several conditions of robust stability in the presence of time-varying perturbations weighted by a nonlinear functional gain are obtained. In Theorem 1 it is demonstrated that in the studied case the zero solution is either locally asymptotically stable (for positive homogeneity degree) or practically globally asymptotically stable (for negative degree). Theorems 2 and 3 discover next generic robustness properties (in ISS sense) of the system without using the averaging approach (without assuming certain periodicity of the perturbations). Theorems 4–7 formulate several sets of restrictions on the time-varying perturbations, based on the averaging techniques, improving the result of Theorem 2 (the homogeneity degree of the perturbation can be equal to one of the system itself, or in the case of positive degree, even smaller). The results are based on utilization of LK and LR approaches, and interestingly to note, in many cases only one of these tools can be applied. To show efficiency of the approach, the models of mechanical systems are explored, described by a vector Rayleigh equation and Euler equation of angular motions for a rigid body.

References

- A.Yu. Aleksandrov and A.P. Zhabko. On the asymptotic stability of solutions of nonlinear systems with delay. *Siberian Mathematical Journal*, 53(3):393–403, 2012.
- A.Yu. Aleksandrov and A.P. Zhabko. Delay-independent stability of homogeneous systems. *Applied Mathematics Letters*, 34(8):43–50, 2014.
- A.Yu. Aleksandrov, A.P. Zhabko, and V.S. Pecherskiy. Complete type functionals for some classes of homogeneous differential-difference systems. In *Proc. 8th international conference "Modern methods of applied mathematics, control theory and computer technology"*, pages 5–8, Voronezh, 2015. in Russian.
- I. M. Anan'evskii and V. B. Kolmanovskii. On stabilization of some control systems with an aftereffect. *Automation and Remote Control*, 9:1174–1181, 1989.
- A. Bacciotti and L. Rosier. *Liapunov Functions and Stability in Control Theory*, volume 267 of *Lecture Notes in Control and Inform. Sci.* Springer, Berlin, 2001.
- N. N. Bogoliubov and Y. A. Mitropolsky. *Asymptotic Methods in the Theory of Non-Linear Oscillations*. Gordon and Breach, New York, 1961.
- S.N. Dashkovskiy, D.V. Efimov, and E.D. Sontag. Input to state stability and allied system properties. *Automation and Remote Control*, 72(8):1579–1614, 2011.
- D. Efimov and A. Aleksandrov. Analysis of robustness of homogeneous systems with time delays using Lyapunov-Krasovskii functionals. *Int. J. Robust and Nonlinear Control*, 31:3730–3746, 2021.
- D. Efimov and E. Fridman. Converse Lyapunov-Krasovskii theorem for ISS of neutral systems in Sobolev spaces. *Automatica*, 118(8):109042, 2020.
- D. Efimov and A. Polyakov. Finite-time stability tools for control and estimation. *Foundations and Trends in Systems and Control*, 9(2-3):171–364, 2021. doi: 10.1561/26000000026.
- D. Efimov, W. Perruquetti, and J.-P. Richard. Development of homogeneity concept for time-delay systems. *SIAM J. Control Optim.*, 52(3):1403–1808, 2014.
- D. Efimov, A. Polyakov, W. Perruquetti, and J.-P. Richard. Weighted homogeneity for time-delay systems: Finite-time and independent of delay stability. *IEEE Trans. Automatic Control*, 61(1):210–215, 2016.
- D. Efimov, R. Ushirobira, J.A. Moreno, and W. Perruquetti. Homogeneous Lyapunov functions: from converse design to numerical implementation. *SIAM J. Control Optimization*, 56(5):3454–3477, 2018.
- Q. Feng, S.K. Nguang, and W. Perruquetti. Dissipative stabilization of linear systems with time-varying general distributed delays. *Automatica*, 122:109227, 2020. doi: <https://doi.org/10.1016/j.automat.2020.109227>.
- Z. Feng and J. Lam. Integral partitioning approach to robust stabilization for uncertain distributed time-delay systems. *Int. J. Robust. Nonlinear Control*, 22:676–689, 2012.
- A. Formal'sky. On a modification of the PID controller. *Dyn. Control*, 7(3):269–277, 1997. URL <https://doi.org/10.1023/A:1008202618580>.
- E. Fridman. *Introduction to Time-Delay Systems: Analysis and Control*. Birkhäuser, Basel, 2014.
- E. Fridman and J. Zhang. Averaging of linear systems with almost periodic coefficients: A time-delay approach. *Automatica*, 122:109287, 2020. doi: <https://doi.org/10.1016/j.automat.2020.109287>.
- Emilia Fridman, Michel Dambrine, and Nima Yeganefar. On input-to-state stability of systems with time-delay: A matrix inequalities approach. *Automatica*, 44(9):2364–2369, 2008. doi: <https://doi.org/10.1016/j.automat.2008.01.012>.
- K. Gu, V.L. Kharitonov, and J. Chen. *Stability of Time-Delay Systems*. Control Engineering. Birkhäuser, Boston, 2003.
- J.K. Hale. *Theory of Functional Differential Equations*. Springer-Verlag, 1977.
- Laurentiu Hetel, Christophe Fiter, Hassan Omran, Alexandre Seuret, Emilia Fridman, Jean-Pierre Richard, and Silviu Iulian Niculescu. Recent developments on the stability of systems with aperiodic sampling: An overview. *Automatica*, 76:309–335, 2017. doi: <https://doi.org/10.1016/j.automat.2016.10.023>.
- I. Karafyllis, M. Malisoff, F. Mazenc, and P. Pepe, editors. *Recent Results on Nonlinear Delay Control Systems*, volume 4 of *Advances in Delays and Dynamics*. Springer International Publishing, 2016.
- H. K. Khalil. *Nonlinear Systems*. Prentice-Hall, Upper Saddle River NJ, 2002.
- M. M. Khapaev. *Averaging in Stability Theory*. Kluwer, Dordrecht, 1993.
- V. Kolmanovskii and A. Myshkis. *Introduction to the Theory and Applications of Functional Differential Equations*, volume 463 of *Mathematics and Its Applications*. Springer, 1999.
- D. R. Merkin. *Introduction to the Theory of Stability*. Springer, New York, 1997.
- P. Pepe, I. Karafyllis, and Z.-P. Jiang. Lyapunov-Krasovskii characterization of the input-to-state stability for neutral systems in Hale's form. *Systems & Control Letters*, 102:48–56, 2017. doi: <https://doi.org/10.1016/j.sysconle.2017.01.008>.
- S.M. Radaideh and M.T. Hayajneh. A modified PID controller (PII σ β D). *Journal of the Franklin Institute*, 339(6):543–553, 2002.
- John William Strutt Rayleigh. *The Theory of Sound*, volume 1 and 2. Dover, 1945.
- J.-P. Richard. Time-delay systems: an overview of some recent advances and open problems. *Automatica*, 39:1667–1694, 2003.
- L. Rosier. Homogeneous Lyapunov function for homogeneous continuous vector field. *Systems & Control Lett.*, 19:467–473, 1992.
- N. Rouche, P. Habets, and M. Laloy. *Stability Theory by Liapunov's Direct Method*. Springer, New York, 1977.
- O. Solomon and E. Fridman. New stability conditions for systems with distributed delays. *Automatica*, 49(11):3467–3475, 2013.
- E.D. Sontag. Input to state stability: Basic concepts and

- results. In P. Nistri and G. Stefani, editors, *Nonlinear and Optimal Control Theory*, pages 163–220. Springer-Verlag, Berlin, 2007.
- Andrew R. Teel. Connections between Razumikhin-type theorems and the ISS nonlinear small gain theorem. *IEEE Trans. Automat. Control*, 43(7):960–964, 1998.
- L. Xie, E. Fridman, and U. Shaked. A robust H_∞ control of distributed delay systems with application to combustion control. *IEEE Trans. on Automatic control*, 46(12):1930–1935, 2001.
- J. Zhang and E. Fridman. L2-gain analysis via time-delay approach to periodic averaging with stochastic extension. *Automatica*, 137:110126, 2022.
- K. Zimenko, D. Efimov, A. Polyakov, and W. Perruquetti. A note on delay robustness for homogeneous systems with negative degree. *Automatica*, 79(5):178–184, 2017.
- V.I. Zubov. On systems of ordinary differential equations with generalized homogenous right-hand sides. *Izvestia vuzov. Mathematica.*, 1:80–88, 1958. in Russian.