

# **On approximation with spline generated framelets** Rémi Gribonval, Morten Nielsen

# **To cite this version:**

Rémi Gribonval, Morten Nielsen. On approximation with spline generated framelets. Constructive Approximation, 2004, 20 (2), pp.207-232. 10.1007/s00365-003-0532-7. inria-00567338

# **HAL Id: inria-00567338 <https://inria.hal.science/inria-00567338>**

Submitted on 20 Feb 2011

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

# ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS

#### R. GRIBONVAL AND M. NIELSEN

ABSTRACT. We characterize the approximation spaces associated with the best n-term approximation in  $L_p(\mathbb{R})$  by elements from a tight wavelet frame associated with a spline scaling function. The approximation spaces are shown to be interpolation spaces between  $L_p$  and classical Besov spaces, and the result coincide with the result for nonlinear approximation with an orthonormal wavelet with the same smoothness as the spline scaling function. We also show that, under certain conditions, the Besov smoothness can be measured in terms of the sparsity of expansions in the wavelet frame, just like the nonredundant wavelet case. However the characterization now holds even for wavelet frame systems that do not have the usually required number of vanishing moments, e.g. for systems built through the Unitary Extension Principle, which can have no more than one vanishing moment. Using these results, we describe a fast algorithm that takes as input any function and provides a near sparsest expansion of it in the framelet system as well as approximants that reach the optimal rate of nonlinear approximation. Together with the existence of a fast algorithm, the absence of need for vanishing moments may have an important qualitative impact for applications to signal compression, as high vanishing moments usually introduce Gibbs-type phenomenon (or "ringing" artifacts) in the approximants.

#### 1. INTRODUCTION

We are interested in characterizing the approximation spaces associated with the best  $n$ term approximation in Lp  $\mu$  ,  $\mu$  is the time  $\mu$  tight wavelet from a tight wavelet from a tight wavelet frame. For orthonormal and bi-orthogonal wavelets such spaces are known to be characterized by the sparsity of the wavelet coefficients, and they turn out to be (essentially) Besov spaces [15]. Tight wavelet frames are different from orthonormal wavelets in one important respect; they are (in general) redundant systems but with the same fundamental structure as wavelet systems.

Most constructions of tight wavelet frames based on a multiresolution structure are spline based since it helps make the construction easy and transparent. In the present paper we will keep up this tradition and only consider wavelet frames in  $L_2$  with an underlying multiresolution structure generated by a B-spline. For such systems we characterize the approximation spaces and prove that they are characterized by the sparsity of the framelet representation. Because the framelet system is redundant, the sparsity is defined by searching over all possible representations and choosing the "most sparse" one. As we will show, this leads to a characterization of the approximation spaces (essentially) in terms of Besov spaces just like the nonredundant wavelet case. However, the characterization now holds even for framelet systems that do not have the number of vanishing moments usually required by the theory, because the sparsity is no longer defined in terms of the inner products with the framelets, or analysis coefficients, but in terms of the optimized synthesis coefficients.

Date: January 17, 2002.

Key words and phrases. Wavelet frame, framelets, spline multiresolution, bi-orthogonal spline wavelet, nonlinear approximation, redundant system, adaptive sparse expansions, direct and inverse theorems, Besov spaces.

Research supported by NSF grant no. DMS-9872890.

# ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 2

Characterization of approximation spaces for framelet systems has not only purely theoretical interest, but will also provide some guidance to which class of functions/objects can be compressed efficiently by (nonlinear) framelet expansions. It has already been demonstrated that wavelets do a good job compressing images  $[12]$ , but are framelets "better" in any quantitative way ? The results in this paper show that no substantial asymptotic gain can be hoped for (that is to say no improvement of the distortion-rate curve at high bitrates), but there may be a substantial gain for approximations with few framelets *(i.e.* compression with a small bitbudget) compared to approximation with few wavelets. This gain may be quantitative (smaller distortion in Let  $\sim$  ) as well as well as well assumed that we can use  $\sim$ framelets with only one vanishing moment, we may obtain approximants which yield less Gibbs phenomenon (*i.e.* less "ringing" artifacts) than with wavelets.

The structure of the paper is as follows: Section 2 contains the basic definitions and results needed for the paper. First, we introduce the framelet systems based on the B-spline multiresolution analysis. In Section 2.3 some basic facts about bi-orthogonal wavelets are discussed and we recall the definition of the Chui-Wang semi-orthogonal wavelet that will play an important role later. In the last part of Section 2 we dene the approximation spaces associated with best n-term approximation with elements from the framelet system or from oversampled versions thereof. Abstract smoothness spaces associated with the framelet system are also introduced, and we recall the definition of Besov spaces as well as some elements of interpolation theory.

In Section 3 we prove that a nice bi-orthogonal wavelet can be build in such a way that it has a finite expansion in the twice oversampled framelet system. The wavelet will turn out to be either the Chui-Wang semi-orthogonal spline wavelet or, in some cases, a slight modication thereof.

Section 4 contains direct and inverse estimates for approximation with the framelet system. The estimates are used to completely characterize the approximation spaces associated with best n-term approximation in Lp with elements from the twice oversampled framelet system. The direct estimate (Jackson inequality) is based on the expansion of the Chui-Wang type wavelet in the oversampled framelet system obtained in the previous section, and the inverse estimate (Bernstein inequality) is based on Petrushev's results on approximation with freeknot splines. Similar estimates are also obtained for the framelet system itself (i.e. without oversampling) but these results are limited by the number of vanishing moments of the framelet system which may be only one. Section 4 also contains a characterization of certain Besov spaces in terms of sparsity of the (non-unique) framelet coefficients.

Section 5 contains some more results and some open problems. In particular, we show that in some, but not all cases, the direct estimates in Section 4 hold for the framelet system itself, and not only for the associated twice oversampled system. Finally, there is a conclusion in Section 6 where we discuss practical algorithms and applications to signal compression.

# 2. Framelets and nonlinear approximation

2.1. Tight wavelet frames. We will briefly touch upon some of the main ideas in the construction of multiresolution analysis (MRA) based tight wavelet frames, see [10, 25, 24]. For historical notes on this construction, we refer the reader to [10]. Such MRA based tight wavelet frames are called **framelets**. We begin by introducing some basic notation and general assumptions.

Let  $\tau = (\tau^*, \tau^*, \ldots, \tau^*)$  be a vector of  $2\pi$ -periodic measurable functions with  $\tau^*$  the mask of a refinable scaling function  $\phi$  of a MRA  $\{V_j\}_{j\in\mathbb{Z}}$ . We assume that  $\phi$  satisfies  $\lim_{\xi\to 0} \widehat{\phi}(\xi)=1$ and there exist  $0 < A \leq B < \infty$  such that  $A \leq \sum_{k \in \mathbb{Z}} |\phi(\cdot - 2\pi k)|^2 \leq B$ , i.e.  $\phi$  generates a

ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 3

**Riesz basis** of the scaling space  $V_0$  of the MRA. We associate the "wavelets"  $\Psi = {\psi^{\ell}}_{\ell=1}^{L}$  $-1$ to  $\tau$  by letting  $\psi^*(z\xi) = \tau^*(\xi)\phi(\xi)$ . For any finite set F of functions in  $L_2$  we consider the following dictionaries of functions:

•  $X_R(F) := \{2^{j/2}\eta(2^j \cdot -k/R)\}_{i,k \in \mathbb{Z}}^{\infty}$ , t the integer  $R \geq 1$  is an "oversampling ratio".

$$
\bullet\ \underline{X_\infty}(F):=\{2^{j/2}\eta(2^j\cdot-b)\}_{j\in\mathbb{Z},b\in\mathbb{R}}^{j\in T}.
$$

$$
\bullet\,\,X(F):=\{a^{1/2}\eta(a\cdot-b)\}_{a,b\in\mathbb{R}}^{ \eta\in F}
$$

We will simplify the notations by writing  $X(F)$  instead of  $X_1(F)$  and, for single generator systems,  $X(\psi)$  instead of  $X(\{\psi\})$ . The following is the fundamental tool to construct framelets:

**Theorem 2.1** (The Oblique Extension Principle (OEP) [10]). Suppose there exists a  $2\pi$ periodic function - that is non-negative, essential ly bounded, continuous at the origin with -(0) = 1. If for every <sup>2</sup> [; ] and 2 f0; g,

(2.1) 
$$
\Theta(2\xi)\tau^0(\xi)\overline{\tau^0(\xi+\nu)} + \sum_{\ell=1}^L \tau^{\ell}(\xi)\overline{\tau^{\ell}(\xi+\nu)} = \begin{cases} \Theta(\xi), & \nu=0, \\ 0, & otherwise, \end{cases}
$$

then the wavelet system  $X(\Psi)$  defined by  $\tau$  is a tight wavelet frame.

The system  $X(\Psi)$  is usually called the **framelet system generated by**  $\Psi$ .

Remark 2.2. Theorem 2.1 can be stated in slightly more generality by introducing the notion of a spectrum for the scaling space  $V_0$  and dropping the requirement that  $\phi$  generates a Riesz basis, see [10], but this more general construction will not be used in this paper.

Remark 2.3. For - 1, Theorem 2.1 reduces to the Unitary Extension Principle (UEP) of Ron and Shen [25].

Conversely, if we are given a tight wavelet frame  $\Psi$  associated to  $(\tau^*,\ldots,\tau^-)$  we can define the function  $\mathbf{f}(\mathbf{f})$  function  $\mathbf{f}(\mathbf{f})$  function  $\mathbf{f}(\mathbf{f})$  function  $\mathbf{f}(\mathbf{f})$  function  $\mathbf{f}(\mathbf{f})$ 

(2.2) 
$$
\Theta(\xi) := \sum_{j=0}^{\infty} \sum_{\ell=1}^{L} |\tau^{\ell}(2^{j}\xi)|^{2} \prod_{m=0}^{j-1} |\tau^{0}(2^{m}\xi)|^{2},
$$

which satisfies Property (2.1) and is  $2\pi$ -periodic, see [10] for more details.

We will now specialize our setup to the special case of framelets based on B-spline generated MRAs.

2.2. B-spling generated framework framework and  $\pm$  2.1 and 100.000 and let  $\tau$  be the r-th order order order cardinal B-spline defined recursively by  $\phi_1(x) = \chi_{[0,1)}(x)$  and  $\phi_{r+1} = \phi_r * \phi_1$ . The function  $\phi_r$ is a scaling function for a MRA  $V_i := \text{clos}_{L_2} \{ \text{span} \{ \phi_r(2^j \cdot - k) \}_{k \in \mathbb{Z}} \}, V_i \subset V_{i+1}$  with Fourier transform

(2.3) 
$$
\widehat{\phi}_r(\xi) = \left(\frac{\sin(\xi/2)}{\xi/2}\right)^r e^{-ir\xi}
$$

and rennement mask  $\tau_r^*(\xi) = m_r^*(e^{-\xi})$  where rr

$$
(2.4) \t\t\t m_r^0(z) = \left(\frac{1+z}{2}\right)^r.
$$

Let  $\Psi \, = \, \{\psi^*\}_{\ell=1}^\infty$  be a nnite set of **compactly supported** generators of a tight wavelet frame. Unless otherwise specied, we will always assume that the frame is associated with the **NIRA generated by the B-spline**  $\varphi_r$ , and that the masks  $(7^-, \ldots, 7^+)$  are trigonometric

ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS  $\,$   $\,$   $\,$   $\,$   $\,$   $\,$ 

polynomials. We denote by  $m^{\ell}(z) = \sum_{k \in \mathbb{Z}} a_k^{\ell} z^k, 0 \leq l \leq L$ , the Laurent polynomial such that  $\tau^*(\xi) = m^*(e \to)$ . For z on the unit circle,  $z = z$  fience we can write  $m^*(z) =$  $m^{\ell}(z^{-1}) := \sum_{k \in \mathbb{Z}} a_k^{\ell} z^{-k}$ . Note that  $X_R(\Psi)$  and  $X(\Psi)$  are unchanged when a framelet  $\psi^{\ell}$  in  $\Psi$  is replaced by one of its shifts  $\psi^*(\cdot - \kappa)$ , for some  $\kappa \in \mathbb{Z}$ . Hence we can always assume that the masks are pure polynomials with  $m(y) \neq 0, \ i.e. \ a_k = 0, \kappa \le -1$  and  $a_0 \neq 0$ . We let

$$
(2.5) \tG(z) := \gcd\{m^{\ell}(z), 1 \le \ell \le L\}
$$

this will be used in Section 3. As r is piecewise polynomial with r  $\mathcal{H} = \mathcal{H}$  . The interval random and rnonzero rno polynomial pieces of degree  $r - 1$ , each  $\psi^+$  is also piecewise polynomial with at most

$$
\kappa = (r+1) \cdot \max \deg(\tau^{\ell})_{\ell=1}^{L}
$$

knots.

2.3. Bi-orthogonal B-spline wavelets. Throughout this paper, we only consider bi-orthogonal wavelet systems  $(\psi, \tilde{\psi})$  that are MRA based, i.e. such that there exists an associated biorthogonal scaling function pair  $(\phi, \phi)$  that generates a pair of MRA's  $\{V_i\}$  and  $\{V_i\}$  for which Mallat's algorithm holds:

(2.7) 
$$
\sum_{k \in \mathbb{Z}} \langle f, \widetilde{\phi}_{j+1,k} \rangle \phi_{j+1,k} = \sum_{k \in \mathbb{Z}} \langle f, \widetilde{\phi}_{j,k} \rangle \phi_{j,k} + \sum_{k \in \mathbb{Z}} \langle f, \widetilde{\psi}_{j,k} \rangle \psi_{j,k}.
$$

We refer to [8, 9] for more details on such bi-orthogonal systems.

We first recall Chui and Wang's construction [6] of a bi-orthogonal spline wavelet pair  $(\psi_r, \psi_r)$  based on a scaling function pair  $(\psi_r, \psi_r)$ , where  $\psi_r$  is the B-spline of order r and  $\psi_r$ has compact support. The region of the region  $\mathbb{R}^n$  is given by  $\mathbb{R}^n$  is given by  $\mathbb{R}^n$  $\psi_r(z\zeta) := m_r(e^{-z\zeta})\phi_r(\zeta)$ , with mask

(2.8) 
$$
m_r(z) := \left(\frac{1-z}{2}\right)^r \times \sum_{k=0}^{2r-2} \phi_{2r}(k+1)(-z)^k.
$$

The dual functions are given explicitly by

(2.9) 
$$
\widehat{\widetilde{\phi}_r}(\xi) := \frac{\widehat{\phi_r}(\xi)}{\sum_{k \in \mathbb{Z}} |\widehat{\phi_r}(\xi + 2\pi k)|^2} \quad \text{and} \quad \widehat{\widetilde{\psi_r}}(\xi) := \frac{\widehat{\psi_r}(\xi)}{\sum_{k \in \mathbb{Z}} |\widehat{\psi_r}(\xi + 2\pi k)|^2}.
$$

From (2.8) and (2.9) it is easy to verify that  $\psi_r$  and  $\psi_r$  both have r vanishing moments and are both splines of order r, hence they are in  $C^{r-\varepsilon}(\mathbb{R})$  for every  $\varepsilon > 0$ . Also from (2.9),  $\widetilde{\phi}_r$ ris a spillie of order  $r$ , and in this particular case,  $v_j = v_j$ . Moreover,  $\varphi_r$  and  $\varphi_r$  both have exponential decay which can be verified directly from the expressions in (2.9) and, e.g.,  $\mu$ Proposition 5.4.1].

It is known [5] that these bi-orthogonal wavelets are *semi-orthogonal*, that is to say  $V_{i+1}$  =  $\mathcal{N}$  , with  $\mathcal{N}$  with  $\mathcal{N}$  with  $\mathcal{N}$  with  $\mathcal{N}$  with  $\mathcal{N}$  with  $\mathcal{N}$ 

(2.10) 
$$
W_j := \operatorname{clos}_{L_2} \left\{ \operatorname{span} \{ \psi_r(2^j \cdot -k) \}_{k \in \mathbb{Z}} \right\} = \operatorname{clos}_{L_2} \left\{ \operatorname{span} \{ \widetilde{\psi}_r(2^j \cdot -k) \}_{k \in \mathbb{Z}} \right\},
$$

hence Mallat's algorithm  $(2.7)$  holds for this bi-orthogonal system.

# ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS  $5$

2.4. **Nonlinear approximation with dictionaries.** We will be interested in characterizing the approximation spaces associated with the framelet system  $X(\Psi)$  and certain oversampled versions of it. We will also consider the corresponding spaces for the system  $X(\phi)$ . First we need some notation to clarify the definition of the relevant approximation spaces. By a dictionary in Lp we measure in  $\mu$  collection of non-zero elements of  $\mu$ . The approximation of  $\mu$ spaces for a general dictionary D in Lp are defined as follows. D in Le are defined as follows. D in Le are defined as follows.

**Definition 2.4** (Approximation spaces). For D a dictionary in  $L_p$  we let  $\Sigma_n(\mathcal{D})$  be the set of all functions S of the form  $S = \sum_{I \in \Lambda_n} c_I g_I$ , where each  $g_I \in \mathcal{D}$  and  $\#\Lambda_n \leq n$ . The error of the best n-term approximation of  $f$   $\in$   $\mathbb{R}$  is the proportion of  $f$ 

$$
\sigma_n(f, \mathcal{D})_p = \inf_{S \in \Sigma_n(\mathcal{D})} ||f - S||_p,
$$

and the approximation space  $\mathcal{A}_q^{\prime} (L_p, \nu)$  is defined by

$$
|f|_{\mathcal{A}_q^{\gamma}(L_p,\mathcal{D})} := \bigg( \sum_{n=1}^{\infty} \left( n^{\gamma} \sigma_n(f,\mathcal{D})_p \right)^q \frac{1}{n} \bigg)^{1/q} < \infty,
$$

and (quasi)normed by  $||J||A_a(L_p,D) = ||J||p + |J|A_a(L_p)$ , for  $0 \leq q$ ,  $j \leq \infty$  with the  $\vee q$  norm replaced with the sup-norm when  $q = \infty$ 

One of the nice properties of orthonormal wavelets is that there is an equivalence between the rate of best n-term wavelet approximation of a given function, the sparsity of the wavelet representation of that function, and the smoothness of that function. The same is true for framelet systems of the type considered in this paper, however the relation between rate of approximation, sparsity and smoothness is slightly different. Since the framelet system is redundant, it is not immediately clear what is meant by a sparse representation. As will be shown in section 4 we have to search all possible representations of a given function and choose the one that is the "most sparse", and this representation will correspond to smoothness measured in the Besov (quasi)norm.

**Definition 2.5** (Abstract smoothness spaces). For  $\mathcal{D} = \{g_k, k \in \mathbb{Z}\}\$ a countable quasi**normalized** dictionary in  $L_p, \tau \in (0,\infty)$  and  $q \in (0,\infty],$  we let  $\mathcal{N}_q(L_p, D, M)$  denote the set

$$
\operatorname{clos}_{L_p}\bigg\{f\in L_p\,|\,\exists \Lambda\subset\mathbb{N},|\Lambda|<\infty,\,f=\sum_{k\in\Lambda}c_kg_k,\,\|\{c_k\}\|_{\ell_q^{\tau}}\leq M\bigg\}.
$$

Then we define

$$
\mathcal{K}^\tau_q(L_p, \mathcal{D}) := \bigcup_{M > 0} \mathcal{K}^\tau_q(L_p, \mathcal{D}, M),
$$

with

$$
|f|_{\mathcal{K}_q^{\tau}(L_p,\mathcal{D})}=\inf\{M:f\in\mathcal{K}_q^{\tau}(L_p,\mathcal{D},M)\}.
$$

*Remark* 2.6. By abuse of notation we will denote  $\mathcal{N}_q(L_p, D)$  even when D is not quasinormalized, simply meaning that one should replace D with  $\{\lambda(g)g, g \in \mathcal{D}\}\,$ , where  $c \leq$  $\| \lambda(g)g \|_p \leq C$  for some constants  $0 \leq c \leq C \leq \infty$ . For example, while  $\Lambda(\Psi) = \{2^{j\prime - \psi} (2^j + 1) \}$  $(-\kappa)\}_{i,k\in\mathbb{Z}}$  is obviously quasi-normalized in  $L_2$ , we have to replace it with  $\{Z^{j+r}\psi^-(Z^{j}+\kappa)\}_{i,k\in\mathbb{Z}}$ for the definition of  $\mathcal{N}_q(L_p, \Lambda(\Psi))$  when  $p \neq 2$ .

Besov spaces are essentially the natural spaces related to nonlinear wavelet approximation, and we will use them extensively in this paper. We recall here their definition.

ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 6

**Definition 2.7** (Besov spaces). Let  $\alpha > 0, l = |\alpha| + 1$  and

$$
\omega_l(f,t)_p = \sup_{0 < h \le t} \left\| \sum_{k=0}^l \binom{l}{k} (-1)^{l-k} f(\cdot - kh) \right\|_p
$$

the *l*-th order  $L_p$ -modulus of smoothness. We let

$$
|f|_{B_q^{\alpha}(L_p)} := \left(\int_0^{\infty} [t^{-\alpha} \omega_l(f,t)_p]^q \frac{dt}{t}\right)^{1/q}, 0 < q < \infty,
$$

with the  $L_q(a\tau/\tau)$  horm replaced with the sup-norm when  $q = \infty$ . The Besov space  $B_q^-(L_p)$ is defined as

$$
B_q^{\alpha}(L_p) := \{ f : ||f||_{B_q^{\alpha}(L_p)} := ||f||_p + |f|_{B_q^{\alpha}(L_p)} < \infty \}.
$$

Remark 2.8. The reader can verify by direct computation that on the Sobolev embedding line,  $1/T = \alpha + 1/p$ , the Besov semi-(quasi)norm behaves like  $|J|_{B_r^\alpha(L_\tau)} = \beta^{1-\tau_F} \|J(\beta \cdot)\|_{B_r^\alpha(L_\tau)}$ under dilation by  $\beta > 0$ . This fact will be crucial in the proof of Proposition 4.4.

2.5. Elements of interpolation theory. It is well known that the main tool in the characterization of  $\mathcal{A}_s^{\prime}(L_p,\, D)$  comes from the link between approximation theory and interpolation stheory (see e.g. [16, Theorem 9.1, Chapter 7]). The Jackson inequality

$$
(2.11) \qquad \sigma_n(f, \mathcal{D})_p \leq C n^{-\alpha} |f|_{B_r^{\alpha}(L_\tau)}, \qquad \forall f \in B_\tau^{\alpha}(L_\tau), \forall n \geq 1
$$

and the Bernstein inequality

$$
(2.12) \t\t |S|_{B^{\alpha}_{\tau}(L_{\tau})} \leq C' n^{\alpha} ||S||_{p}, \t\t \forall S \in \Sigma_{n}(\mathcal{D})
$$

(with some constants C and C' independent of f, S and n) imply respectively the continuous embedding  $(L_p, B^{\pm}_{\tau}(L_{\tau}))_{\gamma/\alpha, q} \hookrightarrow A^{\pm}_{q}(L_p, D)$  and the converse embedding  $A^{\pm}_{q}(L_p, D) \hookrightarrow$  $(L_p, B_\tau^-(L_\tau))_{\gamma/\alpha,q}$  for all  $0 \leq \gamma \leq \alpha$  and  $q \in (0,\infty]$ . The notation  $V \hookrightarrow W$  means that the two (quasi)normed spaces V and W satisfy V W and there is a constant C < <sup>1</sup> such that  $\|\cdot\|_W \leq C \|\cdot\|_V.$ 

# 3. EXPANDING A BI-ORTHOGONAL SPLINE WAVELET IN THE FRAMELET SYSTEM

We are going to show in this section that there exist a nice bi-orthogonal spline wavelet that can be written as a finite linear combination of framelets from the **twice oversampled** system  $X_2(\Psi)$ . The following is the main result of this section.

**Theorem 3.1.** Assume  $X(\Psi)$  is a tight framelet system based on the B-spline of order r, with fundamental function  $\Theta\geq c$  for some  $c>0.$  There exist coefficients  $\{p_k^-,1\leq \ell\leq L,0\leq \ell\leq L\}$  $k \leq K - 1$  such that

(3.1) 
$$
\psi(x) := \sum_{\ell=1}^{L} \sum_{k=0}^{K-1} p_k^{\ell} \psi^{\ell}(x - k/2)
$$

and

(3.2) 
$$
\widehat{\widetilde{\psi}}(\xi) := \frac{\widehat{\psi}(\xi)}{\sum_{k \in \mathbb{Z}} |\widehat{\psi}(\xi + 2\pi k)|^2}
$$

 $a$ ejines a bi-orthogonal spline wavelet system  $(\psi,\psi)$  based on the D-spline pair  $(\psi_r,\psi_r)$  by order r, where both  $\psi$  and  $\widetilde{\psi}$  have r vanishing moments,  $\psi$  has compact support and  $\widetilde{\widetilde{\psi}}$  has exponential decay.

ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS  $7$ 

, if  $\mathbf{M}$  is built through the  $\mathbf{M}$  is built through the above results hold with  $\mathbf{M}$ wavelet of Chui and Wang.

Remark 3.2. It follows that the orthogonal complement  $W_0$  of  $V_0$  in  $V_1$  is contained in the span of the half-integer shifts of the framelets. This is noticeable since the integer shifts  $\{\psi^{\ell}(x - k), 1 \leq \ell \leq L, k \in \mathbb{Z}\}\$  of the framelets are not even in  $W_0$  in general: to be in  $W_0$ , they would need to be orthogonal to  $V_0$  which is only possible if they have r vanishing moments. However it is known that in UEP-based framelet systems, at least one framelet has no more than one vanishing moment.

To prove Theorem 3.1 we will need a characterization of  $G(z)$ . Its proof will appear at the end of this section.

**Proposition 3.3.** Let  $X(\Psi)$  be a tight framelet system based on the B-spline of order r.

If If  $\mathbf{I} = \mathbf{I}$  is the state through the UEP, i.e  $\mathbf{I} = \mathbf{I}$ 

$$
(3.3) \tG(z) = 1 - z.
$$

 $\blacksquare$  . Then the contract the contract of th

$$
(3.4) \tG(z) = (1-z)^n \widetilde{G}(z)
$$

where  $1 \leq n \leq r$  and  $\widetilde{G}(z)$  has no zero on the unit circle.

*Remark* 3.4. Note that in the first case,  $G(z) = 1-z$  gives the well known fact [10] that when framelets are built from a B-spline by the UEP, at least one of the framelets has exactly one vanishing moment.

Remark 3.5. We conjecture that  $\widetilde{G}(z) = 1$  holds for any spline framelet system. This can be checked manually on several examples [10, Examples 2.18, 2.19, A.1.a].

Using Proposition 3.3 we are now in a situation to prove Theorem 3.1.

Proof. (Theorem 3.1) We take

$$
(3.5) \qquad \qquad m(z) := \widetilde{G}(z)\widetilde{G}(-z)m_r(z)
$$

with  $m_r(z)$  the mask of Chui and Wang's B-wavelet (see Equation (2.8). One can easily check from Proposition 3.3 that  $m(z) = Q(z)G(z)$  for some polynomial  $Q(z)$ . Moreover, by Bezout's theorem, there exist polynomials  $\{q^{\ell}(z), 1 \leq \ell \leq L\}$  such that  $\sum_{\ell=1}^{L} q^{\ell}(z) m^{\ell}(z) = G(z)$ . Hence

$$
m(z) = \sum_{\ell=1}^{L} Q(z)q^{\ell}(z)m^{\ell}(z) = \sum_{\ell=1}^{L} p^{\ell}(z)m^{\ell}(z)
$$

with some polynomials  $p^{\ell}(z)$ . It follows that if we define  $\psi$  with mask  $m(z)$  based on the s scaling function r we have a series of  $\mathcal{L}_1$ 

$$
\widehat{\psi}(2\xi) := m(e^{-i\xi})\widehat{\phi}_r(\xi) = \sum_{\ell=1}^L p^\ell(e^{-i\xi})\tau^\ell(\xi)\widehat{\phi}_r(\xi) = \sum_{\ell=1}^L p^\ell(e^{-i\xi})\widehat{\psi^\ell}(2\xi).
$$

This gives Eq (3.1). There only remains to check that the pair  $(\psi, \tilde{\psi})$  defined by (3.1) and (3.2) is a bi-orthogonal wavelet pair with the desired moments/smoothness/decay properties.

First, if  $\mathbf{r}$  is built through the UEP,  $\mathbf{r}$  is a matrix that independent matrix independent matrix in hence  $\psi = \psi_r, \psi = \psi_r$  and the concrusion is reached. Let us now address the general case case

ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 8

where  $\Lambda$  (  $\Psi$  ) is built through the OEP with  $\Theta \geq 0.$  As  $G(z)G(-z)$  is an even polynomial with no zero on the unit circle, we can write it

$$
\widetilde{G}(z)\widetilde{G}(-z)=P(z^2)
$$

with  $P(z)$  some polynomial with no zero on the unit circle, and we obtain  $m(z) = P(z^2)m_r(z)$ . It follows that  $\psi(z\zeta) = F(e^{-z\zeta})m_r(e^{-z\zeta})\varphi_r(\zeta) = F(e^{-z\zeta})\psi_r(z\zeta)$  *i.e.* 

$$
\widetilde{\psi}(\xi) = P(e^{-i\xi})\widetilde{\psi}_r(\xi).
$$

It easily follows that

- is a compilation of integration of integration of integration of  $\mathcal{I}(t)$  integration of r problem with respect to vanishing moments and compact support.
- $\psi_r(\cdot) = \sum_n a_n \psi(\cdot n)$  with  $\{a_n\} \in \ell_2$  the Fourier series of  $1/P(e^{-i\xi})$ , hence

$$
\text{clos}_{L_{2}}\big\{\text{span}\{\psi(2^j\cdot-k)\}_{k\in\mathbb{Z}}\big\}=\text{clos}_{L_{2}}\big\{\text{span}\{\psi_{r}(2^j\cdot-k)\}_{k\in\mathbb{Z}}\big\}
$$

equals  $W_i$ , the orthogonal complement of  $V_i$  in  $V_{i+1}$  (see Eq. (2.10)), and Mallat's algorithm, (2.7), holds for the bi-orthogonal system  $(\psi, \tilde{\psi})$ .

• The dual wavelet  $\psi$  satisfies  $\psi(\xi) = \psi_r(\xi)/P(e^{-i\xi})$ , from which it is easy to check that  $\widetilde{\psi}$  is a spline of order r with r vanishing moments and exponential decay.

 $\kappa$  and  $\kappa$  3.6. By using the Euclidean algorithm, one can explicitly build polynomials  $q^*(z)$ which satisfy the Bezout relation with degrees deg  $q^\ast \leq \max_{1\leq \ell \leq L} \{ \deg m^\ast -1 \}$ . Let us take the example of the UEP case : as deg  $p^* = \deg q^* + \deg Q = \deg q^* + \deg m_r - 1 = \deg q^* + 3(r-1),$ we get an upper estimate for the smallest  $K$  in Theorem 3.1

$$
K - 1 = \max_{\ell} \deg p^{\ell} \le 3(r - 1) + \max_{1 \le \ell \le L} \{ \deg m^{\ell} - 1 \}.
$$

Let us now turn to a proof of Proposition 3.3. We will use the following result, which is easily derived from [10, Proposition 1.7] (see also [25]).

**Lemma 3.7.** Let  $X(\Psi)$  any tight framelet system (not necessarily based on the B-splines), with combined MRA mask  $\tau$  a trigonometric polynomial. Then there exist a rational function  $T(z)$ , with  $T(1) = 1$ , such that for (almost) all  $\xi$ ,  $T(e^{-z}) = \Theta(\xi)$ , and

(3.6) 
$$
m^{0}(z)\overline{m^{0}}(z^{-1})T(z^{2}) + \sum_{\ell=1}^{L} m^{\ell}(z)\overline{m^{\ell}}(z^{-1}) = T(z)
$$

(3.7) 
$$
m^{0}(z)\overline{m^{0}}(-z^{-1})T(z^{2}) + \sum_{\ell=1}^{L} m^{\ell}(z)\overline{m^{\ell}}(-z^{-1}) = 0.
$$

**Proof of Proposition 3.3.** Let  $z_0 \neq 0$  be a zero of order n of  $G(z)$ . From Eq. (3.7) we have

$$
m_r^0(z_0)\overline{m_r^0}(-z_0^{-1})T(z_0^2)=0,
$$

which gives three possibilities

(1)  $m_r^0(-z_0^-) = 0$ , *i.e.*  $z_0 = 1$ . Then  $(1-z)^0(1+z^{-1})^n$  is a factor of  $G(z)G(-z^{-1})$  and by Eq. (5.*1*) it is a factor of  $m_r^2(z) m_r^2(-z^{-2}) I(z^{-2})$ . As  $I(1) = 1$ , this implies  $0 \le n \le r$ .

ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 9

In the case  $\Theta = 1$  we get  $n \leq 1$  by observing that  $(1 - z)^{n}(1 - z^{-1})^{n}$  is a factor of  $G(z)G(z^{-1})$  hence, by Eq. (3.6), it is a factor of

$$
1 - m_r^0(z) \overline{m_r^0}(z^{-1}) = 1 - \left(\frac{(1+z)(1+z^{-1})}{4}\right)^r
$$
  
= 
$$
\left(1 - \frac{(1+z)(1+z^{-1})}{4}\right) \sum_{k=0}^{r-1} \left(\frac{(1+z)(1+z^{-1})}{4}\right)^k
$$
  
= 
$$
\frac{(1-z)(1-z^{-1})}{4} \sum_{k=0}^{r-1} \left(\frac{(1+z)(1+z^{-1})}{4}\right)^k.
$$

- (2)  $m_r(z_0) = 0, i.e. z_0 = -1$ . Then, from Eq. (5.0),  $\Theta(\pi) = 1$  (-1)  $= m_r(-1)m_r^2(-1)I(1) =$ rrate and the contract of the c  $\mathbb{R}$  , which contradicts the assumption of the assumption  $\mathbb{R}$  is not assumption  $\mathbb{R}$ root of  $G(z)$ .
- (3)  $I(z_0^*) = 0$ . This is excluded in the case  $\Theta = 1$ , and implies  $|z_0| \neq 1$  in the case -() > 0.

So far we know that  $G(z) = (1 - z)^n$ , where  $0 \leq n \leq 1$  in the case  $\Theta = 1$ , and  $G(z) =$ (1 - z)  $G(z)$ , where  $0 \le n \le r$  and  $G(z)$  has no zero on the unit circle, in the case  $\Theta > 0$ . It is simple to check that  $n \ge 1$ : since  $\sum_{\ell=1}^{L} |m^{\ell}(1)|^2 = 1 - T(1)|m_r^0(1)|^2 = 0$  we have  $m^{\ell}(1) = 0$ for  $1 \leq \ell \leq L$ , hence  $1 - z$  is a common divisor of the family  $\{m^*(z), 1 \leq \ell \leq L\}$ .

#### 4. Jackson and Bernstein inequalities

In this section we are concerned with Jackson and Bernstein inequalities for the Framelet systems and for certain oversampled versions of the systems. We have already noticed, see Equations  $(2.11)$  and  $(2.12)$ , that such inequalities will allow us to characterize the approximation spaces associated with the framelet systems. Let us now state the main result, the proof will appear later in this section.

**Theorem 4.1.** Let  $X(\Psi)$  be a framelet system based on the B-spline MRA of order r. We have, with equivalent norms, for  $0 < \gamma < \alpha < r$ ,  $1 < p < \infty$ ,  $1/\tau = \alpha + 1/p$ , and  $0 < q \leq \infty$ ,

 $\mathcal{A}_q^+(\overline{L}_p, X_R(\varphi_r))=(\overline{L}_p, \overline{B}_\tau^\infty(L_\tau))_{\gamma/\sigma}$  $\sim$ 

(4.2) 
$$
\mathcal{A}_{q}^{\gamma}(L_{p}, \overline{X}(\phi_{r})) = (L_{p}, B_{\tau}^{\alpha}(L_{\tau}))_{\gamma/\alpha,q}.
$$

, we have that  $\mathbf{C} = \mathbf{C} \cdot \mathbf{C}$  , we have that  $\mathbf{C} = \mathbf{C} \cdot \mathbf{C}$  , we have that  $\mathbf{C} = \mathbf{C} \cdot \mathbf{C}$ 

(4.3) 
$$
\mathcal{A}_q^{\gamma}(L_p, X_{2R}(\Psi)) = (L_p, B_\tau^{\alpha}(L_\tau))_{\gamma/\alpha,q}, \quad 1 \leq R \leq \infty,
$$

(4.4) 
$$
\mathcal{A}_q^{\gamma}(L_p, \overline{X}(\Psi)) = (L_p, B_\tau^{\alpha}(L_\tau))_{\gamma/\alpha,q}, \qquad \overline{\mathcal{A}}_q^{\gamma}(L_p, \overline{X}(\Psi)) = (L_p, B_\tau^{\alpha}(L_\tau))_{\gamma/\alpha,q},
$$

and

$$
(4.5) \t\t B_{\tau}^{\alpha}(L_{\tau}) = \mathcal{K}_{\tau}^{\tau}(L_{p}, X_{2}(\Psi)).
$$

For Theorem 4.1, the smoothness parameter  $\alpha$  is not limited by the number N of vanishing moments of the generators of the framelet system which may be only  $N = 1$  if the system is build with the UEP. If we assume this type of restriction on  $\alpha$  we have the following Theorem on the framelet system  $X(\Psi)$  instead of the twice oversampled system  $X_2(\Psi)$  (*i.e.* Eqs. (4.6) and (4.7) complete Eqs. (4.3) and (4.5)).

ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 10

**Theorem 4.2.** Let  $X(\Psi)$  be a framelet system based on the B-spline MRA of order r. Suppose each of the generators of the framelet system has at least  $N \geq 1$  vanishing moments, then for  $0 < \gamma < \alpha < \min\{r, N\}, 1 < p < \infty$ , and  $1/\tau = \alpha + 1/p$ ,

$$
(4.6) \qquad \mathcal{A}_q^{\gamma}(L_p, X_{2R+1}(\Psi)) = (L_p, B_\tau^{\alpha}(L_\tau))_{\gamma/\alpha,q}, \quad 0 \le R \le \infty.
$$

and

$$
(4.7) \t\t B_{\tau}^{\alpha}(L_{\tau}) = \mathcal{K}_{\tau}^{\tau}(L_{p}, X(\Psi)).
$$

We will now indicate how the structure of the proof of Theorems 4.1 and 4.2 will be. First we notice that the following result holds true.

**Proposition 4.3.** Let  $\Psi$  be any finitely generated framelet system based on the scaling function  $\phi$ . We have the following continuous embeddings, for  $0 < \alpha < \infty$ ,  $1 < p < \infty$ ,  $0 < q \leq \infty$ , and  $1 \leq R \leq \infty$ ,

$$
\mathcal{A}_q^{\alpha}(L_p, X_R(\Psi)) \hookrightarrow \mathcal{A}_q^{\alpha}(L_p, \overline{X}(\Psi))
$$
  

$$
\downarrow \qquad \qquad \downarrow
$$
  

$$
\mathcal{A}_q^{\alpha}(L_p, X_R(\phi)) \hookrightarrow \mathcal{A}_q^{\alpha}(L_p, \overline{X}(\phi))
$$

*Proof.* Follows from the fact that each framelet has a finite expansion  $\psi^{\ell}(x) = \sum_{k \in \mathbb{Z}} a_k^{\ell} \phi(2x$ k) in terms of the scaling function  $\phi$ .

From Proposition 4.3, together with the easy fact that  $\mathcal{A}^+_q(L_p, \Lambda_2(\Psi)) \hookrightarrow \mathcal{A}^+_q(L_p, \Lambda_{2R}(\Psi))$ for  $1 \leq R \leq \infty$ , we see that it suffices to obtain a Bernstein inequality for the system  $\overline{X}(\phi_r)$ and a Jackson inequality for the system  $X_2(\Psi)$ , to obtain Eqs. (4.2), (4.3), and (4.4), and Eq  $(4.1)$  with even R. To obtain  $(4.1)$  with odd R and  $(4.6)$ , respectively, we use the fact that  $\mathcal{A}_{q}^{-1}(L_p, \Lambda(r)) \hookrightarrow \mathcal{A}_{q}^{-1}(L_p, \Lambda_{2R+1}(r))$  for  $1 \leq R \leq \infty$  and  $r \in \{\{\varphi_r\}, \Psi\}$ . Thus, we only need to prove a Jackson inequality for  $X(\phi)$  and  $X(\Psi)$ , respectively.

In Section 4.1 we will obtain a Bernstein inequality for the system  $\overline{X}(\phi)$  (Proposition 4.4). In Section 4.2 we prove a Jackson inequality for  $X(\phi)$  (Proposition 4.6) that will give (4.1) for all R and (4.2). In Section 4.3 we prove a Jackson inequality for  $X_2(\Psi)$  under the assumption that - c > 0 (Proposition 4.10), which gives (4.3) and (4.4). We will prove Eq. (4.5) in Section 4.11 (Proposition 4.13).

Finally, Section 4.15 is devoted to the proof of Eqs. (4.6) and (4.7), which require some vanishing moments on the framelets. First we prove a Jackson inequality for the framelet system (Proposition 4.15) that gives  $(4.6)$ , then we get  $(4.7)$  by a "sandwich" argument.

4.1. **Bernstein inequalities.** We have the following general Bernstein inequality for different dictionaries derived from the framelet system.

**Proposition 4.4.** Let  $0 < \alpha < r$  and  $1 < p < \infty$ . There exists a constant  $C < \infty$  such that the Bernstein inequality

$$
|S|_{B^{\alpha}_{\tau}(L_{\tau})} \leq Cn^{\alpha} ||S||_{p}, \qquad 1/\tau = \alpha + 1/p,
$$

holds for  $S \in \Sigma_n(\mathcal{D})$ ,  $n \ge 1$  where  $\mathcal{D} \in \{X_R(\Psi), \overline{X}(\Psi), X_R(\phi), \overline{X}(\phi)\}, 1 \le R \le \infty$ .<br>First we prove the following Lemma:

**Lemma 4.5.** Fix  $\alpha > 0$ . For any interval  $I = [-A, A]$  there exist  $0 < \delta$  and  $C < \infty$  such that for  $f \in B_n^{\infty}(L_p(I))$  with support in  $[-0, 0], 1 \leq p \leq \infty, 0 \leq q \leq \infty$ ,  $\tilde{\phantom{a}}$ 

$$
||f||_{B^{\alpha}_{q}(L_p(\mathbb{R}))} \leq C||f||_{B^{\alpha}_{q}(L_p(I))}.
$$

#### ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 11

*Proof.* Expand f in a wavelet system on  $[-A, A]$  based on a compactly supported wavelet with sufficient smoothness as explained in [7]. If  $\delta$  is small enough (depends on the support diameter of the wavelet) then  $f$  will not meet any of the boundary wavelets and the bounded  $\Box$ extension operator  $\mathcal{E}: B_0^-(L_p(I)) \to B_0^-(L_p(\mathbb{R}))$  defined in [*i*] is the identity on f.  $\mathbf{q}$  $\mathbf{q}$ 

*Proof.* (Alternative proof for  $p = q$ ): We can assume that  $I = [-2, 2]$ . Let  $\eta \in C^{\infty}(\mathbb{R})$  be a function with supp $(\eta) \subset [-2, 2], \, \eta = 1$  on  $[-1/4, 1/4]$  and  $\sum_{k} \eta(x - k) = 1$ . By the Fubini property of the space  $B_p^{\infty}(L_p(\mathbb{R}))$  we have, for any  $g \in B_p^{\infty}(L_p(\mathbb{R}))$  [27],

$$
||g||_{B_p^{\alpha}(L_p(\mathbb{R}))} \asymp \bigg(\sum_{m\in\mathbb{Z}} ||g\eta(\cdot-m)||_{B_p^{\alpha}(L_p(\mathbb{R}))}^p\bigg)^{1/p}.
$$

Let  $f \in D_p^{\infty}(L_p[-2, 2])$  with supp $(f) \subseteq [-1/4, 1/4]$ . Thus for  $g \in D_p^{\infty}(L_p(\mathbb{R}))$  with  $g|_{[-2, 2]} = f$ is follows that  $||\beta||D_p^{\gamma}(Lp(\mathbb{R}))| = \sum ||\beta' I \setminus f||D_p^{\gamma}(Lp(\mathbb{R}))|$  .  $||J||D_p^{\gamma}(Lp(\mathbb{R}))|$  . The result can then be deduced directly from the definition:

$$
||f||_{B_p^{\alpha}(L_p[-2,2])} := \inf_{g \in B_p^{\alpha}(L_p(\mathbb{R})); g|_{[-2,2]} = f} ||g||_{B_p^{\alpha}(L_p(\mathbb{R}))}.
$$

We are ready to prove Proposition 4.4.

*Proof.* Let  $\delta$  be as in Lemma 4.5 for  $I = [-2, 2]$  and fix  $S(x) = \sum_{\lambda \in \Lambda} c_{\lambda} h_{\lambda}(x) \in \Sigma_n(\mathcal{D})$ . Choose  1 such that g(x) = S(x) has support contained in [; ] (the size of  depends on the diameter and center of support of S). Notice that  $\|g\|_p = \rho^{-1/p} \|\mathcal{S}\|_p$  and also  $|g|_{B^{\alpha}_{\tau}(L_{\tau}(\mathbb{R}))} = \beta^{-1/\nu} |\mathcal{S}|_{B^{\alpha}_{\tau}(L_{\tau}(\mathbb{R}))}$  which holds because of the relation  $1/\tau = \alpha + 1/p$ . Now g is piecewise polynomial with at most  $\kappa \cdot n$  knots ( $\kappa$  is defined in Eq. (2.6)) so from the result by P. Petrushev [23] on approximation with free knot splines, we have

$$
|g|_{B^{\alpha}_{\tau}(L_{\tau}([-2,2])} \leq C\kappa^{\alpha}n^{\alpha}||g||_{p}.
$$

Using Lemma 4.5 we write

$$
\beta^{-1/p}|S|_{B^{\alpha}_{\tau}(L_{\tau}(\mathbb{R}))} = |g|_{B^{\alpha}_{\tau}(L_{\tau}(\mathbb{R}))}
$$
\n
$$
\leq ||g||_{B^{\alpha}_{\tau}(L_{\tau}(\mathbb{R}))}
$$
\n
$$
\leq C||g||_{B^{\alpha}_{\tau}(L_{\tau}([-2,2]))}
$$
\n
$$
= C|g|_{B^{\alpha}_{\tau}(L_{\tau}([-2,2]))} + C||g||_{L_{\tau}([-2,2])}
$$
\n
$$
\leq \tilde{C}\kappa^{\alpha}n^{\alpha}||g||_{p} + C'||g||_{L_{p}([-2,2])}
$$
\n
$$
\leq C\kappa^{\alpha}n^{\alpha}||g||_{p}
$$
\n
$$
= C\beta^{-1/p}\kappa^{\alpha}n^{\alpha}||S||_{p},
$$

where in (\*) we used  $L_p([-2,2]) \hookrightarrow L_{\tau}([-2,2])$ . Multiplying by  $p^{\tau/r}$  we obtain the desired inequality is a contract of the contract of the

4.2. Jackson inequality for the scaling system. We now turn to the proof of the Jackson inequalities for the different dictionaries derived from the underlying MRA. First we consider a Jackson inequality for the scaling system. Proposition 4.6 below will imply Eqs. (4.1) and (4.2). We sketch a proof of the result using a result by Petrushev [22]. It should be noted that the technique works not only for any scaling function satisfying function satisfying function satisfying  $\mu$ Strang-Fix condition, see [22] for details. An alternative proof of Proposition 4.6 (that works only for  $\phi_r$ ) can be found in [15].

ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 12

**Proposition 4.6.** Let  $0 < \alpha < r$  and  $1 < p < \infty$ . There exists a constant  $C < \infty$  such that

$$
\sigma_n(f, X(\phi_r))_p \leq Cn^{-\alpha}|f|_{B^{\alpha}_{\tau}(L_{\tau})}, \quad \text{for } f \in B^{\alpha}_{\tau}(L_{\tau}),
$$

with  $1/\tau = \alpha + 1/p$ .

Proof. By the result of Petrushev [22] there exists a nite set F f0; 1;:::; g - <sup>Z</sup> and a corresponding function

$$
\theta(x) = \sum_{(j',k') \in F} c_{(j',k')} \phi_r(2^{j'}x - k')
$$

for which the system  $X(\theta) = \{2^{j/2}\theta(2^jx - k)\}_{j,k\in\mathbb{Z}}$  satisfies the Jackson inequality

$$
\sigma_n(f, X(\theta))_p \le Cn^{-\alpha}|f|_{B_\tau^\alpha(L_\tau)}
$$

The result follows from

$$
\sigma_{\#F\cdot n}(f, X(\phi_r))_p \leq \sigma_n(f, X(\theta))_p.
$$

4.3. Jackson inequalities for the framelet system. Now we turn to the Jackson inequalities for the framelet system. First we need a few results about bi-orthogonal B-spline wavelet systems. The results will only be stated in the generality needed for this paper. For more general results we would have to assume vanishing moments of the wavelets, however this is guaranteed here by the fact that  $W_0 \perp V_0$  and  $V_0$  contains (piecewise) polynomials up to degree r.

**THEOREM 4.1.** Let  $(\psi, \psi)$  be a bi-orthogonal wavelet system based on the bi-orthogonal Dspune pair  $(\varphi_r, \varphi_r)$  of Section 2.3. Assume that  $|\psi(x)| \leq C(1+|x|)$  is for some  $\varepsilon > 0$ , and that  $\psi$  has compact support. Then for  $0 < \alpha < r$ ,  $1 < p < \infty$ ,  $0 < q \leq \infty$ ,

$$
|f|_{B_q^{\alpha}(L_p)} \geq C \bigg( \sum_{j \in \mathbb{Z}} \bigg( \sum_{k \in \mathbb{Z}} \big( 2^{j(\alpha+1/2-1/p)} |\langle f, \tilde{\psi}_{j,k} \rangle| \big)^p \bigg)^{q/p} \bigg)^{1/q},
$$

with the usual modification for  $q = \infty$ .

 $P^{\text{max}}$  (such that  $P$  is  $P$  is  $P$  is the form of  $P$  is the form of  $P$  is  $\left(\sum_{j\in\mathbb{Z}}[2^{j\alpha}s_j(f)_p]^q\right)^{1/q}$ with simple  $p$  is the group  $p$  and  $p$  is the spline MRA associated with  $p$  is the splitter  $p$  . The splitter  $p$  $P_j f := \sum_{k \in \mathbb{Z}} \langle f, \phi_{r,j,k} \rangle \phi_{r,j,k}$  the orthonormal projection onto  $V_j$ . Using standard techniques, see e.g. it is the see e.g. it is bounded on Lemma is bounded on Lemma is bounded on Lemma is bounded on Lemma of j. The fact that  $P$  is a projection onto  $\ell$  , the from one  $\ell$  that  $\ell$  is  $p$  is  $p$  (fine  $p$  from  $p$ which we get  $||(P_{j+1} - P_j)f||_p \leq 2(1 + C_p)s_j(f)_p$ . Hence

$$
|f|_{B_q^{\alpha}(L_p)} \ge \tilde{C} \left( \sum_{j \in \mathbb{Z}} [2^{j\alpha} || (P_{j+1} - P_j) f ||_p]^q \right)^{1/q}.
$$

By Mallat's algorithm, (2.7), we have

$$
(P_{j+1} - P_j)f = \sum_{k \in \mathbb{Z}} \langle f, \tilde{\psi}_{j,k} \rangle \psi_{j,k}.
$$

Now, notice that  $\psi \in C$  if for every  $\varepsilon > 0$  since  $\psi$  is a spline of order r. We apply the technique from [21, p. 31] again to get (independent of j)

$$
\bigg\|\sum_{k\in\mathbb{Z}}\langle f,\tilde{\psi}_{j,k}\rangle\psi_{j,k}\bigg\|_p\asymp 2^{j(1/2-1/p)}\bigg(\sum_{k\in\mathbb{Z}}|\langle f,\tilde{\psi}_{j,k}\rangle|^p\bigg)^{1/p},
$$

 $\Box$ 

# ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 13

from which the claim follows.

**THEOREM 4.8.** Let  $(\psi, \psi)$  be a bi-orthogonal wavelet system based on the bi-orthogonal Dspline pair  $(\varphi_r, \varphi_r)$  of Section 2.3. Assume that  $|\psi(x)| \leq C(1+|x|)$  is for some  $\varepsilon > 0$ , and that  $\psi$  has compact support. Then for  $0 < \alpha < r$ ,  $1 < p < \infty$ ,  $1/\tau = \alpha + 1/p$ , there exists a constant  $C < \infty$  such that

$$
\sigma_n(f, X(\psi))_p \leq Cn^{-\alpha}|f|_{B_r^{\alpha}(L_\tau)}.
$$

Proof. (outline) As above,  $\psi \in C$  if for every  $\varepsilon > 0$  since  $\psi$  is a spline of order r. Using the technique explained in e.g. [14,  $\S7.4$ ] combined with Theorem 4.7, we notice that the claim of the Theorem will follow if we have the theorem  $\mu$  ,  $\mu$ function of  $f$  given by

$$
S(f)(x) = \bigg(\sum_{j,k\in\mathbb{Z}} |\langle f,\tilde{\psi}_{j,k}\rangle|^2 \chi_{[2^{-j}k,2^{-j}(k+1)]}(x)\bigg)^{1/2}.
$$

 $\mathcal{F}$  that the fact that the fact that kip is under the given hypothesis is well as well a known, see e.g. [13, 28].  $\Box$ 

Remark 4.9. It is possible to generalize Theorems 4.7 and 4.8 to wavelets  $\psi$  not based on the B-splines and also to wavelets without compact support by assuming appropriate smoothness and decay of  $\psi$ . We refer to, e.g., [15] for more details.

We apply Theorem 4.8 to the bi-orthogonal wavelet systems  $(\psi, \widetilde{\psi})$  built using Theorem 3.1. We obtain the following Jackson inequality with  $C < \infty$ 

$$
\sigma_n(f, X(\psi))_p \le Cn^{-\alpha}|f|_{B_\tau^\alpha(L_\tau)},
$$

for  $\alpha < r$  and  $1/\tau = \alpha + 1/p$ . Combining with Theorem 3.1 gives the proof of the following result. Notice that the result will imply Eqs. (4.3) and (4.4).

**Proposition 4.10.** Assume  $X(\Psi)$  is a tight framelet system based on the B-spline of order r, and - c > 0. Then the fol lowing Jackson inequality holds with C < <sup>1</sup>

$$
(4.8) \qquad \sigma_{LKn}(f, X_2(\Psi))_p \le \sigma_n(f, X(\psi_r))_p \le Cn^{-\alpha}|f|_{B_r^\alpha(L_r)}
$$

for any  $f \in L_p$ , with  $\alpha < r$ ,  $1/\tau = \alpha + 1/p$ , and K given by Theorem 3.1.

4.4. Sparsity of framelet expansions. We will now prove some more results on the twice oversampled framelet system  $X_2(\Psi)$  that will lead to a characterization of the Besov spaces using the smoothness spaces  $\mathcal{N}_q(L_p, \Lambda_2(\Psi))$ . We begin with the following result: the twice oversampled framelet system  $X_2(\Psi)$  is actually a frame in  $L_2$ .

**Theorem 4.11.** Let  $X(\Psi) = {\{\psi^*\}}_{\ell=1}^T$  be any framelet system (not necessarily based on the Bsplines) with compactly supported generators in C  $\mathcal{C}(\mathbb{R})$  for some  $\rho > 0$ . Then for  $1 \leq p < \infty$ there exists a constant  $\mathcal{L}$  and the twice oversample system  $\mathcal{L}$  and  $\mathcal{L}$ 

$$
\bigg\|\sum_{j,k,\ell,\varepsilon}c_{j,k,\varepsilon}^\ell \frac{\psi^{\ell}_{j,k,\varepsilon}}{\|\psi^{\ell}_{j,k,\varepsilon}\|_p}\bigg\|_p \leq C_p \|\{c_{j,k,\varepsilon}^\ell\}\|_{\ell_1^p},
$$

with

$$
\psi_{j,k,\varepsilon}^{\ell}(\cdot) := 2^{j/2} \psi^{\ell}(2^j \cdot -k - \varepsilon/2)
$$

ana  $\{c_{i,k,\varepsilon}\}$  any sequence of scalars.

#### ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 14

*Proof.* The case  $p = 1$  is trivial. Next we consider the case  $p = 2$ , and we will show that the system is actually a frame. Let  $\{e_{\lambda}\}_{\lambda \in \Lambda}$  be the canonical basis of  $\ell_2(\Lambda)$  with  $\Lambda =$  $\mathbb{Z} \times \mathbb{Z} \times \mathbb{Z}_L \times \mathbb{Z}_2$ . Define T formally by letting  $I e_{\lambda} = \psi_{i,k,\varepsilon}(\cdot)$  for  $\lambda := (f,\kappa,\ell,\varepsilon) \in \Lambda$ . Since  $X(\Psi)$  is a frame, we notice that

$$
T\left\{\cosh_{\ell_2(\Lambda)}\left\{\mathrm{span}\{e_\lambda|\lambda\in\mathbb{Z}\times\mathbb{Z}\times\mathbb{Z}_L\times\{0\}\}\right\}\right\}=L_2.
$$

Thus, we just have to verify that T is bounded from  $\ell_2(\Lambda)$  to  $L_2(\mathbb{R})$  (see for example [2]). which we have  $\mathcal{L} = \mathcal{L}$  and the system of the system system is a zero of  $\mathcal{L}$ 

$$
X(\psi^{\ell}(\cdot - 1/2)) = \{2^{j/2}\psi^{\ell}(2^{j} \cdot -k - 1/2)\}_{j,k \in \mathbb{Z}}
$$

is a system of **vaguelettes** in the terminology of  $|z_0|$  using that each  $\psi^* \in C^{\infty}(\mathbb{R})$ . Using  $|z_0|$ , Theoreme 2, p. 270] we conclude that this subsystem is hilbertian. As this is true for each  $\ell$ we may conclude that T is indeed a bounded mapping of  $\ell_2(\Lambda)$  onto  $L_2$ .<br>Take  $\{\psi_{j,k}\}$  any orthonormal wavelet system with a compactly supported  $C^1(\mathbb{R})$  generator.

For each  $\ell$  and  $\varepsilon = 0, 1$  we consider the integral kernel

$$
K^{\ell,\varepsilon}(x,y)=\sum_{j,k\in\mathbb{Z}}\psi_{j,k,\varepsilon}^\ell(x)\overline{\psi_{j,k}(y)}.
$$

Standard estimates (see [9, Chap. 9] when  $\beta \geq 1$ , or [20] for  $0 < \beta < 1$ ) show that the associated integral operator

$$
(T^{\ell,\varepsilon}f)(x)=\int K^{\ell,\varepsilon}(x,y)f(y)\,dy=\sum_{j,k}\langle f,\psi_{j,k}\rangle\psi_{j,k,\varepsilon}^\ell(x)
$$

is a Calderon-Zygmund operator (notice that  $L_2$ -boundedness follows from the  $p = 2$  case discussed above). Thus, for each  $\ell$  and  $\varepsilon$ ,  $T^{\ell,\varepsilon}$  extends to a bounded operator on  $L_p$ ,  $1 < p <$  $\infty$ . Given that  $\|\psi^*\|_p / \|\psi_{i,k,\varepsilon}\|_p = \|\psi\|_p / \|\psi_{i,k}\|_p$  we obtain

$$
\left\| \sum_{j,k,\ell,\varepsilon} \frac{c_{j,k,\varepsilon}^{\ell}}{\|\psi_{j,k,\varepsilon}^{\ell}\|_p} \psi_{j,k,\varepsilon}^{\ell} \right\|_p = \left\| \sum_{\ell,\varepsilon} T^{\ell,\varepsilon} \left( \frac{\|\psi\|_p}{\|\psi^{\ell}\|_p} \sum_{j,k} \frac{c_{j,k,\varepsilon}^{\ell}}{\|\psi_{j,k}\|_p} \psi_{j,k} \right) \right\|_p
$$
  

$$
\leq C_p \sum_{\ell,\varepsilon} \left\| \sum_{j,k} c_{j,k,\varepsilon}^{\ell} \frac{\psi_{j,k}}{\|\psi_{j,k}\|_p} \right\|_p.
$$

We conclude using the fact that the  $L_p$ -normalized wavelet system  $\{\psi_{j,k}/\|\psi_{j,k}\|_p\}$  is  $\ell_1^*$ hilbertian in  $L_p$ .

Remark 4.12. It is known, see [25], that  $X_2(\Phi)$  is not a **tight** frame, but a frame nevertheless as we have just demonstrated.

We can now use Lemma 4.11 to obtain the following characterization of the Besov spaces  $B^{\pm}_{\tau}(L_{\tau})$  in terms of the smoothness spaces  $\mathcal{N}_{\tau}(L_{p}, \Lambda_{2}(\Psi))$ . Notice that we do not require the framelet system to have any prescribed number of **vanishing moments**. This seems to indicate that for a very smooth function  $f$  (very smooth compared to the number of vanishing moments of the generators of the framelet system), one should not use the framelet coefficients  $\{\langle f, \psi_{i,k}^{\ell} \rangle\}$  to represent that function but instead optimize the representation  $f = \sum c_{i,k}^{\ell} \psi_{j,k}^{\ell}$ for sparseness of the coefficients  $\{c_{i,k}\}$ . We will further discuss this issue in the Conclusion.

**Proposition 4.13.** Let  $0 < \alpha < r$ . For any framelet system  $X(\Psi)$  based on the B-spline MRA of order r, assuming that - c > 0, we have with equivalent norms

$$
B^{\alpha}_{\tau}(L_{\tau}) = \mathcal{K}^{\tau}_{\tau}(L_{p}, X_{2}(\Psi)),
$$

with  $1 < p < \infty$  and  $1/\tau = \alpha + 1/p$ .

# ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 15

The proof relies on [18, Theorem 3.2] of which we use only the following weak form.

**Theorem 4.14** (Gribonval, Nielsen). For any  $1 < p < \infty$ ,  $0 < \tau < p$  and  $q \in (0, \infty]$ , there is a constant C such that for any normalized atclionary D in  $L_p$  and any  $f \in \mathcal{K}_q(L_p, D)$ 

(4.9) 
$$
||f||_{\mathcal{A}_q^{\alpha}(L_p,\mathcal{D})} \leq C \cdot C_p(\mathcal{D}) \cdot |f|_{\mathcal{K}_q^{\tau}(L_p,\mathcal{D})}, \qquad 1/\tau = \alpha + 1/p
$$

with

$$
C_p(\mathcal{D}):=\sup_{\|\mathbf{c}\|_{\ell_1^P}=1}\|\sum_kc_kg_k\|_p.
$$

 $\mathcal{L} = \mathcal{D} \setminus \mathcal{D}$  in general behind be in general behind be in the contract  $\mathcal{D} = \mathcal{D} \setminus \mathcal{D} = \mathcal{D}$ for  $\mathcal{D} = X_2(\Psi)$  properly normalized in  $X = L_p, 1 \leq p < \infty$ .

Proof. From Proposition 4.4 and the above Theorem, we have

$$
\mathcal{K}_{\tau}^{\tau}(L_p, X_2(\Psi)) \hookrightarrow \mathcal{A}_{\tau}^{\alpha}(L_p, X_2(\Psi)) \hookrightarrow B_{\tau}^{\alpha}(L_{\tau}),
$$

for  $1/7 = \alpha + 1/p$ , for the other embedding,  $B_T^-(L_7) \hookrightarrow \mathcal{N}_T^-(L_p, \Lambda_2^-(\Psi))$ , we take  $f \in B_T^-(L_7)$ . Then f has an wavelet expansion  $f = \sum_{j,k} c_{j,k} \psi_{j,k}$  where  $\psi_{j,k}$  is Chui and Wang's wavelet (see Section 2.3) normalized in Le,  $\mu$ , and for  $\mu$ , see Theorem 4.7. But we have seen in a normalized in  $\mu$ The second 3.1 that is not that  $\mu_{i,h}$  from a nite expansion in the size  $\mu_{i}$  with a  $\mu_{i}$  with a minimizer  $\mu_{i}$ of terms that does not depend on  $j$  or  $k$ . The conclusion follows easily from this fact and this completes the proof of Proposition 4.13.

4.5. Where vanishing moments eventually come into play. We now turn to results where we require some vanishing moments of the generators of the framelet system, unlike the abstract smoothness spaces considered so far. It turns out that in the more restrictive case where the smoothness index  $\alpha$  is below the minimum number of vanishing moments of the framelet generators, we can actually characterize the Besov spaces using the framelet coefficients  $\{\langle f, \psi_{i,k}^*\rangle\}$  instead of the optimized coefficients  $\{c_{j,k,\varepsilon}\}$  in the twice oversampled system  $X_2(\Psi)$ . Thus in such cases smooth functions **compress the framelet coefficients** just as they do for the wavelet coefficients  $[15]$ . A consequence of this will be the following Jackson inequality for the framelet system  $X(\Psi)$ .

**Proposition 4.15.** Let  $\Psi$  be a framelet system with compactly supported generators each with at least  $N \geq 1$  vanishing moments. For  $\alpha < \min\{r, N\}$ ,  $1/\tau = \alpha + 1/p$ , and  $1 < p < \infty$ , we have

$$
\sigma_n(f, X(\Psi))_p \le Cn^{-\alpha}|f|_{B_\tau^\alpha(L_\tau)}, \qquad \text{for } f \in B_\tau^\alpha(L_\tau).
$$

For the proof of Proposition 4.15 we will need Proposition 4.17 below. First we introduce some additional notation. For any framelet system  $\Psi$  we define for  $0 < p < \infty$ ,  $0 < q \leq \infty$ , and  $\tau \geq p$ ,

$$
\mathcal{B}_{q}^{\alpha}(L_{p}, X(\Psi)) := \{f \in L_{p} : \{ \langle f, \psi_{j,k}^{\ell} \rangle \}_{j,k} \in \dot{b}_{p,q}^{\alpha}, \ell = 1, 2, \ldots, L \},\
$$

where the homogeneous discrete Besov space  $o_{p,q}^-$  is defined by

$$
\bigg\{\{c_{j,k}\}_{j,k\in\mathbb{Z}}\bigg|\|\{c_{j,k}\}\|_{\dot{b}^{\alpha}_{p,q}}:=\bigg(\sum_{j\in\mathbb{Z}}\bigg(\sum_{k\in\mathbb{Z}}\big(2^{j(\alpha+1/2-1/p)}|c_{j,k}|\big)^p\bigg)^{q/p}\bigg)^{1/q}<\infty\bigg\}.
$$

We norm  $\mathcal{D}_q^-(L_p, \Lambda(\Psi))$  by letting

$$
||f||_{\mathcal{B}_q^{\alpha}(L_p, X(\Psi))} := ||f||_p + \sum_{\ell=1}^L ||\{\langle f, \psi_{j,k}^{\ell}\rangle\}\|_{\dot{b}_{p,q}^{\alpha}}.
$$

#### ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 16

Remark 4.16. We notice that in the case where  $1/\tau = \alpha + 1/p$ ,  $1 < p < \infty$ ,  $\mathcal{D}^{\pi}_{\tau}(L_{\tau}, \Lambda(\Psi))$  is the collections whose framelet coecients are contained in  $\mathcal{N}$  when the coecients are contained in  $\mathcal{N}$ functionals are normalized in  $L_{p'}$  with p' the conjugate index to p.

As the notation suggest, the class  $\mathcal{D}_{q}^{\infty}(L_{p}, \Lambda\left(\Psi\right))$  will coincide with a classical Besov space  $D_q^-(L_p)$  for certain values of  $\alpha$ . The result is as follows (for the definition of r-regular functions, see [21]).

**Proposition 4.17.** Fix  $N > 1$ . Suppose  $\Psi$  is a framelet system with each generators being an r-regular function having at least  $N$  vanishing moments. Then the following identity holds, with equivalent norms,  $0 < p < \infty$ ,  $0 < q < \infty$ ,

$$
\mathcal{B}_q^{\alpha}(L_p, X(\Psi)) = B_q^{\alpha}(L_p),
$$

provided that  $\min\{r, N\} > \max\{J - 1 - \alpha, \alpha\}$  where  $J = 1/\min\{1, p\}.$ 

*Proof.* The embedding  $D_q^-(L_p, \Lambda(\Psi)) \hookrightarrow D_q^-(L_p)$  follows immediately from the theory of atomic decomposition of  $B^\sigma_q(L_p)$ , see [17]. To get the other inclusion, we let  $\{\psi^{+}_{i,k}\}$  be the orthonormal Meyer wavelet on  $\mathbb{R}$ . Then for  $f \in B_q^-(L_p)$  we have an expansion  $f =$ <u>Personal and the set of the set of</u>  $j_k a_{j,k} \psi_{j,k}^m$ , with  $\{a_{j,k}\}\in \vartheta_{p,q}^m$ , see [14]. We notice that the framelet coefficient  $\langle j, \psi_{j',k'}^m \rangle$  is given by

(4.10) 
$$
\langle f, \psi_{j',k'}^{\ell} \rangle = \sum_{j,k} \langle \psi_{j,k}^{m}, \psi_{j',k'}^{\ell} \rangle d_{j,k}.
$$

For each  $\ell$  we consider the following matrix operator  $M^{\ell}$  defined on sequences by

$$
(M^\ell c)_{j',k'} = \sum_{j,k\in\mathbb{Z}} \langle \psi^m_{j,k}, \psi^\ell_{j',k'} \rangle c_{j,k}.
$$

Using the fact that each of the generators of the framelet system is an  $r$ -regular function it follows from standard estimates that the matrix  $M^+$  is almost diagonal for  $\theta_{p,q}^-$  and thus  $\sim$  . . bounded on  $\theta_{p,q}^*$  provided  $\min\{r,N\} > \max\{J-1-\alpha,\alpha\}$ , see [17, 20]. It now follows immediately that  $f \in \mathcal{D}_q^-(L_p, \Lambda(\Psi))$ .

Finally we are in a position to prove the Jackson inequality for the framelet system  $X(\Psi)$ (Proposition 4.15).

*Proof.* (Proposition 4.15) From Lemma 4.11 one can easily check that  $C_p(X(\Psi)) < \infty$  with the notation from Theorem 4.14. Applying Theorem 4.14 one gets with  $1/\tau = \alpha + 1/p$ 

$$
\sigma_n(f, X(\Psi))_p \le n^{-\alpha} \|f\|_{\mathcal{A}^\alpha_\tau(L_p, X(\Psi))} \le Cn^{-\alpha} |f|_{\mathcal{K}^\tau_\tau(L_p, X(\Psi))} \le Cn^{-\alpha} |f|_{\mathcal{B}^\tau_\tau(L_p, X(\Psi))}
$$

It is well known that the B-spling r , r , r , p. 21, p. 1, p. 21, p to the general setup considered in this paper, and we can conclude using the identification of the framelet smoothness space  $D^{\pm}_{\tau}(L_{\tau})$  with a classical besov space  $D^{\pm}_{\tau}(L_{\tau}).$ 

To conclude this section, the above results together with an easy "sandwich" argument provide the proof of Eq. (4.7) in Theorem 4.2.

# 5. Additional results and some open questions

In the most important tool we provide (Theorem 3.1) a nice bi-orthogonal wavelet is expanded in the **twice oversampled** framelet system  $X_2(\Psi)$ . This prevents us from writing results such as Theorem 4.1 directly with  $X(\Psi)$ , and we need assumptions on the vanishing moments of  $\Psi$  to get a complete result in Theorem 4.2. Can we get rid of this oversampling?

# ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 17

5.1. A direct approach. The easy way to improve Theorem 3.1 would be to expand the Three wavelet  $\psi$  of Section 3 in terms of integer shifts of the framelets  $\psi^\ast$  instead of half-shifts. A necessary and sufficient condition for such an expansion to be possible is the existence of polynomials  $p^{\ell}(z)$  such that

(5.1) 
$$
\widehat{\psi}(\xi) = \sum_{\ell=1}^{L} p^{\ell} (e^{-i\xi}) \widehat{\psi^{\ell}}(\xi).
$$

Recall that the high-pass litter  $m(z)$  associated with  $\psi$  can be written  $m(z) = F(z/m_r(z)$ for some polynomial P with no zeroes on the unit circle and with  $m_r(z)$  the mask of the Chui-Wang wavelet. Thus, (5.1) is equivalent to the existence of polynomials  $p^{\ell}$  such that

(5.2) 
$$
P(z^2)m_r(z) = \sum_{\ell=1}^L p^{\ell}(z^2)m^{\ell}(z).
$$

We want to study (5.2) in more detail. Using Equation (3.4) we write each mask  $m^{\ell}(z)$  as

$$
m^{\ell}(z) = (1-z)^{n} (a^{\ell}(z^{2}) + zb^{\ell}(z^{2}))
$$

as well as  $m_r(z) = (1-z)^r (A(z^r) + zB(z^r))$ . Let  $P(z)$  a polynomial with no zero on the unit circle. Now we divide (5.2) by  $(1-z)^n$  and split it into its even/odd part to get

$$
P(z2)A(z2) = \sum_{\ell} p^{\ell}(z2)a^{\ell}(z2)
$$
  

$$
P(z2)zB(z2) = \sum_{\ell} p^{\ell}(z2)zb^{\ell}(z2)
$$

that is to say

(5.3) 
$$
P(z) \begin{bmatrix} A(z) \\ B(z) \end{bmatrix} = \begin{bmatrix} a^1(z) & \cdots & a^L(z) \\ b^1(z) & \cdots & b^L(z) \end{bmatrix} \begin{bmatrix} p^1(z) \\ \cdots \\ p^L(z) \end{bmatrix}.
$$

Next we study when (5.3) has a solution in the case  $L = 2$ .

, the 2 - 2 - 2 - 2 - 2 - 2. Any solution of the 2 - 2. Any solution of the 2 - 2. Any solution of the 2 - 2 satisfy

(5.4) 
$$
P(z) \begin{bmatrix} C(z) \\ D(z) \end{bmatrix} := P(z) \begin{bmatrix} b^2(z) & -a^2(z) \\ -b^1(z) & a^1(z) \end{bmatrix} \begin{bmatrix} A(z) \\ B(z) \end{bmatrix} = \Delta(z) \begin{bmatrix} p^1(z) \\ p^2(z) \end{bmatrix}
$$

with  $\Delta(z) := a^2(z) b^2(z) - b^2(z) a^2(z)$ . Let us write  $\Delta(z) = \Delta(z) \Delta_0(z)$  where  $\Delta(z)$  has no zero on the unit circle while all zeros of  $\Delta_0$  are on it (or  $\Delta_0$  might be identically 1).

**Proposition 5.1.** There is a solution  $p^1(z)$ ,  $p^2(z)$ ,  $P(z)$  to (5.3) with  $P(z) \neq 0$ ,  $|z| = 1$  if and only if  $\Delta_0(z)$  divides  $gcd\{C(z), D(z)\}.$ 

*Proof.* Necessary condition. Let  $p^1(z)$ ,  $p^2(z)$ ,  $P(z)$  be such a solution. By hypothesis  $P(z)$ has no zeroes on the unit circle while  $\Delta_0(z)$  has all (if any) of its zeroes on the unit circle, so generally are the contracted property of the  $|gcd(P \cdot C, P \cdot D)|$  and it follows easily that  $\Delta_0 |gcd(0)$  $\gcd(C, D)$ . **Sufficient condition.** Assuming  $\Delta_0(z)$  divides  $gcd{C(z), D(z)}$ , we can take

$$
p^{1}(z) := C(z)/\Delta_{0}(z)
$$
  
\n
$$
p^{2}(z) := D(z)/\Delta_{0}(z)
$$
  
\n
$$
P(z) := \tilde{\Delta}(z).
$$

 $\Box$ 

 $\sim$  3  $\sim$ 

#### ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 18

Let us now consider two examples of framelet systems (both taken from  $[10]$ ). The first example shows that (5.3) has a solution in some cases. The second example will show that there are framelet systems for which (5.3) has no solution.

**Example 5.2.** [10, Example 2.10] Take  $r = 2$ ,  $m(z) := m_2(z)$ ,  $m(z) := -(1-z)^2/4$ , and  $m^2(z) := -\sqrt{2}(1+z)(1-z)/4$ . One can easily check that (up to a constant)

$$
\begin{bmatrix} a^1(z) & a^2(z) \\ b^1(z) & b^2(z) \end{bmatrix} = \begin{bmatrix} 1 & 1 \\ -1 & 1 \end{bmatrix},
$$

so  $\Delta(z) = 2$  and Proposition 5.1 shows that (5.3) has a solution in this case, i.e. that  $\psi_2$  can be written as a linear combination of integer shifts of the framelets.

**Example 5.3.** [10, Example 2.18] Take  $r = 2$ ,  $m_2(z) = (1-z)^2(\alpha_1 - \alpha_2 z + \alpha_3 z^2)$  with  $\alpha_1, \alpha_2$ , and  $\alpha_3$  given by (2.8)],  $m^1(z) := -(1-z)^2/4$ , and  $m^2(z) := -\sqrt{\frac{6}{24}}(1-z)^2(z+4z^2+z^3)$ . It is easy to obtain

$$
\begin{bmatrix} a^1(z) & a^2(z) \\ b^1(z) & b^2(z) \end{bmatrix} = \begin{bmatrix} 1 & 4z \\ 0 & 1+z \end{bmatrix},
$$

 $A(z) = \alpha_1 = \alpha_3 z$ , and  $D(z) = \alpha_2$ . Consequently,  $\Delta(z) = 1 \pm z$  with  $\Delta(z) = 1$  and  $\Delta_0(z) = 1$  $1 + z$ . Also,  $C(z) = (1 + z)(\alpha_1 - \alpha_3 z) - 4\alpha_2 z$  and  $D(z) = \alpha_2$  so  $gcd(C, D) = 1$  which implies that  $\Delta_0$  does not divide gcd(C, D) and the expansion of the type (5.3) is not possible for this framelet system.

5.3. The hypothesis - c > 0. Another question relative to our results is the assumption that the function of the function of the function of the frame system system satisfactor  $\mathbf{C}$ we do not have a proof that this holds for any spline framelet system, we have a series of indications that it is not a very restrictive assumption.

- We have manually checked on several spline framelet systems [10, Examples 2.18, 2.19, A.1.a, A.1.b, A.2, A.3.a, A.3.b, A.4] that, indeed - 1.
- It is the system of all systems built using the systematic construction of the systematic construction of the s of spline framelets of high approximation order (see [10, Lemma 3.4]).

A recent result by A. Ron and Z. Shen [26] relates - to the dimension function

$$
D_{\Psi}(\xi) := \sum_{\psi \in \Psi} \sum_{k \in 2\pi \mathbb{Z}} \sum_{j=1}^{\infty} |\hat{\psi}(2^j(\xi + k))|^2
$$

of the framelet system. Under some assumptions of the scaling function  $\phi$  of a MRA-based framelet system, we have the relation

$$
(5.5) \t\t D_{\Psi} = \Theta[\hat{\phi}, \hat{\phi}],
$$

where we used the bracket-product notation  $[f,\widehat{g}] := \sum_{k \in \mathbb{Z}} f(\xi + 2\pi k) \widehat{g}(\xi + 2\pi k)$ . For the spline MRA, the bracket product is easily seen to be continuous and it is bounded and strictly positive by the stability of the shifts of  $\phi$ , see [26]. Hence the problem becomes the strict positivity of the dimension function, however this seems to be an open question.

#### 6. Conclusion and applications

In this paper we have characterized approximation spaces based on tight spline framelet systems and shown they are essentially Besov spaces, just as the orthogonal wavelet case. Contrary to the wavelet case, our characterization holds with no assumption on vanishing moments of the framelets. This is of special importance since framelets constructed using the Unitary Extension Principle can have no more than one vanishing moment.

# ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 19

One of the interesting and challenging aspects of approximation/expansion with a redundant system such asa framelet system is the non-uniqueness of the expansion of a function  $f$  in the system. In general redundant dictionaries, this brings some potentially intractable computational issues [11, 19] as well as a potential increase in the quality of approximation of individual functions. Our results show that for framelet systems

- there is a fast expansion/approximation algorithm that reaches near optimal sparsity and the optimal rate of approximation;
- the gain in approximation power (compared to a wavelet basis) may only be marginal.

6.1. Fast algorithm for near sparsest framelet expansion. In a redundant dictionary, finding an expansion  $f = \sum_k c_k g_k$  that (approximately) minimizes the  $\ell_1$  norm  $\|\{c_k\}\|_{\ell_1}$  is a computationally intensive problem. Combining modern techniques of numerical linear programming and computational harmonic analysis, it is sometimes possible to (approximately) solve this problem with  $\mathcal{O}(N^{3.5})$  elementary operations [3]. In a twice oversampled framelet dictionary there is an  $\mathcal{O}(N)$  algorithm for that.

For any given framelet system, the Euclidean algorithm can be used to solve for the Bezout relation that yields the expansion coefficients  $\{p_n^{\ell}\}\$ in Equation (3.1). Then, a near sparsest expansion of a function  $f$  in the framelet system can be obtained as follows. We put into brackets the computational complexity for a finite dimensional signal of size  $N$ .

(1) Using Mallat's algorithm, perform a fast expansion  $[O(N)]$ 

$$
f(x) = \sum_{j,m} \langle f, \widetilde{\psi}_{j,m} \rangle \psi_{j,m}(x)
$$

with  $(\psi, \widetilde{\psi})$  the "nice" bi-orthogonal wavelet system of Theorem 3.1;

(2) Using Equation (3.1), rewrite the above expansion in terms of framelets  $[O(NLK)]$ 

$$
f(x) = \sum_{j,m} \sum_{\ell=1}^{L} \sum_{n=0}^{K-1} \langle f, \widetilde{\psi}_{j,m} \rangle p_n^{\ell} 2^{j/2} \psi^{\ell} (2^{j}x - m - n/2)
$$
  
= 
$$
\sum_{j,k,\ell} \sum_{\substack{2m+n=k \ c_{j,k,\ell}}} \langle f, \widetilde{\psi}_{j,m} \rangle p_n^{\ell} 2^{j/2} \psi^{\ell} (2^{j}x - k/2)
$$

This expansion algorithm **adapts to unknown sparsity** of  $f$  just as a wavelet expansion does: this is the essence of the proof of the equality  $D_{\tau}^{\pm}(L_{\tau}) = \mathcal{N}_{\tau}(\Lambda_2(\Psi))$ . It follows that the **thresholding algorithm**, which provides m-term approximants  $A_m(f)$  by keeping the  $m$  largest coefficients from the latter expansion, yields the optimal rate of approximation. That is to say, for all f and  $\alpha$  if

$$
\sigma_m(f,X_2(\Psi))_{L_p(\mathbb{R})} = \mathcal{O}(m^{-\alpha}), \qquad m \ge 1
$$

then

$$
||f - A_m(f)||_{L_p(\mathbb{R})} = \mathcal{O}(m^{-\alpha}), \qquad m \ge 1.
$$

It should be noted, however, that we do not have the stronger result

$$
||f - A_m(f)||_{L_p(\mathbb{R})} \leq C \sigma_m(f, X_2(\Psi))_{L_p(\mathbb{R})}
$$

as can obviously be seen by taking  $f = \psi_{j,k}^*$ .

If the above algorithm is replaced by thresholding performed on the frame decomposition

$$
f = \sum_{j,k,\ell} \langle f, \psi_{j,k}^{\ell} \rangle \psi_{j,k}^{\ell},
$$

#### ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 20

Proposition 4.17 shows that similar good properties hold, however we do not know if the new algorithm can adapt to sparsity/rates of approximation  $\alpha > N$ , where N is the number of vanishing moments of the system.

6.2. Application to compression. It is commonly claimed that  $m$ -term expansion from redundant systems can provide lower distortion than from a basis, and this should be useful for, e.g., image compression. With framelet systems, we have just shown that no substantial gain in the rate of nonlinear approximation can be hoped for, compared to approximation from a standard wavelet basis. However this is only a theoretical result, which is far from a "proof" that nothing can be gained from the use of framelets.

First, even though there is an equivalence of the norms kkA <sup>q</sup> (Lp;XR( )) kkA <sup>q</sup> (Lp;B) with  $\beta$  a wavelet basis, the value of the constants in this equivalence may be significantly different one from another. In particular,  $\sigma_m(f, X_2(\Psi))$  may be significantly smaller than  $\sigma_m(f, \mathcal{B})$  in general.

Then, the results in this paper only show that no substantial **asymptotic** gain can be hoped for, but there may be a substantial gain for approximations with few framelets compared to approximation with few wavelets. This gain may be quantitative (smaller error  $\sigma_m(f, X_2(\Psi)) \ll \sigma_m$ ,  $(f, \mathcal{B})$  as well as **qualitative**. Indeed, because we can use framelets with only one vanishing moment, we may obtain approximants which yield less "ringing" artifacts (i.e. less Gibbs phenomenon) than with wavelets.

Redundancy is a crucial element here: in wavelet approximation, approximants to a function f are built using the inner products  $\langle f, \psi_{i,k} \rangle$ . Hence, oscillating wavelets (vanishing moments) with  $\langle x^{\shortparallel}, \psi_{i,k} \rangle, 0 \leq n \leq r$  are needed to  $\|$  kill the low order terms of the Taylor expansion  $f(x) \approx a_0 + a_1x + a_2x^2 + \dots$  With a redundant framelet system, we have more freedom in building approximants. Hence, we may take advantage of the variety of shapes (number of vanishing moments) of the framelets to fit the various types of features that are present in a signal/image.

In practical applications of framelet decomposition, it may be useful to combine

- the above described Mallat+rewrite frame decomposition
- $\bullet$  standard tight frame coefficients

and some numerical optimization methods, in order to get an expansion that fully takes advantage of the various "feature detectors".

Acknowledgments. The authors would like to thank Amos Ron and Zuowei Shen for interesting discussions of matters related to this paper during our visits to Madison, WI. We should also mention that Narfi Stefansson's promising numerical results using framelets for compression purposes served asan inspiration for much of this work. Finally, we would like to thank Ronald DeVore for his constant encouragement and support.

#### **REFERENCES**

- [1] Colin Bennett and Robert Sharpley. Interpolation of operators. Academic Press Inc., Boston, MA, 1988.
- [2] P. Casazza. Every frame is a sum of three (but not two) orthonormal bases—and other frame representations. *J. Fourier Anal. Appl.*,  $4(6)$ :  $727–732$ , 1998.
- [3] S. Chen and D.L. Donoho. Atomic decomposition by basis pursuit. SIAM Journal on Scientific Computing,  $20(1)$ :33-61, January 1999.
- [4] Charles K. Chui. An introduction to wavelets. Academic Press Inc., Boston, MA, 1992.
- [5] Charles K. Chui. On cardinal spline-wavelets. In Wavelets and their applications, pages 419–438. Jones and Bartlett, Boston, MA, 1992.
- [6] Charles K. Chui and Jian-Zhong Wang. On compactly supported spline wavelets and a duality principle. Trans. Amer. Math. Soc., 330(2):903-915, 1992.

#### ON APPROXIMATION WITH SPLINE GENERATED FRAMELETS 21

- [7] A. Cohen, W. Dahmen, and R. DeVore. Multiscale decompositions on bounded domains. Trans. Amer. Math. Soc.,  $352(8):3651-3685, 2000$ .
- [8] Albert Cohen. Biorthogonal wavelets. In Charles K. Chui, editor, Wavelets: A Tutorial in Theory and Applications, volume 2, pages 123-152. Academic Press, Boston, MA, 1992.
- [9] Ingrid Daubechies. Ten lectures on wavelets. Society for Industrial and Applied Mathematics (SIAM), Philadelphia, PA, 1992.
- [10] Ingrid Daubechies, Bin Han, Amos Ron, and Zuowei Shen. Framelets: MRA-based constructions of wavelet frames. Preprint, 2001.
- [11] G. Davis, S. Mallat, and M. Avellaneda. Adaptive greedy approximations. Constr. Approx., 13(1):57-98, 1997.
- [12] R. De Vore, B. Jawerth, and B.J. Lucier. Image compression through wavelet transform coding. IEEE Trans. on Inform. Theory,  $38:719-746$ , March 1992.
- [13] R. A. DeVore, S. V. Konyagin, and V. N. Temlyakov. Hyperbolic wavelet approximation. Constr. Approx.,  $14(1):1-26$ , 1998.
- [14] Ronald A. DeVore. Nonlinear approximation. In Acta numerica, 1998, pages 51–150. Cambridge Univ. Press, Cambridge, 1998.
- [15] Ronald A. DeVore, Björn Jawerth, and Vasil Popov. Compression of wavelet decompositions. Amer. J.  $Math., 114(4): 737–785, 1992.$
- [16] Ronald A. DeVore and George G. Lorentz. Constructive approximation. Springer-Verlag, Berlin, 1993.
- [17] Michael Frazier and Björn Jawerth. Decomposition of Besov spaces. *Indiana Univ. Math. J.*, 34(4):777– 799, 1985.
- [18] R. Gribonval and M. Nielsen. Nonlinear approximation with redundant dictionaries. IMI preprint, 2002.
- [19] Lee K. Jones. The computational intractability of training sigmoidal neural networks. IEEE Trans. Inform. Theory,  $43(1):167–173$ , 1997.
- [20] Yves Meyer. Ondelettes et operateurs. II. Hermann, Paris, 1990. Operateurs de Calderon-Zygmund. [Calderón-Zygmund operators].
- [21] Yves Meyer. Wavelets and operators. Cambridge University Press, Cambridge, 1992. Translated from the 1990 French original by D. H. Salinger.
- [22] Pencho Petrushev. Bases consisting of rational functions of uniformly bounded degrees or more general functions. *J. Funct. Anal.*,  $174(1):18–75, 2000$ .
- [23] Pencho P. Petrushev. Direct and converse theorems for spline and rational approximation and Besov spaces. In Function spaces and applications  $(Lund, 1986)$ , pages 363–377. Springer, Berlin, 1988.
- [24] Amos Ron and Zuowei Shen. Amne systems in  $L_2(\mathbf{R}^*)$ . II. Dual systems. *J. Fourier Anal. Appl.*, 3(5):617(= 637, 1997. Dedicated to the memory of Richard J. Duffin.
- [25] Amos Ron and Zuowei Shen. Anime systems in  $L_2({\bf R}^*)$ : the analysis of the analysis operator. J. Funct. Anal.,  $148(2)$ :  $408-447$ , 1997.
- [26] Amos Ron and Zuowei Shen. The wavelet dimension function is the trace of a shift-invariant system. preprint, 2001.
- [27] Hans Triebel. The structure of functions. Birkhäuser Verlag, Basel, 2001.
- [28] P. Wojtaszczyk. Wavelets as unconditional bases in  $L_p(\mathbb{R})$ . J. Fourier Anal. Appl., 5(1):73-85, 1999.

IRISA-INRIA, Campus de Beaulieu, 35042 Rennes CEDEX, France  $E\text{-}mail address:$  Remi.Gribonval@inria.fr

Department of Mathematics, University of South Carolina, South Carolina 29208, USA  $E-mail$   $address:$   $nielsen@math$ .sc.edu