



HAL
open science

On the construction of Patchy Feedbacks for stabilization and optimization problems

Fabio Ancona

► **To cite this version:**

Fabio Ancona. On the construction of Patchy Feedbacks for stabilization and optimization problems. SADCO Kick off, Mar 2011, Paris, France. inria-00585711

HAL Id: inria-00585711

<https://inria.hal.science/inria-00585711>

Submitted on 13 Apr 2011

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

On the construction of Patchy Feedbacks for stabilization and optimization problems

Fabio ANCONA

University of Padova

ITN SADCO - Kick off Meeting

Ensta Paris Tech, Paris

March 3 - 4, 2011

Outline

- 1 Introduction
 - General Setting
 - Main Difficulties
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - Robustness of Patchy Vector Fields
- 3 Patchy Feedbacks
 - Definition
 - Stabilizing Patchy Feedback
 - Nearly Optimal Patchy Feedback
 - ISS Patchy Feedback

Outline

- 1 **Introduction**
 - General Setting
 - Main Difficulties
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - Robustness of Patchy Vector Fields
- 3 Patchy Feedbacks
 - Definition
 - Stabilizing Patchy Feedback
 - Nearly Optimal Patchy Feedback
 - ISS Patchy Feedback

Consider a control system

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in \mathbb{R}^m \quad (1)$$

- f smooth with sublinear growth

$$|f(x, u)| \leq c(1 + |x|) \quad \forall x, u$$

- (I) **Asymptotic Feedback Stabilization:** Seek feedback control $u = U(x)$ s.t. all trajectories of

$$\dot{x} = g(x) \doteq f(x, U(x)) \quad (2)$$

approach the origin as $t \rightarrow \infty$ (and the origin is Lyapunov stable).

- (II) **Optimal Feedback Control:** Given compact set $K \subset \mathbb{R}^n$, seek feedback control $u = U(x)$ s.t. all sol'ns of (1) reach given target set S in minimum time.

Consider a control system

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in \mathbb{R}^m \quad (1)$$

- f smooth with sublinear growth

$$|f(x, u)| \leq c(1 + |x|) \quad \forall x, u$$

- (I) **Asymptotic Feedback Stabilization:** Seek feedback control $u = U(x)$ s.t. all trajectories of

$$\dot{x} = g(x) \doteq f(x, U(x)) \quad (2)$$

approach the origin as $t \rightarrow \infty$ (and the origin is Lyapunov stable).

- (II) **Optimal Feedback Control:** Given compact set $K \subset \mathbb{R}^n$, seek feedback control $u = U(x)$ s.t. all sol'ns of (1) reach given target set S in minimum time.

Consider a control system

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in \mathbb{R}^m \quad (1)$$

- f smooth with sublinear growth

$$|f(x, u)| \leq c(1 + |x|) \quad \forall x, u$$

- (I) **Asymptotic Feedback Stabilization:** Seek feedback control $u = U(x)$ s.t. all trajectories of

$$\dot{x} = g(x) \doteq f(x, U(x)) \quad (2)$$

approach the origin as $t \rightarrow \infty$ (and the origin is Lyapunov stable).

- (II) **Optimal Feedback Control:** Given compact set $K \subset \mathbb{R}^n$, seek feedback control $u = U(x)$ s.t. all sol'ns of (1) reach given target set S in minimum time.

Consider a control system

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in \mathbb{R}^m \quad (1)$$

- f smooth with sublinear growth

$$|f(x, u)| \leq c(1 + |x|) \quad \forall x, u$$

- (I) **Asymptotic Feedback Stabilization:** Seek feedback control $u = U(x)$ s.t. all trajectories of

$$\dot{x} = g(x) \doteq f(x, U(x)) \quad (2)$$

approach the origin as $t \rightarrow \infty$ (and the origin is Lyapunov stable).

- (II) **Optimal Feedback Control:** Given compact set $K \subset \mathbb{R}^n$, seek feedback control $u = U(x)$ s.t. all sol'ns of (1) reach given target set S in minimum time.

Outline

- 1 Introduction
 - General Setting
 - **Main Difficulties**
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - Robustness of Patchy Vector Fields
- 3 Patchy Feedbacks
 - Definition
 - Stabilizing Patchy Feedback
 - Nearly Optimal Patchy Feedback
 - ISS Patchy Feedback

- Smooth feedback controls that solve (I)-(II) in general may not exist

(I) Topological obstructions may prevent the existence of smooth (or even continuous) stabilizing feedback

(SUSSMANN '79; SONTAG & SUSSMANN '80; BROCKETT '83; CORON '90)

Ex: Brockett's nonholonomic integrator

$$\left. \begin{aligned} \dot{x}_1 &= u_1 \\ \dot{x}_2 &= u_2 \\ \dot{x}_3 &= x_1 u_2 - x_2 u_1 \end{aligned} \right\} \doteq f(x, u) \quad \begin{aligned} &(x_1, x_2, u_1, u_2) \rightarrow f(x, u) \\ &\text{not open at zero :} \\ &(0, 0, x_3) \notin \text{Im}(f) \quad \text{when } x_3 \neq 0 \end{aligned}$$

(II) Optimal feedback can be discontinuous with quite complicated structure, while optimal (open-loop) controls may have infinitely many switchings

- Smooth feedback controls that solve (I)-(II) in general may not exist

(I) Topological obstructions may prevent the existence of smooth (or even continuous) stabilizing feedback

(SUSSMANN '79; SONTAG & SUSSMANN '80; BROCKETT '83; CORON '90)

Ex: Brockett's nonholonomic integrator

$$\left. \begin{aligned} \dot{x}_1 &= u_1 \\ \dot{x}_2 &= u_2 \\ \dot{x}_3 &= x_1 u_2 - x_2 u_1 \end{aligned} \right\} \doteq f(x, u) \quad \begin{aligned} &(x_1, x_2, u_1, u_2) \rightarrow f(x, u) \\ &\text{not open at zero :} \\ &(0, 0, x_3) \notin \text{Im}(f) \text{ when } x_3 \neq 0 \end{aligned}$$

(II) Optimal feedback can be discontinuous with quite complicated structure, while optimal (open-loop) controls may have infinitely many switchings

- Smooth feedback controls that solve (I)-(II) in general may not exist

(I) Topological obstructions may prevent the existence of smooth (or even continuous) stabilizing feedback

(SUSSMANN '79; SONTAG & SUSSMANN '80; BROCKETT '83; CORON '90)

Ex: Brockett's nonholonomic integrator

$$\left. \begin{aligned} \dot{x}_1 &= u_1 \\ \dot{x}_2 &= u_2 \\ \dot{x}_3 &= x_1 u_2 - x_2 u_1 \end{aligned} \right\} \doteq f(x, u) \quad \begin{aligned} &(x_1, x_2, u_1, u_2) \rightarrow f(x, u) \\ &\text{not open at zero :} \\ &(0, 0, x_3) \notin \text{Im}(f) \text{ when } x_3 \neq 0 \end{aligned}$$

(II) Optimal feedback can be discontinuous with quite complicated structure, while optimal (open-loop) controls may have infinitely many switchings

- Smooth feedback controls that solve (I)-(II) in general may not exist

(I) Topological obstructions may prevent the existence of smooth (or even continuous) stabilizing feedback

(SUSSMANN '79; SONTAG & SUSSMANN '80; BROCKETT '83; CORON '90)

Ex: Brockett's nonholonomic integrator

$$\left. \begin{aligned} \dot{x}_1 &= u_1 \\ \dot{x}_2 &= u_2 \\ \dot{x}_3 &= x_1 u_2 - x_2 u_1 \end{aligned} \right\} \doteq f(x, u) \quad \begin{aligned} (x_1, x_2, u_1, u_2) &\rightarrow f(x, u) \\ \text{not open at zero :} \\ (0, 0, x_3) &\notin \text{Im}(f) \text{ when } x_3 \neq 0 \end{aligned}$$

(II) Optimal feedback can be discontinuous with quite complicated structure, while optimal (open-loop) controls may have infinitely many switchings

- Smooth feedback controls that solve (I)-(II) in general may not exist

(I) Topological obstructions may prevent the existence of smooth (or even continuous) stabilizing feedback

(SUSSMANN '79; SONTAG & SUSSMANN '80; BROCKETT '83; CORON '90)

Ex: Brockett's nonholonomic integrator

$$\left. \begin{aligned} \dot{x}_1 &= u_1 \\ \dot{x}_2 &= u_2 \\ \dot{x}_3 &= x_1 u_2 - x_2 u_1 \end{aligned} \right\} \doteq f(x, u) \quad \begin{aligned} &(x_1, x_2, u_1, u_2) \rightarrow f(x, u) \\ &\text{not open at zero :} \\ &(0, 0, x_3) \notin \text{Im}(f) \text{ when } x_3 \neq 0 \end{aligned}$$

(II) Optimal feedback can be discontinuous with quite complicated structure, while optimal (open-loop) controls may have infinitely many switchings

- Smooth feedback controls that solve (I)-(II) in general may not exist

(I) Topological obstructions may prevent the existence of smooth (or even continuous) stabilizing feedback

(SUSSMANN '79; SONTAG & SUSSMANN '80; BROCKETT '83; CORON '90)

Ex: Brockett's nonholonomic integrator

$$\left. \begin{aligned} \dot{x}_1 &= u_1 \\ \dot{x}_2 &= u_2 \\ \dot{x}_3 &= x_1 u_2 - x_2 u_1 \end{aligned} \right\} \doteq f(x, u) \quad \begin{aligned} (x_1, x_2, u_1, u_2) &\rightarrow f(x, u) \\ \text{not open at zero :} \\ (0, 0, x_3) &\notin \text{Im}(f) \text{ when } x_3 \neq 0 \end{aligned}$$

(II) Optimal feedback can be discontinuous with quite complicated structure, while optimal (open-loop) controls may have infinitely many switchings

- Smooth feedback controls that solve (I)-(II) in general may not exist

(I) Topological obstructions may prevent the existence of smooth (or even continuous) stabilizing feedback

(SUSSMANN '79; SONTAG & SUSSMANN '80; BROCKETT '83; CORON '90)

Ex: Brockett's nonholonomic integrator

$$\left. \begin{aligned} \dot{x}_1 &= u_1 \\ \dot{x}_2 &= u_2 \\ \dot{x}_3 &= x_1 u_2 - x_2 u_1 \end{aligned} \right\} \doteq f(x, u) \quad \begin{aligned} (x_1, x_2, u_1, u_2) &\rightarrow f(x, u) \\ \text{not open at zero :} \\ (0, 0, x_3) &\notin \text{Im}(f) \text{ when } x_3 \neq 0 \end{aligned}$$

(II) Optimal feedback can be discontinuous with quite complicated structure, while optimal (open-loop) controls may have infinitely many switchings

- Smooth feedback controls that solve (I)-(II) in general may not exist

(I) Topological obstructions may prevent the existence of smooth (or even continuous) stabilizing feedback

(SUSSMANN '79; SONTAG & SUSSMANN '80; BROCKETT '83; CORON '90)

Ex: Brockett's nonholonomic integrator

$$\left. \begin{aligned} \dot{x}_1 &= u_1 \\ \dot{x}_2 &= u_2 \\ \dot{x}_3 &= x_1 u_2 - x_2 u_1 \end{aligned} \right\} \doteq f(x, u) \quad \begin{aligned} (x_1, x_2, u_1, u_2) &\rightarrow f(x, u) \\ \text{not open at zero :} \\ (0, 0, x_3) &\notin \text{Im}(f) \text{ when } x_3 \neq 0 \end{aligned}$$

(II) Optimal feedback can be discontinuous with quite complicated structure, while optimal (open-loop) controls may have infinitely many switchings

- Discontinuous stabilizing (or optimal) feedback in general are not robust w.r.t. (inner and outer) perturbations

$$\dot{x} = f(x, U(x + e_1(t))) + e_2(t) \quad (3)$$

(e_1 : measurement error, e_2 : external disturbance)

achieves much worse performance than the stabilizing (or optimal) one.

- Discontinuous stabilizing (or optimal) feedback in general are not robust w.r.t. (inner and outer) perturbations

$$\dot{x} = f(x, U(x + e_1(t))) + e_2(t) \quad (3)$$

(e_1 : measurement error, e_2 : external disturbance)

achieves much worse performance than the stabilizing (or optimal) one.

Two possible approaches

in dealing with stabilization and optimization problems for

$$\dot{x} = f(x, U(x)).$$

1. Allow **arbitrary discontinuous feedback** controls $u = U(x)$ and work with weak or generalized solutions of discontinuous ODEs.
2. Use a particular class of feedback controls $U(x)$ whose **discontinuities** are **sufficiently tame** so to guarantee the existence of **Carathéodory solutions**

$$x(t) = \bar{x} + \int_0^t f(x(s), U(x(s))) ds.$$

Two possible approaches

in dealing with stabilization and optimization problems for

$$\dot{x} = f(x, U(x)).$$

1. Allow **arbitrary discontinuous feedback** controls $u = U(x)$ and work with weak or generalized solutions of discontinuous ODEs.
2. Use a particular class of feedback controls $U(x)$ whose **discontinuities** are **sufficiently tame** so to guarantee the existence of **Carathéodory solutions**

$$x(t) = \bar{x} + \int_0^t f(x(s), U(x(s))) ds.$$

Two possible approaches

in dealing with stabilization and optimization problems for

$$\dot{x} = f(x, U(x)).$$

1. Allow **arbitrary discontinuous feedback** controls $u = U(x)$ and work with weak or generalized solutions of discontinuous ODEs.
2. Use a particular class of feedback controls $U(x)$ whose **discontinuities** are **sufficiently tame** so to guarantee the existence of **Carathéodory solutions**

$$x(t) = \bar{x} + \int_0^t f(x(s), U(x(s))) ds.$$

How to interpret solutions to discontinuous ODEs ?

- Define weaker concept of solution

For example, one can consider Krasovskii sol'ns, i.e. trajectories of the differential inclusion

$$\dot{x} \in G(x) \doteq \bigcap_{\varepsilon > 0} \overline{\text{co}} \{ g(y); |y - x| < \varepsilon \}, \quad g(y) \doteq f(x, U(x)). \quad (4)$$

Drawback: too many sol'ns are obtained. Not all enjoy desired properties.

- Introduce suitable generalized solutions:

"Sample-and-hold-solutions" & "Euler solutions" : successfully implemented for problems (I)-(II)

(CLARKE, LEDYAEV, SONTAG & SUBBOTIN '97; RIFFORD 2000, 2002)

How to interpret solutions to discontinuous ODEs ?

- Define weaker concept of solution

For example, one can consider Krasovskii sol'ns, i.e. trajectories of the differential inclusion

$$\dot{x} \in G(x) \doteq \bigcap_{\varepsilon > 0} \overline{\text{co}} \{ g(y); |y - x| < \varepsilon \}, \quad g(y) \doteq f(x, U(x)). \quad (4)$$

Drawback: too many sol'ns are obtained. Not all enjoy desired properties.

- Introduce suitable generalized solutions:

“Sample-and-hold-solutions” & “Euler solutions” : successfully implemented for problems (I)-(II)

(CLARKE, LEDYAEV, SONTAG & SUBBOTIN '97; RIFFORD 2000, 2002)

S-a-h solutions & Euler solutions of $\dot{x} = f(x, U(x))$

S-a-h solution $x(t)$ recursively defined as follows.

1. fix a time mesh $t_0 = 0 < t_1 < \dots < t_i < \dots$, with size $\delta \doteq \sup |t_{i+1} - t_i|$;
2. sample $U(x(t_i)) \doteq u_i$ and compute $x(t) \doteq x_{i+1}(t)$, $t \in]t_i, t_{i+1}]$ solving

$$\dot{x}_{i+1} = f(x_{i+1}, u_i), \quad x_{i+1}(t_i) = x_i(t_i) \quad \text{on }]t_i, t_{i+1}].$$

Euler solution is a (uniform) limit of S-a-h solutions as size $\delta \rightarrow 0$.

S-a-h solutions & Euler solutions of $\dot{x} = f(x, U(x))$

S-a-h solution $x(t)$ recursively defined as follows.

1. fix a time mesh $t_0 = 0 < t_1 < \dots < t_i < \dots$, with size $\delta \doteq \sup |t_{i+1} - t_i|$;
2. sample $U(x(t_i)) \doteq u_i$ and compute $x(t) \doteq x_{i+1}(t)$, $t \in]t_i, t_{i+1}]$ solving

$$\dot{x}_{i+1} = f(x_{i+1}, u_i), \quad x_{i+1}(t_i) = x_i(t_i) \quad \text{on }]t_i, t_{i+1}].$$

Euler solution is a (uniform) limit of S-a-h solutions as size $\delta \rightarrow 0$.

S-a-h solutions & Euler solutions of $\dot{x} = f(x, U(x))$

S-a-h solution $x(t)$ recursively defined as follows.

1. fix a time mesh $t_0 = 0 < t_1 < \dots < t_i < \dots$, with size $\delta \doteq \sup |t_{i+1} - t_i|$;
2. sample $U(x(t_i)) \doteq u_i$ and compute $x(t) \doteq x_{i+1}(t)$, $t \in]t_i, t_{i+1}]$ solving

$$\dot{x}_{i+1} = f(x_{i+1}, u_i), \quad x_{i+1}(t_i) = x_i(t_i) \quad \text{on }]t_i, t_{i+1}].$$

Euler solution is a (uniform) limit of S-a-h solutions as size $\delta \rightarrow 0$.

An alternative approach

1. Introduce a class of discontinuous, piecewise smooth vector fields “**Patchy Vector Fields**” (PVF) which admit (forward) Carathéodory solutions, and analyze their properties.
2. Construct piecewise smooth stabilizing or optimal feedback $U = U(x)$ so that corresponding vector field $g(x) \doteq f(x, U(x))$ belongs to such class of PVF.
3. Establish **robustness properties** of stabilizing or optimal feedback in this class, relative to **external disturbances** and **internal measurement errors**.

(A. & BRESSAN '99-2008; BRESSAN & PRIULI 2008; A. & PRIULI 2011)

An alternative approach

1. Introduce a class of discontinuous, piecewise smooth vector fields “**Patchy Vector Fields**” (PVF) which admit (forward) Carathéodory solutions, and analyze their properties.
2. Construct piecewise smooth stabilizing or optimal feedback $U = U(x)$ so that corresponding vector field $g(x) \doteq f(x, U(x))$ belongs to such class of PVF.
3. Establish **robustness properties** of stabilizing or optimal feedback in this class, relative to **external disturbances** and **internal measurement errors**.

(A. & BRESSAN '99-2008; BRESSAN & PRIULI 2008; A. & PRIULI 2011)

An alternative approach

1. Introduce a class of discontinuous, piecewise smooth vector fields “**Patchy Vector Fields**” (PVF) which admit (forward) Carathéodory solutions, and analyze their properties.
2. Construct piecewise smooth stabilizing or optimal feedback $U = U(x)$ so that corresponding vector field $g(x) \doteq f(x, U(x))$ belongs to such class of PVF.
3. Establish **robustness properties** of stabilizing or optimal feedback in this class, relative to **external disturbances** and **internal measurement errors**.

(A. & BRESSAN '99-2008; BRESSAN & PRIULI 2008; A. & PRIULI 2011)

An alternative approach

1. Introduce a class of discontinuous, piecewise smooth vector fields “**Patchy Vector Fields**” (PVF) which admit (forward) Carathéodory solutions, and analyze their properties.
2. Construct piecewise smooth stabilizing or optimal feedback $U = U(x)$ so that corresponding vector field $g(x) \doteq f(x, U(x))$ belongs to such class of PVF.
3. Establish **robustness properties** of stabilizing or optimal feedback in this class, relative to **external disturbances** and **internal measurement errors**.

(A. & BRESSAN '99-2008; BRESSAN & PRIULI 2008; A. & PRIULI 2011)

An alternative approach

1. Introduce a class of discontinuous, piecewise smooth vector fields “**Patchy Vector Fields**” (PVF) which admit (forward) Carathéodory solutions, and analyze their properties.
2. Construct piecewise smooth stabilizing or optimal feedback $U = U(x)$ so that corresponding vector field $g(x) \doteq f(x, U(x))$ belongs to such class of PVF.
3. Establish **robustness properties** of stabilizing or optimal feedback in this class, relative to **external disturbances** and **internal measurement errors**.

(A. & BRESSAN '99-2008; BRESSAN & PRIULI 2008; A. & PRIULI 2011)

Outline

- 1 Introduction
 - General Setting
 - Main Difficulties
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - Robustness of Patchy Vector Fields
- 3 Patchy Feedbacks
 - Definition
 - Stabilizing Patchy Feedback
 - Nearly Optimal Patchy Feedback
 - ISS Patchy Feedback


- **Patches**

(Ω, g) is said to be a **patch** if:

- $\Omega \subset \mathbb{R}^n$ is open domain with (piecewise) smooth boundary $\partial\Omega$
- g smooth vector field on a neighborhood of $\partial\Omega$, that points strictly inward at each point $x \in \partial\Omega$

$$\langle g(x), \mathbf{n}(x) \rangle < 0 \quad \forall x \in \partial\Omega$$

$\mathbf{n}(x)$ outer normal to $\partial\Omega$ in x




- **Patches**

(Ω, g) is said to be a **patch** if:

- $\Omega \subset \mathbb{R}^n$ is open domain with (piecewise) smooth boundary $\partial\Omega$
- g smooth vector field on a neighborhood of $\partial\Omega$, that points strictly inward at each point $x \in \partial\Omega$

$$\langle g(x), \mathbf{n}(x) \rangle < 0 \quad \forall x \in \partial\Omega$$

$\mathbf{n}(x)$ outer normal to $\partial\Omega$ in x




- **Patches**

(Ω, g) is said to be a **patch** if:

- $\Omega \subset \mathbb{R}^n$ is open domain with (piecewise) smooth boundary $\partial\Omega$
- g smooth vector field on a neighborhood of $\partial\Omega$, that points strictly inward at each point $x \in \partial\Omega$

$$\langle g(x), \mathbf{n}(x) \rangle < 0 \quad \forall x \in \partial\Omega$$


$\mathbf{n}(x)$ outer normal to $\partial\Omega$ in x



- Patchy Vector Fields

locally finite covering in terms of patches (Ω_i, g_i) , $i \in \mathbb{Z}$.
 $g : \Omega \rightarrow \mathbb{R}^n$ is said to be a **patchy vector field** if:

$$g(x) = g_i(x) \iff x \in \Omega_i \setminus \bigcup_{j>i} \Omega_j$$




$$\implies g(x) = g_{i^*}(x), \quad i^*(x) \doteq \max\{i \in \mathbb{Z} : x \in \Omega_i\}$$

- Patchy Vector Fields

locally finite covering in terms of patches (Ω_i, g_i) , $i \in \mathbb{Z}$.
 $g : \Omega \rightarrow \mathbb{R}^n$ is said to be a **patchy vector field** if:

$$g(x) = g_i(x) \iff x \in \Omega_i \setminus \bigcup_{j>i} \Omega_j$$




$$\implies g(x) = g_{i^*(x)}(x), \quad i^*(x) \doteq \max\{i \in \mathbb{Z} : x \in \Omega_i\}$$

- Patchy Vector Fields

locally finite covering in terms of patches (Ω_i, g_i) , $i \in \mathbb{Z}$.
 $g : \Omega \rightarrow \mathbb{R}^n$ is said to be a **patchy vector field** if:

$$g(x) = g_i(x) \iff x \in \Omega_i \setminus \bigcup_{j>i} \Omega_j$$




$$\implies g(x) = g_{i^*(x)}(x), \quad i^*(x) \doteq \max\{i \in \mathbb{Z} : x \in \Omega_i\}$$

- Patchy Vector Fields

locally finite covering in terms of patches (Ω_i, g_i) , $i \in \mathbb{Z}$.
 $g : \Omega \rightarrow \mathbb{R}^n$ is said to be a **patchy vector field** if:

$$g(x) = g_i(x) \iff x \in \Omega_i \setminus \bigcup_{j>i} \Omega_j$$



$$\implies g(x) = g_{i^*(x)}(x), \quad i^*(x) \doteq \max\{j \in \mathbb{Z} : x \in \Omega_j\}$$

Properties of Patchy Vector Fields

$$\dot{x} = g(x) = g_{j^*(x)}(x)$$

ODEs with patchy right hand side (A. & BRESSAN '99)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Then the following holds.

i) For every $\bar{x} \in \Omega$

$$\begin{cases} \dot{x} = g(x) \\ x(0) = \bar{x} \end{cases}$$

has

at least 1 (local) forward at most 1 backward
--

Carathéodory soln

- ii) sol'ns $x(t)$ are piecewise smooth, with derivatives having finite set of jumps on any compact time interval. The map $t \mapsto j_*(x(t))$ is **piecewise constant, non-decreasing**.
- iii) Set of Carathéodory sol'ns is closed in the topology of uniform convergence.

Properties of Patchy Vector Fields

$$\dot{x} = g(x) = g_{j^*(x)}(x)$$

ODEs with patchy right hand side (A. & BRESSAN '99)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Then the following holds.

i) For every $\bar{x} \in \Omega$

$$\begin{cases} \dot{x} = g(x) \\ x(0) = \bar{x} \end{cases} \text{ has } \begin{array}{|c|} \hline \text{at least 1 (local) forward} \\ \text{at most 1 backward} \\ \hline \end{array} \text{ Carathéodory soln}$$

- ii) sol'ns $x(t)$ are piecewise smooth, with derivatives having finite set of jumps on any compact time interval. The map $t \mapsto i_*(x(t))$ is piecewise constant, non-decreasing.
- iii) Set of Carathéodory sol'ns is closed in the topology of uniform convergence.

Properties of Patchy Vector Fields

$$\dot{x} = g(x) = g_{j^*(x)}(x)$$

ODEs with patchy right hand side (A. & BRESSAN '99)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Then the following holds.

i) For every $\bar{x} \in \Omega$

$$\begin{cases} \dot{x} = g(x) \\ x(0) = \bar{x} \end{cases}$$

has

at least 1 (local) forward
at most 1 backward

Carathéodory soln

- ii) sol'ns $x(t)$ are piecewise smooth, with derivatives having finite set of jumps on any compact time interval. The map $t \mapsto j_*(x(t))$ is piecewise constant, non-decreasing.
- iii) Set of Carathéodory sol'ns is closed in the topology of uniform convergence.

Properties of Patchy Vector Fields

$$\dot{x} = g(x) = g_{j^*(x)}(x)$$

ODEs with patchy right hand side (A. & BRESSAN '99)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Then the following holds.

i) For every $\bar{x} \in \Omega$

$$\begin{cases} \dot{x} = g(x) \\ x(0) = \bar{x} \end{cases}$$

has

at least 1 (local) forward
at most 1 backward

Carathéodory soln

- ii) sol'ns $x(t)$ are piecewise smooth, with derivatives having finite set of jumps on any compact time interval. The map $t \mapsto j_*(x(t))$ is piecewise constant, non-decreasing.
- iii) Set of Carathéodory sol'ns is closed in the topology of uniform convergence.

Properties of Patchy Vector Fields

$$\dot{x} = g(x) = g_{j^*(x)}(x)$$

ODEs with patchy right hand side (A. & BRESSAN '99)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Then the following holds.

i) For every $\bar{x} \in \Omega$

$$\begin{cases} \dot{x} = g(x) \\ x(0) = \bar{x} \end{cases} \text{ has } \boxed{\begin{array}{l} \text{at least 1 (local) forward} \\ \text{at most 1 backward} \end{array}} \text{ Carathéodory soln}$$

ii) sol'ns $x(t)$ are piecewise smooth, with derivatives having finite set of jumps on any compact time interval. The map $t \mapsto j_*(x(t))$ is **piecewise constant, non-decreasing**.

iii) Set of Carathéodory sol'ns is closed in the topology of uniform convergence.

Properties of Patchy Vector Fields

$$\dot{x} = g(x) = g_{j^*(x)}(x)$$

ODEs with patchy right hand side (A. & BRESSAN '99)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Then the following holds.

i) For every $\bar{x} \in \Omega$


$$\begin{cases} \dot{x} = g(x) \\ x(0) = \bar{x} \end{cases} \text{ has } \boxed{\begin{array}{l} \text{at least 1 (local) forward} \\ \text{at most 1 backward} \end{array}} \text{ Carathéodory soln}$$

- ii) sol'ns $x(t)$ are piecewise smooth, with derivatives having finite set of jumps on any compact time interval. The map $t \mapsto j_*(x(t))$ is piecewise constant, non-decreasing.
- iii) Set of Carathéodory sol'ns is closed in the topology of uniform convergence.

Properties of Patchy Vector Fields ... continued

Note: in general, the **set of Carathéodory solutions** to a Cauchy problem is **not connected**, not acyclic.


This is GOOD, because it avoids topological obstructions toward the existence of stabilizing (or optimal) patchy feedbacks.



Properties of Patchy Vector Fields ... continued

Note: in general, the **set of Carathéodory solutions** to a Cauchy problem is **not connected**, not acyclic.

This is GOOD, because it avoids topological obstructions toward the existence of stabilizing (or optimal) patchy feedbacks.



Outline

- 1 Introduction
 - General Setting
 - Main Difficulties
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - **Robustness of Patchy Vector Fields**
- 3 Patchy Feedbacks
 - Definition
 - Stabilizing Patchy Feedback
 - Nearly Optimal Patchy Feedback
 - ISS Patchy Feedback

Robustness w.r.t. (small) inner and outer perturbations

$$\dot{y} = g(y + e_1(t)) + e_2(t) \quad (5)$$

Flow stability of a Patchy Vector Field (A. & BRESSAN 2003, 2004)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Given any compact subset $C_0 \subset \Omega$, and any $T, \varepsilon > 0$, there exists $\delta > 0$ such that the following holds.

If $y : [0, T] \mapsto \Omega$ is a solution of the perturbed system (5), with $y(0) \in C_0$, and

$$\|e_1\|_{BV} \leq \delta, \quad \|e_2\|_{L^1} \leq \delta,$$

then there exists a solution $x : [0, T] \mapsto \Omega$ of the unperturbed equation

$$\dot{x} = g(x),$$

with

$$|x(t) - y(t)| < \varepsilon \quad \forall t \in [0, T].$$

Robustness w.r.t. (small) inner and outer perturbations

$$\dot{y} = g(y + e_1(t)) + e_2(t) \quad (5)$$

Flow stability of a Patchy Vector Field (A. & BRESSAN 2003, 2004)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Given any compact subset $C_0 \subset \Omega$, and any $T, \varepsilon > 0$, there exists $\delta > 0$ such that the following holds.

If $y : [0, T] \mapsto \Omega$ is a solution of the perturbed system (5), with $y(0) \in C_0$, and

$$\|e_1\|_{BV} \leq \delta, \quad \|e_2\|_{L^1} \leq \delta,$$

then there exists a solution $x : [0, T] \mapsto \Omega$ of the unperturbed equation

$$\dot{x} = g(x),$$

with

$$|x(t) - y(t)| < \varepsilon \quad \forall t \in [0, T].$$

Robustness w.r.t. (small) inner and outer perturbations

$$\dot{y} = g(y + e_1(t)) + e_2(t) \quad (5)$$

Flow stability of a Patchy Vector Field (A. & BRESSAN 2003, 2004)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Given any compact subset $C_0 \subset \Omega$, and any $T, \varepsilon > 0$, there exists $\delta > 0$ such that the following holds.

If $y : [0, T] \mapsto \Omega$ is a solution of the perturbed system (5), with $y(0) \in C_0$, and

$$\|e_1\|_{BV} \leq \delta, \quad \|e_2\|_{L^1} \leq \delta,$$

then there exists a solution $x : [0, T] \mapsto \Omega$ of the unperturbed equation

$$\dot{x} = g(x),$$

with

$$|x(t) - y(t)| < \varepsilon \quad \forall t \in [0, T].$$

Robustness w.r.t. (small) inner and outer perturbations

$$\dot{y} = g(y + e_1(t)) + e_2(t) \quad (5)$$

Flow stability of a Patchy Vector Field (A. & BRESSAN 2003, 2004)

Let g be a patchy vector field on $\Omega \subset \mathbb{R}^n$. Given any compact subset $C_0 \subset \Omega$, and any $T, \varepsilon > 0$, there exists $\delta > 0$ such that the following holds.

If $y : [0, T] \mapsto \Omega$ is a solution of the perturbed system (5), with $y(0) \in C_0$, and

$$\|e_1\|_{BV} \leq \delta, \quad \|e_2\|_{L^1} \leq \delta,$$

then there exists a solution $x : [0, T] \mapsto \Omega$ of the unperturbed equation


$$\dot{x} = g(x),$$

with

$$|x(t) - y(t)| < \varepsilon \quad \forall t \in [0, T].$$

Note: Since Cauchy problem for PVF lacks of forward uniqueness & continuous dependence, one cannot expect to have single sol'n's of PVF be stable w.r.t. perturbations.

Here we have **stability property** involving whole Carathéodory **solution set**: upper semicontinuity property of the solution set.



Outline

- 1 Introduction
 - General Setting
 - Main Difficulties
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - Robustness of Patchy Vector Fields
- 3 Patchy Feedbacks
 - Definition
 - Stabilizing Patchy Feedback
 - Nearly Optimal Patchy Feedback
 - ISS Patchy Feedback

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m$$

A piecewise smooth map $U : \Omega \rightarrow \mathbb{R}^m$ is a **patchy feedback** control on open domain $\Omega \subset \mathbb{R}^n$ if:

- there exist $U_i : \Omega_i \rightarrow \mathbb{R}^m$, $i \in \mathbb{Z}$, smooth maps, with $\{\Omega_i\}_{i \in \mathbb{Z}}$ locally finite covering of Ω ;
- (Ω_i, g_i) , with

$$g_i(x) \doteq f(x, U_i(x)), \quad x \in \Omega_i,$$

is a **patch** for every $i \in \mathbb{Z}$;

-

$$U(x) = U_i(x) \quad \forall x \in \Omega_i \setminus \bigcup_{j>i} \Omega_j.$$

⇓

$$f(x, U(x)) = f(x, U_{i^*(x)}(x))$$

is a **patchy vector field** on Ω .

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m$$

A piecewise smooth map $U : \Omega \rightarrow \mathbb{R}^m$ is a **patchy feedback** control on open domain $\Omega \subset \mathbb{R}^n$ if:

- there exist $U_i : \Omega_i \rightarrow \mathbb{R}^m$, $i \in \mathbb{Z}$, smooth maps, with $\{\Omega_i\}_{i \in \mathbb{Z}}$ locally finite covering of Ω ;
- (Ω_i, g_i) , with

$$g_i(x) \doteq f(x, U_i(x)), \quad x \in \Omega_i,$$

is a **patch** for every $i \in \mathbb{Z}$;

$$U(x) = U_i(x) \quad \forall x \in \Omega_i \setminus \bigcup_{j>i} \Omega_j.$$

⇓

$$f(x, U(x)) = f(x, U_{i^*(x)}(x))$$

is a **patchy vector field** on Ω .

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m$$

A piecewise smooth map $U : \Omega \rightarrow \mathbb{R}^m$ is a **patchy feedback** control on open domain $\Omega \subset \mathbb{R}^n$ if:

- there exist $U_i : \Omega_i \rightarrow \mathbb{R}^m$, $i \in \mathbb{Z}$, smooth maps, with $\{\Omega_i\}_{i \in \mathbb{Z}}$ locally finite covering of Ω ;
- (Ω_i, g_i) , with

$$g_i(x) \doteq f(x, U_i(x)), \quad x \in \Omega_i,$$

is a **patch** for every $i \in \mathbb{Z}$;

-

$$U(x) = U_i(x) \quad \forall x \in \Omega_i \setminus \bigcup_{j>i} \Omega_j.$$

\Downarrow

$$f(x, U(x)) = f(x, U_{i^*(x)}(x))$$

is a **patchy vector field** on Ω .

Outline


- 1 Introduction
 - General Setting
 - Main Difficulties
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - Robustness of Patchy Vector Fields
- 3 Patchy Feedbacks
 - Definition
 - **Stabilizing Patchy Feedback**
 - Nearly Optimal Patchy Feedback
 - ISS Patchy Feedback

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m \quad (6)$$

Stabilization by Patchy Feedback (A. & BRESSAN 1999)

Assume: (6) is globally asymptotically controllable to the origin:

1. **Attractiveness:** $\forall x_0 \in \mathbb{R}^n \exists$ admissible open-loop control $u^{x_0}(t)$ s.t. the trajectory $x(\cdot, u^{x_0})$ starting at x_0 is defined $\forall t \geq 0$ and satisfies $x(t, u^{x_0}) \rightarrow 0$ as $t \rightarrow \infty$.
2. **Lyapunov stability:** $\forall \varepsilon > 0 \exists \delta > 0$ s.t. $\forall x_0 \in \mathbb{R}^n, |x_0| \leq \delta$, \exists admissible control $u^{x_0}(t)$ as in 1., with $|x(t, u^{x_0})| \leq \varepsilon, \forall t \geq 0$.




$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m \quad (6)$$

Stabilization by Patchy Feedback (A. & BRESSAN 1999)

Assume: (6) is globally asymptotically controllable to the origin:

1. **Attractiveness:** $\forall x_0 \in \mathbb{R}^n \exists$ admissible open-loop control $u^{x_0}(t)$ s.t. the trajectory $x(\cdot, u^{x_0})$ starting at x_0 is defined $\forall t \geq 0$ and satisfies $x(t, u^{x_0}) \rightarrow 0$ as $t \rightarrow \infty$.
2. **Lyapunov stability:** $\forall \varepsilon > 0 \exists \delta > 0$ s.t. $\forall x_0 \in \mathbb{R}^n, |x_0| \leq \delta$, \exists admissible control $u^{x_0}(t)$ as in 1., with $|x(t, u^{x_0})| \leq \varepsilon, \forall t \geq 0$.




$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m \quad (6)$$

Stabilization by Patchy Feedback (A. & BRESSAN 1999)

Assume: (6) is globally asymptotically controllable to the origin:

1. **Attractiveness:** $\forall x_0 \in \mathbb{R}^n \exists$ admissible open-loop control $u^{x_0}(t)$ s.t. the trajectory $x(\cdot, u^{x_0})$ starting at x_0 is defined $\forall t \geq 0$ and satisfies $x(t, u^{x_0}) \rightarrow 0$ as $t \rightarrow \infty$.
2. **Lyapunov stability:** $\forall \varepsilon > 0 \exists \delta > 0$ s.t. $\forall x_0 \in \mathbb{R}^n, |x_0| \leq \delta$, \exists admissible control $u^{x_0}(t)$ as in 1., with $|x(t, u^{x_0})| \leq \varepsilon, \forall t \geq 0$.




$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m \quad (6)$$

Stabilization by Patchy Feedback (A. & BRESSAN 1999)

Assume: (6) is globally asymptotically controllable to the origin:

1. **Attractiveness:** $\forall x_0 \in \mathbb{R}^n \exists$ admissible open-loop control $u^{x_0}(t)$ s.t. the trajectory $x(\cdot, u^{x_0})$ starting at x_0 is defined $\forall t \geq 0$ and satisfies $x(t, u^{x_0}) \rightarrow 0$ as $t \rightarrow \infty$.
2. **Lyapunov stability:** $\forall \varepsilon > 0 \exists \delta > 0$ s.t. $\forall x_0 \in \mathbb{R}^n, |x_0| \leq \delta$, \exists admissible control $u^{x_0}(t)$ as in 1., with $|x(t, u^{x_0})| \leq \varepsilon, \forall t \geq 0$.




Stabilization by Patchy Feedback ... continued

Then: there exists a **patchy feedback** control $U(x)$ that makes **asymptotically stable** the closed-loop system

$$\dot{x} = f(x, U(x)) \quad (7)$$


every Carathéodory solution of (7) either tends asymptotically to the origin, or reaches the origin in finite time. System enjoys (7) Lyapunov stability.

Construction of a stabilizing patchy feedback by patching together open-loop controls



Semi-global practical stabilization by a patchy feedback

Construct a patchy feedback that steers every point of a ball B inside a smaller ball $B' \subsetneq B$, within finite time.



Outline

- 1 Introduction
 - General Setting
 - Main Difficulties
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - Robustness of Patchy Vector Fields
- 3 Patchy Feedbacks
 - Definition
 - Stabilizing Patchy Feedback
 - **Nearly Optimal Patchy Feedback**
 - ISS Patchy Feedback

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m$$

- f smooth with sublinear growth
- $T(y) \doteq$ minimum time to steer the system from y to the origin

Nearly Time Optimal Patchy Feedback

(A. & BRESSAN 2007; BRESSAN & PRIULI 2008)

Given $\varepsilon > 0$, $\tau > 0$, there exists a sub-optimal patchy feedback $u = U(x)$ defined on sub-level set

$$R_\tau = \{y : T(y) \leq \tau\},$$

such that $\forall y \in R_\tau$, $|y| > \varepsilon$, any (Carathéodory) solution of

$$\dot{x} = f(x, U(x)) \quad x(0) = y,$$

reaches the ε -ball $B_\varepsilon = \{|x| \leq \varepsilon\}$ within time $T(y) + \varepsilon$.

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m$$

- f smooth with sublinear growth
- $T(y) \doteq$ minimum time to steer the system from y to the origin

Nearly Time Optimal Patchy Feedback

(A. & BRESSAN 2007; BRESSAN & PRIULI 2008)

Given $\varepsilon > 0$, $\tau > 0$, there exists a sub-optimal patchy feedback $u = U(x)$ defined on sub-level set

$$R_\tau = \{y : T(y) \leq \tau\},$$

such that $\forall y \in R_\tau$, $|y| > \varepsilon$, any (Carathéodory) solution of

$$\dot{x} = f(x, U(x)) \quad x(0) = y,$$

reaches the ε -ball $B_\varepsilon = \{|x| \leq \varepsilon\}$ within time $T(y) + \varepsilon$.

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m$$

- f smooth with sublinear growth
- $T(y) \doteq$ minimum time to steer the system from y to the origin

Nearly Time Optimal Patchy Feedback

(A. & BRESSAN 2007; BRESSAN & PRIULI 2008)

Given $\varepsilon > 0$, $\tau > 0$, there exists a sub-optimal patchy feedback $u = U(x)$ defined on sub-level set

$$R_\tau = \{y : T(y) \leq \tau\},$$

such that $\forall y \in R_\tau$, $|y| > \varepsilon$, any (Carathéodory) solution of

$$\dot{x} = f(x, U(x)) \quad x(0) = y,$$

reaches the ε -ball $B_\varepsilon = \{|x| \leq \varepsilon\}$ within time $T(y) + \varepsilon$.

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m$$

- f smooth with sublinear growth
- $T(y) \doteq$ minimum time to steer the system from y to the origin

Nearly Time Optimal Patchy Feedback

(A. & BRESSAN 2007; BRESSAN & PRIULI 2008)

Given $\varepsilon > 0$, $\tau > 0$, there exists a sub-optimal patchy feedback $u = U(x)$ defined on sub-level set

$$R_\tau = \{y : T(y) \leq \tau\},$$

such that $\forall y \in R_\tau$, $|y| > \varepsilon$, any (Carathéodory) solution of

$$\dot{x} = f(x, U(x)) \quad x(0) = y,$$

reaches the ε -ball $B_\varepsilon = \{|x| \leq \varepsilon\}$ within time $T(y) + \varepsilon$.

$$\dot{x} = f(x, u), \quad x \in \mathbb{R}^n, \quad u \in K \subset \mathbb{R}^m$$

- f smooth with sublinear growth
- $T(y) \doteq$ minimum time to steer the system from y to the origin

Nearly Time Optimal Patchy Feedback

(A. & BRESSAN 2007; BRESSAN & PRIULI 2008)

Given $\varepsilon > 0$, $\tau > 0$, there exists a sub-optimal patchy feedback $u = U(x)$ defined on sub-level set


$$R_\tau = \{y : T(y) \leq \tau\},$$

such that $\forall y \in R_\tau$, $|y| > \varepsilon$, any (Carathéodory) solution of

$$\dot{x} = f(x, U(x)) \quad x(0) = y,$$


reaches the ε -ball $B_\varepsilon = \{|x| \leq \varepsilon\}$ within time $T(y) + \varepsilon$.

Note: patching together nearly-optimal open-loop controls does not work!



Alternative construction: work with the value function

Note: patching together nearly-optimal open-loop controls does not work!



Alternative construction: work with the value function

Construction of Nearly Time Optimal Patchy Feedback

- Approximate the minimum time function $T(\cdot)$ with a semi-concave, piecewise quadratic function:

$$\tilde{T}(x) = \min_{j=1, \dots, N} \left\{ a_j + \mathbf{b}_j \cdot x \right\} + M \cdot |x|^2.$$

- Set of points where \tilde{T} not differentiable is contained in finite union of hyperplanes

$$\Gamma_{i,j} \doteq \left\{ a_i + \mathbf{b}_i \cdot x = a_j + \mathbf{b}_j \cdot x \right\}.$$

- Level sets $\tilde{T}(x) = \text{const.}$ contained in union of spherical surfaces.

Construction of Nearly Time Optimal Patchy Feedback

- Approximate the minimum time function $T(\cdot)$ with a semi-concave, piecewise quadratic function:

$$\tilde{T}(x) = \min_{j=1, \dots, N} \left\{ a_j + \mathbf{b}_j \cdot x \right\} + M \cdot |x|^2.$$

- Set of points where \tilde{T} not differentiable is contained in finite union of hyperplanes

$$\Gamma_{i,j} \doteq \left\{ a_i + \mathbf{b}_i \cdot x = a_j + \mathbf{b}_j \cdot x \right\}.$$

- Level sets $\tilde{T}(x) = \text{const.}$ contained in union of spherical surfaces.

Construction of Nearly Time Optimal Patchy Feedback

- Approximate the minimum time function $T(\cdot)$ with a semi-concave, piecewise quadratic function:

$$\tilde{T}(x) = \min_{j=1, \dots, N} \left\{ a_j + \mathbf{b}_j \cdot x \right\} + M \cdot |x|^2.$$


- Set of points where \tilde{T} not differentiable is contained in finite union of hyperplanes

$$\Gamma_{i,j} \doteq \left\{ a_i + \mathbf{b}_i \cdot x = a_j + \mathbf{b}_j \cdot x \right\}.$$

- Level sets $\tilde{T}(x) = \text{const.}$ contained in union of spherical surfaces.

Construction of Nearly Time Optimal Patchy Feedback ... continued

- Construct the patchy feedback by induction, progressively working on larger sub-level sets of \tilde{T}



Outline

- 1 Introduction
 - General Setting
 - Main Difficulties
- 2 Patchy Vector Fields
 - Definition and Basic Properties
 - Robustness of Patchy Vector Fields
- 3 Patchy Feedbacks
 - Definition
 - Stabilizing Patchy Feedback
 - Nearly Optimal Patchy Feedback
 - **ISS Patchy Feedback**

ISS Stability: robustness of stabilization in presence of **large external perturbations** (SONTAG 1989)

- In presence of large external disturbances, solutions remain in a ball around the origin of the same size of the L^∞ -strength of the perturbation
- If there exists a continuous stabilizing feedback control $U(x)$, then one can easily modify U so that the resulting system becomes ISS
- systems with a quadratic scalar control may not admit (even discontinuous) ISS stabilizing feedback

ISS Stability: robustness of stabilization in presence of **large external perturbations** (SONTAG 1989)

- In presence of large external disturbances, solutions remain in a ball around the origin of the same size of the L^∞ -strength of the perturbation
- If there exists a continuous stabilizing feedback control $U(x)$, then one can easily modify U so that the resulting system becomes ISS
- systems with a quadratic scalar control may not admit (even discontinuous) ISS stabilizing feedback

ISS Stability: robustness of stabilization in presence of **large external perturbations** (SONTAG 1989)

- In presence of large external disturbances, solutions remain in a ball around the origin of the same size of the L^∞ -strength of the perturbation
- If there exists a continuous stabilizing feedback control $U(x)$, then one can easily modify U so that the resulting system becomes ISS
- systems with a quadratic scalar control may not admit (even discontinuous) ISS stabilizing feedback

Consider affine system

$$f_0(x) + \sum_{i=1}^m u_i f_i(x) \quad x \in \mathbb{R}^n$$

ISS Stability S-a-h solns (MALISOFF, RIFFORD & SONTAG 2004)

$$\dot{x} = f_0(x) + \sum_{i=1}^m \left(U_i(x + \zeta(t)) + d_i(t) \right) f_i(x)$$

ISS Stabilizing Patchy Feedback for Carathéodory solns
(A. & PRIULI 2011)

Consider affine system


$$f_0(x) + \sum_{i=1}^m u_i f_i(x) \quad x \in \mathbb{R}^n$$

ISS Stability S-a-h solns (MALISOFF, RIFFORD & SONTAG 2004)


$$\dot{x} = f_0(x) + \sum_{i=1}^m \left(U_i(x + \zeta(t)) + d_i(t) \right) f_i(x)$$

ISS Stabilizing Patchy Feedback for Carathéodory solns
(A. & PRIULI 2011)


Stabilizing Patchy Feedback for Nonholonomic Integrator



ISS Stabilizing Patchy Feedback for Nonholonomic Integrator



ISS Stabilizing Patchy Feedback for Nonholonomic Integrator



Future directions

- Construction of stabilizing or sub-optimal patchy feedback for control **problems with constraints**.
- Construction of stabilizing or sub-optimal **hybrid** patchy feedback.
(GOEBEL, PRIEUR, TEEL)
- Introduction of **numeric schemes** to solve HJ or HJB equations, based on patchy decomposition technique.
(NEVASCA & KRENER 2007-2008; FALCONE & PICARELLI 2011)

Future directions

- Costruction of stabilizing or sub-optimal patchy feedback for control **problems with constraints**.
- Costruction of stabilizing or sub-optimal **hybrid** patchy feedback.
(GOEBEL, PRIEUR, TEEL)
- Introduction of **numeric schemes** to solve HJ or HJB equations, based on patchy decomposition technique.
(NEVASCA & KRENER 2007-2008; FALCONE & PICARELLI 2011)

Future directions

- Costruction of stabilizing or sub-optimal patchy feedback for control **problems with constraints**.
- Costruction of stabilizing or sub-optimal **hybrid** patchy feedback.
(GOEBEL, PRIEUR, TEEL)
- Introduction of **numeric schemes** to solve HJ or HJB equations, based on patchy decomposition technique.
(NEVASCA & KRENER 2007-2008; FALCONE & PICARELLI 2011)

et finalement....

Merci de votre attention!